


# ALL the SCIENCES



### 1500 Pages 1200 Illustrations

THIS great new work presents-for the first time in one volume—a complete coverage of the terms of science and enmethods of calculation are fully described with the formulae and units-chemical structures and reactions, physical laws and instruments, engineering design, construction, and operation are merely suggestive of its tremendous scope-which extends throughout the entire range of technical knowledge up to the most recent advances and inventions. The great number of photographs, diagrams, and charts have been specially prepared and selected to show the salient facts most clearly. Innumerable tables and summaries make all this information easily available for instant reference.

This vast fund of information has been prepared and organized by a plan that insures its usefulness, completeness, and accuracy. Each entry is first explained in simple, broad terms that are easy to understand, and that serve as an illuminating introduction to the detailed and more advanced information which follows.

### From Fundamentals to Latest Advanced Discoveries—

Principles, Methods, Formulas-Clear Charts, Diagrams

For the student, the hobbyist, the manual worker, this great volume supplies, for the first time, a single, convenient source of reference covering all the sciences. The ample cross-references make it easy to follow a complete course of study on any chosen subject. By this flexible plan of arrangement, the professional scientist, who wants specific information instantly, either in his own field or any related field, can find it in a few seconds in its alphabetical place—comprehensively treated in the language he works with—the language of science.

Answers tens of thousands of questions such as: The value of radial, rotary gas engines—How the Diesel Engine operates—How air conditioning functions—What is the coming television system—How storage batteries work—How to find your position at sea—How to do dead reckoning—How your nervous system works—How to recognize every star, planet, constellation—How optical instruments are constructed—How to work arithmetic, algebra, geometry problems—How bridges are constructed—How an airplane beacon system works—How petroleum is cracked to make gasoline—How rayon is made—How to survey a piece of land—and thousands more.

MAIL COUPON ON OPPOSITE PAGE




### of the ORIAL HISTOR

Ready for Immediate Shipment!

WE originally planned to sell this PICTORIAL HISTORY as a 4-volume set, one volume for each year of the war, and to rice the set at \$22.00. Now by combining the full contents of these volumes into 2 giant books and making other economies, we are ble to offer you, in spite of today's skyhigh scarcity prices, this exensive illustrated set, durably bound in Novelex, at the bargain C - 1 60 00 --- bask slore - fem some skinning skinning

price may be paid in easy installments. Send no money now unless you wish to-just mail the coupon attached. We will mail the 2volume set to you for FREE examination. At the end of 7 days, you may return them without further obligation or pay for them on the easy terms explained in the coupon. (We also have a superb De Luxe Edition in real Morocco-Grained Arteraft binding for only \$1 extra per book. Check box in coupon if you prefer FREE Trial of this edition.) WM. H. WISE & CO., INC., 50 West 47th Street, New York 19, N. Y.

LIMITED SUPPLY! MAIL COUPON



Field messages come through, thanks to the battery that can take it—the Mallory Tropical Dry Battery.

Right from the war's start, the problem has been to keep field communication power unbroken—to find dry cell batteries that stand up under the toughest conditions that weather can produce.

That problem has been solved by the Mallory Tropical Dry Battery, a new and mentally different in its characteristics. Mallory Tropical Dry Batteries were originally developed by Mallory for the United States Army Signal Corps.

As is to be expected, the Mallory Tropical Dry Battery is now made solely for wartime needs. But it suggests infinite possibilities for peacetime improvements in a wide range of fields—radio, hearing aid, marine and railroad, just to mention a few.

# MALLORY TROPICAL\* DRY BATTERIES

ALSO MAKERS OF PRECISION METALLURGICAL AND ELECTRONIC PRODUCTS—AND MALLORY BEARINGS



P. R. MALLORY & CO., Inc., INDIANAPOLIS 6, INDIANA

# in Une GIANT Book

12 Big Volumes in One! 10,000 Separate Subjects

### The Instant Question-Answerer for Laboratory and Shop-Workers, Mechanics, Home Scientists, Students

The vast wealth of useful information in the Scientific Encyclopedia, if published in the ordinary way, would fill more than 12 average-size volumes. Here is just a brief outline of some of the subjects covered:

CHEMISTRY: Chemical elements-symbols, atomic number, atomic weight, density, hardness, melting point, etc.-common reactions, occurrence in nature, method of production from ores,

uses in industry. Compounds-full information, including manufacture and use. Organic compounds; industrial products. Agricultural chemistry, food chemistry.

PHYSICS: Mechanics, heat, light, sound, electricity, magnetism, X-rays, fully covered; principles and application profusely illustrated.

MATHEMATICS: From fundamentals of arithmetic to algebra, geometry, trigonometry, calculus, differential equations, etc.; with special emphasis on their application to science.

ASTRONOMY: Articles cover the entire subject. Each important constellation is shown on a star map so that it can be easily located in the sky. Complete information on planets, use of telescope, spectrometer, etc.

ZOOLOGY: The whole story of life from the tiniest single-celled organisms up to man himself, including vast numbers of common insects, mollusks, worms; birds, fish, reptiles, mammals.

MEDICINE: Thorough coverage of anatomy, circulatory system, nervous system, muscular system, skeletal system, excretory systems, etc. Vitamins, hormones. Bacteriology. Diseases-symptoms, diagnosis, treatment. Drugs. Latest researches and findings.

MECHANICAL ENGINEERING: Principles of mechanics, machine design, engineering parts and instruments. Types and functions of bolts, cams, gears, and other fundamentals up to automobiles, aeroplanes, locomotives, etc. Steam, gas, gasoline, diesel engines.

CIVIL ENGINEERING: Surveying. Bridges, highways, railways-every subject thoroughly explained.

ELECTRICAL ENGINEERING: Motors, generators, lighting, radio and television-every branch fully covered and clearly illustrated.

The foregoing is only a partial list of the countless special subjects covered. You will find hundreds of articles on GEOLOGY, BOTANY, NAVIGATION, CHEMICAL ENGINEERING, and, in fact, any special branch of science in which you want information.

### EXAMINE A COPY FREE

It is difficult in this limited space to give you a complete adequate idea of the immense amount of material contained in the Scientific Encyclopedia. See this volume for yourself, without expense or obligation. We will send it to you for free examination. D. Van Nostrand Co., Inc., 250 Fourth Ave., New York 3, N. Y.



### **Prepared by Outstanding Authorities** In Each Field of Science

The high technical standing of the editors is your assurance of the authoritativeness and accuracy of every statement. Although the responsibility for each subject was in the hands of a single noted scientist, the authors and publishers have had the co-operation and advice of a large group of well-known authorities. authorities.

### CONTRIBUTING EDITORS

Richard M. Field, Ph. D.—Princeton University—Geology Warren K. Green, Ph. D.—Amherst College—Astronomy and

Arthur W. Lindsey, Ph. D.—Denison University—Zoology
Frederick T. Morse, M. E., E. E.—University of Virginia—
Engineering and Aeronautics
R. S. Mueller, M. D.—Columbia University—Medicine
Lloyd L. Small, Ph. D.—Lehigh University—Mathematics
Edward S. C. Smith, S. B., A. M.—Union College—Mineralogy
Ralph K. Strong, Ph. D.—Rose Polytechnic Institute—
Chemistry Chemistry

LeRoy D. Weld, Ph. D.—Coe College—Physics R. M. Whelden, Ph. D.—Massachusetts Institute of Technology


### Among the many CONSULTING EDITORS

### MAIL THIS COUPON

D. VAN NOSTRAND CO., Inc. 250 Fourth Avenue, New York 3, N. Y.

Send me Van Nostrand's SCIENTIFIC ENCYCLOPEDIA. complete in one volume. 1500 pages, bound in sturdy Fabrikoid. Within 10 days I will either return it or send you \$2.00 as first payment. and \$2.00 monthly for four months until the total price of \$10.00 plus a few cents postage is paid. (If you send remittance of \$10.00 with this coupon, we will pay the postage. Same return privilege with refund guaranteed.) (P.S.M. 3-45)

	The second secon
Name	 
	 State
	······
Address	





to use infra-red rays for drying!



Invisible rays, with frequencies millions of times greater than the highest frequency radio wave, now do the paint drying at Ford

Motor Company.

In gleaming tunnels, the rays from infra-red lamps keep up a steady bombardment. Without heating the air, they strike through the metal. This raises the temperature—dries the paint from the inside out.

This system, 5 to 10 times faster than the hottest paint baking oven, helps speed such critical items as aircraft parts.

Patented by Ford, this infrared process is one more of the many important developments

Ford has made available to industry without charge.

Today, thousands of concerns use this process—for everything from making safety glass to dehydrating fruits and vegetables.

Here is just one more in a long series of famous Ford "firsts."

New Ford-built cars and trucks will continue to profit by this progressive spirit and American ingenuity. Mr. Ford has often said: "One thing we don't believe in is standing still."

"STARS OF THE FUTURE". Listen to the new Ford musical program on all Blue Network stations. Every Friday night - 8:00 E. W.T., 7:00 C.W.T., 9:30 M.W.T., 8:30 P.W.T.

EXPECT THE



FROM FORD!



# The tire that was "frozen and fried"

It started life in Pittsburgh and moved to San Antonio. Look at it, then guess its mileage

WHEN Russell Angert, shown above, worked in a Pittsburgh shipyard, he bought a B. F. Goodrich all-synthetic tire. Two months later, believing that these new synthetics were O. K., Mr. Angert bought two more.

Driving 46 miles a day to and from his job, Mr. Angert covered roads that he classes as "newly constructed," "extremely bad," and "impossible." Most of this driving was done in the coldest part of winter. Most people didn't know then whether synthetic rubber could take that kind of usage.

Later the tires that had been "frozen" on Pennsylvania's winter

MARCH, 1945

roads were sent to "fry" in San Antonio. Mr. Angert had to drive cross-country to a new job, on pavements that could fry eggs in less than two minutes. Most people didn't know whether synthetic rubber could take that either.

The tire you see here had covered 21,000 miles when this picture was taken. It has not been recapped, and Mr. Angert says he expects "at least another 25,000 miles." (That seems optimistic, but B. F. Goodrich tires have set even higher mileage records, and we can't help admiring his enthusiasm.)


Tires of synthetic rubber may not yet be quite as good as pre-war

Buy War Savings Bonds and Stamps regularly.

tires, but they're a definite success when made the B. F. Goodrich way. Mr. Angert's case is just one of many. One reason is that B. F. Goodrich had a three-year head start in making and selling tires containing synthetic rubber. That was in 1940, eighteen months before the war. After that extra experience, B. F. Goodrich tires today offer extra wear, extra safety, extra value to essential drivers who qualify for them. The B. F. Goodrich Company, Akron, Ohio.



IN SERVICE ON EVERY FRONT



"Hold 'er, Luke — 'tain't no mole . . . Oncle Rafe's playin' he's a Undergroun' Movement"

# "PLUG-CHEK"HELPS UNCOVER GAS WASTE QUICK

Gas-wasting plugs can be spotted quickly and accurately the "Plug-Chek" way. This Auto-Lite Inspection Service helps put the finger on faulty or improper plugs, may add as much as 12% to gas mileage, according to tests by the American Automobile Association.

Stop in today at your friendly Auto-Lite Spark Plug Dealer and have your spark plugs inspected the "Plug-Chek" way. Possibly all they need is cleaning or regapping. But if new spark plugs are needed, ask for Auto-Lites . . . the ignition engineered spark plug.

THE ELECTRIC AUTO-LITE COMPANY
TOLEDO, 1 • Merchandising Division • OHIO
BACK THE ATTACK—BUY WAR BONDS

Tune in the AUTO-LITE



### Dick Haymes

HELEN FORREST - GORDON JENKINS' ORCHESTRA

Every Tuesday Night • NBC

Featuring men and women on the fighting fronts



### A MODERN SYLLOGISM

### MAJOR PREMISE:

Bell Telephone System serves the American Public.





### MINOR PREMISE:

Bell Telephone Laboratories develop the facilities of the Bell System.





### CONCLUSION:

Therefore, Bell Laboratories serve the American Public.





And that is the raison d'être of the Laboratories. For the Bell Telephone System, the Laboratories carry on research studies in all the sciences and development work in all the engineering arts that relate to electrical communication.

For the Western Electric Company, the manufacturing unit of the System, the Laboratories develop equipment, prepare specifications for its construction, and engage in various engineering activities.

For the Armed Forces of the United States, under contracts of the Western Electric, the Laboratories have undertaken more than a thousand development projects — many with spectacular effect upon our enemies.



BELL TELEPHONE LABORATORIES explore and invent, devise and perfect for our Armed Forces at war and for continued improvements and economies in telephone service.

# POPULAR SCIENCE

FOUNDED 1872

MONTHLY

VOL. 146 NO. 3

### Mechanics & Handicraft

### A TECHNICAL JOURNAL OF SCIENCE AND INDUSTRY

### CONTENTS for MARCH, 1945

Cover: Painting by Jo Kotula

# News

What's in the Earth's Basement?	65
Mechanic's View of Jet Plane	70
You Can't Fly Without Airfields	74
Zoom Boats Sock Like Battleships	82
Take a Look Inside a B-29	86
Bombing Through Clouds	89
Why Pressure-Cabin Transports?	91
Ever See a Molecule?	93
Planes You'll Fly After the War	100
"Big Mo": 45,000 Tons of Fight	112
Life of Our Migrating Butterfly	116
Across the Roof of the World	120
We Move the Earth for Copper	122
World's Biggest Bargain Counter	128
Why Japan Can't Win on Land	130

# Automobiles

Things Boil Over at Gus's	138
Ideas for the Car Owner	141
Engine Noises-What They Mean	142

# Home and Workshop

Waterline Model of a Navy Tug	147
The Kingcobra in Miniature	160
Machine Aids That Save Time	162
Tricks for the Dinner Table	172
Controlling Photographic Light	174
2,000-Degree Shop Furnace	182
Carrier-Current Receiver (II)	192
Home Experiments in Magnetism	196
The Chemistry of Silver	198



COULD YOU USE THIS coldweather face mask? Developed for U. S. troops in the Arctic, it may be among the thousands of items of surplus war property to be sold to civilians after the war. On page 129 Popular Science offers \$200 in prizes for letters suggesting uses for goods from this mammoth bargain counter.

ASSISTANT EDITOR . . . Arthur Wakeling AVIATION EDITOR . . . C. B. Colby HOME & WORKSHOP EDITOR . Harry Walton ART EDITOR . . . . . Carsten Grande

EDITORIAL · ASSOCIATES: Fred O. Newman, news editor; Alden P. Armagnac, B. T. Richards, Harry Samuels, Michele de Santis, Volta Torrey, Frank Rowsome, Jr., Carl W. Bertsch, Ruth Westphal, Edward F. Allen, Devon Francis, John G. Kingdon, Gold V. Sanders.

ART ASSOCIATES: Stewart Rouse, William Patrick, Samuel Dukler, Evelyn Cooper.

PHOTOGRAPHY: W. W. Morris, Robert F. Smith.

Published monthly at 353 Fourth Avenue, New York 10, N. Y., by Popular Science Publishing Co., Inc. Godfrey Hammond, President and Treasurer; R. C. Wilson, Raymond J. Brown, Charles McLendon, Stephen P. Glennon. Vice-Presidents; F. W. Briggs. Secretary, Entered as second-class matter Dec. 28, 1918, at the Post Office at New York under the act of March 3, 1879; additional entry as second-class matter at Dayton, Ohio, Entered as second-class matter at the Post Office Department, Canada. Printed in U.S.A. Copyright, 1944, by Popular Science Publishing Co., Inc. All rights reserved in the United States, Great Britain, and in all countries participating in the International Copyright Convention and the Pan-American Copyright Convention. Yearly subscriptions to United States and its possessions, \$2.50; Canada, \$3.00; foreign countries, excepting Canada, \$3.50. Subscribers must notify us of change of address four weeks in advance of the next publication date. Be sure to give both old and new address,

# "EVEN BETTER THAN I HAD!"



Of course, the I. C. S. Course which Bill is studying has it all over the one the Boss completed.

I. C. S. texts constantly are revised in response to student questions and reactions . . . brought up to date on technical advances.

Today's texts embody the experience of more than 53 years, the expenditure of nearly six million dollars. This is the reservoir of Vocational Training knowledge from which every student draws his personalized instruction.

I. C. S. graduates, including many employers, will tell you how good I. C. S. Courses were in their day. But current texts, they find, are better.


Employers have a very real interest in I.C.S. This famous educational system regularly reports the progress of its students to the men for whom they're working. And it regularly receives letters expressing keen appreciation for this service.

I. C. S. training goes on record with these executives — counts in your record. Join the "coming" men! Mail the coupon for your own information as thousands of now successful men did for theirs. Possibly your own employer was one of them.

### INTERNATIONAL CORRESPONDENCE SCHOOLS



□ Air Conditioning □ Heating □ Plumbing □ Refrigeration □ Steam Fitting □ Chemistry Courses □ Chemistry Courses □ Chemistry, Analytical □ Chemistry, Industrial □ Chemistry, Mfg. Iron & Steel □ Petroleum Refining □ Plastics □ Pulp and Paper Making □ Civil Engineering, Architectural and Mining Courses □ Architectural Drafting □ Architecture □ Bridge and Building Foreman □ Building Estimating □ Civil Engineering □ Coal Mining □ Civil Engineering □ Coal Mining □ Highway Engineering □ Lumber Dealer □ Reading Structural Blueprints □ Sanitary Engineering □ Structural Drafting □ Structural Engineering	Electrical Courses  Electrical Drafting Electrical Engineering Power House Electric Practical Electrician Practical Telephony Telegraph Engineering Internal Combustion Engines Courses Auto Technician Aviation Diesel-Electric Diesel Engines Gas Engine Mechanical Courses Airplane Drafting Flight Engineer Foundry Work Heat Treatment of Metals	lars about the course before    Ship Drafting   Ship Fitting   Shop Practice   Steel Mill Workers   Tool Designing   Welding, Gas and Electric   Radio Courses   Electronics   Radio General   Radio Operating   Radio Servicing	which I have marked X:    Textile Designing   Wooten Manufacturing     Business and   Academic Courses   Accounting   Advertising     Arithmetic   Bookkeeping   Business Correspondence     Business Management   Certified Public Accounting     College Preparatory     Commercial   Cost Accounting     Federal Tax   First Year College   Foremanship     French   Good English   High School   Higher Mathematics   Illustrating     Motor Traffic   Postal Service   Salesmanship     Secretarial   Sign Lettering   D'Spanish     Stenography   Traffic Management
996 IV-51		Home Address	



# Contents [CONTINUED]

### Aviation

Shoulder Harness for Pilots	94
Suit Prevents Blackout	94
Fighter-Approach Trainer	94
World's Biggest Bomber	95
Radio-Controlled Glider Bomb	95
Jet-Propelled Helicopter	95
Pin-Up of A-26 Invader	97

### Facts and Ideas

Lights Trace Hand Movements	69
Plastic Slows Wool Shrinkage	72
Better Fit for Stocking Heels	72
Artificial Eyes of Plastic	72
Rubberizing Warship Shafts	73
Heat Makes Eggs Keep	73
House Built of Paper	85
Tank Carries Flame Thrower	88
Navy's Floating Dry Docks	88
Model Crane Teaches Safety	90
How Testers Wind Watches	90
Saving Cartridge Cases	90
Magnesium Stops Pipe Rust	92
Armadillo Armored Car	92
"Holy Ghost" Sea Shell	96
Coast Survey Vessels Aid War	96
Model Teaches Dry-Docking	99
Telling Army-Navy Time	119
Chronograph Clocks Shells	121

### Inventions

Screwdriver Torque Gauge	98
Transparent Center Punch	98
Removing Broken Taps	98
Drag Brake for Trucks	114
Fluorescent Home Lighting	114
De Luxe Cigarette Roller	114
Pincer Coat Hanger	115
Wanted: Pancake Assembly Line	115
Inflatable Beach Chair	115
Skis for Baby Buggy	115
Electricity Smooths Paint	118
Sighting Device Trains Marksmen	119
Model Oil Derricks	206
Plastic Binocular Case	206
"Doll-House" Factories	206

### (Contents continued on page 10)

IMPORTANT NOTICE: The contents of this magazine must not be reprinted without permission. The editors are not responsible for unsolicited contributions, and cannot guarantee the return of such material or insure against its loss. Contributions on accompanied by sufficient postage will not be returned: In presenting numerous stories of new products of applied science. Popular Science Monthly does not underwrite the business methods of the individuals or concerns producing them. To avoid liability for patent infringement, readers should investigate before making, using, or offering for sale any of the devices, machines, or processes described; Popular Science Monthly takes no responsibility. The use of Popular Science Monthly articles for stock-selling schemes is never authorized.



Are YOU
doing
bookkeeping
"chores"?
CLIMB

HIGHER!

As you go along you absorb the principles of auditing, business law, statistical control, cost accounting, organization, management and finance, etc.

This way is not magic. It is not easy. It requires giving up certain spare time to serious study. How long will it take you to acquire

this accountancy training is strictly up to you you can go as fast or as slowly as you choose. But after you have gone part way (you need not wait until you are clear through the training) you will find yourself stepping up to better positions.

And once you have mastered this fascinating profession—once you have become an accountant—then you will have the money and the standing to make your dreams come true. You will be a respected member of the best paying profession and equipped to go out into public accounting or to climb to a top management position.

Our free 48-page booklet, "Accountancy, the Profession That Pays," tells you what you must know to be an accountant and how you can prepare in your leisure time at moderate cost. The coupon below will bring this booklet quickly without cost or obligation. You already have a start in this field; now find out how you can go all the way. Do it today.

IF you are doing the "chore" work of accounting as a bookkeeper, ledger clerk, cost clerk, billing clerk, or in one of the other many record keeping jobs—

You should consider climbing higher—becoming an accountant.

Why be satisfied all your life with a small salary and an ordinary job when there is such a large future for the man or woman who understands accountancy in all its forms and phases?

One big difference between you and the successful accountant is that he doesn't do the chores. He bosses those who do the drudgery and he gets the money and prestige. And he does that because he knows the principles behind the records you keep—can plan those records and interpret them to management. He knows what you know—and a lot more.

There are two ways in which you can get this knowledge which will qualify you for an accountant's position.

First—the old way of day-by-day experience on the job. This is the long route—taking many, many years, sometimes a lifetime. Most people taking this way never get anywhere. Why sacrifice years of success—lose time and money—when there is a better and easier way?

Second, the LaSalle way of learning in your spare time—studying and preparing for the step ahead. You learn by doing—you study accounting principles and solve accounting problems. You cover accountancy from the basic principles right up through Accounting Systems and Income Tax Procedure—C.P.A. training if you so desire.

# LASALLE EXTENSION UNIVERSITY A Correspondence Institution

Dept. 383-H, 417 S. Dearborn Street, Chicago 5, Illinois

I'd like to know more about your home study program to help me prepare for an accounting career. Please send me your free 48-page booklet, "Accountancy, the Profession That Pays."

ame	
resent position	
ddress	
ity & State	

# . . the next 250 miles

you drive, add 3 ounces of...



The next 250 miles on your car-or the miles after that may be the straw that breaks the camel's back. When mileage begins to pile up-that's the time to be sure that lubrication is always efficient. Pyroil maintains a protective covering of oil on cylinder walls-reduces wear-rust-sludge formation and makes starting easier. Put a pint of Pyroil in the crank case-3 ounces in your gas tank every 250 miles.

Manufactured and Guaranteed by Pyroil Company,

### **PYROIL** Adds life to your Car

9	YROIL COMPANY 47 Main Street, La Crosse, Wisconsin
n	I want my car to last and run properly. Please tell me nore about Pyroil and how it can accomplish this for me.
N	Name
A	.ddress
C	City or TownState

# Contents [CONTINUED]

Craftwork	
Amateur Craftsmen at Work	151
Carved Desk-Top Turtle Box	158
Tin-Plate Bowl Accessories	167
Electrical	
Electric Wiring Puzzlers	190
Electrical Shop-Data Card	191
New Ideas in the Radio Field	195
Flashing Lights Scare Ducks	203
Miscellaneous	136
What's New in Modern Living New Ideas in the Auto World	145
Of Interest to Home Owners	146
Solving a Knotty Problem	154
Table Tricks—Facts for Fun	156
Exposure-Meter Telescope	159
How Are Your Checker Wits?	168
Exciting Action Checker Game	169
Secret-Combination Latch	171
Can You Beat These Pictures?	179
Of Interest to Photo Fans	180
Ideas that Speed Victory	181
Lathe Tool for Slender Work	The second second
Question Bee-Auto Parts	187
Magic Tricks You Can Make	
New Shop Ideas	
Handy Proportional Angle	157
New Ideas for the Workshop	185
String-and-Spool Tool Switch	188
The Handy Man  Keeping the Home Shipshape	152
Decorations from Old Decoys	
Mobile Roadside Fruit Stand	202
Custom Duilt Window Shades	204

### Woodworking

Novel Midget Corner Cupboard	150
What's Wrong? Chisel Errors	166
Toy Walkie-Talkie Radio Set	170
	189


Extra Recreation-Room Couch.....



**Building this** A. M. SIGNAL GENERATOR

gives you valuable experience. Provides amplitude - modulated cignals for test and experiment purposes.

Radio Servicing pays many good money for full time work. Many others make \$5, \$10 a week EXTRA fixing Radios in



# Learn RADIO Learn RADIO by PRACTICING in Spare Time

# with 6 Big Kits of Radio Parts I Send You

Here's a practical way to learn Radio at home in spare time—to train for a good Radio job, or start your own spare time or full time Radio Service Business! You get Radio EXPERIENCE building real Radio Circuits with kits of standard parts I send. You get solid KNOWLEDGE of Radio, Television, Electronic fundamentals from my easy-to-grasp lessons. You follow the same "50-50" method that has helped hundreds of beginners make \$5, \$10 EXTRA a week in spare time while learning—and prepare for good full time jobs at good pay. time jobs at good pay.

### Future Looks Bright for Trained Radio Technicians, Operators

The Radio Repair Business is booming. Profits are large and peacetime prospects are briging.
Broadcasting Stations, Aviation Radio, Police
Radio, Loudspeaker Systems, Radio Manufacturing, all employ trained Radio men at good pay.

### Be Ready to Cash in on Jobs Coming With Television, Electronics

Think of the NEW jobs that Television, Frequency Modulation, Electronics, other Radio developments promise for the peacetime future. You have a real opportunity. I will train you to be ready to cash in when amazing wartime Radio developments are released for unlimited peace-

### Mail Coupon for Free Copy of Lesson and 64-Page Illustrated Book


I will send you FREE, a sample Lesson, "Getting Acquainted with Receiver Servicing," to show you how practical it is to train for Radio in spare time. And with it I'll send FREE, my 64-page, illustrated book, "Win Rich Rewards in Radio." It describes many fascinating jobs in Radio, tells how you can get started. No obligation—no salesman will call. Just mail coupon in an envelope or paste it on a penny postal.—J. E. SMITH, President, Dept. 5CP3, National Radio institute Piercer Home Starte Padio School Western Institute, Pioneer Home Study Radio School, Washington 9, D. C.

My Course Includes Training in TELEVISION • ELECTRONICS FREQUENCY MODULATION



You build this MEASURING INSTRUMENT

yourself early in the course-use it for practical Radio work on neighborhood Radios to pick up EXTRA spare time



CIRCUIT that brings in local

and distant stations. You get practical experience putting this set through fascinating

# BE A SUCCESS in RADIO Will Train You at Home Sample Lesson FREE

GETTING ACQUAINTED WITH RECEIVER SERVICING

FREE LESSON gives hints on Receiver Servicing, Locating Defects, Repair of Loudspeakers, I.F. Transformer, Gang Tuner Condenser, etc. 31 illustrations, Study it—keep it—use it—without obligation! Mail Coupon NOW for your copy!

### 64 PAGE BOOK SAMPLE LESSON

MR, J. E. SMITH, President, Dept. 5CP3 NATIONAL RADIO INSTITUTE, Washington 9, D. C.

Mail me FREE, without obligation, Sample Lesson and 64-page book, "Win Rich Rewards in Radio." (No Salesman will call. Please write plainly.)

Name......Age....

\_\_\_\_\_





# On the Threshold of Danger— Strange Things Happen!

HAVE YOU ever sensed the imminent danger of a loved one—even though he is across sea or continent? Have you been suddenly awakened by the call of your name—then realize that the one who spoke it was thousands of miles distant? If you ever had these experiences—as millions now have—learn the truth about them.

Love and friendship create a bond of consciousness between humans. This consciousness can be extended to bridge the voids of time and space. When human souls are bared under great emotional stress, then this indwelling faculty is released. Learn that there is far more to life, to the fullness and glory of living, than you suspect.

### **Accept This FREE Book**

Let the Rosicrucians (not a religion), a worldwide organization of thinking men and women, show you that material limitations need not actually separate you from those you love. Convert the mysteries of your being into intelligible, usable laws of accomplishment. Write today for free copy of the book The Mastery of Life. It will explain how you may share these startling truths of self.

Address Scribe: M.L.K.

### The ROSICRUCIANS

SAN JOSE

(AMORC)

**CALIFORNIA** 

# The Insult "CHUMP" Into



HEY, SUGAR. WHY DON'T YOU QUIT THAT **HUMAN SKELETON** AND GET A REAL MAN L

SEE HERE, YOU BETTER SHUT UP



OH, JOE, WHEN ARE YOU GOING YOU POOR CHUMP TO GROW UP AND BE A MAN.



YOU'LL WHAT -

DOGGONE! I'M FED UP WITH BEING A WEAKLING-I'LL GET CHARLES ATLAS'S FREE BOOK AND FIND OUT WHAT HE CAN DO FOR ME !



GOLLY, ATLAS BUILDS MUSCLES FAST! JUST WATCH MY SMOKE NOW!



ONE HAND IS AS THERE GOES GOOD AS TWO WHEN THE BELL -



OUT OF THE WAY SMALL-FRY, MAKE WAY FOR A MAN

O-OH, JOE, YOU'RE MORE THAN



actual photo of the man who bolds World's Most Perfeetly Developed

### I Can Make YOU A New Man, Too in Only 15 Minutes a Day!

HAVE YOU ever felt like Joe—absolutely fed up with having bigger huskier fellows "push you around"? If you have, then give me just 15 minutes a day! I'LL PROVE you can have a body you'll be proud of, packed with redblooded vitality. packed with redblooded vitality!

"Dynamic Tension." That's the se-That's how I changed myself from a scrawny, 97-pound weakling to winner of the title, "World's Most Perfectly Developed Man.

### "Dynamic Tension" Does It!

Using "Dynamic Tension" only 15 minutes a day, in the privacy of your own room, you quickly begin to put on muscle, increase your chest measurements, broaden your back, fill out your arms and legs. This easy, NATURAL method will make you a finer specimen of REAL MANHOOD than you ever dreamed you could be! than you ever dreamed you could be!

### You Get Results FAST

Almost before you realize it, you will notice a general "toning up" of your entire system! You will have more pep, bright eyes, clear head.

real spring and zip in your step! You get sledge-hammer fists, a battering ram punch—chest and back muscles so big they almost split your coat seams—ridges of solid stomach muscle—mighty legs that never get tired. You're a New Man!

### FREE BOOK

Thousands of fellows have used my marvelous system. Read what they say—see how they look before and after—in my book. "Everlasting Health and Strength."

Send NOW for this book-FREE.

It tells all about "Dynamic Tension," shows you actual

photos of men I've turned from puny weaklings into Atlas Champions. It tells how I can do the same for YOU. Don't put it off! Address me personally. Charles Atlas. Department 13, 115 East 23rd Street, New York 10, New York.



CHARLES ATLAS, Dept. 13, 115 East 23rd St., New York 10, N. Y.

I want the proof that your system of "Dynamic Tension" will help make a New Man of me-give me a healthy, husky body and big muscular development. Send me your free book, "Everlasting Health and Strength."

Name			*			œ.		×			œ.		œ		,		*	200		0	œ.			
	Pl	ea	18	e	1	91	ri	n	t	0	r	٧	V	ri	te	•	p	la	ı	n	ly	1		

Address	٠	٠		*	٠	٠	*	٠	٠	*	*	٠	*	*	٠	٠	٠	*	٠	٠	٠

City	State	
Check here if	under 16 for Booklet	A



ever been invented, and if not, how to protect your invention?
Our new 48-page book "Patent Guide for the Inventor" will show you how to proceed with your invention. You'll get a good idea of whether you "have something" or not. Would you like to know how you may judge the marketability of your invention? This book gives you several important tests prepared by authorities. Read of the experiences of Bell, Edison, Westinghouse, and other outstanding, successful inventors who patented and thereby protected their inventions. This book not only tells you how to obtain a patent, it also explains the steps that must be taken afterward to promote the success of your MAIL THE COUPON TODAY to Clarence A. invention. O'Brien & Harvey B. Jacobson, Registered Patent Attorneys, 52-C Adams Building, Washington 4, D. C.

Movement

# NOW Is the Time to PATENT and SELL Your Invention

Now, more than ever before, is the right time to patent your invention. Why? Because manufacturers everywhere presently engaged in war production are looking ahead to the future by buying up patent rights now, so they will have new and attractive items to make and sell for civilian consumption as soon as the war is over. This is what happened during and after the last war. Hence, the smart thing for you to do is to look ahead to the future too. Protect your invention and yourself by applying for a patent now.

### Patent Guide Shows What To Do


Our f'Patent Guide for the Inventor" answers many important questions concerning Patents that inventors constantly ask. It tells what facts, details, drawings, sketches, etc. are necessary to apply for a Patent; how to protect your invention through dated and witnessed disclosure; how to do this AT ONCE to safeguard your rights; how Patent Office Records can be checked to determine whether the invention is probably patentable before filing fees need be paid; discusses costs involved and a practical way these can be paid as the application progresses. It tells how some inventors secured financial backing, how many simple inventions have proved large commercial successes; how Patents covering improvements also can be profitably utilized and marketed; tells countless other facts of interest.

# Why You Need Expert Assistance

The Patent Laws were enacted for your benefit—to give you protection for the features of your invention which are Patentable. But these features must be legally and concisely set forth in the form of "claims." This phase of the procedure is so complex that the Patent Office advises the Inventor to engage a competent Registered Patent Attorney. We maintain a large staff—carefully trained registered patent attorneys—expert draftsmen—experienced searchers—to serve you. We have been serving inventors for more than 20 years.

# Take First Step Now

With the Patent Guide you will receive also Free a "Record of Invention" form which will enable you at once to establish the date of your invention, before you file your Patent application. This step costs you nothing yet may be vital to your success. Remember—in Patent Matters, ACTION is IMPORTANT. Delay can be costly. Mail the coupon in an envelope, or paste it on a penny postcard NOW.



# FREE COPY Mail Coupon Today

### CLARENCE A. O'BRIEN & HARVEY B. JACOBSON

CLARENCE A. O'BRIEN & HARVEY B. JACOBSON Registered Patent Attorneys before the United States Patent Office 52-C Adams Building, Washington 4, D. C.

Please send me your 48-Page "Patent Guide for the Inventor" and your specially prepared "Record of Invention" form FREE. This request does not obligate me.

Name	<b>.</b>
Address	
City	State

- (Please write or print plainly.) - -



Buy as little as \$1500. of this solid protection —or more—at proportionately low rates. But buy your Postal Policy now!

Postal Life of New York has specialized for 40 years in insurance by mail and over the counter. The savings due to this direct dealing are passed on to policy holders. Current dividends 9½%. Further savings are made if premiums are paid quarterly, semi-annually or annually.

### POSTAL LIFE OF NEW YORK

operates under the rigid New York State Insurance Laws and has paid out over

### \$55,000,000.00

to its Policy Holders and Beneficiaries.

Postal issues all Standard Policies to men or women, from ages 10-60, at low cost.

Send coupon today for rates on this Modified "4", Policy at your age and other details. Life Insurance is vital!

### CLIP AND MAIL COUPON TODAY

POSTAL LIFE INSURANCE COMPANY
511 Fifth Ave., Dept. M-433
New York 17, N. Y.
Mail me without obligation complete informa-
tion about your low-cost Modified "4" Policy
at my age.
Name
Date of Birth
Occupation
Address
(Street and No., Zone, City and State)

### **Coming Next Month**

MOVING TROOPS across the oceans by the millions is one of the biggest jobs of global war. How is it done? Alden P. Armagnac will tell you about the ships that carry our armies abroad in the greatest mass movements of human beings ever made. You'll be amazed at the complicated transport system that puts America's fighting manpower on the fronts where it is needed.

THE RED LANTERN of early railroading has given birth to marvelous automatic signaling systems that safeguard modern high-speed trains. Even greater wonders are in store, with radio, radar, and other recent developments ready to start riding the rails. Read about the development of railroad signaling to date and the promise of greater safety and efficiency for the future.

INVADER MODEL. You've read about the A-26, the versatile low-level attack plane that does more jobs well than a Yankee handy man. Here's your chance to build an accurate scale model of this newsmaking aircraft. It's another in our series of easy-to-build modern-warplane models, using the same construction methods that have proved so popular in earlier projects.

FLYING TANKS may be the next step in air warfare. The one weakness of airborne troops—lack of armored vehicles—may be remedied by ferrying whole armored divisions to the airhead by plane. Already we have a flying boxcar that can carry them and land on rough fields behind the enemy's lines. Read this forecast of tomorrow's battles.

WHAT IS COMBAT LIKE? Is it true, as some GI's say, that only a fool isn't scared under fire? Civilians, and soldiers who have not yet smelled powder, always wonder how they would feel in battle. Here's the answer from a man who has dodged Japanese bombs, bullets, and shells all over the Pacific theater.

THE STORAGE BATTERY is a mystery to many people, in spite of the important role it plays in our automobiles, railways, and ships. A pleasant way to get better acquainted with this magic black box is to perform the series of simple experiments that shows exactly what goes on when a storage battery is charged and discharged.



### MODERN BUSINESS WANTS INVENTIONS

Practical and novel inventions are in big demand today. The opportunity for quick money is enticing. Sales sources are many if your invention has merit. But, be sure-before you place your device in strange hands-that it is fully protected. A United States Patent gives you this protection. The first step toward inventive success always isand always has been-the application for a U.S. Patent. There is no other way to protect your invention in accordance with the laws of this country.

MAKE THIS RECORD NOW If you have an invention, and wish to secure it for the future, act at once. Have it dated now and recorded in our office. We will send you this FREE Invention Record Form for the purpose. Fill out the Invention Record Form fully describing the nature of your invention. Make a sketch of its main features. Mail it to us and we will record the date it was received in our office. The earlier the date the better your chance of combating rival inventors who may lay claim to your idea later. Don't delay a single minute in taking this important step. Your whole future may depend upon it. Mail the coupon for our FREE Invention Record Blank and New FREE Book Today!

### HOW WE SERVE YOU AS REGISTERED PATENT ATTORNEYS The U. S. Patent Office

strongly recommends-unless the inventor is familiar with such matters—that he employ the services of a Registered Patent Attorney in the preparation of his Patent Application. We are Registered Patent Attorneys fully qualified to represent you at the Patent Office. We have had long experience in studying hundreds of types of inventions. This gives us the ability to judge your invention and to describe it accurately and convincingly in technical language. It gives us the perception to center arguments upon those details of your invention which, in our judgment, will be looked upon most favorably by the Patent Office Examiner.

Mail the coupon today for our new FREE Book, "How to Protect, Finance and Sell Your Invention," and our FREE Invention Record Form-maybe this step will pave the way to future security for you and your family. Act Today!

We paint no glowing road to fortune-but if you have an invention . . . if it serves a definite new need . . . if the public accepts it—we can tell you it may provide the security and benefits you are seeking.

### McMorrow & Berman

Patent Attorneys 1427 Atlantic Building Washington 4, D. C.

MARCH, 1945

ROFEGIFON

Invention Record

### Know How Successful Inventors Protect and Sell Their Inventions

Our new FREE Book is the latest volume on Inventions and Patents off the press. It's a book every inventor should have. Mail the coupon today for our book "How to Protect, Finance and Sell Your Invention" and learn these important facts—

How to know if there is a prior U. S. patent on your invention.

How to save steps in getting patent action. How we prepare your application for presentation to the Patent Office.

How you may patent an improvement on something in use now.

How to obtain funds to patent and pro-

mote your invention. How to find a buyer or backer for

your invention. How to protect yourself in making royalty agree-

These and many other inven-tive facts you'll learn by reading our new FREE Book, "How to Pro-Book, "How to Protect, Finance and Sell Your Invention.

ments.

McMORROW 1427 Atlantic Building, ... How to Protect. Final Scend me your new FREE book. ... How to Protect. 1427 Attantic Building, Washington A. D. Fing. To Protect form.

Buy War Savings Bonds and Stamps regularly.

# HOW MANY TIMES HAVE YOU SAID . . .



You can play a wind instrument, and play it well, as there's only one line of notes to follow! Don't be content to sit back and listen—make music yourself and be one of the popular group. Anyone who can whistle a tune can play a new Conn. The fingering is simple and the scale comes easily because of exclusive, patented Conn features and advanced design. Plan now to make music your hobby ... and be sure you get a genuine CONN as soon as they are available.



PARENTS—send for "Music, The Emotional Outlet for Youth." See your local Conn

dealer, ot write direct to C. G. CONN LTD., Dept. 332, Elkhart, Indiana.

WORLD'S LARGEST MANUFACTURERS OF BAND INSTRUMENTS

**AUDELS REFRIGERATION &** 

AIR CONDITIONING GUIDE...\$4

New from Cover to Cover—1280 Pages, Fully Illus. Covering basic principles, servicing, operation & repair of household, commercial & industrial refrigeration & air conditioning. A gold mine of essential important facts for engineers, servicemen, users.

### **AUDELS CARPENTERS & BUILDERS** GUIDES-4 Vols. .....

A practical illustrated trade assistant on modern construction for carpenters, joiners, builders, mechanics and all woodworkers. 4 vols., 1600 pages, 3700 illustrations, flexible covers. Pocket size. Each volume sold separately \$1.50 a vol.

AUDELS AUTOMOBILE GUIDE.....\$4 A practical quick ready reference book for auto mechanics, service men, operators & owners. Explains theory, construction & servicing of modern motor cars, trucks, buses & auto type Diesel engines. 1540 pages, fully illustrated. 55 chapters. Indexed. A standard book for mechanics. New fluid drive covered.

AUDELS DIESEL ENGINE MANUAL.\$2 A practical, concise treatise with questions and answers on the theory, operation and maintenance of modern diesel engines including General Motors 2 cycle Diesel. 384 pages, fully illus., flexible binding, pocket size. All details plainly brought out, this book is of extreme value to engineers, operators & students.

AUDELS WIRING DIAGRAMS......51
210 Pages, Illustrated. Gives practical facts on wiring of electrical apparatus. It shows clearly how to wire apparatus for practically all fields of electricity. Each diagram is complete & self-explanatory. Highly Endorsed Pocket Companion.

AUDELS PLUMBERS & STEAMFITT GUIDES-4 Vols.

A Practical Trade Assistant & Ready Reference, Explains in plain language & by clear illustrations, diagrams, charts, graphs, pictures principles of modern plumbing practice including Marine Pipe Fitting and Air Conditioning, 4 Vols.—1670 Pages—3642 Diagrams. Pocket size. Each Vol. Sold Separately \$1.50 a Vol.

388 pages. Illustrated, 11 sections. Clearly written. Essential & important facts, figures, pointers in everyday language. Ref. Index.

AUDELS SHEETMETAL

problems. Covers all phases of sheet metal work including Pattern Cutting, Pattern Development & Shop Procedure.

AUDELS ANSWERS ON

AUDELS NEW MACHINIST &

TOOLMAKERS HANDY BOOK...\$4
Covers modern machine shop practice in all its branches. 5 practical books in 1. New from cover to cover. Tells how to set up & operate lathes, screw and milling machines, shapers, drill presses and all other machine tools. 1600 pages, fully illustrated, 5 x 6½ x 2. Indexed. 5 sections. 1—Modern Machine Shop Practice. 2—Blue Print Reading & How to Draw. 3—Calculations & Mathematics for Machinists. 4—Shop Physics, 5—How to Use the Slide Rule, 60 chapters. Easy to read and understand. A shop

companion that answers your questions. AUDELS MATHEMATICS & CALCULATIONS FOR MECHANICS \$2 Mathematics for home study or reference, 700 pages, 550 illus. Practical mathematics from beginning. How to figure correctly. Easy, correct methods covering a complete review. Iil. & Indexed.

AUDELS HANDY BOOK OF PRACTICAL ELECTRICITY

For maintenance engineers, electricians & all electrical workers, 1440 Pages, 2600 Illus, Covers important electrical information in handy form—including Marine Witten -including Welding. Indexed. A Key to a practical understanding of electricity.

AUDELS RADIOMANS GUIDE. \$4

A key to the practical understanding of radio including Frequency Modulation, Television, etc., Aircraft & Marine Radio. For radio engineers, servicemen, amateurs. 772 pages. 400 Illustrations & Diagrams. Photos. Review Questions & Answers, Reference Index.

Authentic, clear, concise.

AUDELS ELECTRONIC DEVICES. \$2
Tells What You Want to Know About Electric Eye. Easily Understood. Covers photo-electric cells & their applications. Amplifiers, illumination, frequencies, voltage, photocell, tubes, Ohm's Law, wiring diagrams, etc.

methods of electric and acetylene welding including airplane work.

AUDEL, Publishers, 49 W. 23 St., N. Y. 10



### AN AUDEL GUIDE IS A GOOD FRIEND!

Use the brains and experience of others in these Guides of the Trades. Save time and money with right methods, short cuts, labor saving ideas. CHECK NOW! You can look over any Audel Guide in your home. Start the Easy Payments if satisfied.

# ----CUT HERE---


THEO. AUDEL & CO., 49 W. 23 St., New York 10, N.Y.

Please mail me for 7 days' free examination the books marked (X) below. I agree to mail \$1 in 7 days on each book or set ordered, and to further mail \$1 a month on each book or set ordered until I have paid purchase price.

If I am not satisfied with Guides I will return them.

Ξ	☐ Audels REFRIGERATION & Air Conditioning Guid	e 54.
	Audels PUMPS, HYDRAULICS & AIR COMPRESSOR	
=	Audels WELDERS GUIDE	
	Audels BLUE PRINT READING	: 2
-		
		. 1.
-	Audels SHEET METAL PATTERN LAYOUTS .	. 4.
	Audels AIRCRAFT WORKER	. 1.
-	Audels MATHEMATICS and CALCULATIONS	. 2.
	Audels MACHINISTS & TOOLMAKERS Handy Boo	
	Audels DIESEL ENGINE MANUAL	. 2.
	Audels MECHANICAL Dictionary	. 4.
	Audels AUTOMOBILE GUIDE	. 4.
	Audels MARINE ENGINEERS Handy Book	. 4.
	Audels SHIPFITTERS Handy Book	. 1.
-	Gueths MECHANICAL DRAWING COURSE	. 1.
1	Rogers DRAWING and DESIGN	. 2.
=	Audels MILLWRIGHTS and Mechanics Guide .	. 4.
	Audels CARPENTERS and Builders Guides (4 vols.)	. 6.
=	Audels PLUMBERS and Steamfitters Guides (4 vols.	
	Audels MASONS and Builders Guides (4 vols.) .	. 6.
=	Master PAINTER and DECORATOR	. 2.
	Audels GARDENERS & GROWERS GUIDES (4 vols.	
=	Audels ENGINEERS and Mechanics Guides	,
	Nos. 1, 2, 3, 4, 5, 6, 7 and 8 complete	. 12.
=	Audels Answers on Practical ENGINEERING .	: 1
п	Hawkins Aids to ENGINEERS EXAMINATION	. 2.
=	Audels WIRING DIAGRAMS	î.
	Audels Handy Book of PRACTICAL ELECTRICITY	: 4.
=		
•	Audels ELECTRICAL POWER CALCULATIONS	. 2. 10.
-	Hawkins ELECTRICAL Guides at \$1, each	
	Audels ELECTRONIC DEVICES	: 2.
-	Audels ELECTRIC Dictionary	
	Audels RADIOMANS GUIDE	. 4.
	☐ Audels NEW ELECTRIC LIBRARY at \$1.50 a Volu	
	Vols. I, II, III, IV, V, VI, VII, VIII, IX, X, XI, XII	
	Name	
	2 000 000 000 000 000 000 000 000 000 0	
-		

Employed by PSM



### A Free Copy Is Yours for the Asking

How Much Do You Know About the SMITHSONIAN INSTITUTION Its Origin and Activities?

his interesting brochure, beautifully illustrated in four colors, tells a story that is little known. It is being distributed to acquaint you with one of the methods employed by the Smithsonian Institution to enable you to enjoy the benefits of its investigations and research activities.

Write to


# THE SERIES PUBLISHERS INC.

Dept. 108, 11 West 42nd St. New York 18, N. Y.

Buy War Savings Bonds and Stamps regularly.

# How to Make Money by Mail

ness profitably, using expertly for your good fortune the employees, trains, planes which Gov't places at your disposal CHEAP. Get orders by mail, ship by express or freight or mail, get out of the kindergarten... 2nd printing of this book now selling. It's YOUR winner, Make this year and the following years worth more.



THE EASY WAY your present occupation. Do it NOW.

Extraordinary plain, simple skill, know-Extraordinary plain, simple skill, know-how. No theory. Fact story of rich experience of author E. Rice day-by-day. How many times have we heard: "I wish I had some money, this patent would earn me a fortune." or "why can't my crop pay better?" or "I wish I knew how to sell this gadget my-self." or "why should my boss alone do this when I know too how the money is made?" Listen, you do not need money to start this Rice way. His method automatically pays all bills same day rendered, no bank loans, pay bills same day rendered, no bank loans, pay as you go, no borrowing from relatives or friends, no salesmen. Also no worry, quickly a home of your own all paid for. Rice paid off \$5000 in mortgages a year after using this

### 44 Years of PROOF

Sounds fishy? Sure, but this has been done steadily for 44 years, depression or no depression, by the author: that is why he wrote this book to pass the good word along, Make it go with anything you have which is salable. Rice did it with poultry when living in one room in a city lodging house. Turn your city or country home, your work, your hobby, into money. How to get orders at cost of only \$4 for each \$100 taken in. The popular error to avoid in trying for sales, Business won free while others have to pay for it. How to conceive the money-getting advertisement.

Profitable changes from ordinary ideas and methods, Not usual cut-dried pattern, 60 adventures, a dictated book in everyday talk, no dictionary writing. Take a chance on this book being worth a fortune to

Take a chance on this book being worth a fortune to you and yours and send \$2.50. Book mailed same day order is received. Or ask two friends to chip in 83 cents each with your 84c to get this book. Hundreds of buyers whose letters we show you declare emphatically its superlative goodness. Follow its easy pattern for Success. Cloth-bound, 512 pp., 812 by 512. Best seller, 2nd edition now selling. Cut out the \$2.50 HOW BOX here, pin or stick it to sheet of paper bearing your name and address, mail in envelope with money order or check for \$2.50 to

HOW \$**9**50

HOWARD ST. HOUSE, Melrose 76E, Massachusetts

Most well-paid positions demand high school training. Without it, or equivalent, you can't advance to the full extent of your abilities in any trade, business or profession. Whatever your age, however you're situated, IT ISN'T NECESSARY TO STRUGGLE UNDER THAT HANDICAP. I.C.S., famous for more than 50 years, enables you to start your own high school in your own home. You're in a class by yourself—study in your spare time—acquire a high school education at astonishingly low cost. Authoritative texts! Rapid Progress! Write today for free booklet.

International Correspondence Schools, Box 7613-L. Scranton 9, Pa.

# SHORTHAND

Famous Speedwriting system, no signs or symbols, preparation for a job. Surprisingly low cost. 100,000 taught by mail. leading offices and Civil Service. Write for free booklet. Speedwriting, Dept. 2603. 55 West 42 St., N. Y. 18 Used in leading offices and Civil Service.



Light Switch

LUMINOUS PAINT

101 Uses

SEND NO MONEY Complete original Magi-Glo Kit only \$1.29. Send name, address, pay postman plus postal charges, Send cash, we pay postage, SATIS-FACTION OR MONEY BACK, MAGI-GLO, Dept. 19, 32 W. Randolph, Chicago 1, III.



### I'll Show You a New, Fast Way to Test Radio Sets without Mfg. Equipment

The very same Radio parts I supply with your Course for gaining pre-experience in Radio work may be adapted through an exclusive Sprayberry wiring procedure to serve for complete, fast, accurate Radio Receiver trouble-shooting. Thus, you do not have one cent of outlay for manufactured Test Equipment, which is not only expensive but scarce. In every respect, my training is practical, complete... tested and proved for results. It will give you the broad, fundamental principles so necessary as a background, no matter which branch of Radio you wish to specialize in.

### COUPON

F. L. Sprayberry, President Room 5535, Pueblo, Colorado.

Please rush my FREE copies of "How to MAKE MONEY in RADIO, ELECTRONICS and TELEVISION," and "HOW TO READ RADIO DIAGRAMS and SYMBOLS."

City.....State..... (Mail in plain envelope or paste on penny postcard)

# Choose Your Road to a Postwar Aviation Career



# START TRAINING NOW AT ERO TE



Select one of the eight modern courses available at Aero Tech. Train where complete shops, laboratories and classrooms have started many civilians and servicemen on successful aviation careers.

### ... TO VETERANS OR SERVICEMEN

Expand your aviation knowledge by planning now to enroll in Aero Tech's special, advanced courses. This will insure your post-war opportunities in the new "aviation age," which will require trained, alert men by the thousands.

### .. GREATLY EXPANDED COURSES

New requirements by commercial aviation, worldwide airlines, service depots, feeder lines...have created many new courses now offered by Aero Tech. Always up-to-the-minute, Aero Tech steps ahead with special plans for the "aviation age of the future."



Approved by CAA for Aircraft and Engine Mechanics Training

Civilian

### **GET COURSE BULLETINS NOW...** New classes now forming

Thousands secured their start from this institution...thousands more will secure a "priority" on their careers by attending Aero Tech in the near future. Send coupon for free bulletins NOW-act today!

AERO INDUSTRIES TECHNICAL INSTITUTE

Herbert W. Hartley, President

5247 W. San Fernando Rd., Los Angeles 26, Calif.

**AERO INDUSTRIES TECHNICAL INSTITUTE** 5247 W. San Fernando Road, Los Angeles 26, Calif. Gentlemen: Please send free bulletins, and data on courses checked: ☐ Aircraft Mechanics ☐ Airport Management ☐ Instrument Technician ☐ Flying (all licenses) ■ Aeronautical Engineering ■ Engine Mechanics ☐ Flight Engineer Dispatcher Street

Buy War Savings Bonds and Stamps regularly.

In Service

Zone

State

Veteran

### "It is the BEST Handy-Sized Dictionary!" ACTUAL use proves that WEB-STER'S COLLEGIATE defines all the most commonly used words -is the BEST, 1,300 pages; 110,000 entries; 1,800 pictures; abridged from "the Supreme Authority"-WEBSTER'S NEW INTERNATIONAL DICTIONARY, Second Edition. \$4.00 to \$8.75, depending on bindings. G. & C. Merriam Co., Springfield 2, Mass. COLLEGIATE DICTIONARY FIFTH EDITION

YOU MAY HAVE TO WAIT for your copy of Webster's Collegiate. Paper rationing, plus heavy government needs, plus unprecedented public demand, make it impossible to supply everyone promptly. Your bookseller will do his best to provide your copy with the least delay. Also ask to see:

WEBSTER'S DICTIONARY OF SYNONYMS WEBSTER'S BIOGRAPHICAL DICTIONARY

RADIO ENGINEERING. Broadcasting, Servicing, Electronics, Aviation, Marine & Police Radio taught thoroughly.

48 weeks' Engineering course equivalent to 3 years' college radio work. All expenses low. Co-

educational. Catalog upon request. Valparaiso Technical Institute. Dept. 503 Valparaiso, Ind.

### TUDY AT HO

With A Chartered Educational Institution
Courses in ENGINEERING: Electrical, Civil, Mechanical, Drafting,
Architectural, Steam, Aeronautical, Radio, Structural, Mining, Industrial, Highway, Petroleum, Marine, Chemical,
Courses in ARTS AND SCIENCES: Philosophy; Education; Letters;
Public Health; Medical Jurisprudence; Psychology; Sociology; Physics;
Chemistry; Geology; Pol. Science: Theology; Law; Business and
Commerce; Accounting; Mathematics; Statistics; Agriculture. McKinley-Roesevelt Incorporated, 4610-AC, Sheridan Road, Chicago, 40, Illinois

P. O. No. 9752 Ad. No. 9L



The fascinating field of Art offers commercial opportunities to men and women. COMMERCIAL ART, CARTOONING, DESIGNING all in one complete course. TWO ART OUTFITS furnished. Learn to draw step-by-step. Trained Ar-


tists are capable of earning \$30, \$50, \$75 a week.
Write today for full information in FREE BOOK,
"Art for Pleasure and Profit." Mail coupon now.

### FREE BOOK gives details

Washington School of Art, Studio 133P 1115-15th St., N. W., Washington 5, D. C. City......State....

# To Help You Learn AD Control of Half Electronics Half Faster Easier





### Make 133 Fascinating Experiments In Spare Time At Hon

THINK OF IT—real radio parts and sup-assemblies—Eight Big Kits of them—enough genuine parts to assemble not one but Six Radio Receiving Circuits that work. You build a Super-Het, a Short-Wave, a Long-Wave Aviation Band Circuit, a Light Beam Transmitter, a Wireless Microphone, Electric Eye devices, a Radio Telephone and scores of other fascinating projects. DeForest's unique "Block System" speeds

ects. DeForest's unique "Block System" speeds
building of new circuits—gires you valuable "Learn-By-Doing" experience at home—helps you prepare effectively for today's many grand
Radio-Electronic opportunities. Get the complete facts! Mail coupon
today for big, free book "Victory For You." You also get the colorful
Kit Folder that tells about some of the many exciting experiments
you build from DeForest's "Home Laboratory."

### GET INTO RADIO AND ELECTRONICS

See how you may prepare in your spare time at your home—and without interfering with your present position—to get into the vast, Billion
Dollar Radio field that needs so many trained men Today, and that
promises many exciting postwar opportunities. Find out about the
opportunities ahead of F. M. Radio, Two-Way Train Radio, Radio
Manufacturing, Police Radio, Broadcast Radio, Motion Picture Sound
—about the postwar possibilities of Television—about the opportunity
to be your own boss in your own Radio Business.

### GET FACTS ABOUT THIS MODERN FIELD

... that offers so many real money-making opportunities for the trained man who is on his toes. Mail the coupon Now—Today. Do this! Find out about this Newer... Brighter future facing you in the grand field of Radio and Electronics. See how DeForest's helps you make your start by means of its effective "A-B-C" Training method.

### YOU GET EMPLOYMENT SERVICE

DeForest's also provides its students and graduates with an effective EMPLOYMENT SERVICE that has long-established contacts with employers who use many DeForest's trained men. Mail the coupon today!

VETERANS: Check coupon at right for Special Information

Deforest's Training, INC. CHICAGO 14, ILLINOIS

### "Learn-By-Seeing" Movies — Add Life to Lesson Texts

You Get Movies—exciting training films which you project in your own home! How much more Interesting it is to grasp important fundamentals when right on the wall of your room you are able to see Radio waves in motion...circuits come to life... Electrons on the march. Thanks to the use of a genuine DeVRY movie projector and 12 reels of exclusive training films, you see Radio-Electronic actions otherwise hidden from the eye. Think how much it will help you, to actually see In Motion the principles of what you are learning. DeForest's modern training, alone, provides this valuable aid to learning Radio-Electronics at home.

### 90 LOOSE-LEAF LESSONS . . . .

Where else can you get such a combination of proved major training features as—(A) 90 modern, well-illustrated loose-leaf lessons prepared under the supervision of Dr. Lee DeForest, often called the "Father of Radio"; (B) the use of "Learn-by-Seeing" home movie training films and a genuine DEVRY movie projector; and (C) the use of many practical Radio parts? You be the judge. No obligation.

Deforest's Training Offers Instruction in Motion Picture Sound Equipment, FM Radio and Television



You Use Both

with DeFOREST'S




E. B. DEVry, President,
DeForest's Training, Inc., Dept. P S.B3
2535-41 N. Ashland Ave., Chicago 14, Illinois
Please send me—FREE and WITHOUT OBLIGATION—illustrated book, "VICTORY FOR YOU,"
and Kit Folder.

and Kit Folder.	
Name.	

/194/638,	
City	State

IN COME SECT OFFI THE THE SECT OFFI SECT OFFI

☐ If under 16, check here for special information. ☐ If a veteran of World War II check here.



George A. Owl's prize-winning design (top) for the plane he'd like to own featured the "ruddervator" tail. Compare it with this new Beechcraft AT-10

### Postwar Plane's V Tail Is Already in the Air

I NOTE that the V-tail idea was used in one of the entries for your very interesting contest "The Plane You'd Like to Own." Of course it had been in the works here for some time before your contest results appeared, but the soundness of your contestant's idea gains striking proof from the enclosed picture of the modified Beechcraft AT-10 trainer in flight.—Wm. H. McDaniel, Beech Aircraft Corp., Wichita, Kans.

### Bunk Thoughts on Molecules from a GI in France

CURIOSITY killed a cat, says the old saw, but history teaches that directed curiosity has led to many an important scientific discovery. While goldbricking on my GI bunk this morning, I gave birth to a question in abstract science. If any fellow P.S.M. reader knows the answer, I wish ye editor would let him give it in these columns.

We know that a pulsating or alternatingcurrent magnetic field will so agitate the molecules of a piece of iron that heat is evolved. That is, a moving field causes comparatively still molecules to go into a jitterbug dance "hot" enough to melt even metals, as in the case of the induction furnace. But now suppose we start off with a white-hot



piece of iron instead of a cold one. Could a powerful stationary magnetic field bring the rapidly vibrating iron molecules back to comparative rest faster than by ordinary cooling? And if so, would there be any other effect produced in the iron—an alteration in its temper, let us say, for better or for worse?

Being in France at the moment, I'm in no position to experiment, but I suspect that if a high-frequency field can cause molecular motion, then, conversely, a stationary field could be used as a "molecular brake" to arrest that motion. Who knows the right answer? P. S.M. is a great source of inspiration and vitamin-loaded food for thought.—Pfc. A. V., New York City.

# P.S.M. Molded His Career —and in Plastics, Too

As a regular reader of P.S.M., I felt that a bond existed between me and a young man who sat beside me on the bus. He was carrying copies of the magazine. So I said, "What do you think of that book?" "I like it fine," he replied with enthusiasm. "Been reading it for several years. In fact, it was through Popular Science that I got into my present work." I asked him what that was, and he said, "Plastics." Thought you'd be interested to know that you people at P.S.M. are helping to shape careers.—E. F. Z., New York City.

### Another Plane-Contest Winner Tells About Himself

You may be interested in the following information about me that was not included in P.S.M. with reference to my winning second prize (professional class) in "The Plane You'd Like to Own" contest. I am 24

years old. Prior to entering service, I was employed as inspector by the Glenn L. Martin Co., Baltimore, Md. I have studied some mechanical and aeronautical engineering, and hope some day to become an aircraft engineer. At present I am studying aviation metal-smithing in the Navy—Robert



in the Navy.—Robert C. Kelley, S 2/C AM., Class 23A, N.A.T.T.C., Norman, Okla.





The 1945 Wearever Zenith is fashioned with utter precision . . . the uncompromising standards of precision applied to the making of a fine telescope.

Telescope Precision! Its value is reflected in the skillful "C-Flow" feed, the accurate 14-carat gold point, the balance and beauty of ruby-topped Wearever Zenith. See ... try ... buy the Zenith. Made by David Kahn, Inc.





### Two Readers with But a Single Thought—and a Good One


Your new visual filing aid—a red stripe on the back of Popular Science Monthly—is excellent, and I want to compliment you on this idea. However, may I suggest that the stripe for ensuing years should be of various colors so the books may be easily segregated as to years as well as months? Or the stripe may be a diagonal in the opposite direction for the following year, so that a two-year group will form a large V. "Readers Say" is the first section of P.S.M. that I read. How about a little more of this department?—A. F., Warren, Pa.

I THOUGHT the idea of the stripe on the back of P.S.M. was swell, and I dashed out to show my wife the picture of the rack and magazines. She liked the idea, but said, "Why don't they make the stripe a different color for each year?" Well, why not? I look forward to many more years of pleasure in P.S.M. and the new idea.—C. E. C., Larkspur, Calif.

### Revolving-Door Generator Seems to Have Drawbacks

I WOULD like to make a few comments on J. H. Van B.'s letter, in which he suggested gearing up generators to revolving doors to supply electricity to storage batteries, which would in turn run the neon signs, thus saving coal for the power companies. I suppose it would save a little coal, but the extra energy required to use the revolving doors would have to be supplied by the people

using them. This would mean that these people would need to consume enough extra food to make up for this energy, so instead of wasting coal, we'd waste food, and, as well, have to use batteries and generators needed by our armed forces.—H. E. S., Dupont, Ind.



26

Training is essential to advancement in any field—and it's important to have it on record.

International Correspondence Schools' sound and practical training goes on record—and counts in the record. I. C. S. regularly reports the progress of its students to their employers, regularly receives letters expressing appreciation for this service.

A typical employer communication notes: "I have every I. C. S. report on my men filed with their personal records, the records which help to determine any action taken in regard to those men."\*

YOU want your record to show you have trained for promotion.
YOU want your employer to know that you have prepared yourself for larger responsibilities. Then act now to obtain that training.
I. C. S. Courses cover more than 400 business and technical subjects.
The coupon brings full information.

\*Name furnished on request



### INTERNATIONAL CORRESPONDENCE SCHOOLS



### BOX 7611-L, SCRANTON 9, PENNA. Without cost or obligation, please send me full particulars about the course before which I have marked X: ☐ Ship Drafting ☐ Ship Fitting ☐ Shop Practice ☐ Steel Mill Workers ☐ Tool Designing ☐ Textile Designing ☐ Woolen Manufacturing **Electrical Courses** Air Conditioning and Plumbing Courses ☐ Air Conditioning ☐ Heating ☐ Plumbing ☐ Refrigeration ☐ Steam Fitting Electrical Drafting Electrical Engineering **Business** and ☐ Power House Electric ☐ Practical Electrician Academic Courses Accounting Advertising Arithmetic Bookkeeping ☐ Accounting ☐ Welding, Gas and Electric ☐ Practical Telephon, ☐ Telegraph Engineering Chemistry Courses Chemical Engineering Radio Courses Business Correspondence Internal Combustion ☐ Electronics Business Management Certified Public Accounting College Preparatory Chemistry, Analytical Radio, General Chemistry, Industrial Chemistry, Mfg. Iron & Steel Petroleum Refining Plastics Pulp and Paper Making Engines Courses Auto Technician Aviation Radio Operating Diesel-Electric ☐ Radio Servicing Commercial Cost Account Commercial Diesel Engines Gas Engines Cost Accounting Railroad Courses Civil Engineering, Archi-Mechanical Courses ☐ Air Brake ☐ Car Inspector ☐ Locomotive Engineer | Architectural Drafting | | Architectural Drafting | | Architecture | | Bridge and Building Foreman | | Building Estimating | | Civil Engineering □ Coal Min | | Contracting and Building | | Highway Engineering | | Lumber Dealer | | Reading Structural Blueprints | | Sanitary Engineering | | Structural Drafting | tectural and Mining Aeronautical Engineering First Year College ☐ Airplane Drafting ☐ Flight Engineer ☐ Foundry Work ☐ Heat Treatment of Metals Foremanship ☐ Locomotive Fireman French ☐ Railroad Section Foreman Good English Steam Engineering Courses High School Higher Mathematics Boilermaking Combustion Engineering Combustion En Illustrating Motor Traffie Industrial Metallurgy Engine Running Mechanical Drafting Marine Engineering ☐ Mechanical Engineering ☐ Mold-Loft Work Postal Service Salesmanship ☐ Patternmaking ☐ Reading Shop Blueprints ☐ Sheet-Metal Drafting ☐ Sheet-Metal Worker Secretarial Sign Lettering Structural Drafting Structural Engineering Textile Courses Cotton Manufacturiae Rayon Weaving □ Spanish Stenography Traffic Management Surveying and Mapping Canadian residents send coupon to International Correspondence Schools Condition, Lid., Montreal, Canada, British residents send coupon to I. C. S., 71 Kingsway, Lond., V. C. 2, England. DISCOUNT TO DISCHARGED VETERANS-SPECIAL TUITION RATES FOR MEMBERS OF THE ARMED FORCES

# **NEW SECURITY PLAN** PAYS DOCTOR and HOSPITAL BILLS



### INDIVIDUAL or FAMILY

Insure NOW, before it's too late! Protect your savings against Hospital expense. Here's an amazing offer of safe, dependable coverage under America's most popular Hospitalization Plan. Family or individual eligible. No Medical Examination. When sickness or accident strikes, you may go to any Hospital in U.S. or Canada under any Doctor's care. YOUR EXPENSES WILL BE PAID exactly as Policy specifies. WAR coverage included. The Company under supervision of the Insurance Dept. No agent will call.



### MAIL COUPON AT ONCE!

NORTH AMERICAN MUTUAL INSURANCE CO. Dept. PS5-3, Wilmington, Del.

Please send me, without obligation, details about

your "3c A Day Hospitalization Insurance Plan".

------

Address------

City----- State-----

Readers Say:

### Maybe This Is the Last Word in the Monkey-Wrench Controversy

I HAVE been closely associated with the hardware business since my grandfather had a store in Binghamton, N. Y., some 70 years ago. When I was a boy, I was told that the name "monkey wrench" came from the resemblance of the tool to the "monkey on a stick," which



was a popular toy. You pulled a string and the monkey climbed up in a very life-like manner. Also, the wrench when closed looks a bit like a monkey.-C. C. F., Seattle, Wash.

### Molecules Bump Their Little Gums and Light Up the Place

Tell S. F. C., Jr., that the Scotch Tape phosphorescence phenomenon is caused by molecular friction; just the molecules of sticky cement bumping their little gums against the cellulose material of the tape when he jerked it away from the wall. Unroll a package of black friction tape in a dark room and you will see a line of fire where the tape separates from the roll. Jerk it a little at a time and the fun lasts longer. You can generate static electricity this way, too. Disconnect the ground wire of your radio, but retain the aerial if there is any; then turn the volume way up, and tune off the station. Now unwind your roll of tape close to the aerial post. If you do this on a very dry day, you'll get the most awful noises you ever heard. This is worth the work of rolling up the tape again.

Did you know that you could crush a lump of sugar in the dark and get a distinct glow? You can: it's sort of purplish white most of the time. When the little molecules are pulled or pushed that violently, their cries are so high-pitched that they generate light instead of sound. I hope this explanation pleases S. F. C., Jr., and will give him some

fun as well .- O. P., Jefferson City, Mo.



Hundreds of Industries Need Radio and Television Men Now and for Great Future Demands

The man trained in electronics is wanted not only in Radio and Television, but in Aviation, Transportation, Communications, ... in the designing, engineering and operation of hundreds of industries today and for years to come. Learn how great the field is for YOU... How you may GET INTO BUSINESS FOR YOURSELF. Mail the coupon now.







### Learn by Doing!

Use real Radio Equipment Furnished with your Course



Experience
is the best
teacher. You
learn by experience with
the exclusive
N a t i o n a l
Shop - Method
o f H o m e
Training—actually
its and do experi-

build many circuits and do experi-ments with the big kits of standard radio parts included in your trainequipment at no extra cost to

Build a superhetero-dyne receiver. Make tests and conduct ex-periments that show you the why and how of electronics. Build an audio oscillator, signal generators and other instruments with the parts and supplies the parts and supplies included in your course.



"F.M." Means Future Money Frequency Modulation (F.M.) ishere

on (F.M.) Is here
to stay. Thousands of F.M.
licenses have
been granted by
the government
F.C.C. all over
the country. Learn what this means to you. Get ready for TELEVISION.
Get your share of the RADIO
SERVICE Business. Here is a
sensationally improved way for
you to get the right training—
a thoroughly proved system
whereby you study in spare
time—odd hours, even minutes—
and have the advantage of actual
shop experience behind you.
This exclusive shop method of

This exclusive shop method of home training comes to you right from one of the world's greatest vocational educational centers— the resident training shops and exthe resident training shops and ex-perimental laboratories of National Schools. It is the sound, practical training based on actual experi-ence of qualified instructors and engineers who have prepared thousands of National graduates now employed in the radio in-dustry. dustry.

It is up-to-date-matches the ogress constantly being made progress constantly being made in modern radio, television and electronics. It is time tested. National Schools has been training men for higher pay and greater opportunity for more than a third of a century. Fill out and mail the coupon below for details.

### Shop Method Training Wins Good Jobs



"My latest offer was \$5,800.00 as Radio Photo Engi-neer . . . but I'm doing well where I Joseph Grumich, Lake Hiawatha,

"Due to my training at National I was selected to instruct in the laboratory work of Navy and Marines."—
R. R. Wright, Blackfoot, Idaho.





"I believe Na-tional offers the best course to be had. . . . Keep up the good work."—O. K. Ivey. Washington, D. C.

Read what hundreds of other enthusiastic students have writ-ten about National Training. Send in your coupon today.



Now, right now, is the time
to prepare for SUCCESS AND SECURITY in the great expansion after the
war. The field is
wide open. Trained
men will get the
preference in the
broadcasting stations—in industry tions—in industry— will make quick progress with small capital in their own

capital in their own business. Soldiers, sailors and marines make use of your free time to get ready for the future. Study while still in uniform. Thousands of men in the armed forces have trained at National Schools under U. S. Government sponsorship.

### See for Yourself

Now, right now, is the time to grasp the great opportunity of today—a successful career for tomorrow. Get into the big money, rapid advancement, a position of importance. A BUSINESS OF YOUR OWN. The industry is crying for trained men everywhere. A rapidly expanding business—probably the greatest in industrial history—holds out the promise of a rich future—prosperous security. But to win it you must be ready. Well-trained men ONLY are wanted.

Examine the National Shop Method of Home Training carefully. Be con-vinced. Study the lesson we will send you FREE. No obligation of any sort. Fill out the coupon and mail it today.



Learn for yourself just how easy this SHOP METHOD HOME TRAINING gives you the practical, down-to-earth experience you can never get from theory alone.

### NATIONAL SCHOOLS

	LOS ANGELES	37, CALIF	ORNIA EST. 1	905	TOWN IN	的自由的
П	OPPORTL	MITY	COUPON	FOR		

1011011	too mitottee or, enti	Country Courted	TOTAL CONTRACTOR
AIL	OPPORTUNITY	COUPON FOR	QUICK

National Schools, Dept. 3-PS 4000 South Figueroa Street, Los Angeles 37, California

(Mail in envelope or paste on penny post card)


Mail me FREE the two books mentioned in your ad including a sample lesson of your course. I understand no salesman will call

NAME	AGE
Market and the second of the s	

Include your zone number

Buy War Savings Bonds and Stamps regularly.

AUDELS Carpenters and Builders Guides



inside Trade information for Carpenters, Builders, Joiners, Building Mechanics and all Woodworkers. These Guides give you the short-cut instructions that you want—including new methods, ideas, solutions, plans, systems and money saving suggestions. An easy progressive course for the apprentice and student. A practical daily helper and Quick Reference for the master worker. Carpenters everywhere are using these Guides as a Helping Hand to Easier Work, Better Work and Better Pay. To get this assistance for yourself, simply fill in and mail the FREE COUPON below.

### Inside Trade Information On:

How to use the steel square-How to file and set saws—How to build furniture—How to use a mitre box—How to use the chalk line—How to use rules and scales—How to make joints—Carpenters arithmetic—Solving mensuration problems—Estimating strength of timbers—How to set girders and sills—How to frame houses and roofs—How to estimate costs—How to build houses, barns, garages, bungalows, etc.—How to read and draw plans—Drawing up specifications—How to excavate—How to use settings 12, 13 and 17 on the steel square—How to build hoists and scaffolds—stylights—How to build stairs—How to put on skylights—How to build stairs—How to put on interior trim—How to hang doors—How to lath lay floors-How to paint



### THEO. AUDEL & CO., 49 W. 23rd St., New York City

Mail Audels Carpenters and Builders Guides, 4 vols., on 7 days' free trial. If O.K. I will remit \$1 in 7 days, and \$1 monthly until \$6 is paid. Otherwise I will return them: No obligation unless I am satisfied.

Name	
Address	
Occupation	
Rejerence	PSM

### Learn REFRIGERATION and AIR-CONDITIONING

### ARE YOU HANDY WITH TOOLS?

Exceptional opportunity for men of all ages up to 60. The demand for repair and service mechanics in both REFRIGERATION and AIR-CONDITIONING is acute and will continue after the war. You can easily and quickly-

### Learn to Be a Service Mechanic at Home or in Our Shops

Our practical, thorough course is easy to grasp and can be studied at home in your spare hours. No previous experience is needed. A common school education is enough. Learn how to start your own business with \$50.00 worth of tools in garage or basement. Open up your own shop or take a well paid job in this active field.

START YOUR OWN DEDAIR SHOP Write for free booklet today. No obligation

ALI AIR SHOT	MAIL COUP	ON TODAY	
Send for 1	FREE BO	OKLET!	
Mechanics 4701 W. Pico, De Dear Sirs: Plea free catalog and	pt. S-3, Los An	geles 6, Calif. without obli	
Name			
Address			8552
City		State	

# Get into Good Paying



BIG DEMAND in Auto Body and Fender work. Start training now spare time at home for good pay work now and postwar. Practical shop experience included. U.E.I. Training covers metal work, welding, painting, etc. Placement service-or we will show you how to start own shop. Behind U.E.I. TRAINING is a large national organization founded 1927. Write today for Free Facts—No obligation

BUTO CRAFTS . UTILITIES ENGINEERING INSTITUTE 1314 BELDEN AVENUE, DEPT. 335-X, CHICAGO 14, ILLINOIS



STUDY AT HOME Legally trained men win higher posi-tions and bigger success in business and public life. Greater opportunities now than ever before. More Ability: More Prestige: More Money We guide you can train at home during spare time. Degree of LL.B. We furnish all text material, including 14-volume Law Library. Low cost, easy terms. Get our valuable 48-page "Law Training for Leadership" and "Evidence" books FREE, Send for them NOW.

LASALLE EXTENSION UNIVERSITY, 417 South Dearborn Street A Correspondence Institution Dept. 383-L Chicago 5, Ill.

### MECHANICAL

### ENGINEERING PAYS!

This is the machine age. And back of every machine—every part—are the engineers who designed it, the trained mechanics who built it. No wonder there's high pay . . . many opportunities to advance . . . for these indispensable men. Be one of them! Don't stick in a rut! Let I.C.S. show you the way to success! These Schools, famous for more than 50 years, offer authoritative, practical Courses to meet the needs of almost any man in mechanical trades. Mechanical Engineering . . . Drafting . . . Mechanical Drawing . . . Shop Practice. Write today for free booklet.

International Correspondence Schools, Box 7613-L, Scranton 9, Pa.



You can learn plain, rapid writing or fancy ornamental writing for social and business advancement, right in your own home during spare time by my Simplified Method. Write for my free book, "How to Become an Expert Penman," which shows what others have ac-complished by taking my Courses, Send 10c for one of my favorite Pen Points and your name with a beautiful flourished bird written on a card. Write today.

T. M. TEVIS, BOX 25R, CHILLICOTHE, MO.

ARTHRITIS - NEURITIS - SCIATICA Why continue to suffer the agoniz-ing pains of these diseases when the usual remedies have failed? Learn about a new trustworthy, modern,

treatment method. This marvelous non-surgical treatment is completely explained in the Ball Clinic's FREE Book. Write today. No obligation.

BALL CLINIC, Dept. 5100, Excelsior Springs, Mo.



This Horseshoe Ring, Handmade, Hand - engraved, inlaid with simulated pearl, is a KNOCKOUTI Shoeand shank of everlasting Monel Metal is

### **GUARANTEED 20 YEARS**

Supply is limited . . . rush your order! SEND NO MONEY. Pay Postman only \$3.85, plus excise tax and postage. Return for refund in five days if not delighted. State size. Address:

AMERICAN JEWELRY CO., Wheeling, W. Va.

IIIIIIIIIII





IF YOU are interested in a future in commercial art or in just dabbling around for

NO MONEY

your own atisfaction . . . you'll find each of these .ateway books a real help.

- 3. LETTERING and DESIGN. Covers every style of letter and design used in modern advertising used in national magazines and campaigns. Includes Trademarks, Monograms, Numerals and Package Design—270 pp..\$3.00
- 4. MODERN LETTERING . . . . . . . . . . . \$1.00
- 5. ART OF CARICATURING ......\$2.00
- 6. HOW TO DRAW FUNNY PICTURES.\$2.00

### HOMECRAFT

- 7 REFRIGERATION SERVICE ENGINEER.
  Includes domestic and commercial types of refrigeration such as used in markets, milk depots, soda fountains, flower shops, etc., as well as in many air conditioning systems and homes. 300 pages, illustrated.....\$2.00
- 9. PRACTICAL ELECTRICITY and HOUSE WIRING. Discusses basic principles of circuits, wires and insulation, grounding.
- 10. MODERN HOMECRAFT. 240 pages crammed full of ideas for modern furniture... and how to make it. Gives working drawings. Make your own furniture and SAVE. 240 pages... fully illustrated......\$3.00
- 11 QUICK CONSTRUCTION. Includes tem-problems, special uses of tools, concrete prob-lems, stairs, shingles, cornices, "Tricks of the Trade" and hundreds of other useful sub-jects for the amateur or professional carpenjects for the amateur or professional carpen-ter. 250 pages-670 illustrations.....\$2.00
- 12. BUILDING—FORMS, STAIRS, ROOFS, Staircases and roof-building. Top notch book for carpenters or helpers, 210 pages, 495

antee. You take no chances.

- 14. FURNITURE, FURNITURE FINISHING, New book that covers: 1, Period Furniture: 2, Furniture Decoration: 3, Furniture Finishing: 4, Furniture Patching: 5, Modern Special Finishes, 580 pages and 353 illustrations....\$4.00
- 15. PLUMBING INSTALLATION and RE-PAIR. 236 page book explaining how to do repair jobs such as leaky faucets, clogged to detains, traps, vents, sewers, etc. Tells how to cut pipe, make pipe joints, and install fixtures. Tops for the home. 153 illustra-52.00

### ELECTRICITY

- 16. CYCLOPEDIA OF RADIO and ELEC-TRONICS. A complete non-technical reference book of 1,000 pages, 1,700 head-ings, 1,178 illustrations, 130 tables, and 105 graphs cover over 500 definite articles, .\$5.00
- 17. ELECTRICAL and RADIO DICTIONARY.
  Over 3,800 definitions of technical
  words and terms used in all branches of
  radio and electricity. 300 pages, 550 illustrations. \$2.50
- 18. PRACTICAL ELECTRICITY and HOUSE work, 200 pages, 227 illustrations...,\$1.50
- 19. SLIDE RULE and LOGARITHMIC TA-and logarithmic tables fully covered. Includes even 10 place log tables, 200 pages...\$1.50

### PAINTING AND DECORATING

20. THE MIXING OF COLORS and PAINTS. How to mix colors for interior decorating. Covers house painting, arts, crafts, general paint mixing methods. A handy book

- 23 HOUSE PAINTING METHODS. 400 pages and over 150 illustrations cover the subject of house painting (of any surface) thoroughly . . . includes instructions on use of spray guns, paints, thinners and tricks of the trade. A real time and money saver. \$2.00
- 24. CYCLOPEDIA OF PAINTING and DEC-ods, tools and materials for the home and the workshop, in-cluding every branch of painting and doc-

of painting and decorating from A to Z. Any particular job is fully explained with illustrations to clarify the text, whether the reader is interested in finishing walls, floors, furniture, automo-biles, boats, houses, or in fact anything which has to do with painting or decorating methods. 350 pages-288 illustrations-

So, take advantage of the knowledge and experience of experts NOW. Let them show and tell you how to make your time pay more money. Prepare now. Study this list of authoritative books . . . choose the ones you want. Remember . . . Gateway books are sold only on a 5-day money back guar-



### GATEWAY PUBLISHING CO.

Dept. P.S.-3, 53 W. Jackson, Chicago 4, III.

D	ept		P.	s.	-3,	5	3	w	٠,	aci	ks	on,		hi	ca	go	4,	11	Hir	ois															
Į×	K. Mta fui	域的	٠.	11	111	ny	- 11	HUU	I'	ve is	ci	rel t	ed	l, e	C.C	1.0	), ati	r'll sfa	l p	ny	pe	istr I w	nn	n e	rtt	to	f b	5	da	plu ys	s aı	a fo	yo	u	wi
1	2	3		4	5	6		7	8	9	1	10	1	1	1	2	13		14	1	5	16		17	1	8	19	. :	20	21		22	2	23	2
Safe	ve	.1	01	in in	-e	ne'	los	se na	fu	II y	cu	nt.	of	Su	1114	k e r	ane	1 y	we b	wi	11	pa	y	the	e	T	tag he	Pu	say	she	rs	you	. (	c.0	, I
N	ame	e					٠.					٠.					٠.	٠.		٠.	٠.		٠.		٠.		٠.	٠.	٠.					٠.	
A	ldr	es.								•••			٠.			٠.		٠.	٠.	• •					٠.	٠.	••					٠.,		٠.	2.0

# N SPARE TIME

LEARN MUSIC for Pleasure or Profit

...START NOW

 Enjoyment and earnings are rich rewards from musical training, but there is no magical door to success. If you are ambitious to learn and will devote spare time to serious effort, our 40 years of successful instruction experience can lead you to your goal. You can go as fast as your time and talents permit. Ours is the only home study school offering all courses required for Bachelor of Music degree. Check courses in which interested and mail coupon NOW for FREE SAMPLE ILLUSTRATED LESSON AND BOOKLET.

### UNIVERSITY EXTENSION CONSERVATORY 1525 E. 53rd St., Suite U155, Chicago 15, Ill.

Piano D	Violin	0	Corne	t D	Trump	et 🗆 Sa	xophone	□ Clarinet
□ Quitar [	Mando	lin	□ V	oice	□ Ear	Trainin	g and Sig	ght Singing
☐ Choral C	onductio	ng	□ Pu	blic	School	Music	☐ Histor	y of Music
☐ Harmony	□ Adv	ance	ed Co	mpo	sition	☐ Arran	ging	
Name								
Street			•••	• • •				<b></b>
City & Stat	te							
Music expe	rience.						A	ge



A SIMPLIFIED ART ANATOMY OF THE HUMAN FIGURE
by Charles Carlson. The book they're talking about! One of the
most informative books of its kind for both student and professional artists. Charts, notes, and over 350 drawings show
detailed studies of every part of the body, posed and in action.

ONLY \$1 POSTPAID
HOUSE OF LITTLE BOOKS, 155-P Fifth Ave., New York





# LANGUAGE

... Forge ahead, win special assignments, promotion, better job in global peace time opportunities through ability to speak a foreign language.

MASTER A NEW LANGUAGE quickly, easily, correctly by

The world-famous Linguaphone Conversational Method brings voices of native teachers INTO YOUR OWN HOME. You learn the new language by LISTENING. It's amazingly simple; thousands have succeeded.

**HCME-STUDY COURSES IN 29 LANGUAGES** Send for FREE book-

### LINGUAPHONE INSTITUTE 58A RCA Building, New York 20, N. Y. Circle 7-0830

LINGUAPHONE INSTITUTE,
58A RCA Bldg., New York 20, N. Y.
Send me the FREE Linguaphone Book.
Name
Address City
Language Interested

Buy War Savings Bonds and Stamps regularly.

START YOUR OWN BUSINESS

### SMALL CAPITAL - WORK

New miracle Plastics industry offers you unlimited career opportunities. Get started now in your own Plastics business or prepare for postwar plastics em-ployment. Take your place in the new Plastics Era. Now for the first time you get practical training in your own home. This new plan gives you the fundamental technical knowledge covering all branches of the Plastics industry including all types of Plastics materials. This is not a novelty program but a real sound educational plan. The actual practical work sound educational plan. The actual practical work consists of working with many different types of Plastics materials—teaching you fabrication, shaping, forming, finishing, cementing methods, mold making, casting, compounding, etc. For full information send this ad with your name in an envelope or paste on a penny postcard.—To Dept. N.

1845 E. 9th St., Cleveland 14, Ohio

# anageme

There's always opportunity in the business world for the man who wants to join the management. Routine jobs are easily filled, but men with the rounded knowledge needed by executives are hard to find. That's where I.C.S. comes in. A ploneer in business training, these schools have graduated thousands who became executives. Through the I.C.S. Business Management Course, experts train you in finance and business law, accounting and production, salesmanship and advertising. Write today for free booklet. International Correspondence Schools, Box 7613-L, Scranton 9, Pa.

### Open Your Own Electric Appliance Repair Shop

Be your own boss! Thousands of electric appliances need service and repairs constantly. Every neighborhood a fer-tile field. Our complete illustrated course trains you at home in appliance repair, house wiring, motor repairs, etc. SEND FOR FREE BOOKLET.

PACIFIC TRAINING SCHOOL

4701 W. Pico Dept. AS-3 Los Angeles 6, Calif.

STUDY AT HOME With A Chartered Educational Institution Men with legal training win higher positions, larger earnings, and are bigger successes in business and public life. Opportunities NOW greater than ever before. Complete course includes 21 college grade textbooks. Send for Catalog. McKinley-Roosevelt Incorporated, 4610-LB, Sheridan Road, Chicago 40, Illinois.

### Become a Doctor of PSYCHO

Win the degree of Ps.D. Teach the secret of contentment, happiness. Solve mental worries. Experience the revelation of truth college, Individual help. Write for FREE book, COI UNIVERSAL TRUTH, 5153-A North Clark St., Chicago. COLLEGE OF







Prepare for a REAL opportunity NOW-and for even greater opportunities when war is won! Thousands of Meat Cutters, Clerks, Apprentices, Managers, Inspectors, Supervisors, etc., needed by Meat Stores, Super Markets, Packing Houses, Processing Plants, Hotels and Restaurants, Whether you are a beginner or experienced you can learn easily and quickly AT HOME how to develop and use your REAL ABILITIES as Meat Cutter, Market Manager or Market Owner, Know how to figure percentage-CUT MORE PROFIT-merchandise, Be an expert Meat Cutter and get the extra earnings of an expert, Make more money in a store of your own. Instructions based on 30 years experience and "Learn By Doing" training methods used at National's famous Resident School of Meat Cutting. GUARANTEED, Endorsed by leading meat men, Diploma, This vital field pays better NOW than ever before—and at the same time offers you security of a peace-time future, Investigate! Send for FREE bulletin today! No obligation,

National School of Send me your FRE	f Meat Cutting, Inc., De E Bulletin, (No Salesman	pt. 028, Toledo 4, Ohlo Will Call)  I know nothing about meat cutting.
I work in a market,	I own my own store,	I know nothing about meat cutting.
Name		
Street	········	•••••
City and State		

# Mow! NO AUTO REPAIR JOB IS TOO TOUGH FOR YOU



JOB ALL FINISHED IN ONLY HALF THE TIME!

Whether you do auto repairs either as full-time or as part-time work, no service or repair job can "throw" you when you've got MoTOR'SAUTO REPAIR MANUAL! Just look up make, model, and the job in the streamlined index-and you're ready to lick ANY job from carburetor to rear end. Faster, easier, better!



MotoR's AUTO REPAIR MANUAL Shows You How to Service and Repair ANY Part of ANY Car Built Since 1935!

Nearly 200,000 service and repair facts on all 31 makes, 764 big pages; including 50 pages of carburetor text, charts, illustrations, covering all models, retor text, charts, illustrations, covering all models. Over 500 charts, tables; Tune-up Chart; Valve Measurements; Compression Pressure; Torque Measurements; Starting Motor; Engine Clear-Wrench Reading; Starting Motor; Engine Clear-Wrench Reading; Clutch & Brake Specifications; ances; Generator; Clutch & Brake Specifications; Front End Measurements, etc., Engines; Electric, Front End Measurements, etc., Engines; Transmissions; Fuel, Cooling, Lubricating Systems; Transmissions; Universals; Front Ends; Wheels; Rear Ends, etc.

# Covers All These Makes!

American Bantam Auburn Austin Buick Cadillac Chevrolet Chrysler

Cord Crosley De Soto Dodge Ford Graham Hudson Hupmobile Lafayette La Salle Lincoln Zephyr

Lincoln Mercury Nash Overland

Oldsmobile Packard Pierce Arrow Plymouth Pontiac Reo Studebaker Terraplane

Willys

Try this great book for 7 days FREE! It's "headquarters" for 200,000 facts about service, repair, adjustment, replacement, and tuneup—on every car built from 1935 through 1942. The engineer-editors of MoToR Magazine built this Manual for YOU, by collecting and organizing all the vital informa-tion from 150 official factory shop manuals. Then they put ALL the facts into this ONE amazing work-

# More Than 1,000 Pictures!

MoToR's AUTO REPAIR MAN-UAL not only TELLS you clearly what to do. It SHOWS you, too!in over 1,000 cut-away photos, diagrams, drawings, 764 BIG pages (8½x11 inches) put the complete "know-how" right at your fingertips! And the fabric binding is strong, built for years of day-inday-out service!

No wonder it is used by the U. S.

Army, Navy, trade and technical schools, thousands of auto servicemen and handymen everywhere! No wonder we're willing to have YOU try it, FREE, for 7 days! Once you use it—and see for yourself how much valuable time and hard work it saves—you'll never again want to be without it!

# SEND NO MONEY 7-Day Free Examination

Don't send any cash—unless you wish to do so in order to save postage charges! Simply mail cou-pon NOW. When postman brings your book, pay him nothing. First make the book show you what it does for you! Unless convinced it's the greatest time-saver and worksaver you've ever seen-return book in 7 days, pay nothing. Mail cou-pon NOW! Address: MoToR Book Dept., Desk 2C, 572 Madison Ave-nue, New York 22, N. Y.

# Same FREE 7-Day Offer Applies on MoToR's TRUCK REPAIR MANUAL

For mechanics, truck specialists, service stations, fleet owners. Covers EVERY job on EVERY truck made since 1936! 1400 pictures, 914 pages, 300,000 facts. Used by Armed

All types Gasoline Engines, Die-sels, Hesselman, Fuel Systems, Gov-ernors, Lubrication Systems, Ignition Systems, Starters, Generators, Clutches, Transmissions, Axles. Torque Dividers, Transfer Cases, Brakes, Steering, etc.

ALSO SERVICES many buses, farm and industrial tractors, confarm and industrial tractors, con-tractor and road building equipment. MoloR tive Business Mag-tractor and road building equipment. MoloR's (on all parts described in Manual.) Check box in coupon at right,



Published by MoToR, The manuals assure high standards of repair work,

# MAIL COUPON NOW FOR 7-DAY FREE TRIAL

MoToR Book Dept., Desk 2C, 572 Madison Ave., New York 22, N. Y. Rush to me at once: (check box opposite book you want).

MoToR's AUTO REPAIR MANUAL If O.K. I will remit \$1 in 7 days. \$1 monthly for 4 months, plus 35c delivery charge with final payment (\$5.35 in all). Otherwise I will return book postpaid in 7 days. (Foreign price.

remit \$7 cash with order). Motor's TRUCK REPAIR MANUAL. (Described at left.) If O.K., I will remit \$2 in 7 days, and \$2 monthly for 3 months, plus 35c delivery charges with final payment (\$8.35 in all). Otherwise I will return book postpaid in 7 days. (Foreign, remit \$11 cash with order).

Print Name.

Print Address\_ Zone No. City\_ (if any).

\_Occupation\_ SAVE 35c! We pay postage if you ENCLOSE full pay't. (check, m.o.). Same 7-day return-refund privilege.

# THESE Free Books

GIVE PRACTICAL POINTERS ON HOW TO PROTECT, PATENT AND SELL YOUR

# ENT



These two valuable books, "Patent Protection" and "When and How to Sell Your Invention" have guided many an inventor like you straight to a strong patent and SUCCESS. They tell you step by step, the proper procedure to find out if your invention can be patented . . . the steps necessary to secure a patent, and reliable, helpful suggestions on how to sell your invention. IN ADDITION . . . you'll find illustrated for your guidance . . . 115 MECHANICAL MOVEMENTS . . . just the information you may need to complete your invention.


# **GET THESE FREE BOOKS AT ONCE...** DON'T WAIT UNTIL TOMORROW INDUSTRY WANTS YOUR INVENTION NOW

Now . . . while industry and business are looking ahead to post-war markets . . . now, when they are eagerly seeking new and improved products, new and improved machines, tools and methods . . . is the RIGHT TIME TO SECURE YOUR PATENT. If you have an invention . . . BE A DO-ER! Don't take the chance of someone's beating you to it.

THE RIGHT START will save you time, money and trouble. That's why we advise you to get . . . RIGHT AWAY . . . the FREE books and the FREE important "Evidence of Invention" form that may help you establish your claim.

THIS COUPON MAY BE YOUR TICKET TO SUCCESS ... Mail 9t Today

LIC	CTOR	111	ANS	& Lo
			ys for Nearly Washington 6,	
Please "Whe portar	send me you	our books- to Sell Yo	"Patent Prote ur Invention" ion" form, w	ction" and
Name	*******************************	***************************************	***************************************	
Addre	ss			
City a	and State			



of slide. All values direct reading. (41/8"x9") Send only 10c in coin to cover cost of handling. OHMITE MFG. CO., 4944 Flournoy St., Chicago 44, Ill.

# "How to Make Money With Simple Cartoons"

A book everyone who likes to draw should have. It is free; no obligations. Simply address

CARTOONISTS' EXCHANGE

Dept. 1443

Pleasant Hill, Ohio

# For Today's & Tomorrow's

Nationwide opportunities, sound postwar career waiting for trained photographers. N.Y.I. graduates winning success from coast to coast. Resident or home study. Write today for FREE catalog.

NEW YORK INSTITUTE OF PHOTOGRAPHY Dept. 5, 10 West 33 St., New York 1. N. V. New York 1, N. Y.

# Nhat Every Mason V



We have Important Masonic books for Blue Lodge, Chapter, Commandery, Scottish Rite, and Shrine.

OUR RITUALS ARE USED THE WORLD OVER Send for free catalog of books and rituals for Masons, Odd Fellows, Knights of Pythias, Knights of Columbus, etc. EZRA A. COOK, Publisher, P. O. Box 796, RM Chicago 90, III.

STUDY AT HOME for PERSONAL SUCCESS and LARGER EARNINGS. 35 years expert instruction -over 108,000 students enrolled. LL.B. Degree awarded. All texts furnished. Easy payments. Send for FREE BOOK-"Law and Executive Guidance"


AMERICAN EXTENSION SCHOOL OF LAW Dept.51.8.646 N. Michigan Ave., Chicago 11, III.

Find out your ability. Send name, age, occupation and address for Free Vocational Art Test.

ART INSTRUCTION, INC., 3145 Art Instruction Bidg., Minneapolis, Minn. (Formerly Federal Schools, Inc.)

basic training, Long-established school, Send for free book, "Opportunities in Photography," No obligation.

American School of Photography, 1315 S. Michigan Ave., Dept. 1363 Chicago 5, Ill.





Leaders in science and industry have long been saying, "Keep your eye on Plastics." But now the time for action has arrived. The future of huge possibilities has already begun. Developments in Plastics for hundreds of wartime uses have set the pace for revolutionary changes in peacetime production of thousands of products.

# THIS IS YOUR BIG CHANCE

Today there's a big need in vital war production for those who are trained in Plastics. From one to a hundred articles made of Plastics must be supplied for every man in our fighting forces. Start training now in Plastics Engineering, in spare

time in your own home. Fit yourself for a responsible, well-paid position. Help to win Victory. And at the same time you will be preparing for even greater opportunities when the war is over.

There is scarcely an industry in which these so-called "miracle materials" will not play an important part. After the war many old materials, methods and skills will be replaced. Acquire the all-important "know how." Be in a position to step into one of the key jobs.

# YOU CAN LEARN WHILE YOU EARN

Turn at least part of your leisure time into money. Qualify at home for a larger income in an interesting career. Build greater security for your future in a vocation that looms large on the horizon of the new industrial era. Hours you might

otherwise waste can put you well on your way toward lasting success.

**ECTIV** 

ш

¥.

PRACTIC/

It's easy to find out about Plastics training. To get details and outline of study prepared by specialists, and about the school that has helped thousands to success during the past 46 years, write us or check and mail the coupon. Send today. The

sooner you take this easy step, the sooner you will reach your goal and reap the rich rewards.

# AMERICAN SCHOOL OFFERS COMPLETE TRAINING SERVICE IN MANY SUBJECTS

You who have not completed high school or have missed vocational training in college, and who cannot spare time to go away to school, can complete your education in your choice of many subjects. Several of these are listed in the coupon at right. Check the subject in which you are interested, fill in your name and address, clip and mail the coupon today.

# AMERICAN SCHOOL

Dept. G-346 Drexel at 58th Street, Chicago 37

ME - STUDY TRAINING SINCE 1897

Take This First Easy Step

# CHECK, CLIP AND MAIL COUPON NOW

AMERICAN SCHOOL, Dept. G-346, Drexel at 58th, Chicago 37, III.

Without obligation, Please send FREE and postpaid, bulletin and details of the Subjects checked.

- □PLASTICS ENG'R
  □Refrigeration
  □Architecture and Building □Practical Plumbing □Automotive Engineering Aviation Drafting
- □Accounting and C.P.A.
  □Cost Accounting for Manufacturing □Bookkeeping □Private Secretary □Diesel Engineering
  □Surveying & Topographical Drafting
  □Sheet Metal □ Aviation Business Magment
  Railway Training
- Drafting and Design for Men and Women □ Radio □Radio
  □High School
  □Air Conditioning
  □Shipbuilding
  □Mechanical Eng.
  □Shop Management
  □Tool Making Better Foremanship ☐Machine Shop

Name . . . . . . . Occupation . . . . . . 



# Start now to earn the bigger pay in electrical repair

WAS there ever such an opportunity to get started

in electrical maintenance and repair-and at top-notch wages? Are you ready-with experience and ability-to cash in on it? Others are getting just the sort of background needed-quick! practical!-to handle the great variety of electrical maintenance and repair work TODAY-from this well-known electrical library. You can too!

# LIBRARY OF ELECTRICAL MAINTENANCE AND REPAIR

5 vols., 1826 pages, 1724 illustrations

Gives you the "know-how" to tackle any wiring or motor job. Five books show you HOW—to install all types of motor and generator units-to inspect and repair motor starters and generators-to diagnose motor and generator troubles-to figure new windings for old cores-DC and AC windings-to test armature windings-test induction motors, etc., etc. One book is full of trouble-shooting charts that show quickly symptoms, causes, specific remedies, etc.

Take the first step toward improving YOUR future— Mail this coupon TODAY

No money down—special price—easy payments—FREE trial

Send me for te tenance and Repa \$1.00 in 10 days	n days' free air Library. and \$2.00 r	examination If satisfacto monthly until	the Electrical Main ory I will send you the price of \$15.00 is postpaid. (To in il in all lines.)
Name			
Home Address			
Position			
Name of Company			

# Learn this Profitable Profession IN 90 DAYS

# Money-Making Career Open to Men and Women, 18 to 50

Hundreds of men and women between 18 and 50 make \$10 to \$20 in a single day giving scientific Swedish Massage and Hydro-Therapy treatments. There is big demand from doctors, hospitals, sana-toriums and clubs. Graduates earn large full time incomes from



these or in private practice in their own offices. Others make good money from home treatments given in spare time. Learn this interesting, money-making profession in your own home, through our home study course. Same instructors as in our nationally known resident school. You can win independence and prepare for future security by qualifying for your Diploma. Course can be completed in 3 to 4 months. Many earn while they learn. Begin your training at once.

# **Anatomy Charts & Booklet FREE**

Enroll now and we will include, at no extra cost, many needed supplies. Fit yourself to help meet growing demand for massage now and after the war. Send the coupon at once for complete details, Anatomy Charts and 32-Page Illustrated Booklet, FREE, postpaid.

Please send me FREE and postpaid, Anatomy Charts, Booklet and complete details on Home Training.	, 32-page
Name	
Address	

THE COLLEGE OF SWEDISH MASSAGE Dept. 570-C, 100 East Ohio St., Chicago II, Illinois



Complete Course

Only \$15.00

# DRAW CARTOONS

EASY...PLEASANT WORKI

Let CHAS. H. KUHN, with 25 years actual experience in drawing a daily newspaper cartoon, teach you how to create, draw and sell your work. 52 complete lessons—one sent each week. Professional criticism on every lesson. Write today.

KUHN SCHOOL OF CARTOONING 420 MURPHY BUILDING Dept. S. INDIANAPOLIS 4, INDIANA



# **Build with Cement Composition**

Strongly reinforced with cheap wood. Modern stream-lined roof, walls and gutters. How to build a house 22x24, three rooms, as low as \$100 for materials; garage, \$20; 20x50 poultry house, \$50. Farm buildings for a few dollars. Homemade equipment to make wall-high building blocks with inside and outside finish; roof, wall and floor tile in color, and durable wallboard of sawdust for a few cents. Several formulas. Labortional cabins, 100 money and labor saving building ideas, Mixer and saw easily made from old auto. 40 War-time Plans, Earn \$10 a day. Guaranteed, Illustrated instruction book, \$1.00. MAKE FURNITURE OF COMPOSITION, Cement, sawdust, paper, asbestos. Homemade cements. Some part scrap wood and metal. Make tables, cabinets, chests, racks, shelves, inclosed sinks, lawn novelties and toys. Over 500 % profit. 50c.

HOW TO MAKE ACCURATE WOODWORKING MACHINES, saws, drills, sanding wheels, tools, electric weed cutters and many other things from old auto parts and used motors, Illustrated, 50c. Special: All of the booklets described above, \$2.00 postpaid. No C.O.D. HOME INDUSTRIES, 1318 So.30th Ave., Dept.PS, Omaha 5, Nebr.

 Make beautiful artificial Marble slabs. Pour from

liquid state. Glazed or un-glazed. Mottled, veined, snow-white, or multi-colored. Unsurpassed on kitchen or bathroom walls. Easy to make and install. PLASTIC FLOORING. Any color. Lifetime wear, Dustproof, Soundproof, Verminproof. Resilient to the tread. Lay out solid or in pattern design. FLEXIBLE MOLDS for plaster casting. Make your own molds for few cents each. \$1.00 in raw materials will make up to \$25.00 of finished goods. We furnish names of buyers. Write now for free information.

COMPO-TEX,

BOX 786-G,

ST. LOUIS (1), MO.

RAYE BURNS will teach you HOW to CREATE ORIGINAL CARTOONS at home that you may SELL! Course contains 26 lessons and over 600 illustrations. All for Only...

Send name and address for free details.

RAYE BURNS SCHOOL, Dept. S. Box 3583, CLEVELAND, OHIO





# IVENTORS Do Not Delay!

Have you ever been startled by seeing a successful article on the market, and exclaimed-"W -I didn't think it was valuable enough to Patent!"

The Patent Laws were intended for the protection of the Inventor, and the Inventor who slumbers on his rights may wake up to find someone else reaping the reward that could have

The Inventor with a valuable Invention should act NOW. Send this coupon TO-DAY—to RANDOLPH & BEAVERS. 340-D Columbian Bldg., Washington, D. C.

# PERSONALIZED SERVICE 340-D Columbian Bidg.

Registered Patent Attorneys Washington, D.

Please send me full particulars on Patents, fees, etc., and "RECORD of INVENTION form"-Free.


	0.000	777	2-0700	
Name				
Address				

# IMAGINE THEIR JOY

# WHEN THEY FOUND THEY COULD PLAY This easy as A.B.C. way!

## PLAYS ON RADIO

"As a proud student I can't keep from telling you that as a result of my course I have a good position play-ing from KTHS, Hot Springs, Ark., every morning." \*J. S., Okla.



# WOULDN'T TAKE \$1000 FOR COURSE

"The lessons are so simple that anyone to play by note in a little more than a month. I wouldn't take a thousand dollars for my course."

\*S. E. A., Kansas City, Mo.



# "YOU CAN'T BEAT IT!"

"I am glad to tell anyone about the U. S. School. It is just what they say it is and they will do what they say they will. If you want to learn music you can't beat it!"

\*W. E. D., N. Mex.

# to Play for Less Than 7c a Day Thousands Have Learned

7 HAT instrument would you like to play? We'll show you how you can learn to play it-quickly, easily, in spare time at home for less than SEVEN CENTS A DAY! Never mind if you don't know one note of music from another-don't worry about "special talent."

The truth of the matter is that thousands now play who never thought they could! Yes, men and women everywhere are enjoying the thrilling satisfaction of playing the piano. violin, guitar, saxophone or other favorite instrument. Some of them are playing in orchestras and over the radio; others are teaching music, making money in spare or full time. And

thousands are playing for their own enjoyment and the entertainment of their friends.

It all came about when they wrote to the U. S. School of Music for the Free Booklet that shows you how EASY it is to learn music at home this modern way. No tedious scales, no tiresome exercises. You learn to play by playing—start right in almost at once with the melody of a simple tune! It takes only a few minutes a day and the cost is trifling; you save the expense of a private teacher. Does it sound too good to be true? Mail the coupon and get the FREE PROOF! (Our forty-seventh year—Est. 1898.) U. S. School of Music, 83 Brunswick Bldg., New York 10, N. Y.

# NOTICE

Please do not confuse the U. S. School of Mumethod with any system of teaching music "by ear" or by trick charts. Our method teaches you to play by actual notes. . . not by any "trick" or number system. You are able to pick up any piece of regular sheet music and play by note. And once you've learned to play by note it's just like learning your A-B-C's. It never leaves youyou remember it for life.

# SEND FOR FREE PRINT AND PICTURE SAMPLE

 You'll open your eyes when you find how quickly and easily you can learn to play your favorite instrument. Don't doubt; don't hesitate. Send for the fascinating illustrated booklet that answers all your questions: let the free Print and Picture Sample show you how this method actually works. If interested, mail the coupon NOW.

\*Actual pupils' names on request. Pictures by professional models.

# SUCCESSFUL 47TH YEAR

# U. S. SCHOOL OF MUSIC 83 Brunswick Bldg., New York 10, N. Y.

I am interested in music study, particularly in the in-strument checked below. Please send me your free illustrated booklet. "How to Learn Music at Home."

Piano Guitar Hawaiian Guitar

PLAYS AT DANCES

"I have completed your course and your lessons have been

most satisfactory. I can play all of the popular songs. I have

also earned money playing at dances." \*E.N.J., New York,

Saxophone Trumpet, Cornet Reed Organ Tenor Banjo Piano Accordion Mandolin

**Modern Elementary** Harmony Clarinet Practical Finger

Other Instrument

Have you Instrument?.....

Name........

(Please Print)

NOTE: If you are under 16 years parent must sign coupon. \_\_\_\_Save 2c—Stick coupon on penny postcard. \_\_\_\_

MARCH, 1945

Buy War Savings Bonds and Stamps regularly.

32E

# Look Way Ahead In Your Fascinating INSTRUMENT TECHNICIAN

1945 46 47 48

More and more Instrument Technicians will be needed to repair, test, calibrate and build more instruments ...

in use on more private and commercial planes. Work with all types of instruments, including the automatic pilot, sensitive altimeter and directional gyro. Train now to become a specialist in this well-paid, interesting field, through A. S. A. I.'s practical resident course-or if you prefer, start with the Home Study Course. A.S. A.I. also offers complete training in Watchmaking.

## SERVICE MEN! VETERANS!

Ask about Full Benefits available to you under G. I. Bill of Rights. As a technically trained specialist you will be eligible for the real opportunties in postwar aviation. Now is the time to plan your career!

GET THIS FREE BOOK-The complete 24-page story of the A.S. A. I. Resident and Home Study training programs—send the coupon for your copy today!

AMERICAN SCHOOL OF AIRCRAFT INSTRUMENTS Including Accredited School of Watchmaking 5247 W. San Fernando Road, Los Angeles 26, Calif.

	without obligate Home Study Ins Master Instrume	trument Course	☐ Watchmakir	
Nome_				g•

AMERICA'S OLDEST INSTRUMENT SCHOOL



At Coyne you "Learn by Doing" on real machinery and equipment. Trained Electrical men needed now. Electricity offers you opportunities for the best jobs today, and a real peace-time future.Don't let the opportunities of peace-time catch you unprepared. Get your electrical training now.

# EARN WHILE LEARNING, JOB HELP AFTER GRADUATION

The place to get your electrical training is at Coyne. We have been training men and young men for 45 years - by in the great Chicago shops of Coyne.

Many do part time work to help out with expenses. Free lifetime employment service when the control of the control o the famous "Learn by Doing" method ment service when you graduate.

Right now I'm including extra training in Industrial Electronics at no extra cost. Send coupon now for Free

you have a physical disa-bility of any kind write me whenyousend the coupon.

COURSEIN

INDUSTRIAL

ELECTRONICS

INCLUDED

Book and details. No obligation; no the coupon salesman will call. I want to send you the facts and let you decide. Mail coupon today.

H. C. COYN 500 S. Send plans	Pau Pau	lin	C'a	F St F	u	G/ D	\I	pt	S	35	-7	3.	(	21	hi	c	g	ob	ol	1	2	,	I	I	i.
Name					٠.								•				•	•	•						
Addre	88																								

Zone.

HANDY ASSORTMENT ST S. FOR MECHANICS — GARAGE

SCREWS • NUTS • BOLTS • WASHERS RIVETS . SPRINGS . BRACKETS . MISC.

MORE THAN 1,000 PIECES

5 full pounds-a veritable treasure chest of fastening devices for every practical use. Satisfaction guaranteed. Order now. \$1.98. SPECIAL-2 assortments, over 2,000 pieces, for \$3.69. F.O.B. Chicago

HUDSON TRADING CORPORATION

The House of Handy Assortments M-161 West Hubbard St., Chicago 10, III. FREE! Handy List of Special
Assortments: FIBER
AND BAKELITE WASHERS—RUBBER WASHERS and PADS—FELT
WASHERS and PADS—RADIO LUGS,
CLIPS AND CONNECTORS—
SPRINGS—SELF-TAPPING
SCREWS—etc.

# HOW TO GET A BIG PAY predicted. Big-pay, permanent jobs or your own 6-profit busi-



4015

THEMTROZEK

HERRE OF MU

ness. Salaries up to \$2,500 to \$10,000 a year in property management, brokerage, appraisal, loans, insurance, building. Many make fortunes selling real estate. Thousands of trained men, women, required yearly by real estate firms, insurance companies, banks, Federal agen-cies. Rush post-card for 32-page QUIZ BOOK-mailed FREE with full details on new and only 5-volumes library. MODERN REAL ESTATE PRACTICE! Lane Books, Dept. C-3, 100 East Ohio St., Chicago 11, Illinois.

Most interesting electrical apparatus ever discovered, Make your own Telephone-Amplifier Detectiphone. Transmit your voice or music to distant rooms. Perform hundreds of fascinating experiments. So tiny it can be concealed in dozens of places. Send \$1 now for button and free 5,000 word instruction booklet with 50 illustrated experiments, SPECIAL OFFER 6 buttons and booklets sent post-paid for \$5. Write now to BUCK MFG. COMPANY

North Aurora, Illinois



HAND MADE, Very best. Lowest prices. Buy direct from Factory and Save Money. Send name and address for FREE catalog.

ITALIAN ACCORDION MFG. CO.

ITALIAN ACCORDION MFG. CO.

DEPT. PS-3 CHICAGO 7, ILL.

This new 128-page book, "Stammering, Its Cause and Correction," describes the Bogue Unit Method for scientific correction of stammering and stut-tering—successful for 44 years. Benj. N. Boque, Dept. 1871, Circle Tower, Indianapolis 4, Ind.



## Learn BAKING At

Baking is one of America's high industries in wages. Nearly depression-proof. Thorough basic home course lays sound foundation. If you have aptitude, write for FREE BOOKLET, "Opportunities in Commercial Baking." National Baking School, 1315 Mich. Ave., Dept. 1363, Chicago 5





The kind they like. You will be both a Riot and the Life of the Party with a set of these pocket size joke books. They are full of Entertainment, Fun and Humor. A special assortment of 12 books all different for \$1.00. Print name and address, send cash or stamps to:

TREASURE NOVELTY CO. 72-5th Ave., Dept. 1403, N. Y. 11, N. Y.

1330-33 N. CENTR CHICAGO 51, ILL.



Give me 10 Minutes a Day Learn My Time Tested Secrets of Strength

I'll teach you the "Progressive Power Method" through which I rebuilt myself from a physical wreck the doctors condemned to die at "15, to the holder of more strength records than any other living athlete or teacher! "Progressive Power" has proven its ability to build the strongest, handsomest men in the world. And I stand ready to show you on a money back basis—that no matter how flabby or puny you are I can do the same for you right in your own home. Through my proven secrets I bring to life new power in you inside and out, until YOU are fully missined you are the man you want to be. MY TIME TESTED METHODS RE-BUILD YOU.

PROVE TO YOURSELF IN ONE NIGHT

Send only 25c in full payment for my test course "Moulding A Mighty Arm." Try it for one night! Experience the thrilling strength that will surge through your muscles.

READ WHAT THESE FAMOUS PUPILS SAY ABOUT JOWETT



A. PASSAMONT, Jowett-trained first prize-winner for Physical

REX FERRIS, Champion Strength Athlete of South Africa, Mays he, "I owe everything to Jowett methods!" Look at this chest—then consider the value of the Jowett Courses!



**BUILD A BODY** YOU'LL BE PROUD OF

Send for These FIVE Famous Courses NOW in BOOK FORM ONLY 25c EACH or ALL 5 for \$1

At last, Jowett's world-famous muscleht last, Jowett's world-tamous muscle-building courses, are available in book form to all readers of this publication at an extremely low price of 25 cents each! All 5 for only \$1.00. You owe it to your country, to your family, and to yourself, to make yourself physically fit now! Start at once to improve your physique by following Jowett's simple, easy method of muscle-building!

# 10-DAY TRIAL OFFER!

Think of it — all five of these famous course-books for only ONE DOLLAR—or any one of them for 25c. If you're not delighted with these famous muscle-building books—if you don't actually FEEL results within ONE WEEK, send them back and your money will be promptly refunded!

Don't let this opportunity get away from you! And don't forget—by sending the FREE GIFT COUPON at once you receive a FREE copy of the famous Jowett book; "Nerves of Steel, Muscles of Iron."

JOWETT INSTITUTE OF PHYSICAL CULTURE 230 Fifth Ave., Dept. 363, New York 1, N. Y.



HOW TO MOLD A

"The Jowett System is the greatest in the world!" says R. F. Kelly, Physical Director of YMCA, Washington, D.C.

for a limited time onlyand Jowett's big Photo Book

I want TWICE as many red-blooded Americans to start on the road to Mighty Strength THIS MONTH, so, with Coupon-order, I offer FREE of further cost, all 5 World Famous Inside Secrets!

1 Inside Secrets

3 Inside Secrets 1) Inside Secrets

Inside Secrets

of "Commando Self Defense Tactics". tow to defend yourself against Rough and Tu

of "Strong Man Stunts Made Easy". Easy-to-learn tricks that will amaze your friends.

of "The World's Greatest Knock-out Punch"

of "Hand-balancing Made Easy". How to stand and walk on your hands.

of "Scientific Weight Lifting". How to lift heavy weights with eas



MAIL ORDER-COUPON NOW and get my ------

and PHO	E STRENGTH TO BOOK of S	SECRETS TRONG MEN	ŦR	$\mathbf{E}\mathbf{F}I$
- Inves	to Institute of Bb	unlant Culture		

230 Fifth Avenue, Dept. 363, New York 1, N. Y.1 George F. Jowett: Your proposition looks good to me. Send by return mail, prepaid, the courses checked, for which I enclose ( ). Send 5 Secrets and Photo Book FREE.

All 5 courses for.....\$1 Melding Mignly Legs.25c Molding a Mighty Arm 25c | Molding a Mighty Grip 25c Molding a Mighty Back 25c [ Molding a Mighty Chest 25c

Send all 5 C.O.D. (\$1 plus postage.) No orders less than \$1 sent C.O.D.

......Ag....... Please Print Plainly

ADDRESS..... ......

# Listen to this Record!

# FRENCH, GERMAN, OR ITALIAN

Big opportunities awaiting Americans who speak Spanish. Learn as easily as a child learns—"by listening" to these brand-new CORTINA recordings.

# Only 15 Minutes a Day

THOUSANDS have found it the most fascinating, most satisfactory method. Here is the quick, easy way to learn Spanish for PLEASURE AND BUSINESS. INVESTIGATE!

# Sent on 5 Days Approval



"The Cortina Short-Cut" tells just what you want to know. Interesting.

# Write Today-*N*

CORTINA ACADEMY (Language Specialists for 60 Years) Dept. 123, 105 West 40th Street, New York 18, N. Y.

Please send me free—without obligation—your booklet, "The Cortina Short-Cut." I am interested in (mark):

☐ SP.	ANISH	French	☐ Italian	☐ German
Name		 		
Addres				



a better job, make more money and have greater opportunities to get ahead, start now to become a draftsman. Or if you are now employed in routine drafting work and want a better jobas a real draftsman, on more important work, at bigger pay, start now to qualify for that job.

# Learn at Home in Spare Time

American School has helped thousands to reach higher goals, and can help you. Our practical, up-to-date training plan can provide the know-how that fits men for responsible jobs and opens opportunities. Begin draftsman training now. Check, fill in and mail the coupon below for FREE information—today.

AMERICAN SCHOOL, Dept. DD346, Drexel Ave. at 58th St., Chicago 37, III.

Gentlemen: Send me FREE information covering special training in subjects checked below. No obligation on my part.

- Drafting and Design for Men and Women
- for Men and Wollien
  Cost Accounting for Mfg. High School (
  Architecture and Building Plastics
  Automotive Engineering Mechanical E
  Business Management Aviation
  Railway Training Shipbuilding Cost Accounting for Mfg.
- □ Business Management □ Railway Training

٠.						
-	W-1-	4-1		- 41-		-
3	Fiec	trice	11 E	ngır	eer	ing
						-
J	Dies	el E	ngu	leer	mE	

- High School Course Plastics Mechanical Engineering
- ☐ Radio

avame	• •	•	٠.			٠.	*	*	• •	٠.	• •	٠.	• •	 *	 • •		•	• •	•	٠.	•	٠.	
Address																20		-		20			

FROM OLD **AUTO PARTS** Now anyone can build a

tractor was built sible cost. Easily handles from our plans. from our plans. plowing, cultivating, hauling and heavy farm work. Our proved working plans make it simple to build. Large 22"x34" drawings give every construction detail.

SEND ORDER TODAY. Complete plans, parts book, only \$1.00 postpaid. Money-back guarantee. SCIENCE AND MECHANICS, 154 E. Erie St., Dept. M-164, Chicago 11

This

Fits the pocket. Quickly solves any problem in multiplication, division, proportion. Gives the square, the square root, logarithm and reciprocals of all numbers. Trig scales give sines and tangents of numbers. Fine black graduations on white celluloid. Complete with instructions. In fabricoid case \$1.00, in leather case \$1.25. Money back if not satisfied. Special offer to agents and dealers.



strong, durable, all-pur-

pose tractor at lowest pos-

MONITOR SLIDE RULE 6" Dia.

Made in white Vinylite. Same scales as Mascot Slide Rule. Complete with instructions. Without case, \$2.95, Leatherette case 75c additional.

TAVELLA SALES CO., 21-C West Broadway, New York 7, N. Y.

# IDIANA TECHNICAL COLI

Engineering B.S. degree in 27 months. Aeronautical, Chemical, Civil, Electrical, Mechanical and Radio Engineering, 1-yr, Radio, Drafting. Govt. approved under G. I. Bill. Prep courses, no added cost. Large industrial center. Earn living expenses. Enter March, June, Dec. Catalog. 635 E. Washington Blvd., Fort Wayne 2, Ind.

# STUDY HOME

With A Chartered Educational Institution
Courses in ENGINEERING: Electrical, Civil, Mechanical, Drafting,
Architectural, Steam, Aeronautical, Radio, Structural, Mining, Industrial, Highway. Petroleum, Marine, Chemical.
Courses in ARTS AND SCIENCES: Philosophy; Education; Letters;
Public Health; Medical Jurisprudence: Psychology; Sociology; Physics;
Chemistry; Geology; Pol. Science; Theology; Law; Business and
Commerce: Accounting: Mathematics: Statistics; Agriculture.
McKinley-Reseavelt Incorporated, 4818-8C, Sheridan Read, Chicage 40, Illinois

# Correspondence Courses in RADIO and ELECTRICAL ENGINEERING

ELECTRICAL ENGINEERING. Get good grasp of wide electrical field. Modern. Very understandable. Theory made easy.

RADIO ENGINEERING. Extra fine course in radio, public address, photo-electric work. Trains you to be super-service man, real vacuum tube technician. Tuition ONLY \$25, either course. Deferred payment plan. Servicemen needed badly. Write for free copies of school catalogs, student magazines, etc. LINCOLN ENGINEERING SCHOOL, Box 931-575 LINCOLN, NEBR.



# ELECTRIC HEATING ELEMENTS REPAIRED

New amazing NICHROCITE PASTE will do it in a jiffy. Simply overlap ends, apply paste and turn on current. Used successfully by utility companies and others. Family size, \$1. Satisfaction guaranteed, Advance Mfg. Co., Box 861-B, Minneapolis, Minn.



For Store Fronts and Office Windows. Anyone can put them on, Samples furnished. Imitation gold and silver.

METALLIC LETTER CO., 441 N. Clark, Chicago 10



# MONEY IN RABBITS-CAVIES

WE BUY and put you in touch with other markets.

Catalog and copy of magazine 10c. Or send
for Book Catalog and Price List and 3mo.'s Subscription to the AMERICAN SMALL STOCK FARMER. OUTDOOR ENTERPRISE CO., BV55, PEARL RIVER, N. Y.



# ILLUSTRATED COMIC BOOKLETS

The kind men like! (vest pocket size.) 10 different booklets sent for 50c or 25 assorted for \$1. Shipped prepaid in plain wrap-per. No C. U. D. orders. Send cash or money order. No stamps.

GRAYKO, Dept. A-575 Box 520, G. P. O., New York 1



# ways to be your own boss!

OW, more than ever before, is the right time to start a small profitable business of your own . . . or train yourself for a practical money-making trade in which you can be INDEPENDENT. TODAY . . . take your first step, without cost or any obligation.

Just mail coupon and by return mail you will get full information on the courses listed here.

CCESS... be a professional man!

Practical training on how to run a profitable real estate business of your own. Illustrated self-study lessons on farm and suburban properties, downtown operating. Gain a working knowledge of mortgages, listings, sales techniques, appraisals, property management, commercial leasing, contracts, etc. Real estate is the foundation of all wealth! Rush coupon below for NEW facts you should know about your future in real estate. There's no obligation.

# practical REFRIGERAT

Brand New Streamlined Course for quick training. Authoritative step-by-step instruction on servicing household refrigerators . . . how to install, operate, repair. Easy-to-

follow illustrated directions on troubleshooting, parts replacement, testing. Covers quick-freeze units, lockers, water coolers, freon, air-conditioning systems, etc. Amazing low prize! Free details, see coupon.

Let this PRACTICAL, LOW-PRICED course

get you started in the auto repair trade. Good mechanics make big money NOW... and have a great future! Self-training lessons show you exactly what to do and how to do it. It teaches servicing on all makes of cars . . . adjust-ments, tune-ups, etc. Clearly written and illustrated by expert engineers. Satisfaction or refund. Mail coupon for FREE details.

**BIG OPPORTUNITIES FOR MEN** with the KNOW-HOW! There's a great future in the building trades for trained men. Here are up-todate lessons on how to plan, build, remodel houses. How-to-do-it instructions on stair building, steel square, roofing, painting and dec-orating, etc. Send for full information FREE . . . mail coupon below!



# what to invent—how



# MECHANICAL DRAWING, DESIGN-

Practical course for wide-awake practical men. IDEAS... how to get them, develop them, protect them and promote them! Expert information on how to turn your imagination into money. Plus illustrated self-study lessons on basic mechanical movements and devices, mail coupon below for FREE details.

# SURE YOUR FUTURE Mail This Coupon Today! 🐲

On this coupon check the subjects that interest you. Our world-famous copyrighted Success-Catalog will bring complete details. FREE. . no cost, no obligation.

# NELSON COMPANY

321 S. Wabash Ave., Dept. 8C01, Chicago 4, Ill.

# watch and clock repairing



LearnatHome—InYourSpareTime Prepareforahappyfutureof prosperity, security... and get a big-pay job now. Fascinating, high-grade occupa-tion. You can EARN WHILE YOU LEARN. Excellent field for part-time work at home.

Practical Course in HOROLOGY Thorough self-instruction training in American and Swiss watches, clocks.
Special sections on a larm clock repairs.
Interesting. LEARN-BY-DOING instruction method. Learn QUICKLY, easily. No previous experience necessally. No previous experience necessally. The provious experience necessally experien


INSTRUMENT WORK and other scientific precision jobs. Amazing Low Price! • Money-Back Guarantee! Get into this fast-growing field NOW...big opportunity...don't delay. Mail coupon below for FREE information. No obligation.

# locksmithing and key making

PRACTICAL UP-TO-DATE COURSE

How to pick locks, de-code, make master-keys, repair, install service, etc. New, self-intruc-tionlessons for every handy man, home-owner, carpenter, mechanic, scrvice station operator, fix-it shop, hardware dealer, gunsmith.

53 Easy Illustrated Lessons Low Price! Satisfaction guaranteed or money back. Writenow...noobligation!



# practical RADIO servicing



SELF-INSTRUCTION COURSE Teaches you the practical side of radio ... repair, adjustment, operation, alteration, trouble-shooting. No previous knowledge necessary. Large clear illustrations, diagrams, charts, etc. OINTERESTING
STEADY WORK! Set up a radio

repair shop of your own-or prepare for booming industrial electronics. This useful, how-to-do-it course brings you all the fundamentals, including mathematics, review questions, problems, answers. Strictly up-to-date. Low price. Coupon below will bring you full information you want immediately. Mail it in today !

Your Big Opportunity!

84-lesson course on proved, tested, upto-date, profitable methods, Amazing treasure-house of the best mail order plans and practices. How to start your mail order business on a small one-man scale . . . how to keep it growing more and more profitable month after month. Money-making FACTS.



Sensational details...FREE. Mail coupon below!

		_						
NELSON	COMPANY.	DEPT.	SCO1.	321	S WARASH	AVE.	CHICAGO 4	ILL

meason committee it been at a madasir at a otherwood,	
Please and me. From and without obtained illustrated Consens Catalog sentai	-1
Please send me—Free and without obligation—illustrated Success-Catalog contains	ming
information about the subject (or subjects) I've checked below. No salesman will	en II
intormation about the autifect (or subjects) I we checked below. No sufestion with	COLL

☐ Watch and Clock Repairing. ☐ Practical Radio Servicing. ☐ Mail Order Business.	☐ Locksmithing. ☐ Real Estate. ☐ Carpentry.	☐ Refrigeration. ☐ Auto Mechanic ☐ Inventions.
NAME		

VAME			
DDRESS.			
	govin	5100 A 5110	



# SO IT NEEDS FIXING

By S. T. CHRISTENSEN

the "Fix-it Man"

WELL, I guess I'm the fellow to see, for I've repaired thousands of refrigerators (home and commercial both), vacuum cleaners, radios, washing machines, irons, fans, lamps, mangles, motors, etc. In fact, many of my customers call me their "electrical appliance doctor." And, "doctoring," I might add, has paid me a good substantial income for quite a few years. Funny, in a way, how I got started. Always liked to tinker and by experimenting around I found that most electrical appliances had many things in common. That, regardless of what the appliance was used for, or who the manufacturer was, the basic principles were much the same. From fixing my own appliances to fixing friends' and then for strangers at a fee, seems now to have been but a small step.

# What to Charge?

At first, I let the owner decide the charge and, frankly, I was amazed at what I earned per hour. But then, when one figures what initial costs are involved in buying most electrical appliances, one can readily see that spending extra dollars for repairs is well worth while. Before long I was making more in my spare time repairing than from my regular job. The result . . . I went into business for myself. When war came, business boomed, for new appliances were not available.

For a while, repair parts (needed on some

jobs) were a little difficult to get. But that situation seems to have adjusted itself for many repair parts have today the high priority rating of AA2. After all, we must provide for the health and well-being of our civilian population.

# The Future Offers

Friends ask me about my future. And, I think I've got a grand one. Age is no handicap in repairing. I have in my files enthusiastic letters from repairmen ranging in age from 18 to 79 years. After the war, we're bound to see hundreds of new products on the market . . . products that the average person never dreamt of. These new products and our old appliances are all going to need at some time or other "fixing." Well, I'll still be the fellow to do it. The field open for appliance repairmen is unlimited. I don't worry at all about too much competition.

# If You Are Ambitious

To the contrary, I've prepared a complete course, chuck full of simple, easy to understand photos and drawings and written in the same non-technical language as this article. I know the course is good, because I have hundreds of men all over the country writing to me telling me how the course has helped swell their pockets with cash. If you too want to prepare now for your future, I suggest you read the next page and send me the handy coupon."

34



Θ

\*

A PROFITABLE
LIFETIME
BUSINESS
OF
YOUR OWN!



# PREPARE NOW FOR THE FUTURE

If now in war work, start your home appliance repair business NOW in your spare time and be set with a business of your own when the war is over. You don't need elaborate fixtures or expensive equipment to be a successful repairman. Operate from your garage, basement, vacant store, etc. Work as many hours as you wish—the home appliance repairman is his own boss. It is a profitable occupation for on many types of repairs it is not unusual for a repairman to charge on the basis of \$5.60 to \$6.00 per hour. Don't gamble with your future—learn a trade that will always support you Remember, as long as electrical appliances are used, there will be a need for electrical appliance repairmen.

If you are at all mechanically inclined—can hold and use tools—then you have all of the qualifications required for becoming a big money earning home appliance repairman. It does not matter if you have not had a great deal of schooling or had previous experience along these lines—WE WILL TEACH YOU. Age should be no barrier—nor should any minor physical handicap.

# **New Course Tells All**

Profusely illustrated, our new course shows you in simple, easy to understand language and drawings how to make each repair on refrigerators, vacuum cleaners, washing machines, motors, etc. Explains and gives you a working knowledge of electricity, welding, nickel plating, etc. Shows you how to build the power tools you need and how to solicit and keep business coming to you. Not a theory course but an honest to goodness course written by and used by repairmen the country over. Price of course is so low that the savings on your own household appliance repairs will quickly pay for it. Act now! Mail the handy coupon below today.

# --- Read What Our Students Say About Course--

I really believe your course the best investment a mechanically minded man can make.—Claude E. Allen, Indianapolis, Ind.

I have received your Course in Appliance Repairing and I must say I am well pleased with same. I am only sorry I did not have said Course some years ago. I have learned so much more through this course I would not part with it.—Charles Schwarz, Hamilton, Ohio.

The Course in Appliance Servicing arrived a few days ago. Want to take out a few minutes of my valuable time to let you know that this is just what I have been looking for ever since I opened up my Fix-It shop. I must admit that you told the truth when you said that it contains quite a bit more information than I bargained for. — P. J. Bretl, Sebring, Ohio.

I am a mechanic for the Western Union Telegraph Co. Three days after receiving the lessons in refrigeration I earned the exact cost of the course.—Henry S. Lee, Washington, D. C.

I work day times at the shipyard and after 4:00 P.M. I operate from my cellar and garage. I average \$10.00 to \$15.00 clear every day.—Walter Hanhy, Brockton, Mass.

# GET STARTED TODAY - MAIL THIS COUPON

GET STARTED

CHRISTY SUPPLY CO. 2835 N. Central Ave., Dept. D-2601 Chicago 34, Illinois

Please send me free illustrated literature about America's Fastest Growing Industry—ELECTRICAL APPLIANCE REPAIRING.

Name....

Address

City.....State.....

# The set of books that makes



# MASTER MACHINISTS

and leads to bigger pay!

This big home-study and reference course gives you the practical facts on machines and methods you need to advance in machine shop work. Take advantage of the other man's experience as found in books, to solve your problems, increase your efficiency, with

# The AMERICAN MACHINISTS' LIBRARY

6 volumes—2368 pages—2516 illustrations (A combined home-study course and reference library)

This library of machine shop practice was written for practical men. It gives you the best methods for every kind of machine shop work. It fully explains lathes, drills, and other machine tools and their operation, automatic screw machines, speeds and feeds, gear design and production, jigs and fixtures, punch and die work, metal surfacing, etc., etc. Plainly written—completely illustrated—the best kind of help to the machine shop man who wants to advance himself.

No money down-special price-easy payments.

FYA	111	NA	TI	ON	CO	17	DO	V
LAA	111 1	14.41	1 1	UN		U	U	7 Y

McGRAW-HILL BOOK CO., 330 W. 42nd St., N. Y. C. 18 Send me for ten days' examination the American Machinists' Library. If satisfactory I will send you \$1.50 in 10 days and \$3.00 monthly until the price of \$19.50 is paid. If not wanted, I will return the books postpaid. (To insure prompt shipment write plainly and fill in all lines.)

Name										 	 	 									
Home A	ddres	5													 ٠,		 				
City and																					
Company																					
Position																					

Be Popular-Learn the Newest DANCES in 5 DAYS-or NO COST!

# NEW REVISED EDITION of DANCING

includes the Rhumba, Conga, Sambo, Jitterbug . Trot, Waltz and Tap Dancing.

All the newest Swing steps -- the Rhumba, Conga. Samha, Jitterbug, as well as the Fox Trot. Waitz and basic tap steps—explained with

simple, graphic diagrams.

GET MORE FUN OUT OF
LIFE! Swing your way to
popularity! Start now and
fill your future with Romance! MAKE THIS FREE
TEST! The new REVISED edition of Betty Lee's book.

Dancing, helps you learn correctly and quickly. Be convinced—if not satisfied with results, you will get your money back! And remember, we include two other books—"Tip Top Tapping" and "Swing Steps"—FREE of extra charge.

SEND NO MONEY! Pay the postman \$1.98 plus a few cents postage. Follow instructions in ALL THREE BOOKS—practice simple dance steps each day and in 5 days if you haven't learned to dance, we will refund your money!

PIONEER PUBLICATIONS, INC.

we will refund your money!

1790 Broadway, Dept. 873H New York 19, N. Y. Send me "Dancing," by Betty Lee, and include 2 free books.

Ship C.O.D. I will pay on arrival,

plus postage.

I enclose \$1.98. Ship postage prepaid.

If in 5 days I do not learn to dance, I may

return book and you will refund purchase price.


City......State.....

# Free for Asthma **During Winter**

If you suffer with those terrible attacks of Asthma when it is cold and damp; if raw, Wintry winds make you choke as if each gasp for breath was the very last; if restful sleep is impossible because of the struggle to breathe; if you feel the disease is slowly wearing your life away, don't fail to send at once to the Frontier Asthma Co. for a free trial of a remarkable method. No matter where you live or whether you have any faith in any remedy under the Sun, send for this free trial. If you have suffered for a lifetime and tried everything you could learn of without relief; even if you are utterly discouraged, do not abandon hope but send today for this free trial. It will cost you nothing. Address

Frontier Asthma Co. 462 Niagara Street,

159-R Frontier Bldg. **Buffalo 1, New York** 



# Sturdy steel construction for lifetime use, subtracts, aids multiplication. Capacity 999,-999,99. A real machine—guaranteed 5 years.

Thousands of satisfied users. Send name and address. We ship immediately. On delivery, pay postman \$2.50 (plus C.O.D. and postage charges). If you send \$2.50 with order, we pay postage. Leatherette case 25c additional. Your money back after 10 days' trial if not satisfied,

TAVELLA SALES CO., 21-CA West Broadway, New York 7, N. Y.

# Inventions Patented or Unpatented

Inventions can now be safely sold without patenting expense. If you have a practical, useful idea for sale, either unpatented or patented, write today!

Chartered Institute of American Inventors Dept. 3, 631 Pa. Ave. N. W., Washington, D. C.





Registered Patent Attorneys Since 1875 Write for Free Book and "Certification of Invention" form 427 SNOW BUILDING, WASHINGTON 1, D. C.

# SEND FOR FREE BOOK-

Written by Former Member Examining Corps (1822-24) U.S.Patent Office.

CARL MILLER, Registered Patent Attorney Former Member Examining Corps U. S. Patent Office Waslworth Bids., Dept. 35-C, New York—Band Bidg., Dept. 35-C, Washington, B. C.


Don't go on day after day suffering the tortures of a clumsy truss that presses on your hips and back, gouches your flesh, slips and slides and leaves your rupture DANGEROUSLY UNPROTECTED.

about rupture care THEFT patented Vita-Pneumatic Nature-Ade (U.S. Reg.) appliance with its unique features can help your rupture, misery disappear. Write at once for FREE booklet containing much valuable information.

# PHEUMATIC APPLIANCE, 103 PARK AVE., N. Y. 17, N. Y., DEPT. 72F New Desians in Modernize Your Gun! Improve Your Score! Most durable grips made. Positively un-Ortgies, Luger & Mausers in a wide choice of beautiful

breakable! For Colt, Smith & Wesson, Hi-Standard. designs in ivory, pearl, walnut, onyx, etc. Low prices. FREE CATALOG. Dealers Wanted.

SPORTS, INC., (Mfrs.) 2850 N. Clark St., Dept. S-3, Chicago 14



# LEARN PLASTICS NOW!

Plastics are playing an increasingly important part in almost every industry—improving old products and creating new ones. That is why such a brilliant future is predicted for plastics in the postwar period—offering opportunities to farsighted men and women who know plastics. Now is the time for you to prepare for a career in this fast-growing field.

**LEARN AT HOME**—You can learn plastics in your spare time at home without interrupting your present work. The Plastics Institute has developed a thorough, easy-to-understand course of training, requiring no previous technical experience. It offers complete, authoritative training based on industry requirements.

FASCINATING COURSE—The lessons are readily grasped and practical. Every step is made clear with graphs, diagrams, pictures. Actual specimens of plastics materials are furnished. A bi-weekly bulletin, "Plastics Trends," keeps you posted on new developments.

COMPREHENSIVE—Learn the various phases of plastics from this course... materials, designing, molding, fabricating, estimating and plant management. Acquire a basic knowledge of plastics that can be invaluable in preparing you to take your place in this great new industry.

America's oldest and largest plastics educational organization which devotes all of its facilities exclusively to plastics. It is held in high esteem by members of the plastics industry. Many of our graduates hold responsible positions in the plastics field.

**START YOUR FUTURE—TODAY!** Mail the coupon below now! We will send you an interesting booklet filled with valuable information on plastics and tell you how, at small cost, you can prepare for a career in this important industry. Don't put it off! Mail today!

Dept. PS-3, 122 E. 42nd St., New York 17-Dept. PS-3, 221 N. La Salle, Chicago 1-Dept. PS-3, 186 S. Alvarado, Los Angeles 4

SPECIAL RATES FOR SERVICE MEN G. I. Training INDUSTRIES TECHNICAL INSTITUTE WORLD or PLASTICS Plastics Industries Technical Institute Mail in Envelope of 221 N. La Salle St., Dept. PS-3, paste on penny postcard Chicago 1 Gentlemen: Please send me the booklet "World of Plastics" and information on your training program. I understand there is absolutely no obligation, Name......Occupation...... Street.......Age.......Age...... FREE BOOKLET City......Zone.....State...... Send For It Today! Veterans. Check here for special information on G. I. training privileges. If under 18: Check here for special booklet.



# How to make a good living on a small farm

Want a small farm? Own one now? If you do want the enjoyment of security, a good living, pleasures of rural life, the freedom in being your own boss, FIVE ACRES AND INDE-PENDENCE—the all-inclusive book by M. G. Kains, world's leading small farm expert—shows you how to select, how easily to run your farm successfully.

This book tells what kind of farm to rent or buy; how to choose it; finance it; what and how to plant; choice and care

of livestock, poultry, beer etc.; essentials of fruit an vegetable growing; fertilizers irrigation; spraying; cultiva tion; harvesting; storage; sal of products and by-products Every page packed with prove ways to make the small farr self-supporting-even profitable. Abundantly illustrated with workable plans and diagrams. Over 400 pages.

Plan now to get away from city worries, war shortages, high rents, inflation. Use this book as your

guide. If not satisfied, return for full refund.

Send No Unless You Wish. Pay postman \$2.50 plus 22c. COD and postage charges. If you send cash with order we pay all charges - you save 22 cents.

5	THE OWNER OF THE OWNER OWNER OF THE OWNER OWNE		
2	IVIS	ALI	144
	10	HLII	7
an	a ynai	gena	ence
1	The little	-	
	and the same	*	-
1	-	1	7
	E CHE	FIVE and Shad	FIVE ACH

GREEN 404 M															0	r	k		1	7
Send DEPEN If not within	D	E a t	N is	c	e	d.	a	t	t	\$ 2 n	.5 a	O	P	e	S	t	p	a	ld	ı.
□ Payn																			D	
NAME.	٠.	×		Ç,		•									*					
	55																			

CITY & STATE ..



SPRINGBOARD TO SUCCESS!

Increased salary, larger responsibilities, a real career instead of just a job—these are to be had by the trained draftsman. I.C.S. makes the way to thorough, practical training open to you. Check up and you'll find that nearly every "big name" American in engineering and production acquired experience at the drafting board. Many of them started by writing for the I.C.S. free booklet. Send for it today! It can be the most important act of your life.

International Correspondence Schools, Box 7613-L, Scranton 9, Pa.

# ARMY AUCTION BARGAINS

Musket screwdrivers, 3 for	20
	.00
	.00
	.30
	.75
	.40
	.40
Prices do NOT include postage. 1945 circular showing the	.40
and many other articles mailed for 3c stamp	250

# FRANCIS BANNERMAN SONS 501 Broadway, N. Y. 12

WANT a permanent business profession of your own? Then become a foot correctionist. Earnings of men and women in this greatly needed profession

run as high as \$50.-\$100. weekly after a few weeks home training -not medical or chiropody-easy terms, no further capital needed, no goods to buy. 50th year. Write for free booklet.

Stephenson System of Foot Correction, 62 Back Bay, Boston, Mass.





Exquisite Onyx-like Picture Ring-made from any photo, Send No Money! Mail photo with paper strip for ring size. Pay postman only \$1.00 plus post-sen. Hand tinted 25c extra. Photo returned with ring. guarantee. Send photo and ring PORTRAIT RING CO., Dept. G-66, CINCINNATI, O.

> RE-SOLE Easy—at home. Spread on So-Lo. It wears like leather. For all footwear, children's and grownups'. Also mends tires, raincoats, boots-anything of rubber, leather, cloth.



# MEND THE HOLE for

SPREADS on like butter. Dries tough overnight, Flexible, Non-skid, Waterproof. Won't come off-guaranteed.

SO-LO AT ANY HARDWARE



# hinking of Buying

Don't do it until you send for my "Have-More" Plan to read and examine free-it may save you hundreds of dollars and many heartbreaking mistakes.

Tells how to have a place that will pay for itself!
My "Have-More" Plan is the true story of how my family and I moved from the city to a little two-acre place in the near-by country to find "a little land and a lot more living" and how I've kept a regular full-time job. Tells how we grow most of our own food in spare time—have fun doing it—have better health—more sunshine and fresh air—more peace and quiet more security and independence—in fact, more of just about everything that makes life worth living! My "Have-More" Plan contains over 50,000 words, 73 illustr., many actual photos of our own place,

It tells the how of all our shortcuts, ideas, labor-saving methods -how it takes us only an hour or so of spare time a day to have tender chicken to eat, plenty of eggs, a wonderful garden with a lot less work, delicious rabbit meat at only 8c a pound, rich milk, butter, cream from our miniature dairy, tasty ham, pork, bacon, sausage, geese, turkeys, squab, honey bees, fruit trees instead of shade trees, luscious grapes, berries—how we use

new, easier preserving methods, including quick freezing. Best of all, my Plan tells you how to choose the right kind of place-how to save hundreds of dollars in buying and financing

—how to avoid costly mistakes.

The "Score-Card" of what to look for is worth more by itself than the whole price of the Plan—which is only \$1.00. Honestly, if you're thinking of buying or building (or if you already have a place), my Plan can be the biggest dollar's worth you ever got—and I'll send it to you to look over and examine free. If you don't like it—if you don't agree it's worth many times one dollar—just send it back and owe me nothing. If you keep it—just send me one dollar, full price—I know you're going to be delighted—so drop me a postcard now—Yours for "a little land and a lot more living."

and a lot more living."

ED ROBINSON, Box 2803, Noroton, Conn. (Of course, if you'd prefer to send your dollar now, that would be fine—save me a lot of record keeping. I'll gladly refund your dollar if

you're not delighted.)

# 40 PAGE HOBBY CATALOG

Over 1000 Items — Over 300 Photos

Our new 40 page catalog—just off the press—is the bible" of wide-awake modelers. Practically every nationally advertised model is listed and many, many hard-to-get items. Planes, engines, boats, gliders. supplies, etc.

AMERICAS HOBBY CENTER, Dept. SC35, 40 E. 21 St., N.Y. 10, N.Y.



STUDY AT HOME for PERSONAL SUCCESS and LARGER EARNINGS, 35 years expert instruction —over 108,000 students enrolled, LL.B. Degree awarded. All texts furnished. Easy payments. Send for FREE BOOK—"Law and Executive Guidance"

AMERICAN EXTENSION SCHOOL OF LAW Dept. 51-S, 646 N. Michigan Ave., Chicago 11, III.



STUDIOS

PORTRAIT PAINTING

Under unique Stuart System men and women with no known talent, paint exact oil or charcoal likenesses. Study the evidence in new 42-Portrait Brochure of samples. Many earn while learning. Book is free on request.

121 Monument Circle, Room 283, Indianapolis 9, Ind. Please send me free book and outline of lessons,

Name	 	 
Street	 	 
City	 <b></b>	 



# EFRIGERATION

Air Conditioning and Refrigeration are among the great industries of today and tomorrow. Installations everywherein restaurants, shops, homes, etc., need service. Thousands of businesses are waiting for new installations. The day may come soon when homes, too, will be air conditioned. The Refrigeration and Air Conditioning industries are headed for greater prosperity and men who have the "know how" and experience should ride along.

# Tain NOW Before the Expected EXPANSION Begins

Experts predict large demand for men to install and service Air Conditioning and Refrigeration equipment . . . Rise to the kind of job which requires a competent, trained man who can carry the responsibilities of installing costly equipment and maintaining it. If he knows the answer when he is called in for consultation, his reputation grows and his pay should grow also. Historic SUCCESSES May Repeat Do you realize where you might be today if you had been in on the ground floor when some of our great industries began? Men who see ahead are more apt to be the ones who later cash in on the growth of the industry. FollowThisWay to Knowledge Here is all it will take to get you ready for ex-perience in this modern industry. You just in-

vest a limited amount of your spare time—while you are still on your present job. Through our balanced training, you learn first through home study, how to handle Installation, Maintenance, and Service Work on Refrigeration and Air Con-ditioning equipment, Then you can get practical experience in our big shops under capable in-structors—practical men who will take a personal interest in helping you learn. When you are through you should have the knowledge that enables you to get started in this vast industry.

GET FREE FACTS RIGHT NOW! It costs you nothing to get all the facts about this great field. Simply mail the coupon below and we'll tell you, without obligation the whole, sensational story of what's ahead in Refrigeration and Air Conditioning. Mail the FREE coupon now. UTILITIES NUMBER WITH

FRIGERATION TRAINING Since 1927

1314 W. Belden Avenue, Dept. 335, Chicago 14, Ill. Please send me the FREE FACTS about opportunities in

Air Conditioning and Med	chanical Refrigeration. I have marked
the one that interests me	most.
Air Conditioning	Mechanical Refrigeration

NAME	
	100
ADDRESS.	

CITY.

CONDITIONED

# DON'T WAIT UNTIL THE WAR IS OVER!

Since 1929 Cal-Aero Technical Institute has been specializing in modern, progressive training for Aeronautical Engineers and Master Aviation Mechanics. Prepare now for your Aviation Career, BE READY! Opportuni-

ties are great today and will be greater in tomorrow's Age of Flight. DISCHARGED VETERANS—Write us about Aviation Training as provided under "G. I. Bill of Rights."





FORMERLY CURTISS WRIGHT TECHNICAL INSTITUTE GRAND CENTRAL AIRPORT GLENDALE 1, CALIFORNIA

# THIS COUPON

Cal-Aero Technical Institute, Grand Central Airport, Glendale 1, California. Send information and illustrated catalogue on Aviation Training. FREE . . . without obligation . . . Dept. PS-3

Name	Birth Date
Street	

# Make Your Own Post War Plans NOW! Get Started QUICK in

I Will Train You Until You Get GOOD PAY Engineer Vole

Plan now for a better job and more pay as America Changes over to peace-time production. Drafting is the field-now bigger than ever be-fore. And countless thousands of draftsmen and designers must come first—before new produc-tion can begin. Get into Drafting. Engineer Dobe will train you at home in your spare time. You'll get experience on actual work—the same kind of jobs you will do for the best paying firms. You will be trained until you are competent, experienced, and are actually holding a position that will bring advancement and pay raises as deserved. Write today for details.

# WORKING TOOLS FURNISHED



Engineer	Dobe,	Div.	23,	Libert	vville.	111.

Send me the Vital Facts on Drafting and Industrial Designing. your FREE BOOK and advertised list of positions for Draftsmen and Designers, wanted.

Name			+								٠								ä	A	١g	e	٠.			
Address				9			×	+	*				•				è					×	×			

City......State.....

# LIKE TO RELIEVE INCONVENIENCE

AND **PAIN**?

A Modern Inhalant Method for Relieving the Symptoms of Asthma of Non-Cardiac Nature and Hay Fever

# Breatheasy

Money Back Guarantee

Send for Free Book, Dept. PS

BREATHEASY DISTRIBUTORS

65 Cedar St., Seattle 1, Washington

Use This or Any Similar Product Only As Directed By Accompanying Literature.

# earn LANDSCAPE *GARDENING*

Prepare for the giant postwar home-building program. A thorough, interesting constructive home training for those who wish to become LANDSCAPERS, DESIGNERS, GARDEN-ERS, etc., for profit or pleasure. Write today for FREE INFORMATION without obligation to

NATIONAL LANDSCAPE INSTITUTE

Dept. PS-3, 756 So. Broadway, Los Angeles 14, Cal.

Place your songs with us. Melodies supplied WITHOUT CHARGE by well known Hollywood composers. We record your song and make it presentable to the publishers. Lead sheets and records furnished. Send your song material for free examination. Write for details.

CINEMA SONG CO. Dept. B-21 P. O. Box 670 **Beverly Hills, California** 



To make Crowns, Plates, Bridgework, etc., for Dentists. Easy practical way to learn mechanical dentistry at home in spare time. FULL EQUIPMENT OF TOOLS AND MATERIALS INCLUDED WITH COURSE. Low tuition. Easy terms. Write for FREE BOOK about this money making profession that is not affected by the machine age.

McCarrie School of Mechanical Dentistry road St.

Dept. 836

Philadelphia, Pa.

207 N. Broad St.

# DIRECT TO YOU \$Q95

'ESBLAIR'

1882 1931

Genuine beautiful ROCKDALE Monuments, Markers. Satisfaction or MONEY BACK. Freight paid. TERMS Free catalog. Compare our prices. Rockdale Monument Co., Dept. 501 Joliet, III.

# ROCKET TO THE MOON? SOON!

Wartime Developments in Rocket Technique Point Way to Post-War Inter-Spacial Rocket Adventure!

Join United States Rocket Society, Inc. A nation-wide organization of service men and technicians of all kinds who are determined to see that our Country wins the RACE TO CONQUER SPACE! Send 25c for informative application. Keep in the advance ranks of progress! United States Rocket Society, Inc., Box 29, Glen Ellyn, Illinois,

PREVIOUS EXPERIENCE

NOT NEEDED

I train you through practical jobs and give

your experience as a reference to employ-ers when you become competent. Lack of

previous experience or higher education should not hold you back. Low cost-and



Men! Boys! Amaze your friends, surprise and thrill the girls! Here's the most amazing, spectacular necktie you ever wore, smart, wrinkle-proof, tailored, by day a lovely swank tie in special color combinations to look smart with any suit, and at night like a miracle of light it leaps to life with pulsing, glowing question-"Will You Kiss Me In The Dark, Baby?" Think of the fun in any crowd! Think how the girls gasp with wonder as the question takes form so amazingly. And here's wonderful news! You can see, examine this new, utterly different, glorious tie yourself without risking a penny!

# SEND NO MONEY

Examine-let it thrill you on this FREE TRIAL OFFER. Remem-

ber it's a high-class, distinctive tie by day, ties up perfectly. You might expect to pay \$2 or even \$3 for this cravat just for daytime wear, but the low introductory price is only \$1.49. Send for Glow In The Dark Necktie and on arrival pay postman only \$1.49 plus postage, or send cash with order and maker pays postage. If not thrilled and delighted, return tie for money back. But don't wait. Send now. GLOW IN THE DARK NECKTIE CO., Dept. 450-K, 215 N. Michigan Ave., Chicago 1, Illinois.

# you can be a well-paid

Accountants are well paid and in demand. World-famous I.C.S. shows you how to join them. Wide variety of Courses individually tailored. For men or women with no previous experience. For those already in accounting. Instruction papers by well-known Professors of Accountancy, Certified Public Accountants. Excellent preparation for C.P.A. examinations. Home study . . . low cost . . . rapid progress. Write for free booklet containing full information.

international Correspondence Schools, Box 7613-L. Scranton 9, Pa.

# MONEY-MAKING

IN SPARE TIME — by Easy Picture Chart Method Same Simplified Method that has helped train creators of "Terry & Pirates," "Freckles," "Out Our Way." "Winnie Winkle," "Reg'lar Fellers," "Strange As it Secms." "The Neighbors." and many others. Earn while learning. Send 10c for Picture Chart (to test your ability), and full details. (State age.)


THE LANDON SCHOOL Dept. 4523, Philadelphia I, Penna.



It's so important to write a good hand for business and social advancement Poor illegible penmanship often causes costly errors and marks you for fall-ure. Why write a poor hand? It's so easy to learn at home in spare time. Write for our new free booklet today. If you wish, send 10c for a penpoint suitable for shaded
In Business writing and your name beautifully written.
THE TAMBLYN SCHOOL OF PENMANSHIP
H-439 Ridge Bldg., Kansas City, Mo., U.S.A.



# Amazing Handy ADDING MACHINE



Can Be Carried in Vest Pocket

ONLY

POSTPAID

**ABSOLUTELY** ACCURATE

# YET WEIGHS ONLY 5 OUNCES

- Handles Totals up to \$10,000,000.00.
- Totals appear instantly—as fast as you put the figures down.
- Can be used to subtract, multiply and divide, as well as add.
- Metal construction for years of service.

Haven't you often wished for a handy little device like this . . . that you could take with you ANYWHERE . . . on the road, in the office, at home or in the shop? You can get one now . . . Business man, student, housewife—everyone finds this handy guaranteedaccurate little machine useful . . . ORDER YOURS TODAY.


# SEND NO MONEY

Just send name and address. Then pay postman \$2.50 plus postal charges on delivery. Or send \$2.50 with order and we pay all charges-saving you about 50 cents at the new postal rates.

LEE SPECIALTY CO., Dept. PS-8 Box 3620, Mdse. Mart, Chicago 54, Ill.

-- MAIL COUPON TODAY-

Box 3620, Mdse. Mart, Chicago	5-8, 54, III. MIDGET ADDING MACHINES.
☐ I am enclosing \$2.50	☐ Send C.O.D, plus postage
NAME	
ADDRESS	
CITY & STATE	NT PLAINLY



# Every Ambitious Man in Industry Should Read this Free Booklet!

"FORGING AHEAD IN BUSINESS" contains FACTS for all thoughtful, forward-looking men; it has a message of particular interest to technical men.

This 64-page booklet, of which more than 3,000,000 copies have been circulated, outlines a definite plan of training for your future progress in industry.

Said one man who had sent for it:

"In thirty minutes this booklet gave me a clearer picture of my business future than I have ever had before."

Fill in the coupon below and this helpful manual will be sent to you by mail and without cost.

ALEXANDER HAMILTON INSTITUTE Dept. 255, 73 West 23rd Street, New York 10, N. Y. In Canada, 54 Wellington St., West, Toronto, Ont. Please mail me a copy of the 64-page book— "FORGING AHEAD IN BUSINESS."

Name	•••	••	 ••		•	٠.	•	••	•	••	•	 •	••	•	••	••	••	••
Address																		



THEATRE INSTITUTE

385 Washington St.,

# PRINT ANY PHOTO

on Paper, Cloth, Leather or Wood

# SIMPLE, EASY TO USE

Magic liquid takes only 2 minutes to reproduce any snapshot you have on to stationery, handkerchiefs, ties, scarfs, etc. Won't wash off. Won't hurt negative or fabric it's used on. Personalize your belongings! An ideal gift. Complete outfit with full colors included, enough for 100 photos—only \$1.00 postpaid. Sent C.O.D. for \$1.21.

CHRISTY PHOTO SUPPLY

Dept, 621

2835 N. Central, Chicago

# REPAIRED

Guaranteed Service

FREE

Just mail your Fountain Pen (any make) under insured mailing to us and we'll send you a free repair estimate to put your pen in perfect writing condition. Then we'll quickly, expertly, repair your pen on receipt of your Okey. Then we will return pen insured C. O. D. for the repair cost, plus postage. Low prices; 100% guaranteed work.

EL'GENE REPAIR CO. Dept. PS3, Chicago 30, III.



Begin today. Write now for our Free Book. "How to Become a Good Penman." it contains specimens and tells how others learned to write in spare time. Enclose 10c for your name beautifully written and a pen point suitable for shaded writing. Write today. THE TAMBLYN SCHOOL OF PENMANSHIP N-439 Ridge Building, Kansas City, Mo.

# New OTTAWA WOOD SAW



For Tractors

-Makes wood sawing fast and easy. Can cut enough wood to pay for itself quickly. Easily moved while attached. Big heavy blade. FREE details.

OTTAWA MFG. CO.

W-301 Oak Ave., Ottawa, Kans.

# Wonder-Tone NOISE ELIMINATOR

Just attach to your radio (long, short wave) and enjoy reception free from distracting noises. Send-No-Money Pay Postman 60c plus postage or send 60c and we'll send postpaid. Return in 5 days for refund if not delighted.

Wonder-Tone LINE-NOISE ELIMINATOR

Wonder-Tone Co., 7078 N. Clark St., Dept. 105, Chicago 26.

# HIGH BLOOD PRESSURE

A DANGER SIGNAL

Often associated with Hardening of the Arteries, a Stroke. Paralysis. Heart Trouble. Kidney Disease, and other grave complications. Resultful treating methods of the Ball Clinic have proven dependable for nearly a quarter of a century. Send for FREE Blood Pressure Book today. No obligation.

## BALL CLINIC, Dept. 5160, Excelsior Springs, Mo. This Interesting 24-page Illustrated Book, Full Information **New Home Study Method Fits** You For Bigger Pay in Aviation and Costs The aircraft industry needs trained draftsmen and engineers NOW-and for the big TOMORROW in Aviation, Ryan's new Home Study Method offering you RYAN Aeronautical Institute "direct-from-industry" training in Aeronautical Draft-ing and Engineering will prepare you during your spare 413 Lindbergh Field, San Diego 1, Calif. Please send me, without any obligation on my part, your time for a top-paying job and a future. It's a safe bet FREE 24-page illustrated book, "New Horizons of Opporthat many of the pleasure and commercial airplanes tunity," and full information on R.A.I., including cost of after the war will be created by Ryan Trained Draftstraining and job opportunities. men and Engineers. Course is easy to understand. No HOME STUDY higher education or special experience necessary. AFFILIATE OF Pay as you learn. Send coupon today for FREE 24-page book..."New Horizons of Opportunity." RYAN SCHOOL To save time, send coupon air mail. OF AERONAUTICS State City

# KEEP YOUR EYE ON THE SUPERINTENDENT

If others are getting promotions and you are not, don't discount your ability. There is an easily applied remedy that will bring you to the attention of the top men in your plant.

How to acquire this ability is the subject of a 48 page book-let that is yours for the asking.

It tells how natural ability can be combined with a knowledge of shop practice plus training in the art of handling people. These talents win key positions in industry.

Write to Louis S. Vosburgh

LINCOLN EXTENSION INSTITUTE, INC.

1401 C West 75th Street Cleveland 2, Ohio

# ELECTRIF your career!

There's big money in Electrical Engineering. Be smart—study it NOW. Noted I.C.S. Courses cover the fundamentals and the out-of-the ordinary things it's necessary for specialists to know. I.C.S. has had more than 50 years of training men for success. The School of Electricity is a separate and complete school giving specialized training—yet enjoying benefits and resources which only a vast institution like I.C.S. affords. And you benefit by the teachings of experts connected with the largest concerns in the field. Send for FREE informative booklet telling what I.C.S. can do for you. International Correspondence Schools, Box 7613-L, Scranton 9, Pa.

# Big Money for Workers In Home or Shop



Licensed Concrete Specialists wanted. No experience needed. Make Colorglazed concrete pottery without molds. New, lost cost, patented method, Cemetery products, novelties, tiles, etc. Basement leakscaling, Other big pay projects. Booklet, details free. Men only.

NATIONAL POTTERIES COMPANY 542 West Lincoln, Fergus Falls, Minnesota

Tan SKINS, Make Up FURS
Be a Taxidermist. Double your hunting fun. We teach

you at Home. Mount Birds, Animals, Pets, Heads and Fish. Save your hunting trophies: decorate home and den. MAKE MONEY. Mount and Krome-tan for others. Big sparetime profits. INVESTIGATE TODAY.

FREE BOOK with 100 game pictures. 48 pages. Send postal card TODAY -- This Minute! State your AGE. NORTHWESTERN SCHOOL OF TAXIDERMY: Dept. 3393 Omaha, Nebr.

# FOR COUGHS FROM

cuts, aches, burns, sprains use TAYLOR'S OIL (Called Taylor's Oil of Life over 80 years). At your favorite store.

35c, 75c, \$1.50


# PRINT *any* SNAPSHOTS ON PAPER-CLOTH-LEATHER or WOOD



Remarkable liquid makes photos appear, like magic, IN 2 MINUTES, on any scart, tie, book, shirt, linens, blouse, greeting cards, hankies, etc. Easy to use—no experience needed. No dark room necessary. Won't wash off. Won't hurt negative or fabricit's used on. Personalize your belongings. Wear your picture, your sweetheart's, husband's, or son's, on belongings.

GIVE

Social Stationery Given with every order. Com-plete set. Thrill your friends, seeing your picture on letters.



transfer up to 150 photos. If you prefer, mail 98c and pay postage. You'll be delighted!

Great American Sales Co., 55 E. Washington St., Dept. 751, Chicago 2, Ill.

# 

AND OTHER ELECTRONIC EQUIPMENT

Tells WHAT to do ... Exactly HOW to do it

If you like to repair radios at home in spare time, Ghirardi's RADIO TROUBLESHOOTERS HANDBOOK offers you a new, fast way that makes the work easywithout previous experience or scarce, expensive test equipment. Or, if you are a professional radio man, it helps you repair two sets in the time normally required for one, train new helpers, etc. etc.

# NOT A "STUDY" BOOK

You don't study this Handbook—you simply look up the radio's Make, Model and the Trouble Symptom . . . and go to work! Clear instructions tell you exactly WHAT the trouble is . . . and exactly HOW to fix it. This BIG 744-page HANDBOOK brings you repair data for practically every radio in use—over 4000 models! Pays for itself first time used!

In addition, there are hundreds of pages of helpful repair charts and data on tuning alignment. transformer troubles, tube substitutions, color codes, etc. 5-day Money-Back Guarantee.

Money-Back Guarantee.

A complete

guide to quick,

easy troubleshooting

# LEARN PROFESSIONAL SERVICE WORK AT HOME

Study now for a good job as a Radio-Electronic repairman! It's easy to learn from Ghirardi's 1300-page illustrated MODERN RADIO SERVICING book that costs you only 5 dollars complete! Covers all phases of the work! Explains all necessary test instruments and how to build your own; how to troubleshoot all makes of receivers, analyze their circuits, test components; make adjustments; repairs, etc., all step-by-step. Even explains How to Start a Radio-Electronic Service Business. See Money-Saving Combination offer below.

# COMPLETE BASIC RADIO ELECTRONIC TRAINING FOR BEGINNERS

Easily worth \$50 if you bought it as a course

Ghirardi's famous 972-page RADIO PHYSICS COURSE book with its 500 illustrations and—selftesting review questions has given more beginners their start in Radio-Electronics than any other book or course ever pub-lished. It will do the same for you! Noth-ing is omitted, noth-

ing condensed. Everything made easy as A-B-C. Ask any radio man! You'll be amazed how quickly you'll master the subjects other courses make very compliseem Examine this cated. truly great book for 5 days-and get every cent of your money back if not more than satisfied!

More universally used for home study, by more Signal Corps. Navy and civilian schools than any book of its kind!

LEARN AT HOME—WITHOUT AN INSTRUCTOR!

# 5-DAY MONEY-BACK GUARANTEE

Technical Division, MURRAY HILL BOOKS, INC. Dept. PS-35, 232 Madison Ave., New York 16, N. Y.

☐ Enclosed find \$..... for books checked; or ☐ send C.O.D. (U.S.A. only) plus postage. If not fully satisfied. I may return books within 5 days and receive my money. RADIO PHYSICS COURSE

\$5 (85.50 foreign)

RADIO TROUBLESHOOTER'S HANDBOOK \$5 (\$5.50 foreign)

☐ MODERN RADIO SERVIC-ING \$5 (\$5.50 foreign) ☐ MONEY-SAVING OFFER Modern Radio Servicing AND Troubleshooter's Handbook \$9,50 for the two

						(\$10.50 foreign)	
Name	i s						
City &	Trick Confedence	No.	CTV: NO.		anar casa	State	
		(Please	write	or	print	plainly)	

# REFRIGERATION

SEND FOR FREE TRIAL LESSON

INTERESTING AND EASY TO LEARN

We will prove it to you by sending you afree trial lesson. Send coupon below.

# A BUSINESS OF YOUR OWN

or a better job are both within your reach in this new field of opportunity. Air Conditioning, Home Freezers, Locker Plants, Industrial Refrigeration—all fields which are in need of trained men. You can be one of them. TRAIN WHERE THE U.S. ARMY TRAINED.

# Learn in Your Spare Time—AT HOME

(or full time in our schools in Chicago or Birmingham) Simple, easy to read lessons, with many illustrations, followed by actual practical work in our big complete shops. Free book gives complete details.

Commercial Trades Institute is an approved school for those who qualify for training under the "GI" bill.

## COMMERCIAL TRADES INSTITUTE, DEPT. 5-5 209 W. JACKSON BLVD., CHICAGO 6, ILL. 200 S. 20TH ST., BIRMINGHAM, ALA.

Please send me your FREE trial lesson in Refrig-eration and Air Conditioning. I understand there is no obligation and there is no charge for this lesson

	-	ALCOUR.	
NAM	E		 
ADD	RI	ESS	 

CITY.....STATE....

OCCUPATION.....AGE for EVERY WORK SHOP!

Easy to Plate CHROMIUM GOLD, SILVER, NICKEL, COPPER

. . . For Pleasure and Profit! If you have a workshop-at home or in business-you need this new Warner Electroplater. At the stroke of an electrified brush, you can electroplate models and projectsyou can replate worn articles, faucets, tools, fixtures, silverware, etc. with a durable, sparkling coat of metal . . . Gold, Silver, Nickel. opper or admium. Method is easy, simple, quick. Everything furnished-equipment complete, ready for use. By doing a bit of work for others, your ma-chine can pay for itself within a week. So make your shop complete by getting a Warner Electroplater right away. Send today for FREE SAMPLE and illustrated literature. ACT AT ONCE! Mail Coupen.

WARNER ELECTRIC CO., DEPT.A-29 360 North Michigan, Chicago 1, Illinois

MER ELECTRIC CO., 360 N. Michigan, Chicago 1, Dept. A-29 Gentlemen: Send Free Sample and Details to:

Address\_

City

State

# X ANY RADI

Amazing New Invention

Simplified Radio Servicing Comparison

Learn quickly to repair all radio sets. New, revolutionary different picture method per-mits you to do radio servicing almost immedietely. No previous radio knowledge required. Introductory training included. Find any fault quickly, Use a screw driver, pliers, and a piece of wire—no testers needed. Simple, point-to-point picture suggestions tell you where to look for faults and how to make the repair. Plan U. S. Copyrighted. Covers every radio set — new and old. You may try the plan for 10 days without any risk. Easy to

Price only \$1.50, post-paid. In Manual form, \$1.5x11 in, 72 large job-sheets. Data on 346 radio tubes, 16 trouble shooting blue-prints. Over 1 000 time-saving sorvice bints tubes. 16 trouble shooting blue-prints.
Over 1,000 time-saving service hints.
Idea developed by M. N. Beitman, noted engineer and author. Order without risk for 10 days use, Write today.

SATISFACTION GUARANTEED
Read the introductory job sheets,
follow the step-by-step picture
blueprints, and fix any radio in
minutes instead of hours. The
complete simplified training is
yours for only \$1.50, postpaid, 10
days trial, Money back guarantee,
SIPPEME PURLICATIONS
95. Kedzie Ave. Chicago 12, III.

95. Kedzie Ave., Chicago 12, III.

A Substitute Motor Fuel! Ingre-

dients ration free at popular prices at Paint Houses. Wholesale Drug Companies, Chemical Companies, Free details: AUTO DATA, BOX 571 NEWARK 1, N. J. Please Print!

# JIU-JITSU

HOW TO BECOME EX-PERT, Keep Health, Have

Fun. Teaching 35 years. Send 10c for sample lesson. Modern School Jiu-Jitsu, Dpt. AA, 5 W. 52 St., N. Y. 19

# HOW TO MAKE CIGARETTE ROLLER

Sample and instructions how to make of wood—easy to sell-badly needed. Mail \$1.00 to

Commercial Specialty Company, 342 E. 214, Euclid 19, Ohio.

"The Book They're Talking About"



# OF THE HUMAN FIGURE

For the amateur and professional artist. Contains over 350 illustrations, charts and notes, giving detailed study of every part of the body. MALE and FEMALE—POSED and \$1 IN ACTION. Outside U. S. A. Send \$1.25 MAJOR BOOK CO., Dept. 41-C 72-04 Juno St., Forest Hills, New York



Be a Dealer in your locality for STRONG UNION MADE WORK AND SPORT GARMENTS, No experience necessary, Easy work, Millions of defense workers buy work uniforms, We supply everything needed, Write immediately for FREE Outfit.

ROBT. STRONG GARMENT CO.

319 W. Van Buren St., Dept. G-4
Chicago 7, III.

# do you **WOR**!

Why worry and suffer any longer if we can help you? Try a Brooks Patented Air Cushion. This marvelous appliance for most forms of reducible rupture is GUARAN-TEED to bring YOU heavenly comfort and security-day and night—at work and play—or it costs you NOTHING. Thousands



happy. Light, neat-fitting. No hard pads or springs. For men, women, and children. Durable, cheap. Sent on trial to prove it. Not sold in stores. Beware of imitations. Write for Free Book on Rupture, norisk trial order plan, and proof of results. All Correspondence Confidential.

Brooks Company, 160-D State St., Marshall, Mich.

CARE and USE of HAND TOOLS primer on the care of hand tools for the unskilled primer on the care of hand tools for the unskilled beginner. Simple language. Clear illustrations. Easily understood by those Precise instructions. Easily understood Only basic instructions. Easily understood by those without technical training. Only basic tools are discussed and explained, with emphasis on their safe and efficient use. Thoroughteaching.

CAREANDUSE HAND ools

\$1.25 at all booksellers or direct from

JOHN WILEY & SONS, Inc. 440 Fourth Ave., New York 16, N. Y.

There's no limit to the chemist's chances for advancement . . . in salary . . . in importance. Experiments develop into giant new industries. Established industries rely on laboratories. I.C.S. training . . . practical . . . thorough . . . opens this great field to you. Instruction papers specially written by noted chemical engineers, consulting chemists, metallurgists. And these big experts are EASY TO UNDERSTAND. Our editors have explained all technical terms simply, clearly. Any person of ordinary intelligence can learn and make rapid progress. You have ambition. We have the training you need. Send now for free booklets. International Correspondence Schools, Box 7613-L, Scranton 9, Pa.


# SAMPLE LESSON IN

More good jobs now in Drafting. Learn AT HOME in spare time (or at our Chicago School) Send postcard for FREE SAMPLE LESSON and see how easy to learn at home.

CHICAGO TECHNICAL COLLEGE C-216 Tech Bldg., 2000 S. Mich. Ave., 16 Chicago, III.

FREE TRIAL LESSON! Cash in on your sense of humor—AT HOME—BY MAIL. Have fun! Make money! No experience needed to start. Write today for FREE LESSON, mailed postpaid. No obligation.

MooN Gag-Cartoon School, Dept. S. Argyle, Wisconsin.





Wonderful, new device, guides your hand; corrects your writing in few days. Big improvement in three hours. No failures. Com-plete outline FREE. Write C. J. Ozment, 35-B, St. Louis. Mo

# POEMS

To be set to music. Send your song poem today for free examination by nationally famous hit composer. Our new 6 step plan is most liberal and complete ever offered. Write today for free

SCREENLAND RECORDERS, Dept. PS, Hellywood 28, Calif.

# MACHINIST TRADE TOOL & DIE MAKING

In completely equipped Shops. Also short, special Shop courses for essential War and Post-War Jobs, Learn on actual Shop work, Coeducational. Special Counselor for G.I. Training, Write for Free Booklet, Allled School of Mechanical Trades, 1332 S. Michigan, Chicago 5, III.

# A PROFITABLE BUSINESS—PROFESSION YOU CAN START ANYWHERE

For an extremely profitable lifetime business, operate a Collection Agency-Credit Bureau. Quickly learned. No capital necessary. Free folder. Write: George H. Cole, Pres., Dept. P, S.A.&K. Bldg., Syracuse, N. Y.



# See Either or Both of These 2 New Books FREE

Here's a BRAND NEW, up to the minute Electricians Handbook.

A book electrical workers need for reference on the job. Over 5,000 electrical facts — wiring diagrams essential electrical formulas - latest code rules, tables, charts, and wiring methods. Includes Industrial Electronics data. A PRACTICAL BOOK EVERY ELECTRICAL WORKER CAN USE EVERY DAY. Pocket size. flexible leatherette cover to stand every day hard usage.

# Electricians Handbook

See this book FREE for 7 days. It's a book electricians have been waiting for —350 pages "chuckfull" of VALU-ABLE ELECTRICAL DATA that can earn its small cost many times over. Price \$2.75. payable after 7 days' FREE inspection.

# ELECTRONICS The QUICK Way To BIGGER PAY

To get ahead in Electricity NOW and in the future you should know ELEC-TRONICS. It is the big pay field for Electrical workers. Coyne's new 400 page book just off the press is especially written for busy electricians who want practical "on the job" simplified electronic information. This is no text book it's a practical book written for

practical men. Electricians should find this book a "GOLD MINE" of EASY TO FOL-LOW electronic data. Priced at only \$4.95—payable after 7 days' FREE inspection.

# END NO MOI

See both of these books FREE for 7 days. Here's my offer. I'll send either or both books to you for 7 days' inspection at my expense. If you decide you don't want the books, send them back and you owe nothing; if you keep either or both you can pay as outlined in the coupon. Don't delay! SUPPLY LIMITED due to paper restrictions send that coupon NOW!

# **ELECTRICAL SCHOOL**

H. C. LEWIS, President 500 S. Paulina St., Dept. 35-R8, Chicago 12, Ill.

Send me the books checked below on 7-day free trial. I'll either return them in 7 drys or pay for them according to the plan I select as outlined below.

☐ Coyne Electricians Handbook: 1 Volume. Price \$2.75 after 7 days FREE examination.

GET

THESE

BOOKS

FREE

**ELECTRONICS** 

DAYS

☐ Electronics for Electricians and Radiomen: 1 Volume, Price \$4.95 after 7 days Free examination.

SPECIAL PAYMENT If you keep both books you can send \$2.00 in 7 days and pay \$2 month-ly until \$7.70 is paid.

and I days a c	- Califfications	_
NAME		
ADDRESS'		
	ZONESTATE	
☐ If you want be (shown above	oks sent C. O. D.—you pay postman cash problems here. Same 100% satisfaction guarantee.	ice



# SURPLUS BARGAINS

# SENSATIONAL VALUES FOR QUICK LIQUIDATION

# USED U.S. GOV'T. PUP TENTS

Regulation army pup tents of durable brown canvas. Used, but in good condition. Fine for campers, outdoorsmen, boy scouts, etc. A grand gift for boys,



NIOO-TENT \$4.95

K101-Ropes, wood-en poles and stakes for above. Per set

# HUNDREDS of ITEMS TO CHOOSE FROM

Values galore! Hundreds of hard-to-find items for home, of shop and outdoors at tremendous savings. Order early. Ample stocks are on hand to take care of all needs but at these prices they won't last long. Order direct from this ad. Satisfaction guaranteed.


CATALOG PS3 FREE

# CATHODE RAY TUBES

16 mm AIR CORPS FILMS

Air Corps Gunnery training films. Approximate 350-400 feet of action above the clouds, 16mm only,

RADIO HEAD PHONES



Cathode Ray tubes, ideal for television, scope and experimental work. Slightly used by U.S. Gov't. for test work. Guaranteed to give excellent service. Specify number when ordering.

Ready for projection. K105-

PER REEL....

No. 5BP1 Each No. 5BP4 Each

\$2.00

# CAVALRY SPURS



Genuine wishbone type cavalry spurs, Nickeled brass.

K-102, Patr . 98C K-103 Spur straps per set of 50c

# MOSQUITO TENTS



Of marquisette with taped seams, Metal rods and hars in-cluded, Covers cot or hammock, Brand

K-104 \$2.95



Made of rubber impregnated two-ply balloon eloth. With grommets. Strong, durable and absolutely

water-proof, Ideal for farm and factory use, K107-6x8 feet, each....\$ 4.00 K108-8x10 feet, each....\$ 6.75 K109-10x12 feet, each... 10.00 K110-12x14 feet, each... 14.00 K111-Special sizes to order 75C per sq. yard...

# U.S. GOV'T. SURPLUS CAVALRY SWORDS



# TO DECORATE YOUR DEN OR LODGE

A collector's item for den or hunting lodge. Of finest tempered steel, double edged, with 35 inch blade, 42 inches long overall. May be cut down for hunting, commendo knives, etc. \$1.95 Complete with scabbard. K500-EACH, express collect.


U.S. BOLO KNIVES



Extra heavy Bolo Knife with sheath. Of finest tempered steel. Two piece riveted handle. Ideal for jungle and south Pacific use. Fine for hunters.

campers, etc.
K112-With Army Sheath
K113-With regular
Sheath, EACH.....

# SURPLUS AIR CORPS APPROACH METERS TWO MICRO-AMP. METERS IN ONE




each meter, Calibrated dial may be superimposed on face of meter. Zero adjustments, Original cost \$40,00 or more. K114-EACH ONLY....



Made for use in tank corps helmets, 4000 ohms, Ideal for all radio and com-munications work, With


cord and plug. K106-PER SET \$2.95



14 INCH BOLT CLIPPERS

Heavy duty type with compound lever jaws. Used but guaranteed \$2.95 factory use. K115-EACH ONLY.....

# REGULATION ARMY MESS KITS



but guaranteed perfect. K116-EACH ONLY . . . .



# U.S. GOV'T. CANTEENS

Regular U. S. Gov't. issue canteens. Plastic screw top cap chained to body. Slightly used.

K117-METAL BODY K118-PLASTIC BODY 69c K119-Canteen covers, ea. 35c K120-Canteen cups, ea. 25c

# OPTICAL PRISMS

Finely ground and polished. Two 45 degree angles each 20 mm, by 27 mm—bottom surface 20x40 mm, Regularly used in prism binoculars. Fine for experimental work in optics, etc. A rare buy

ONLY .... \$1.50 FOUR FOR ONLY .... \$5.50

# \*\*\*AIR MATTRESSES



campers, outdoorsmen. boy scouts, servicemen, etc. Six separate (slightly used) air chambers provide a 3 inch cushion of air. Measures 24x54 inches-fits cot or sleep-ing bag. Outer envelope of black, waterproof, rubberized

material, Quickly inflated or deflated, Folds compactly Guaranteed perfect. K122-EACH, COMPLETE

# WATERPROOF



APRONS Waterproof, acid and alkali proof. Used by indus-trials, photog-raphers, florists. chemists, etc. Of salvaged balloon material. Gener-

K123-LADIES, each 980

# 1600 FT.-- 16 MM STORAGE CANS

Storage cans for 1600 ft. reels of 16 mm, motion picture film, All perfect. Rich maroon finish. A splendid value

ONLY. EACH...

etc. Slightly used but service

K128-3 POCKET, EA., 49c

K129-11 POCKET, EA. 69C

BANDO-

LEERS

Army Bando-

leers of heavy khaki. Used

hunters.

scouts.

# U.S. INVASION LIFE BELTS



Regulation Invasion type life belts. inde-

pendent air chambers. Sparkiet car-tridges provide instant emergency inflation, Includes hose for manual inflation, Brand \$4.95 K126-FACH ONLY.



Thousands of fine optical lens elements, prisms of various focal lengths and powers, Ideal for assembling into rifle scopes, projection lenses and other optical systems, Catalor

L2PS gives all details, A post card will bring it.

LENSES, PRISMS, ETC.

WRITE FOR L3PS LENS LIST

# ORDER DIRECT FROM THIS AD

Make remittances by money-order, bank draft or personal check, Send 25% deposit on C.O.D. orders, Include sufficient postage on parcel-post orders—any overage will be promptly refunded. All quotations F.O.B. Chicago. Used items and materials are guaranteed serviceable and as described. Your money back if not more than satisfied.

Pept. PS3, 509 So. State St. Chicago 5, Ill.

# COMB. AIR PILLOW AND LIFE BELT



berized khak 1 10 x 40 inches in

rub.

Of

Used as life belt, raft or air pitlow. Quickly inflated or de-flated. Used but water C guaranteed and air tight. K127 EACH.



## RADIO PARTS ASSORTMENT A find for

radiorepair o men. Seven Pop pounds of rivets. grid leaks colls, etc. Order

now! K130-R \$1.79 NDS. . . .

46

Classified Ads only 35c per word per insertion, payable in advance. Minimum ad 10 words. White space \$2.00 per line. To be included in April issue, copy should be in our office by March 1st. April issue on sale March 1st.

# POPULAR SCIENCE MONTHLY-351 FOURTH AVE.-NEW YORK CITY 10

## ADVERTISING

ADVERTISING Placed everywhere lowest rates. Reliable guidance on publications, expert assistance on ads without charge, Newspaper, magazine, mailing-list ratebook free. Chicago Advertising Agency, 20-MP West Jackson, Chicago 4.

CHICAGO Mail or Branch Office Address. \$1 Monthly. Prompt forwarding. Also Representation, Collections, Calls, Deliveries etc. Write for rates on any legitimate service. Confidential, Faultless Organization, 3439-B. Michigan, Chicago (16).

SALES-Letters by former Assistant Director of Correspondence at Sears, Roebuck & Co. Write fully, Director, 1832 Stanwood Street, Philadelphia 15, Pa.

PRINTERS, artists, draftsmen, anyone, make your own engravings at home. \$5.45 (Simple), Carson Institute, Plainview at Schoolcraft, 23, Detroit.

ADVERTISE: 24 words, 149 newspapers, \$6.50, Lists Free, Advertising Bureau, 4515-P Cottage Grove, Chicago 15,

INCH Display advertisement fifty magazines, year \$16. Wood's Popular Services, Atlantic City, N. J.

1000 NAMES, gun hobbyists, sportsmen, no chiselers. List \$4.00. Bonin, 21 High, Pawtucket, Rhode Island.

50 WORDS 50 Magazines—3 months \$3.00. Renick, Holland, New York.

20 WORDS 30 newspapers \$2.00. Goodale. 37 Gardner, Vallejo, California.

## ADVICE

START your post war planning now. I train beginners at Home to start a business of their own. Send for bulletin 16 yours free. Helgesen, Hillcrest Road, Palatine 11, Ill.

## AGENTS WANTED

SILVER Plating Liquid. Simply rub-on with a cloth. Like a polish. Easily done at home or in any business place. Cleans, silverplates, polishes, one rubbing. Puts on a genuine 1000 fine pure silverplate finish. A rub-on method, not a dipping process. Renews silverplated tableware and other silvered articles like new. Fills in scratches, covers up worn and brassy spots. Lasting finish, won't come off. Also silverplates onto brass, copper, bronze, zince nickel-silver, german-silver, and some other metals. Over 100 other uses in factory, store, office and home. Resilver silverware, jewelry, musical instruments, antiques, art goods, automobile nickel, chromium, light reflectors, heirlooms, and such things. Sales representatives wanted. Details free. NuProcess Products, Dept. 149, Aurora, Illinois.

AMBITIOUS School Seniors—We want Y-O-U to sell classmates the "Tops" in Graduation Name Cards. Highest commissions! Only Firm giving Free Souvenir Chest and Card Case!! Your cards Free! Cardalogs going like wildfire! Hurry! Get yours today! Craftcards, Box 235(M), Pittsburgh 30, Pennsylvania.

100 GENUINE glossy photographs for only \$2.00. Every one can cash in on stamp sized photographs. Any photo, snapshot or negative reproduced to stamp size, gummed and perforated. Write today for Free samples, complete information and agents discount. Repeat orders assure you of steady income without investment. American Foto (Dept. T) 305 Broadway, New York 7.

SCHOOL Seniors—Sell classmates America's most beautiful, distinctive graduation name cards. Positively highest commission. Largest selection. Lowest prices. Free cards and free sample kit. Printcraft 1423 East Elm Street, Scranton 5, Pa.

SELL Greeting Cards—Make easy money showing gorgeous Everyday, Birthday. Easter, Mothers' Day Cards. Stationery. Over 100 quick sellers, Special offer, Write today for \$1.00 All Occasion Assortment on approval. Hedenkamp, 343 Broadway, Dept. 32, New York 13, New York.

START Your Own Business on our capital. Always your own boss. Hundreds average \$6,000 to \$12,000 annual sales year after year. We supply stocks, equipment on credit. 200 home necessities. Selling experience unnecessary to start. Wonderful opportunity to own pleasant, profitable business backed by world wide Industry. Write Rawleigh Co., Dept. C-U-PSC. Freeport, Ill.

\$1 STARTS you in business. Sell DeLuxe five fold ties, 100% wool interlining. Costs you only \$7 per dozen, you make \$5 dozen. Send \$1.00 for special introductory offer two five fold ties. Catalog complete line Free. Philip's Neckwear, 20 West 22nd St., Dept. K-11, New York 10.

GOOD Paying Business Silvering mirrors, plating autoparts, reflectors, bicycles, bathroom fixtures, etc., by late method. No tanks or shop required, outfit furnished. Free Booklet, Gunmetal Co., Ave. G. Decatur, Illinois.

MAKE unusual spare or full-time profits showing genuine Leather Jackets, Raincoats, 200 Style and Comfort Shoes. Sample Outfit Free. Rush postcard. Mason Shoe Co., Dept. M-193, Chippewa Falls, Wisconsin.

MAKE unusual spare or full-time profits showing genuine Leather Jackets, Raincoats, 200 Styles and Comfort Shoes. Sample Outfit Free, Rush postcard to Consolidated Shoe, Dept. S-97, Chippewa Falls, Wisconsin,

HELP People's Health. Very effective preparation. Customer gets choice of "Free Vitamins" or "Free Health Book". You get \$1.50 per order. No investment necessary. Floradex, 178 E. Long, Columbus 15, Ohio.

WRITE today for Free Wholesale Magazine
Price List. Good Commissions, voluntary repeat sales. Supplies furnished. Start
Now! Send penny post card to McGregor
Magazine Agency, Dept. PS 5, Mount Morris, Illinois.

EXCELLENT Sideline for Printing Salesmen, Decalcomania Name Plates in small quantities. Also, make money applying Initials on Automobiles. Free Samples. "Ralco", X-164, Boston (18), Mass.

NEW All Purpose Kitchen Tool, Opens Cans, Jars Bottles, Jar Wrench attachment. Red Hot and available. Penner Sales Co., 910 Moreland Ave., St. Louis 22, Mo.

BIG Money taking orders; shirts, ties, sox, pants, jackets, sweaters, shoes, uniforms, etc. Sales Equipment Free, Experience unnecessary, Nimrod, 4922-AV Lincoln, Chicago.

LUMINOUS pictures that glow in the dark.

Large manufacturer wants factory representatives; wonderful new item; fast seller; free sample. Madison Mills, 303 Fourth Ave., New York City.

BIG profits taking subscriptions for all magazines, Agents' Confidential Catalog listing over 2500 periodicals and complete starting supplies Free, Pines Subscription Agency, Flushing, New York.

SELL New-Used Clothing from home, auto, store. Men's suits 99c, Pants 27c. Topcoats 44c. Dresses 13c. Ladies' Coats 38c. Other bargains. Catalog Free. S&N, 565A, Roosevelt, Chicago.

WHOLESALE: Razor Blades, Laces, Excello, Texide, Silvertex and others. Write for prices and information. National Sales Company, Dept. 114, 1319 Stone Street, Flint 4, Mich.

MAGIC Races—At cigarette touch six horses are off. Fast seller. Big profits. 40 Races \$1.00. Dime brings samples, wholesale prices. Barkley Co., Dryden 5, Virginia.

EVERYDAY Cards. Make \$5.00 with every ten \$1.00 assortments you sell. Also Victory cards and note paper. Unusual demand. Send for samples to-day. Howard P. E'lls. Dept. PS, Pitman, N. J.

DEMONSTRATE Copyholders to those answering our Advertising. See Ad under Authors Service. Write for complete information. Writers Association, Marlboro Pike, Washington 19, D. C.

BEST chances year round selling tricks, jokes, snappy greeting cards and Men's necessities. Send \$1.00 for samples and latest catalogs. La France Products Co., 47-53 Hanover St., Boston 13, Mass.

POWERFUL Mile Stretcher! Increases mileage! Increases power! Increase your Bank-Account! 400% Profits. Thermopower, Peoria 4, Illinois.

FREE Water and our concentrates makes flavors, lotions, shampoos, 72 products, labels, bottles furnished. Qualco, F-20030 Russell, Detroit.

MAGIC Cleaner and laundry soap deal. Hotter than a firecracker. Big profits! Sample free. Uco, 5007 Irving Park, Chicago.

LICK After-war layoffs; Start own business; home, office. Booklet describing "Collection of 127 Tested Plans" free. Elite Co., 214A Grand St., New York.

SELL Dresses at low prices, Hundreds sensational bargains, Actual samples free, Send dress size, age, Harford, Dept, E-360, Cincinnati, Ohio.

HANDY Hair Trimmer. Sells like wild. Trims as you comb. Saves barber bills. Samples sent on trial. Kristee 140, Akron, Ohio.

PRIZE package displays. Jokes, tricks, puzzles on display cards. State your line of business. Eagle Specialty Co., Akron 11, Ohio.

AGENTS, It's New it's Hot. Everyone wants Honor Scrolls for loved ones. Sample on Trial. We deliver-Collect. Kondon, Box 157, Upper Darby, Pa.

25 WAYS to make money with Luminous Paint. (Shines in dark). Rush 25c for complete details. Ward, 97B, Saybrook, Connecticut.

GOLD Lacquered window sign letters, New styles, Absolutely beautiful, Free samples—catalogue, Atlas, 7941 Halsted, Chicago.

TIRED, Aching Feet, Muscles; Use Mains Liniment 50c. Leonard, 1669 Pinewood, Toledo, Ohio.

SPARKLING Religious Mottoes—100, \$4.00. Samples. 25c. Tabernacle, 1321 High, Springfield, Ohio.

SCHOOL Seniors—Highest Commns paid on fastest selling line to schoolmates and others. Hurry. Aristo, Sc. Plainfield, N. J. BIG Money selling Negro calendars and

BIG Money selling Negro calendars and fans. Commercial Ad Inc., 464 W. 153 St., New York 31, N. Y. 200 BUSINESS ideas-Plans-Schemes-Rare

314 Kiefaber, Dayton, Ohio,
TEN cents for samples printed stationery,
Sicocoan, 6348 Windham, St. Louis, Mo.

Formulas-Exposes. Formico Company.

# AMERICAN POLICE JIU JITSU

MILITARY judo is taught in the service.

Learn barehanded combat from Sgt.

Zerick, National Judo Champion, and instructor of many thousands of Army Air
Force men. Send dollar for course to Military Judo, Box 478, Miami Beach, Florida.

FEAR No Man. Learn Ju-Jitsu. Whip toughest Bullies — Easily. Complete Course, \$1.00. Dr. Malcolm Smith, 1104 Union Ave., Montreal 3, Canada.

## ANTIQUES, RELICS INDIAN GOODS

345 ANTIQUE Firearms, Swords, cartridges, 4,000 Bargains, Indian relics. Fossils, Minerals, Coins, Rifles, Catalog 10c, Many photographs, Heike, Wenona, Illinois.

PREHISTORIC Mound Builders' Arrowpoint, 10c plus pamphlet describing Excavations, list Collectors' Items. Ancient Burled City, Wickliffe, Kentucky.

SWORDS, rapiers, daggers, pistols, armor; illustrated catalog, 25c. Robert Abels, 8601/2 Lexington Ave., N, Y.

INDIAN relics. Coins, Minerals, glassware. Catalog 5c, Sistershop, Northbranch, Kansas.

GUNS, swords, daggers, illustrated 48 page catalog 59c. T. A. Woroniecki, 47 W. 44, N. Y. 18, N. Y.

## ARCH SUPPORTS

BIG Profits manufacture custom made arch supports. Particulars. Julis Corssen, 2638 Geyer, St. Louis 4, Missouri.

## AUTHORS SERVICE

NEW writers needed to re-write ideas in newspapers, magazines, and books. Splendid opportunity to "break into" fascinating writing field. May bring you up to \$5.00 per hour spare time. Experience unnecessary. Write today for Free details. No obligation, Postcard will do, Comfort Writer's Service, 210-R South Seventh St. 2, St. Louis, Mo.

WRITERS: Do you need writing assignments, information about selling what you write, or want to improve your writing ability? Write for information! The National Writers Association, Marlboro Pike, Washington 19, D. C.

BINDER-ENVELOPES, Sending envelope, return envelope, and manuscript binder, in one. Submit manuscripts properly. Saves more than cost, reduces postage. Sample lot \$2. Writers Association, Marlboro Pike, Washington 19, D. C.

COPYHOLDER, Holds typed and untyped material at the same time, above typewriter. Work with your head up, not down, \$15. Refund if not satisfied one weeks use. Writers Association, Marlboro Pike, Washington 19, D. C.

WRITERS: Send for Free Circular E-35 with Unified Sales Plan for placing your work. Otts Adelbert Kline, Literary Agent, Established 1923, 507 Fifth Avenue, New York 17.

GHOSTWRITER, research special Washington assignments, Speeches, articles, books, Cooper, 2515 14th NE, Washington 18, D. C.

WRITE Magazine Articles. Complete assistance. No fees; 50-50 basis. Lathrop, Box 361-N, Junction City, Kansas.

# AUTOMOBILES

book. This humorous, educational, historical Scrapbook illustrates, describes hundreds antique and early automobiles, motorcycles. Reo, Oldsmobile, Hupmobile, Metz, Orient, Knox, Winton, Carter, Maxwell, E-M-F, 2-cylinder Ford and Buick, Air-Cooled Chevrolet, Stanley, White, other steamers, electrics, Unusual and steam motorcycles, This is the Scrapbook Time Magazine said is a "Must." Editions one and two now available but entirely different books. Postpaid \$1.50 each, DeLuxe edition \$2.50. We mail overseas any time without request and pay postage. Delivery guaranteed. Clymer, 2125 W. Pico, Los Angeles 6, Calif.

POWER and Speed! World's most famous motor book. 110 large pages. 200 illustrations racing automobiles, motorcycles, airplanes. World's speed record chart, articles by world famous speed kings Cobb, Eyeston, Campbell, Bonneville record details, photos British racers. Describes cams, compression, valves, superchargers, International racing teams, German Auto-Union, Italian, French, British racer specifications, drawings. \$2.50 postpaid. Clymer, 2125 W. Pico, Los Angeles 6, Calif.

MODERN Steam Car, 130 pages, 100 illustrations. Interesting, practical book on steam automobiles. Complete information early and latest makes, models. U. S., foreign makes described. Boilers, generators, engines, valves illustrated, described. Article by Stanley, early steam advertisements. How to drive and care for steam automobiles. Unusual, informative book, Postpaid \$2.00. Clymer, 2125 W. Pico, Los Angeles 6, Cal.

STEAM Automobiles! Send 25c for literature listing names 90 different makes Steamers once manufactured. Illustrations, descriptions, specifications, Stanley, White, Doble, Lane, Ross Steamers, boilers, engines also photos famous White Racer "Whistling Billy" and World's record holder Stanley Racer. Interesting, educational, ancient steamer history, No cars for sale, Clymer, 2125 W, Pico, Los Angeles 6, Calif.

SIR Malcolm Campbell's book of famous motorists! 208 pages, 42 beautiful photographs world famous racing automobiles, drivers. Campbell describes famous race tracks, his American records, European road races, his competitors. Interesting, sensational. \$2.00 postpaid. Clymer, 2125 W. Pico, Los Angeles 6, Calif.

1945 IGNITION Supercharger \$3.50 fast starting, mileage, pep. EG Mfg. Co., B355 E. 149 St., N. Y. 55. AUTOMOBILE Racing Book. Fifth Edition—Revised. Tells how to build dire track bodies, frames, engines, Records, superchargers, rules, formula, plans, stock conversions, roadster racing, fast Fords. \$1.00 postpaid; \$1.15 C.O.D. Ray Kuns, Department 274, Madisonville, Cincinnati, Ohio.

WHIRLGAS Turbinator, \$3, improves carburetor action; increases mileage; quickens acceleration; reduces monoxide. Performance guaranteed, Universities and Oil Corporation tests, Wrench installs 15 minutes, Give auto make, year, John Hanley, 5719 Loraine, Detroit 8, Mich.

GARAGE doors, all types, controlled from dashboard pushbutton. Simple, dependable. Materials inexpensive, obtainable everywhere. Complete "Bulld Yourself" plans \$1.00, refundable, Guaranteed. Free particulars. Kaytor Lab's, Lynwood, California.

WHY burn gasoline, when 100 octane fuel is available at half that. Folio of plans, diagrams and instructions \$1.00. Crescent Engineering, Box 251, South Pasadena, California

CUSTOMIZE your automobile. Illustrated new restyling ideas, instructions, specific model changes by simple methods. \$1. Speedwheel, Box 723-D, Arcadia, California.

# AUTO SUPPLIES & EQUIPMENT

AMAZING new Moto-Vator injects water-vapor into motor just like newest fighter planes. Burns 15% water; saves 20% to 30% gas; Prevents Carbon; Increases power! Eliminates carbon and valve jobs. Not a gadget. Sensational performance keeps motor like new. Wonderful postwar possibilities. No investment. . . One low price includes license to install Moto-Vator in your locality. Send 10c for booklet giving complete details. Dept. S. SX Laboratories, P.O. Box 37, Middle Village, Long Island, New York.

ATTENTION: Run your car on (natural or artificial gas.) Without alterations to carburetor or gasoline system. Build supercharged turbulance plate for more mileage. Make time shutoff control for electric appliances. Easy to install windshield defroster. Cut a five point star with one cut useful for stencil. Five above plans \$1.50. More detailed information free. Harpers Machine Shop, 218 22nd St., Dunbar, W.Va.

"UNLOCKEEZ" is a device that will instantly open any auto lock operated by a Push Button or money refunded, Attention Locksmiths, Parking Lots, Garages, Car Owners, \$2.00 cash or Money Order, Canada & Foreign \$2.50, Unlockeez Lock Device Co., P.O. Box 7218 Station G., Los Angeles 37, Cal.

AUTOMOTIVE Engineer tested Vacudex Exhauster on Technology Institute Dynamometer. Reduced back pressure, increased mileage, used less Gasoline. Vacudex easily, quickly attached. Satisfaction guaranteed, \$3.75 postpaid. Decker Products Co., Pelham 65, New York.

OIL Pumping Motors—brought back to normal without a ring job. Prolong the life of your motor. It takes only a short time and you can use your car immediately. This information \$5.00. Send today. Possibly not available after the war. Joe Mullner, Box 3102, St. Paul 1, Minn.

CONVERT your auto, tractor or marine engine to burn diesel or stove oil. Proven factory method. Different and better. Costs nothing to investigate. Write for free circular No. 3. Harrington Co. 222-224 S. W. Stark St., Portland 4, Oregon.

HAVING Car Trouble? Used, guaranteed auto, truck parts save money. Transmission specialists. Describe needs; immediate reply. Victory, 2439-14 Gunnison, Chicago 25.

GASOLINE Mileage instrument indicates as you drive and analyzes motor trouble when idling. Write for Free literature. Engineering Co., 1155 S. Kenmore, Los Angeles 6, California.

GASADAPTER replaces air cleaner and operates car on bottle gas. Easy to build. No interference with ordinary gasoline operation. Detailed instructions \$1.00. Gasadapter, P.O. Box 214, Fond du Lac, Wis.

"GAS Without Coupons," an article reprinted from Progress Guide Magazine. Harper's Machine Shop, 218-22nd Street, Dunbar, W. Va.

1,000 MOTORISTS needed to make gas saving test. Up to 30% savings. For trial test offer write Vacu-matic Carburetor Co. 7617-1169 W. State Street, Wauwatosa, Wis.

TIRES-Grade Three-6.00x16-\$6.65. Allied Rubber Co., East St. Louis, Illinois.

EXTRA Miles—our instructions will help gas rations. Get more miles per gallon. \$1.00 postpaid. Davy Service, Box 303, New Castle, Ind.

SIX Gasoline Saving Formulas! All Tested Formulas; Only \$1.00 Postpaid. Doane, 355 Mason, San Francisco 2.

PRESERVE your tires with plastic and puncture-proof your tires. Details for stamp. Betke. Box 699, Borger, Texas.

INVENTION Uses kerosene to run motors. Circular on plans. Rush name. Houston Maupin, Tipp City 37, Ohio.

GASLESS Gas; quickly, easily, compound. Formula 25c. Duffy, O47, Covington, Ky.

# AUTO TRAILERS

BUILD your own Trailer! Save Money!
Have every feature you want! Plans for
House, Sport, Camp and Utility trailers,
Catalog describing 9 models 10c. Jim
Dandy, Box 125-B, Wausau, Wisconsin.

# AVIATION

AERONCA \$100 less motor; Waco \$100, wings damaged; Gypsy Moth, \$100 less wings; Pietenpol Air-camper complete; Heath Parasol, uncompleted. Send 25c for big Var-Bargain catalogue listing over 300 used irplanes, crackups, war-surplus, salvage, located everywhere, some probably near you, (35c by first class mail). Used Aircraft Directory, Athens, Ohio.

FUNDAMENTALS of Aircraft Drafting 28
Project sheets. Primary Structures and
details. Full instructions. General Drafting prerequisite. Work home. One dollar.
Robert Brydon, Jr., 615 City Park Ave.,
New Orleans 19, La.

AIRPLANES Used. \$200 up. Also late models. Engines, wings parts, machinery, books. Cheap. Send 25c for list. Airacraft, 2300 West Flagler, Miami 35, Florida.

CUB \$200 (needs repainting), Curtis-Robin \$195, Fairchild \$395, Catalog—over 250 aircraft bargains—25c, Lifetime membership in Aviation Club included free! National Aviation; Box CS-1682; Toledo, Ohio.

PROPELLERS—Quality—quick delivery all sizes—including 3 blade Airliner for sleds, boats, Lists free, Ford aircool conversion diagrams 50c etc. Standard Aerocraft, Ft. Worth, Texas.

DRAWINGS and photographs of warplanes and battleships. Send 15c for sample plus catalog or \$1.00 for large assortment. Craft Art, Dept. P-3, 246 5 Ave., New York 1, N. Y.

GOVERNMENT war surplus airplanes now being sold. Do you know where to buy? List of over 70 government agencies, sales centers and depots for \$2.00. Surplus, Box 544, Denver, Colo.

50c BRINGS 24 issues, hundreds airplane bargains, Airport gossip, surplus. Aviation Advertiser, 8242 Travelair, Houston, Texas.

PRIVATE Pilots questions help you pass CAA examination. With key \$1. Aeronautical Institute, 1522C Flett, Racine, Wisconsin.

# BABY CHICKS

CHICKS: Heavy Red cockerels, \$8.50 per 100, Leghorns, \$2.45. Pure breeds, crossbreeds. Sexed non-sexed. Write for folder, prices. Amstutz Hatcheries, Box 44. Orrville. Ohio.

CHICKS for broilers 100-\$3.75-206 \$7.00. Postpaid. Empire Hatchery, Seward, New York.

# BATTERIES. GENERATORS, ETC.

EDISON Batteries: Power, Light, Five year guarantees. Fifteen year life. Complete lighting equipment. Free literature. See-Jay Company, 321 Yonkers Avenue, Yonkers, New York.

# BLUE PRINTS AND PLANS

TAILORED Homes plan book. Sixty floor plans one-story houses with choice of new, smart exteriors styled Colonial, English, Spanish Moderne, making hundreds of combinations! Price \$1. Prepare for rationing. Plan now! H. P. Jones, 486-PS, Brandeis Bldg., Omaha 2, Nebr.

AUTOMOBILE mechanics cash in on this, Build tractors from second hand automobiles. Convert horse drawn farm equipment into tractor hook-up. Nolan's Garage, East Wareham, Massachusetts.

RECORD Player: Plays thru your radio; Simple and easy to make. Detailed plans and instructions only \$1.00, Jay-M Sales Company, P.O. Box 97, West Haven 16,

# BOATS, OUTBOARD MOTORS, ETC.

SAILKITS 100 Square Feet \$6.95, Canvas, Canvas Cement, Airplane Dope, Marine Equipment, Paints, Carbide Lamps, Carbide, Army Cot Covers, Zippers, Canoe Equipment, Sleeping Bags, Puptents, etc., Catalogue, Alan-Clarke, 100 Chambers, New York City 7.

FULL size, cut to shape boat patterns, blueprints, 712-38 feet. Hlustrated "Build a Boat" catalog, 10c (coin), "How to Build Boats" book, \$1.00, Cleveland Boat Blueprint Co., Station A-77, Cleveland, Ohio.

MARINE Power—Easily convert any Ford motor (domestic and foreign) with Osco parts and kits. Complete catalog 25c (coin). Osco Motors Corp., 2020 E. Orleans St., Philadelphia, Pa.

OUTBOARDS: Latest bulletin available on rebuilt motors. Good used parts most makes and models. Crandall-Hicks Co., 959 Commonwealth Ave., Boston, Mass.

MAKE 16' Rowboat, Blueprint, 30c, Wee-Sho-You, Box 51, Detroit, Michigan,

## BODY-BUILDING COURSES

BAR-BELLS, Dumbbells. Exercise equipment, Courses, Special offers! Free booklet. Good Barbell Co., 3261-PS Watson, St. Louis 9, Missouri.

# BOOKS, PERIODICALS

100,000 POST-WAR Jobs abroad—South America, China, India, Burma, Japan, Russia, Malaya, How and where to apply now, Post-war U. S. participation in world reconstruction and trade demands thousands of American-trained mechanics, salesmen, technicians, engineers, foremen, laborers and business representatives—every trade needed, Our 15,000-word copyrighted forecast—compiled from business, professional and government sources—lists over 200 big U. S. firms with foreign interests, gives job information, salary brackets, contract tips, application letters, passport information, climatic conditions, etc.—vital facts for your immediate application, \$1.00. Return for refund in 7 days if not satisfied, Pacific Industrial Research Bureau, 202-D Studio Building, Portland 5. Oregon.

HYPNOTIZE Anyone! Step by step the secrets of hypnotism are revealed to you so you can hypnotize people easily. Think what this can mean to you. 264 pages of clearly written, practical instruction. No detail overlooked. Start mastering other people right away! Send for "Practical Lessons in Hypnotism"! by Dr. William Cook. Only \$2.00. Ball Square Company, Dept. 55A, 697 Broadway, Somerville 44. Mass.

THOUSANDS of lives really began with reading "The Doctor Alone Can't Cure You", by Rolf Alexander, M.D. From a foundation of scientific knowledge and ageless wisdom, it creates a new vision of life, then gives a definate system of mental exercises by which each reader can make this vision into a personal reality. Get your copy now at your book store, or direct postpaid \$2.50, from The Publishers, Dept. M. Overton Press, Carson City, Nevada.

MAGAZINES.—Choose current single copies from our list of more than 600 different Business. Vocational and Diversion periodicals. Profit by being posted on conditions, developments and opportunities in your line, through magazines devoted to it. Write now for free price-list, Commercial Engraving Publishing Company, 348 N. Ritter, Indianapolls 1, Indiana.

THIS IS IT!! Photos-posed by artists models and show girls, in unusual tantalizing poses. These breath-taking photos are finest quality glossy prints, which give each photo sparkling lifelike appearance. Send \$1. and receive 24 luscious pocket size photos postpaid. Irving Klaw, 212 E. 14 St., Dept. C. New York City 3.

WHAT Every Mason wants, We have Masonic books for Blue Lodge, Chapter, Commandery, Scottish Rite and Shrine. Our rituals are used the world over, Send for our free catalog of books and rituals for Masons, Odd Fellows, Knights of Columbus, etc. Ezra A. Cook, Publisher, Inc., P.O. Box 796-RJY, Chicago 90, Ill.

GOOD living, security, pleasure through the famous practical guide to selection and management of the small farm. 'Five Acres and Independence' \$2.50 postpaid. Check, moneyorder. Modern Technical Book Co., Dept. MS, 55 W. 42 St., New York 18.

CATALOG Free Worthwhile Books, Opportunities, Golden, 5730SD Keith, Oakland 11, Calif. 15 SCENES of Life in the South Seas. Has 11 Actual 3½x5 close-up photos of Native Girls attired only in grass skirts. Taken in the Wilds of New Guinea by a "Seabee" now serving there, \$1.00 postpaid. Mrs. Beatrice Bachand, 7 Potter Pl., Dept. 20, North Adams, Mass.

RUTHBELLA—Love Journal (Sansicchi)— Deluxe profusely decorated Library Edition, price \$5.00, Pocket "Victory" Edition, price \$1.00, Sole distributor: Ferrantebooks, Box 513, G.P.O, New York 1, New York,

4 BEAUTIFUL Pin-ups (Approximately 8x10). Photographed by one of America's foremost photographers only 25c! The Archer Company, Dept. A, 93 Federal Street, Boston 19, Mass.

GIRLIE Photos for adults only, the kind you've been looking for. Actual glossy photographs of gorgeous art models posed to thrill you. Plus Free follow up for only \$1.00 per set. Charm Photo Co. Dept. PS 1, Box 131 Canal St. Sta., New York 13, N. Y.

25 HOLLYWOOD'S Best Postcards—25c.
25 Beautiful homes of movie stars—25c.
25 Famous California Scenic views—25c.
25 Georgeous colorful glamour girls—25c.
"Secrograf"—System of 15625 codes—25c.
All five—\$1.00. "Postopuzl" game free!
Postopres. Box 3150, Hollywood.

YOUR opportunity—we supply all technical and hobby books. Send 15c (credited to order) for catalogues, information specific subjects interesting you. Modern Technical Book Co. Dept. M.S. 2, 55 W. 42 St., New York 18.

HOT Mama! Cartoon Booklets, beautiful girl photos, tantalizing and unusual poses, "Wow" you'll say. Large selection, \$1.60, National Distribution, Box 57, Muskegon Hts. 19, Mich.

MACHINIST, Model Railroaders—Locomotive valve Setting made easy, New book, "Modern Method" for Setting Valve Gears, Only \$2.00, Postpaid, Bridges, Box 3376-P. Jacksonville 6, Florida.

ART books for students. Learn to draw from nude photographs of art models. Volume 1, \$1.00. Sent by express. Merit Book Co., Dept. PS 1, Box 163, Station A, Brooklyn, N. Y.

GLAMOROUS, Thrilling, Informal poses beautiful Girls for adults, real photos. 24 different 50c. 70 different \$1.00, Wm. J. Drake, 100 West 43 St., Dept. P6, New York 18, N. Y.

POKER Secrets of Experts. Percentages, winning strength, all hands draw and discard. Three books complete \$3.00, Dice Book included Free. Topsall, Sepulveda, Calif.

MAGAZINES (back dated)—foreign, domestic, arts, Books, booklets, subscriptions, pin-ups, etc. Catalog 10c. (refunded), Cicerone's, 863 First Ave., New York 17, New York.

EDUCATIONAL Books sold cheaply or rented for small fee. Books bought. Money back guarantee. 4,000 Bargains, Catalog Free. (Courses Bought), Lee Mountain, Pisgah, Alabama.

ART Calendar "Lady Beautiful" Gorgeous, fascinating, in over 10 colors 12"x16" \$1.00 postpaid, no C.O.D.'s. Money Back guaranteed. "Dandee", 3201; W. Second St., Los Angeles 12, California.

"PICTURE Yourself Successful!" Learn How to attain success, wealth, happiness! New book tells you! \$1.00 postpaid, or send for interesting free folder. Buse, 878-B Fillmore, Buffalo 12, New York.

GORGEOUS Full-Color Pin-Ups. 50 different \$1.00, 160 different \$3.00, Samples 10c. Theron Fox, 1024 Carolyn, San Jose 10, California.

60 PIN-UPS, Famous beauties, mostly 7 x 9 or larger, over 300 snappy cartoons, stories, jokes, etc. All for \$1.00, Richardson, Wyoming Pennsylvania,

BOOKS. (out-of-print, new, used) quickly supplied, many 35c bargains, Catalogue, T. Jamkowski, 18870 Marx Ave., Detroit 3, Michigan,

SAVE money by writing for our lists of special cut-rate books, many at less than 50% of original price. Pines, Box 32, Flushing. New York.

GORGEOUS Girls, Fascinating poses for adults, Real photographs, 15 assorted 25c. No stamps, Hirsch, 119 W. 33 St., New York 1, N. Y.

ART Pictures, Glamour Girls, Comic Cards, Books, Booklets; Assortment \$1.00, List with order. Frank Cardone, Box 6818-S, Pittsburgh, Pa.

GORGEOUS Girl Photographs! Daring Candid Poses, Genuine Glossy Prints. Big Samole Assortment—Lists \$2,00. Clover XX-31, Hollis 7, New York,

SILK stocking photos "Greenwich Village Girls at Home"—6 for \$1.00—satisfaction or money back. Varieties, 1472 Broadway, New York, New York.

CLASSIC Pin-ups. Glossy photographs of Hollywood models, new fascinating poses. 20 for \$1.00, 45—\$2.00 size 3½x5½. Charles Scott, P. O. Box 342, Covington, Kentucky. INCREASE your intelligence! Banish misunderstanding! Revealing book \$1.00. Redmont Company, P. O. Box 9264, Los

Angeles 5, California.

NEW 1945 "Classified Swap Directory."

List 1500 swaps, 44 pages \$1.00—Martin's, Box 2414, Desk 77, Bridgeport 8, Conn.

SELF-instruction Books for Authorship, World's largest collection, List free, Humanity Press, 220 W. 42nd St., New York

18, New York,
CHINESE Physicians' Secrets, \$1.00, Illustration, health secrets, peculiar custom, ancient history, Garding Lui, Box 6227, Metro Station, Los Angeles, Calif.

BOOKFINDERS! (Scarce-out-of-print-new books), Supplied promptly, Send wants. Clifton, Box 1377ps, Beverly Hills, California.

PHOTOS of Beautiful models, 3¼ x 5½ posed the way you like em, 35 for \$1.00, 160 for \$3.00. Richardson, Wyoming, Pa. PRETTY girl photos, Large selections \$1. Judy Sellers, Box 123, Terre Haute, Indiana.

BOOKS-for Architects, Artists, Craftsmen, Collectors, Send for catalog, B. R. Arteraft, Box 6827, Baltimore 4, Maryland.

BOOKS, Courses, Aeronautics, Photography, Radio, Catalog, Moorfield-Shannon, Nutley 10, N.J.

ART Studies, few cents each. Lists stamp. Nuart, 436B New York Ave., Brooklyn 25, New York.

PIN-UPS.—180 Beautiful Girl Pictures!— Huge Bargain Assortment—Lists \$1.00. Clover Novelty Company, Hollis 7, N. Y.

PREE Booklet—The Truth About Jesus, John C, Meek—P.O, Box 512—Baltimore 3, Md.

5 MOST Read Mail Order Magazines 25c, Education Publishers . . . Pittsfield, Mass.

BEAUTIFUL pin-up girl pictures. Attractive poses, 24 for \$1. United Arts, 2309 Lawrence, Toledo, Ohio.

OLAMOROUS Pin-ups! Real Photographs! 10—\$1: 25—\$1. Fine-Arts, Box 2084-T, San Antonio 6, Tex.

PROOF of Earth's Concavity, 225 pages, \$1.00. Gay, B-1720 Hough, Ft. Myers, Fla.

BOOKS for sale. Name your favorite—we have it! Cooper. Room 12-PS, 1131/2 East Lafayette, Tampa 2, Florida.

UNBELIEVABLE Breath-taking pin-ups of Dazzling beauties. Rarest type poses. 25c each. Joseph Guilbeau, Scott, Louisiana.

ALMANACS are scarce. Send 13c, stamps or coins for famous Trail Blazers Al-

manac. Dept. B-20. Bloomington, Ill.

ART Pictures—pin-ups—comic cards. Novelty Studios, 301B Eldred, Battle Creek

elty Studios, 301B Eldred, Battle Creek 21, Michigan.

SNAPPY, Georgeous, Pull color, 5x7 Pin-Up Girls. 24 for \$1.00. Studio, Route No. 5, Muncie, Indiana.

PHOTOGRAPHS—Books—Pinups! Latest catalog—dime. "Nuart-Erix" Shop, 591 12th St., Oakland 7, California.

GORGEOUS Girl Photos, Books, etc., 15 Samples 25c. Richardson, Wyoming, Pa.

ADULT Books, Sample and catalogs, 10c, Alstone, 310, Lunenburg, Mass,

FREE copy "The Western Socialist". 12 Hayward Pl., Boston 11, Massachusetts.

RELIGIOUS books. Write Bobbitt, 1609 Tenth Avenue, North, Nashville 8, Tenn.

ADULT Books—gift coupon Free. R. Sullivan, 61-49 56th St., Maspeth, L. I. "A RATIONAL View of Life"-\$1. Benjamin Seibert, Urbana, Ohio.

64 BEAUTIFUL Girl Art-Cards \$1.00. Reed Novelty, Queens Village 9, N. Y.

ADULT Books:—Catalog, Sample 25c. Lefavor, Box 229, San Bernardino, Calif. FREE books for adults. Write Sophisticated

Club, 701, Lunenburg, Mass.

PRETTY Girl Pictures: assortment \$1.00. Cantarini, 1324 Sheffield, Pittsburgh, Pa. ALL books wanted. State your price. Box 1770, Tampa 1, Florida.

## BUILD IT YOURSELF

BUILD your own concrete block machine and make blocks at ½ the retail price. Sell blocks or build your home. Easy, inexpensive. Details free—Horne, 206 W. Wilder, Tampa, Fla.

GARAGE doors dashboard controlled. Additional information under "Automobiles."

TESTED drawing, instructions for building well designed modern cedar chest, 25 cents. Box 7, Athens, Ga.

# BUSINESS OPPORTUNITIES

LEARN How To Build A Mail Order business of your own. Many successful mail order businesses have been built up from very small beginnings, starting on a small capital, using a room at home for office, growing from profits. Our course of 24 big lessons in "Modern Mail Merchandising" gives real fundamentals of mail selling: tells how you may start by following proved procedures. Mail Order business booming as never before. Get our illustrated brochure describing our practical course; see what this grand industry may offer you. Mail Enterprises, Inc., 315 Fox Building, Detroit 1, Michigan.

EXPERIENCED Bookkeepers, accountants, college men, teachers, may earn \$500 to \$5000 fees as cost consultants, installing new modern practical cost systems. Learn direct from Philadelphia firm of successful professional cost consultants and industrial analysts. Practical, profitable, Ten comprehensive parts or lessons, \$10,00 per lesson. Write or register through W. C. Moore, 111 Oak Terrace, Merchantville, New Jersey.

HAVING been granted permission by the War Production Board to resume manufacture of a limited quantity of our No. 5 Kendall Envelope Sealers, we require a few additional distributors. Men with selling experience will find this Sealer an attractive income producer. Sells on demonstration at \$2.50. Kendall Sealer Company, E. Jaffrey, New Hampshire.

DEPENDABLE Business started with 25.00.
All householders potential buyers. Tremendous Profits, 10.00 wholesales yield 7.00 profit. Pack, seil Roach Powder, Bedbug Exterminator. Fly Fumes, Mosquito Repellent. Easily made without experience. Formulas, Instructions: 1.00 no other charge. L. Alarie, Exterminator, 2817 Masson, Montreal 36, Canada.

HOME Craftsmen. We have selected several Alien Patents, toys, novelties, wood, metal, suitable small shop manufacture. Illustrations six patents, instructions to obtain U.S. Government manufacturing license now being sent our members. A great opportunity more coming. Enroll now. Membership \$1.00. The Novelteers. 219 R. 2. Easton, Pa.

LICENSED Concrete Specialists wanted. No experience needed. Make Colorglazed concrete pottery without molds. New, low cost, patented method. Cemetery products, novelties, tiles, floors, etc. Basement leak-sealing. Other money-making projects. Booklet, cost data, details 10c. National Potteries, Fergus Falls, Minnesota.

MAKE new patented toys in your work shop, Lathe required. Pay small royalty. Year around seller. Self advertising. They sell like yoyos. Your ticket to prosperity. Send \$1.00 for blue prints and proposition. People are toy hungry and stores are empty. Act now. Clinton Davidson, 636 "C" St., San Diego 1, Calif.

START Home Business making statuary, plaques, art goods, novelties, souvenirs, concrete pottery, garden furniture, artificial marble flooring, liquid marble. Make your own flexible molds, Amazing profits, Valuable folder free, Creative Publishers, PS3, Glencoe, Illinois.

MECHANICALLY Inclined Men—Own and operate general Appliance Repair shop. Complete, illustrated course shows you how. Welding. Refrigeration, Motor repair. How to get business, etc., all phases covered. Free literature. Christy Supply. Dept. 749, 2835 N. Central Ave., Chicago.

LIQUID Marble; snow-white, multi-colored. Glazed. Unglazed. Composition Flooring. Lifetime wear. Any color. No priorities. Flexible molds. Plaster casting. Get into the big money now. Full information given free. Write—Compo-Tex. Box 786-F, St. Louis. Mo.

LEARN Electroplating—Complete Instructions by a practical plater, with formulas for Brass, Cadmium, Chromium, Copper, Gold, Nickel and Silver Solutions, Price \$1.00, Money Back Guarantee— Plater Hyde, P.O. Box 176, National City, California.

ELECTRICAL Appliance Repair, Open your own shop, Learn house wiring; electric motors, vacuum cleaners, washers, etc. Complete illustrated course shows how. Free booklet. Pacific Training School, Dept. A-3-S, 4703 West Pico, Los Angeles 6.

WE have open machine facilities to manufacture good marketable items such as toys, household and automotive accessories, or what have you. Will consider outright purchase or royalty on sales. Send your proposition to City Machine Co., 868 Tallmadge Ave., Akron, Ohio.

COLOR Concrete with Chemicals. Big money making Hollywood style pottery. birdbaths, without moulds, Wishing-wells, stucco-rock, benches, Marbling, cement water-paint 16c brings sample, literature. Pictures, Hollywood Cementcraft, 8530 Wenderland, Hollywood 46, California,

THOUSANDS of Alarm Clocks need repairing. Jewelry stores swamped, Our simplified course with pictures and drawings teaches you how to repair these clocks. Necessary tools and supplies funished with course, Alarm Clock Repair Service, P.O. Box 1983B, Houston 1, Texas,

GOOD Paying Business Silvering mirrors, plating autoparts, reflectors, bicycles, bathroom fixtures, etc., by late method. No tanks or shop required, outfit furnished. Free Booklet, Gunmetal Co., Ave. E. Decatur, Illinois.

MAIL Order Business course shows you how to make money, spare or fulltime. Teaches professional mail order technique—not penny-snatching schemes. New Success-Catalog Free! Write—Nelson Company, Dept. 4-01, Chicago 4.

START a clock shop while clock repairing is booming. Our easy to learn home study course with pictures and illustrations teaches you how to repair all kinds of clocks. Information free. Houston Clock Shop. P.O. Box 5086B, Houston 12, Texas.

WANTED now! Distributors for nationally advertised products. Big directory 25c. Tells who to contact for samples and literature. Associated, 2557 Charlestown, Toledo, Ohio.

SCHOOL Seniors! A postal will bring you our Kwick-Sell Cardalog of graduation name cards. Hot selling everywhere! Big profits! Hurry! Craftcards. Box 235(AD). Pittsburgh 30, Pennsylvania.

A BUSINESS Of Your Own: Make your spare time pay you a Profit. A few hours a week can build a profitable enterprise for you. We tell you How. C. O. Olson. Box 126B. Grandy, Minn.

SEABEE or friend of a Seabee; send name, rate and address only, for sample set of Seabee Cards, Sensational, Money making, Free. Petyt Studio. 3310 West 65 Street, Chicago 29,

START Mailorder Bookshop—Everything furnished: publisher cooperation, 25c brings booklet, exclusive setup, samples, exciting ideas, General Publications, Ossining 1, New York,

MAKE and mold genuine Plastics, Forty illustrated work-sheets explain methods, processes, Authentic-simplified, \$1.00, Free circular, Plastics Digest, 3937D Tracy, Kansas City 4, Missouri.

GET into legitimate business waterproofing buildings. Enormous profits. High income taxes force orders. K made \$3,000. six weeks. Information Free. Bryan, 12 E. Pearl, Cincinnati, Ohio.

CIGARS. Distribute handmade cigars, wholesale, retail, packed under your own brand. Tremendous demand. Immense profits. Steady Business, Vallesm, New York 13.

OPERATE Profitable Credit Collection Agency Business; Earn \$5000-\$10000 Unwards Annually; Interesting Literature Pree; Write: Extension Service, Department 102, Los Angeles 36.

CAPITAL seekers—Interested in raising \$25,000 or more should write to Amster Leonard, Fox Bldg., Detroit 1, Michigan.

MAKE beautiful, colorful Liquid Marble,— Soundproof Plastic Flooring, and Flexible molds for Novelty Casting. Write for Free Information. Bing Products, 621-B Tremont St., Boston 18, Massachusetts.

HEALTH first! New Drugless Method. Unbelievable results! Operate a "Health Conditioning Club." No apparatus. Metabasic System, D9128, Station S, Los Angeles.

PROFITABLE Home Business, Sensational New Course, Flexible Mold Making, Novelty Casting, No priorities, Valuable folder free, Plastic Arts, Route 5, Muncie, Indiana

PLASTICOAT—Genuine "Bakelac" Clear, Ivory White Covers, protects everything, Sample pint \$1.25, Gallon \$6.00, 20th Century Products, 3151-19 Southport, Chicago.

RUBBERFORM—Plastic; Waterproof, elastic flexible mold making liquid. Sample pint with instructions \$1.25 postpaid. Gallon \$7.00. Plastic Products, 1410 Belmont, Chicago.

ESTABLISH own Business—No selling— No capital required. Why work for others—Be Independent Plan and Instructions \$1.00—Act today. Dillard, Box 2807, Kansas City 13, Missouri.

"OIL Drilling" New Cooperative Development Plan for landowners, investors, dealers. Landowner's Guide, Caddo, Oklahoma.

AMBITIOUS? Anxious to get Ahead? Write for Free Details on "From Fifty Cents a Day to Ten Thousand per year." Webb, Box 184-B, Drexel, Missouri.

SELL Display Signs, Pictures, Calendars, Books, Greeting Cards, Paper Novelties! Big Profits! Bargain Catalog Free! Elfco, 438 N. Wells, Chicago.

PREPARE now for post war security. Start a home business in spare time. Experience not necessary. Literature Free, Oregon Research, Rt. 1, Box 456, Bend, Oregon.

SELL by mail, promote your own proposition and have others selling for you. Particulars Free. Harry Dean, Box 900, Galveston, Texas.

START your own business at home taking magazine subscriptions. Highest commissions. Details. Supplies. American Readers' Service, Gwynedd, Pennsylvania.

TYPEWRITER Repairing—Original Course
—Simplified Home Study. Weber Typewriter Mechanics School, Box 269, Osborn, Ohio.

"HOW to Make Simple Molds and Plaster Plaques". Profitable Business or Hobby! Booklet 25c, Plastercraft, 1406 E. 43rd St., Cleveland 3 Ohio.

GIANT Mail. Big Mail Order Magazine Included. Opportunities galore 10c. The Old Commander, Box 302, Chillicothe, Ohio.

LIQUID Roach Trap solves roach problem. Salesmen wanted, make \$20.00 daily. Samples postpaid \$1.00. Roach Trap Co., Ft. Smith. Arkansas.

INCORPORATE in Delaware. Many advantages. Free details. Corporation Fiscal Company. Inc., Delaware Trust Building, Wilmington, Delaware.

SIX complete and different post card plans for starting profitable spare time business. Gordon Publishers, Box 23, Pawtucket, R. I.

MAKE wine, 10 kinds; Beer, 7 kinds; Whiskey without still, 6 kinds, Any set of the above tested formulas \$1.00, Law Company, 54 East 99th, New York 29.

MAKE Die Metal Castings—in your own shop. One Dollar brings drawings, explanations. Tractor-Lite Mfg. Co., Spirit Lake, Iowa.

PLAN Post War Prosperity Now. Complete plans starting Busin-ss spare time One Dollar. Information Free. G. Schreiner. Batavia 6, Ill.

DOLLAR Making tips, book new ideas, formulas, plans, trade secrets, 25c, Joseph Royer, 82-C Merrimack St., Haverhill, Mass.

MAKE flexible molds! Few cents each! Cast plaques, novelties, bookends! Sample-formula-instructions 25c. H. Tooker, 630-M Chestnut, Hamilton, Ohio.

COLORFUL Plastic Links for Handmade Costume Jewelry; easily assembled, Profitable sideline, Dollar starts you! Hughes, 218 Sidell, Danville 2, Illinois.

CLERKS, Bookkeepers, sparetime earnings, simple, marvelous plan. Send two dollars now. Irving, 207 Shaw St., Toronto, Canada. IMPROVE your job or business. Read the "inside" trade magazines. Profit by knowing "how" and "where". Lists free. Dunbar, New Brunswick 3, N. J.

GET Ready to Start Own Postwar business. Make Venetian Blinds. Illustrated Instruction Book \$1.00. Elwert, 6900 North Ashland, Chicago 26.

PROFITABLE, spare time, unusual mail business earned \$1400 monthly, Copyrighted instructions \$1.00 postpaid, W. S. Boyd, 331 Fourth, Pittsburgh 22, Penna.

LIQUID Marble — Marvelous, colorful. Brush.d. sprayed, molded. Rubberlastic molds! Composition Flooring! Particulars free, Marbelizing Service, Edwardsville, Ill.

LEARN Mailorder. Five big interesting mail trade magazines teach you quickly. Postpaid, 25c. Lewis Co., 828K Carpenter, Oak Park, Illinois.

INDUSTRIAL X-Ray a vast new Post-war profession. Find out how to qualify. Rush name for facts. Ohio Institute of Technology. Box X-233. Greenville. Ohio.

10 IMMERSION Plating Formulas requiring no equipment. Instructions included—Only \$1.00 (Cash accepted). International Service Bureau, St. John. N.B.

RUBR-TEX flexible mold making liquid. Trial size with instructions \$1.25. Gallon \$7.00. Bonyman, 25 Bass, Wollaston, Mass.

POSTWAR Special Sale! Make simple chemical products. Extremely profitable. Easy work. Guaranteed information. Thermoflab, Peoria 4, Illinois.

INFORMATION—Locating most any article, (Dime), Rakes, Box 5931-C, Chicago 80.

FREE Literature describing mail order, and many moneymaking plans, Swenteck, 8840 Warren, Dearborn, Mich.

MORE Money with your own products. Experience unnecessary. No machinery, Information free, C. Kinford, Wayne, Pa.

MOLD-MAKING, Plaster casting, Moneymaking Business, Literature Free, Kemilo, Park Ridge, Illinois,

BOOKKEEPERS Earn Extra money operating Profitable Bookkeeping Service Spare Time, A. Schreiner, Batavia 3, Illinois,

TURN accounts into cash. Good income; quick results. National Collectors. Newark, Ohio.

PLASTICS made without equipment 10c lb. Perfect castings. Formula 50c. Baker, 225 Symington Ave., Toronto, Canada.

INVESTIGATE—Co-operative Mail Promotion Service for profitable opportunities. Russell Johnson, Clarkfield I. Minnesota.

\$24,000 RICHER; used schemes from "Schemer" Magazine, Alliance, Ohio, 47th year, \$1.00; 3 months, 25c,

EARN Money with Textile Painting Course. Details free. George Gundrum, LeRoy, Michigan.

1945 MAMMOTH information portfolio. Write Hutchko, 1153X Princess Ave., Camden, N. J.

OPPORTUNITIES galore. Big Mail Order Magazines. Three months, 25c. Royal Publications, Prospect Heights 3, Illinois. HOMEWORK Business. \$5,000 year. Setup \$1.00. (Prepaid). Factory, 23NE8, Oklahoma City 4.

OPPORTUNITIES, Tips, Ideas Galore, How Magazine, Year 50c copy 10c, Miller, 5104C Holcomb, Detroit 13, Mich.

START profitable rug-upholstery cleaning business, home. Information 3c stamp. Torrey, 93 Federal, Boston.

YOUR Postwar fortune, Money in mailorder business. Free details, Victory, Box 179F, Dowagiac 2, Mich.

PATHWAYS to progress; wealth, Particulars, stamp appreciated, 313 Fitzsimons Bldg., Pittsburgh 22, Pennsylvania,

\$2,000 YEAR sideline easy, inventing simple items for guaranteed cash markets. Hendrixon, Argyle, Wisconsin.

SELL beautiful Woodcraft Desk Names. Nameplates. Big demand. Woodcraft, 1320 Lindsay, Gainesville, Texas.

YOUR own products machinery, experience unnecessary details free. McDaniel, 939 E. Euclid, Detroit 11, Michigan.

RECAST old batteries into new. Latest achievements. Battery Laboratories, Minneapolis.

70 PAGE moneymaking magazine 10 cents. Loren Hollenberg Roseville, Illinois.

SELL Books and Courses by mail in your spare time. Siddall, Atascadero, Calif.

ELEMENTS For electric irons \$1.75 postpaid. Aesco. Box 415, Austin, Texas.

## BUSINESS SERVICE

BUSINESS letters that pull. All types. Application, collection, publicity, sales. \$1 each. Neiberts, Bolton Landing, N. Y.

FOR new things to buy and sell, read New Products Review. Write Chaffee, 308 Washington, Chicago 6.

## CAMERAS, PHOTO SUPPLIES

GORGEOUS Giris! Hollywood's Most Beautiful Models posed in 200 masterpieces of Pin-Up Art! Available as follows: Glossy Finish Post Cards—10 for \$1.00, 25 for \$2.00, 35mm Fine Grain Negatives from which enlargements of desired size may be made—10 for \$1.00, 25 for \$2.00, 35mm Black and White Positive Transparencies for protection, supplied unmounted—15 for \$1.00, 55 for \$3.00. All Postpaid, Send self addressed envelope with order for quick service. Cinema Artists Studios, Box 328-M, Hollywood 28, Calif.

AMATEUR Photographers attention! Improve your hobby of picture taking and learn how to make money with it. Write today for our 40-page book catalog and a sample copy of American Photography, enclosing ten cents for postage, Contains articles and pictures of the world's foremost writers and pictorialists, Camera House 141, 353 Newbury St., Boston, Mass.

BASS Says: War time proves Bass leadership. Amazing selection of finest still cameras—Leica, Contax, Korelle Reflex, Argus, new and used still available. Write for quotations, Satisfaction guaranteed or your money refunded. Bass buys 'em, sells 'em, trades 'em. Bass Camera Company, Dept. SP, 179 W. Madison St., Chicago, Ili.

WAR-Bargain Used Cameras. Bantam Kodak \$5.00, 35mm Camera \$6.00. Graflex \$25.00, 11 x 14 view \$25.00, Movie Camera \$5.00, Projector \$7.50, Film, Meters hundreds of others—complete list, descriptions 25 cents. Used Camera Directory (List 4S) 3111 West Tuscarawas, Canton 3, Ohio.

CASH! Spot cash for cameras, lenses, binoculars, movie or still, sound projectors. Send full description by mail, or wire for prompt cash offer. Over 30 years of dependability insures honorable dealings, Bass Camera Company, 179 West Madison Street, Chicago, Illinois.

OIL coloring photographs can be a fascinating hobby or profitable sideline for those with artistic talent. Learn at home. Easy simplified method. Send for free booklet. National Photo Coloring School, 1315 Michigan, Dept. 1721, Chicago 5, Illinois.

"BIG Bertha" telephoto camera easily made. Trifling cost. Objects miles away photograph close up. Ultra sharp pictures. Telephoto lens and instructions \$2.00. Instructions alone 10c. Carl Jamer, Manorville, New York.

PHOTOGRAPHY for pleasure or profit. Learn at home. Practical basic training. Long established school. Write for booklet. American School of Photography. 1315 Michigan, Dept. 1722, Chicago 5.

ENLARGERS—Build your own. Kit of parts \$6.00. Free particulars. Crescent Engineering, Box 251-C. South Pasadena, California.

USE any camera with plentiful 35mm film. Simple instructions, Rush \$1.00, D. Tirekop Madeira, Ohio.

I BUY sell and exchange cameras. W. K. Crosson, 4515 Grand River, Detroit 8, Michigan.

# CARTOONING, SIGN PAINTING, DRAWING

POCKET Size Cartoon Course—22 Easy Lessons, over 200 sketches including figures and lettering. Prepared by nationally known artist. Mailed postpaid on receipt of 25c in coin. Snack-Pack Co., 32 E. Georgia St., Indianapolis 4, Ind.

POSTER Art Simplified. Make theatrelobby-style portraits from photos, cuts, etc., quickly, easily, accurately for pleasure or profit. For complete instructions send \$2.00 to, Wissink Studios, 3027 S, 16th St. Milwaukee 7, Wisconsin.

SIGNS Made Easily, Instructions and ten sets modern alphabets; numerals, patterns. Sizes up to Eight Inches. All for \$1.00. Co-operative Business, Box 638, Chicago.

CARTOONING Course:—30 illustrated lessons, over 500 sketches, complete \$1.00, Rex Cartoon Studio, Box 892N, Pasadena, California

CARTOONISTS—Sell your work 15 illustrated lessons, 10 money making plans, markets, \$1.00, Cartoon Studio, 1402 Charles, La Crosse, Wisconsin.

ART magazines 25c, 6-\$1.00; Revised modern poster art \$2.00; Figure Drawing, 20 Colored poses, 8½x11, \$2.00, Signs, Farmington, Missouri.

SIGNS easily made with alphabet ruler, one stencil, all letters numerals \$2.00 postpaid. Alphabet Ruler, Melvindale, Michigan.

CASH in on your sense of humor. Write Cartoon Ideas, Booklet shows how, Send 25c. Don's Studios, 518S Wrightwood, Chi-

PORTRAIT or scenery, paintings from photos 15" x 18" \$10.00. Cora Wright, Arroya Grande, Calif.

LEARN Cartooning, Gag writing, Plans, markets, Drawing set given! Hartman, 2438 W. Lincoln, Nebr.

"HOME Cartoening Course" 25c. Gerard Studios, 710 Gaston, Fairment, W. Virginia.

DRAW Gorgeous Gals. Course 50c. Norman Beier, 55 S. Audubon, Indianapolis 1.

# CHALK TALK STUNTS

CHALK Talks, Laugh Producing Program \$1.00. Illustrated Catalog 10c, Cartoonist Balda, Oshkosh, Wisconsin,

## CHEMICALS & APPARATUS

CHEMISTRY Laboratory apparatus and chemicals for industrial, analytical, and experimental laboratories. Complete supply service for students taking correspondence school chemistry courses. Send 3c postage for free 44 page catalog. Dept. M26, Biological Supply Co., 1176 Mt. Hope Ave. Rochester 7, N. Y.

THE House of Winn, the Home of Supplies for Amateur Chemists. See Winn's new idea Chemical Kits and Apparatus Outfits for Home Experimenting, Send 10c for Retail Catalog, John H. Winn, Established 1931, Dept. 607, 124 West 23 St., New York 11, N. Y.

NEW 32 page Chemical Apparatus Order Book. Complete line of Chemical Glassware. Apparatus and Chemicals. Send 10c for this book. Standard Science Supply Co., 1232 N. Paulina St., Chicago 22, Illinois.

HANDBOOK for Chemical Experimenters. Hundreds of experiments; illustrated; 50c, Experiment Booklet, 15c, Chemical Catalog, 5c, Reading Scientific Co., Reading, Pa.

100 DIFFERENT Chemicals. One ounce or more each, Excellent opportunity for diversified laboratory stock, \$6.90. Midwest Chemical Co., 3724 Second Ave., South Minneapolis, Minnesota.

LABORATORY Supplies at Wholesale Prices: Chemistry, Biology, Physics, Catalogue, 10c, National Scientific Co., 2204 W. North Ave., Chicago, Established 1908. LUMINOUS Paints will glow in dark. Six colors, Fairmount Chemical Co., 136 Liberty St., New York City 6.

YOUR Choice of any 10 chemicals \$1.00 catalog 5c, Arc Chemical Co., Box 164 Yonkers, N. Y.

RARE, Unusual Chemicals. Send \$1 for ten different. Ohio Research Laboratory, Box 6305, Cleveland 1, Ohio.

FREE Catalog: Chemistry, mineralogy, Biology, optics, Tracey Laboratories, Evanston, Illinois,

SPECTROSCOPE for quick chemical analysis \$2.50. T. A. Cutting, Campbell 3, Cal.

FREE chemical catalogue. Enclose 3c Postage. Greenwood, 398 Broadway, N. Y.

# COIN COLLECTING

WE buy Indian pennies, Lincoln pennies, and Old Rare Coins. Highest prices paid. Indian pennies worth up to \$15.00 each. Lincoln pennies up to \$2.00 each. Other rare coins \$5.00 to \$2000.00 each. Send 10c today for new 1945 Price Catalog of all wanted U. S. Coins. American Rare Coin Co., Dept. 4, Transportation Bldg., Chicago 5.

RINGLING Brothers Circus Scrip, complete set 6—\$1.00; 12 Wooden Nickels \$1.00; Both \$1.60, 25 Different Indian Head Cents \$1.00. Bebee Coin Company, 1180 E. 63rd Street, Chicago 37, Illinois.

4 ANCIENT Roman Coins 2000 years old \$1.00, 36 Different Foreign \$1.00, 100 Different \$4.00, 43 mixed Indian cents \$1.00. Lists—Approvals, Delmonte, 725 West 172, New York 32 347 ANTIQUE Firearms; 4,000 Bargains, Coins, Indian Relics, Minerals, Cartridges, Rifles, Flintlocks, Fossils, Swords, Catalog with Photographs 20c. Museum, Wenona, Ill.

FREE! Foreign coin, banknote and Coin Collectors' Illustrated Catalog to approval service applicants. Send 3c postage, Tatham Coinco., Springfield-D50, Mass.

WILL Pay \$10.00 Each For Certain Lincoln Pennies! Indianheads \$50.00; Dimes \$1,000.00. Catalogue 10c. Federal Coin Exchange, 3-PS, Columbus. Ohio.

COMMEMORATIVE \$\frac{1}{2}s — Columbus — Stone-Mountain, Texas, Cleveland, \$1.50 each, New illustrated Catalogue 25c, Norman Shultz, Salt Lake, Utah.

QUICK Service; reasonable prices, United States catalog 10c. Foreign catalog 10c. Ben's Coin Shop, 72 W. Washington, Chicago 2, Illinois.

10 INDIAN Head cents, different dates also pricelist, 40c, Schultz, 105334 Richwood, Cincinnati, Ohio.

WE purchase Indianhead pennies. Complete coin catalogue 10c. Fairview, 277 Broadway, New York.

50,000 COINS, medals, papermoney. Lists free, Nagy, 8-A South 18th Street, Philadelphia 3, Pa.

FOREIGN Coin and lists 10c, Oddehon, Box 482, St. Louis, Mo.

FIVE foreign bills, 25c; 25 different \$1.00, Beffel, Box 37, Ottawa, Illinois,

## CONSULTING ENGINEERS

EXPERIMENTAL Engineer. Machines, Tools designed and developed. 25 years experience. Harry Childs, Berwick, Maine.

## CURIOS

AMAZE your friends with Mystery Tropical Leaf! Grows on air before your eyes! Only \$1.00 postpaid. House-O-Tropics, 752 Northwest 66th Street, Miami 38, Florida.

# DETECTIVES

DETECTIVE Training — Secret Investigations Easy Method—Finger Prints. Booklet Free. International Detective System, 1701-P Monroe St. N.E., Washington 18, D. C.

DETECTIVES—Work home—Travel. Experience unnecessary, Write, Wagoner P-125 West 86th, N. Y., N. Y.

DETECTIVE and fingerprint instructions, Prank Mashak, 4127-PS Westminster, St. Louis 8, Missouri,

DETECTIVE Training, Phillips Secret Service, 1917-C North Kenneth, Chicago 39, Illinois.

FINGERPRINT Powder: new and superior powder, William Croll, Box 502, Norristown, Penna.

# DOGS. BIRDS, PETS. RABBITS

SANITARY Rabbit Hutch—Odorless, Selfcleaning. No opening doors to clean, feed, water! Most practical, scientific hutch made. Plans, specifications \$1.00. Automatic Feeder plans \$1.00. All three \$2.50. Catalog finest Pedigreed Angoras free. Grinsteads, Dept. 16-B, Edwardsville, Illinois.

RAISE Giant Chinchilla Rabbits. Valuable Fur. Delicious Meat. Easily Raised. Pleasant Pastime. Large Profit. Free Booklet explains how investment of \$65 can return 1000%. Willow Farm, R16C, Sellersville, Pa.

RAISE Rabbits continuous market, \$9 to \$18 each. Prices guaranteed, literature 10e with Hutch plans 25c, 100% automatic. Hansens Rabbitry, 1347 Miller Ave., Salt Lake City 5, Utah.

RAISE Moneymaking Angora Rabbits. Wool \$9.00 pound, Plenty markets, Particulars free, White's Rabbitry, Marion, O.

WILD Geese, Ducks, Peafowl, Pigeons, Pheasant, Rabbits, Prices Free, Jewel Game Farm, Danville, Ill.

RAISE Rabbits, make money at home. Markets guaranteed, Booklet free, Taylors Rabbit Farm, Hapeville, Georgia.

RABBITS: Flemish Giants, New Zealands. Reasonably priced. Franklin Young, Riverhead, Long Island, New York.

ST, BERNARD Pups: Champion sired beauties, Franklin Young, R 3, Riverhead, Long Island, New York.

MICE, Rabbits, Pigs. Catalogue list 10c. Houck Company, Tiffin, Ohio.

STANDARD Rabbit Journal, Milton, Pa. 3 years \$1.00, Sample dime.

## DRAFTING INSTRUMENTS

812" x 11" BLUE printer, complete with blue print papers, tracing papers, chemical, \$2.75 postpaid. Best Co., Box 5802, Cieveland 1, Ohio.

SAVE on drafting materials. Free catalog. Draftsmen's Supply Co., 32 North Wells, Chicago 6

# EDUCATIONAL & INSTRUCTION

GOOD Jobs and a Sound Postwar Future await you in hotel and institutional field. Men and women - all ages - needed for well-paid positions that offer color, excite-ment, ever-new and fascinating duties. Record-breaking business in hotels, clubs, institutions, means even greater opportunities. Lewis School receiving calls for managers, assistant managers, stewards, hostesses, purchasing agents, and 55 other types of important positions. These are not temporary jobs, but important positions in an essential business that offers splendid opportunities in war or peace, good times or bad. Previous experience proved un-necessary! No need to leave your job to qualify. A good grade school education, plus Lewis Training qualifies you at home, in spare time. Our National Placement Bureau helps to place you—and our amazing Certified Job Plan—actually guarantees you will "make good" when placed. Write today for free book! Lewis Hotel Training School, Room DC-2768, Washington 7, D. C. (First and only School of its kind-Now in its 29th year.)

REFRIGERATION — Air Conditioning.

Mechanically-minded men! Are you interested in the kind of work which offers a "go-getting" man a real chance to make headway—even own his own business? Then write today for free Facts about Refrigeration and Air Conditioning, and how you can start Now to get a working foundation for this field in your spare time; how you can get the kind of training which for 18 years has helped so many U.E.I. men "make the grade" in a big way. Utilities Engineering Institute, Dept. 35W, 1314 W. Belden Ave., Chicago 14, Illinois.

MAKE Up to \$25-35 week as a trained practical nurse. Learn quickly at home, spare time. Easy tuition payments. Earn while you learn—many earn hundreds of dollars while studying. Easy to understand lessons, endorsed by physicians, High school not required. Our 45th year, Write for free booklet and sample lesson pages, Chicago School of Nursing. Dept. K-3, Chicago.

TALKING Letters make friends and bring success! Learn By Mail the secret of writing a letter that talks! No more dreading to "take pen in hand". As easy as talking to your best friend! Send today for sample Bulletin—"How to Begin a Talking Letter." 25c. Write . . . Annette Graebner, Letter Consultant—Creator of Talking Letters, Box 609, General Post Office, New York City 1.

PSYCHOLOGY teaches about mind. Biology teaches about body. Bio-Psychology teaches about powers of mind over body. Use powers subconscious mind. Select proper vocation. Grow. Broaden education. Develop personality. Control emotions. Succeed. Correspondence. Dept. P., Taylor School of Bio-Psychology. Chattanooga 1, Tennessee.

HYPNOTIZE People Easily! Twenty-five simple lessons fully illustrated and clearly written, show the most modern methods known. Get yours today! Only 50c. The Archer Company. Dept. F, 93 Federal Street, Boston, Mass.

WRITE Short stories at home for pleasure and profit. Fame, riches and happiness of achievement are rewards to be realized by students who acquire tested technique. Get free booklet from home study school with 50 years experience. Write today! Blackstone-Sprague, Dept. 72, 307 North Michigan, Chicago I.

HOME study. Over 300 low cost business, technical and vocational courses, including new course on Real Estate. Our method stimulates interest, saves months of study, hundreds of dollars. Free bulletin. State subject wanted. DeVoto Schools, Dept. 1, 35 Vicente, San Francisco 16, Calif.

START building a fortune regardless of present income, Book with definite workable plan. Details free. Princess Press, 2026 Klein Rd., Wilmington, N. C. AUTO Body and Fender work, including metal work, welding and spray painting. Look into it! One of the most profitable branches of tremendous Auto industry offering chances for good job or your own business. Train in spare time, Write for Free facts. Utilities Inst., Dept. 34Y, 1316 W. Belden Ave., Chicago.

CARPENTERS, we teach the square in five easy lessons by mail. Our ¼ size practice square and simplified instructions does the work. Free information, better still send quarter for practice square and partial lesson. Builders' Topics, 3rd Floor, Medical Arts Bldg., Seattle, Washington.

TYPEWRITER Repairmen urgently needed.
Earn \$40 to \$50 weekly spare time. Our
easy to learn home study course teaches
how to repair typewriters. Write for free
information. Houston Typewriter Repair
Service, P.O. Box 5357B, Houston 12,
Texas.

WELDING—electric arc. Learn quickly by actual practice at Hobart Welding School. Individual instruction at bare cost of materials used. 75c in stamps brings valuable welding lessons post paid and full particulars. Hobart Welding School. Box P-352, Troy. Ohio.

VICTORY! Prosperity! World peace! They could quickly be attained! Progressive Humanology shows how. Dime brings literature, showing also how to earn \$1000 Prize. Ornsteen, Box N-29, Englewood, Colorado.

CLINICAL Laboratory Technicians in great demand. We train you in your spare time, in your own home. You can practice while studying. Write for free catalogue. Imperial Technical Institute, Box 973-B, Austin 5, Texas.

DEFENSE Workers—for a better job and postwar employment learn to multiply millions mentally. My new formula teaches how or return it and money refunded. Send \$1 for complete course. Hoey. 376 Hayward Ave., Mt. Vernon, N. Y.

GOOD "Used" self-instruction educational books on all subjects bought, sold, rented, exchanged. Satisfaction guaranteed. Complete information and 92-page illustrated bargain catalog Free, Write. Nelson Company, Dept. 2-01, Chicago 4.

MATHEMATICS: Arithmetic: Algebra: Geometry, Trigonometry, Calculus, Physics, Preparation Electrician, Plumber, Stationary, Architect, Surveyor, Engineer Licenses, Mondell Institute, 230 West 41st, New York.

V-12's FOR SMOOTH Sailing in Math, learn to multiply millions mentally. My new formula teaches how or return it and money refunded. Send \$1 for complete course. Hoey, 376 Hayward Ave., Mt. Vernon, N. Y.

MEMORY means money! To succeed, remember what you learn or you won't profit by it. Train your memory for success! Send \$1.00 for complete Memory Training Course. Kestner & Co., 5 Treacy Ave., Newark 8, N. J.

"HOW To Break And Train Horses"—A book every farmer and horseman should have. It is free; no obligation. Simply address Beery School of Horsemanship, Dept. 583, Pleasant Hill. Ohio.

LEARN to multiply millions mentally. My new formula teaches how or return it and money refunded. Send \$1 for complete course. Hoey. 376 Hayward Ave., Mt. Vernon, N. Y.

BE a Doctor. Learn Chiropractic. Fast Growing Profession. No Correspondence Course. Write for Catalog. Texas Chiropractic College, San Pedro Park, San Antonio, Texas.

LEARN Profitable Credit — Collection Agency Business; Investigate Extension Service Advertisement under Business Opportunities.

TRIGONOMETRY is easy with Quick Trig calculator. Automatic answers. 75c postpaid. Reed Mfg., 124 W. 4th., Los Angeles 13.

MYPNOTISM—Simple proven method. No magic. Learn to Hypnotize or money back. \$3.50. DDK, Box 458, Douglas 4. Arizona.

USED Correspondence courses, Educational and Technical books bought, sold, rented, satisfaction guaranteed, catalog free, Educational Exchange, Henagar, Ala.

WE Teach Marbelizing In all branches. See samples. We instruct in plastics. Free Samples, Address Novelty Supply Co., Grayling, Mich. LEARN To sing beautifully through modern voice culture. Literature free. Ferris, 317-D Hartford Ave., Bremerton, Wash.

LEARN Powerful Mental Telepathy 25c. Elgin, 912 Benton, Nashville 4, Tennessee.

THINK-UP new money-making ideas; advance financially. Dr. Tibolt, 32A, 185 Godfrey, Philadelphia 20.

HOME Study Course, drugless therapy. Free literature, Institute of Drugless Therapy, Tama, Iowa.

LOCKSMITH Course, Lock-picking, keyfitting, etc. \$1.00 prepaid, Miller's Key Shcp, Canadian, Texas.

NON-RESIDENT high school, college, professional degrees. Bulletin free, Capital City College, Washington 5, D. C.

PROPHETS approximated FDR's name. Christ is here! Dime, Nichols, Box 85, Waltham, Mass.

POCKET Cartoon Course, complete. Cartoonist's Magazine. Both 30c cash postpaid. Studios, 2438 W., Lincoln 3, Neb.

COMPLETE Hypnotism Course—25 lessons \$1.00 postpaid. M. Schwartz, 71-01 35 Ave., Jackson Heights, New York.

MEMORIZE — Quickly — Easily. Complete instructions 25c. Rennco, 7157 St. Lawrence, Chicago 19.

BECOME a Finance Man, Particulars free, George Lenhoff, Lincoln 8, Nebraska,

DRAFTING Pays Big-learn at home. Monroe Institute, Alton, Illinois.

LEARN To draw funny faces. Write, Funny Faces, Modesto 1, Calif.

## ELECTRICAL SUPPLIES & EQUIP.

BROKEN—Burned out Electrical Heating elements quickly repaired. Use new amazing Nichrocite Paste, simply overlap ends and turn on current. Family size \$1.00 bill. Satisfaction guaranteed, Advance Electric, Box 861-Y, Minneapolis, Minn.

pour own shop. Learn house wiring; electric motors, vacuum cleaners, washers, etc. Complete illustrated course shows how, Free booklet, Pacific Training School, Dept. SA-3, 4703 West Pico, Los Angeles 6.

HANDY Pocket size electric circuit tester checks all electrical appliances, radios, motors, fuses, etc. 90 to 550 volts, A.C. or D.C. Distinguishes A.C. from D.C. \$1.00 postpaid. Supreme Electric Mfg., 210-B Roebling St., Brooklyn 11, N.Y.

ELECTRICAL Trouble Shooter: Finds Leaks, Opens and Grounds in anything electrical. Indispensable to Electric Shops, Garages, Car Owners. Free Literature. Factory, 811 East 31st, Kansas City 3, Missouri.

NOW—Repair your own electrical appliances with Chanite Self-welding, Electrical Heating, Element Flux, Instructions, delivered, price \$1.00. Chanite Sales Company, 914 South Main, Fort Worth, Texas.

MANUAL, "Know Your Multispeed Motors," explains in every detail this type of electric motor. \$2.00 or descriptive literature sent free. Electric Generator Mfg. Co., 1333 N. Dale St., St. Paul 3, Minn.

ELECTRIC Kilns—new, prompt delivery, two sizes, with temperature dial. M. Fred Keglmyer, North Wales, Pennsylvania, Distributor.

GARAGE doors dashboard controlled. Additional information under "Automobiles".

COILED Nichrome toaster or hotplate element, forty cents coin. Box 434, Worcester, Massachusetts.

ELECTRIC Pencil: Writes—Engraves all Metals, \$1.00 postpaid. Beyer Mfg., 4515-C Cottage Grove, Chicago 15.

HAIR Clippers—vibrators—new 1/40—110—A.C. Motors—Dremel Sales, 1101 Cleveland, Racine, Wisconsin.

REPAIR Electrical Appliances Use Nichrocite. See Ad Page 32H. Advance Electric Co.

# EMPLOYMENT SERVICE

INTERESTED Foreign employment? Thousands jobs throughout world. Names and addresses over 200 firms with sample application \$1.00. "We search the world" Wonder-World Research Bureau, Box 731, Gladewater, Texas.

# ENGINES & MOTORS

MODEL locomotives, gas, steam engines, Supplies Catalogue 25c. Welding Rod without flux for aluminum, Die Cast, Pewter. Samples and Instructions 25c. Howardco. P3-2417 Ashland, Chicago 14, Ill.

MOTORS, small DC 6 volt 3000 RPM suitable for operating models and gadgets on intermittent duty. Postpaid \$1.25. Walthers, 269 Erie, Milwaukee.

TWIN-Cylinder Air Compressors \$17.75. Motors, Hoffmann, 6840 Parrish, North College Hill 31, Ohio.

WINDING Data, listing 225 motors, single and three phase, \$1.00, Motor Data, Box 7631, Kansas City 3, Mo.

## FARMS, OTHER REAL ESTATE

EVERYONE Should own at least a little piece of Texas. Imagine buying a full half acre garden tract or campsite in the fabulous Corpus Christi Bay area for only \$450. Terms \$45 cash, \$5 monthly. Between Corpus city limits and Great Naval Air Base. Good soil, good roads, wonderful investment possibilities. (See February issue National Geographic Magazine, page 163.) Write or send your check to A. F. DeLoney, P.O. Box 167, Austin 2, Texas.

STROUT'S Spring Catalog Just Out! Bigger than ever! Over 1000 bargains from Maine to Florida and west to Texas, California, Oregon and Washington. Write this minute for this dollar-saving time-saving book. Free. Strout Realty, 255-ZB 4th Ave., New York 10, N. Y.

GOOD Farms—Ranches, Washington, Minnesota, Montana, Idaho, Oregon, North Dakota. Dependable crops, favorable climate. Write for literature, lists describing typical farms, Specify which state, J. W. Haw, 120 Northern Pacific Ry., St. Paul, Minn

OZARK Lands for all purposes, Actual River frontages, 5 acres \$90.00 and upwards, Free list and literature, Hubbard, 269 Grossman Bldg., Kansas City, Kansas.

OZARK farms ranches, timber, resorts. List free. Farmfinders, Lonsdale, Arkansas.

OZARK Magazine, Lonsdale, Arkansas. For homeseekers, sportsmen, folklorists. Year, \$1.00.

WISCONSIN, Minnesota Lake, River Frontages \$7.00 acre. 230-C 40 St., Manhattan Beach, California.

# FARM MACHINERY

NEW Farm Mechanical Book. Learn your Farm Machinery Better. Time and Money Saver. Actual Experiences of Better Farmers and Mechanics, \$1.00 Postpaid, Wirtison's, West Burlington, Iowa.

"GARD" Portable Electric Heaters available Now, Gardenhour Mfg., Waynesboro, Pa.

## FIELD GLASSES, TELESCOPES, ETC.

LENSES, prisms, optical specialties. Not Salvage, Not rejects. Not Junk. Highest optical perfection. Nothing like this ever offered before. Fraction original cost. Send for new optical catalog. 10 cents. Ross, 66 W. B'Way. N. Y. C.

TELESCOPE. Powerful Army type, 8-power, vest pocket size. Has scientifically ground 35mm. lens. Length closed, 4½-in., open 7-in. Only \$1.69 postpaid. Satisfaction guaranteed. Utica Mail Order Co., 923 Eagle St., Utica 3, N. Y.

ASTRONOMICAL Telescopes, Binoculars, Cameras, Microscopes; Bought, sold, repaired. Send 10c for list of instruments desired. Rasmussen & Reece, 41 Market, Amsterdam, N. Y.

MAKE Your Own powerful, efficient astronomical telescope. Perfect lenses and instructions, 50X \$1.00. 100X \$2.50. 200X \$3.50. 400X \$5.50. Instructions alone 10c. Carl Jamer, Manorville, New York,

BIG strong 5 power spy glass \$1.59; 5 power color corrected field glasses with case and strap \$16.50; all post free and tax included. Send money order to—Bockserman Company, Peoria 2, Illinois.

MAKE your own efficient compound microscope. Lenses and instructions 50X \$1.00. 100X \$1.50. 200X \$2.00. Instructions alone 10c. Carl Jamer, Manorville, New York.

REAL 17 power telescopes \$3 each. United, 2309-E Lawrence, Toledo, Ohio.

## FOR THE HOME

LIFE-SIZED portraits painted without sitting. Reasonably priced, durable materials and satisfaction guaranteed. Write for Particulars. R & R Studio, 218 West 7th, Taylor, Texas.

## FOR INVENTORS

INVENTORS: Learn now—without obligation—how to protect and sell your invention. Write for free "Record of Invention" form and complete instructions for making disclosure and establishing date of your invention. We also send our new free "Patent Guide for the Inventor", containing complete information about patent procedure and how to sell inventions; giving illustrations of many successful inventions; over 150 basic mechanical movements. We assure you prompt, confidential service. Delays may be dangerous. Write today for your free "Patent Guide" and "Record of Invention" form Clarence A. O'Brien & Harvey Jacobson, Registered Patent Attorneys, 52A-C Adams Building, Washington, D. C.

WHAT Should You Invent? Our Free Book tells you what today's inventive market wants—how to put down, patent, and sell your ideas. Scores of letters in our files attest to the modern demand for inventions—our long experience as Registered Patent Attorneys will help you. Get our Free Book, "How to Protect, Finance and Sell Your Invention". Also special document free. "Invention Record" on which to sketch and describe your invention. Write today. No obligation. McMorrow & Berman, Patent Attorneys, 143-F Atlantic Building, Washington 4, D. C.

RANDOLPH & Beavers, Registered Patent Attorneys, 340-E Columbian Building, Washington, D. C. In order to Protect your invention and reap the reward that should be yours, Patent your invention without Delay, and at the same time have Rights to sell as Manufacturers convert to Civilian Production. Write for Information and Record Form To-day.

INVENTORS! Submit your idea to the right firm! Over 10,000 concerns need new postwar products, are looking for them right now. Get your invention carefully considered through confidential report to manufacturers. Send brief description of invention, details unnecessary. Edward P. Bishop & Associates, Dept. PS, 4031 Goodwin Ave., Los Angeles 26, Calif.

PATENT Your Idea! Write immediately for two free illustrated books, "Patent Protection" and "When and How to Sell an Invention" 64 pages of valuable information for inventors. No obligation. Address: Victor J. Evans & Co., 942-C Merlin Bldg., Washington 6, D. C.

WE locate buyers meritorious patented, unpatented inventions. If will sell, reply immediately. Descriptive booklet, references, free. Invention Reporter, 3A-11106 S. Fairfield, Chicago.

INVENTORS: New military and commercial inventions urgently needed by manufacturers. Write for particulars, Chartered Institute. Dept. 3-A, Washington, D. C.

INVENTORS! Have you good patentable idea? Write Mr. Metzlerr, 11 West 42nd, New York.

CASH for practical ideas and inventions. Mr. Ball. BB-9441 Pleasant, Chicago.

# FORMULAS, PLANS, ETC

AUTHENTIC Formulary, 924 page illustrated book, Prepared by experts, 10,000 practical tested formulas, recipes, secrets, instructions for easily making most any product. Countless profitable business opportunities. Valuable reference for home, industry, Extra! Complete plans: "D.D.T." miraculous new insecticide. One spraying kills all Flies, Mosquitoes, Lice, Jap Beetles, etc. Lasts three months. Big money maker, \$2.98 postpaid (C.O.D. U.S. Only) Foreign \$3.25, Immediate shipment, Adams Brown Company, Dept. 106, Chestnut Hill 67, Massachusetts.

ABSOLUTELY every formula completely described including exact proportion of ingredients, compounding instructions, and addresses of ingredient suppliers. Send \$1.00 for each formula to: Information Research Institute, Box 8765, Pittsburgh, Pennsylvania.

PREWAR Tire carcasses everywhere, from these reclaim pure rubber, to make molds, tire-plastic, etc. Details for stamp. Betke, Box 699, Borger, Texas. MAKE, Wine, Beer, Whisky Without Still, Formulas \$1.00 each, Hendrix Studio, 411 Madison, Wilmington, Delaware.

FORMULAS—All kinds. Latest moneymakers; literature Free, KemiKal, Park Ridge, Ill.

FORMULAS—Latest, best Analysis, Literature free, E. Belfort, Engineering Building, Chicago 6.

ANY formula \$2.00 or refund, Case Kowal, Chemist. 1846 Cullerton, Chicago 8.

LUMINOUS Paint—Three formulas 10c. J.B.M., Box 225-S. Rockaway, Oregon.

ANY Formula \$1.00 or money back. Wike, 171 Norfolk, Brooklyn 29, N.Y.

## FRUITS AND FOODS

WINE easily made—costs little. Recipes and instructions for many varieties. Winemakers Guide \$1.00. Klauser, 311 Zeralda St., Philadelphia 44, Pa.

PEANUTS—Buy direct from growers—Roast them yourself, 10 lbs. \$2.75; 50 lbs. \$10.00; 100 lbs. \$16.50. J. P. Councill Co., Franklin, Virginia.

TREE-ripened Oranges, Grapefruit, Tangeloes. \$5 Bushel shipped anywhere Postpaid. No C.O.D. orders. Sam Rodante, Tavares, Fla.

WHEAT Germ Unexcelled quality 2½ lbs \$1.00 postpaid. Health-Wheat Co., Rochester 8, N. Y.

# FUR FARMING

GIANT Chinchilla Rabbits. Valuable Fur.
Delicious Meat. Easily Raised. Pleasant
Pastime. Tremendous Demand. Small
Investment. Large Profit. Willow Farm,
R16, Sellersville, Pennsylvania.

## GAMES & ENTERTAINMENT

VENTRILOQUISM Complete Instructions Only \$1. Lesieur, 77 Wellesley, Toronto, Canada.

TRIPLE—Deal. Fifty-two cards, Joker. \$1.00 prepaid. Box 842, Denver 1, Colo.

## GARDENING

SILVERTON Soiltester gives scientific soil control. With 16 page manual ppd, 35c. For luxuriant garden, new plants, seedless tomatoes, etc., get a 25c pkg, each of Rootone, Transplantone and Fruitone With Soiltester, \$1.00 postpaid. Silverton Laboratories, 6 Toms River, New Jersey.

CUT Plowers last three to seven days longer with Savabloom preserver. Guaranteed. 3 pkgs. 25c. Savabloom Co., Racine, Wisconsin.

# HIGH GRADE SALESMEN

GENTLEMEN! Write quick for details on our large-profit, fast-selling line of beautiful calendars. Includes Hangers— Commercials. Miles Specialties, Kokomo, Indiana.

# HOBBIES, COLLECTIONS

MAKE \$100 per month or more from any of three Hobbies; no canvassing; no soliciting; strictly home hobbies for old or young, men or women; details all three for dollar bill; money back guarantee. J. R. Carter, 338 Walnut, New Orleans 18, La.

"HOME Lapidary Shop" learn profitable interesting Hobby. Send Dollar for Booklet giving Instructions Illustrations. Mineral Specimens, Box 1191, Santa Monica, California.

FACSIMILE: Allies Military Currency for Germany, Italy; Netherlands; also Japanese money; planned for use upon invasion of America. Send 15c. Hobbyguild, V-35 West 32nd St., New York.

CHEMICAL treatment changes White Hydrangea to Novelty Blue. Treatment for 1 plant \$2.00. 3 plants \$5.00; Agents plan 25c. Dillard, Box 2807, Kansas City 13, Missouri.

COLLECT Foreign Military Insignias and War Prisoners Emblems; Prices, Samples 15c. Hobbyguild F-35 West 32nd St., New York

ONE Dollar starts you on America's newest hobby, Collect Army insignia patches, Cash with order to Springer's, 206 San Francisco St., El Paso, Texas,

PLAY "The Exchange Game"! It's Fun!
It's profitable! Complete details, six
issues. "The Exchange" 25c. Charlotte J.
Klings, Blue Island, Illinois.

UNUSED Match Book Covers, 100 all different \$1.00, 35 Royal Plash Covers \$1.00. Free list, Charles Edelman, 1311 P East 84, Cleveland 3, Ohio. JEWELRY stones removed from rings, etc., 100 assorted \$2.40. Lowe's, Box 311, St. Louis 1, Mo.

SALT-Pepper shakers, bought, sold, exchanged, Ruthers, 337 Commonwealth, Springfield, Mass.

EXCHANGE duplicates. Swappers everywhere. List free. Box 2166-S. Denver 1, Colorado.

SPECIAL Offer! Large assortment real stage money (Phoney-Mazuma) only 25c. Maniss Photo Co., Colorado City, Texas.

WANTED: Old cigarette cards. Write Charles Bray, East Bangor, Pennsylvania.

CARVED, Painted—Fawn, Hound, Colt. \$1.00 each. "Old Whittler", 1402 Charles, LaCrosse, Wisconsin.

MATCH covers, new, different, 125 for \$1.60. Ernlo, 175 Gramercy, Glen Rock, New Jersey.

COLLECT colorful army patches. Latest picture book and catalogue only 15c. Insignia Mart, 703 Broadway, N. Y.

CONTEST FANS—Contact us for big 1945 contest information. Box 43, G.P.O., N. Y. C.

## HOME CRAFTSMEN

PLEXIGLAS and Lucite—The amazing crystal-clear plastics! Saw them, drill them, bend them, twist them into hundreds useful articles that are beautifully different. Special one-pound assortment only \$1.00 postpaid; 6 pounds \$5.00! Plexiglas or Lucite sheets 12" x 12" (144 square inches!) 16" \$2.50; 3/16" \$2.75; 14" \$3.00. Complete directions and project suggestions included free. Order these "plastics of tomorrow" today! Carmen-Bronson, 160A East Fourth Street, Mount Vernon, N. Y.

CATALOG: Large line Decai Transfers.
Patterns for Jig sawing: New designs
easy to make Novelty Furniture. Lawn Ornaments, Silhouettes, Letter and Numerals.
100 Crafts and Hobbies, illustrated Booklets, Tools, Other Lines, 500 articles finely
illustrated, Write Wo-Met Shop, Ashburn,
Georgia.

28 LAWN Ornament patterns 25c. Other patterns: 15"-20" high; Dutch girl, Dutch boy, pirate, bull terrier, Mexican girl, Mexican boy, dwarf, penguin, flower girl, 10c each; 3 for 25c. 25 novelty patterns 30c. All 62 full size patterns \$1.00 postpaid. Strother, Box 383-GT, Bellington, W. Va.

CELLULOID—Beautiful assortment. Mottles, opaques, onyx, pearls. Used by ring makers everywhere. One pound assortment—pieces approximately 30 sq. in. each, Price \$1.00. Please include 10c for postage. Craft Service, 337 University Ave., Rochester 7, New York.

MAKE your own castings in your home workshop. Furnace can be built for a few dollars from scrap material. Will melt brass, copper, aluminum, cast iron, etc. Detailed plans and instructions only 50c (coin). Aladdin Electric Company, 8521 East Fourteenth St., Oakland 3, California.

PLYWOOD—Beautiful nonpriority aircraft, cabinet and paneling stock. Thicknesses 1/16" through 1"; large, small panels. Fir. Gum, Birch, Mahogany, Walnut. Reasonable! Complete lists 10c. Carmen-Bronson, 160A East Fourth Street, Mount Vernon, N. Y.

NOVELTIES made from scrap wood. 25 patterns 25c. 15 toy patterns 25c. 15 Lawn ornament patterns 25c. Other Patterns, 14"-20" high; Dutch Boy, Dutch Girl, clown, Mexican, Pelican, Rooster, 10c each; 3 for 25c. Lynds, Medway, Mass.

ACTION Toy, Ingenious, Different. Runs 4 minutes under own power. Scrap materials. Sells readily year around. Blueprints \$1.00. Alta Products, Box 1109, Pasadena, California.

CAMEOS—Made of beautiful plastic, with delicate details exquisitely produced. Many colors and designs. Sample assortment 10c. Craft Service, 337 University Ave., Rochester 7, New York.

MAKE Shell Jewelry, Shell, Metal and Plastic parts for manufacturing at home. Free illustrated catalogue and detailed instructions, Florida Supply House, Bradenton, Fla.

PIN BACKS—Mounted on celluloid patches for cementing to wood, clay, celluloid, lucite, etc. A quality product. Lengths 1", 1½", 2", 30c dozen. Craft Service, 337 University Ave., Rochester 7, New York.

PLASTIC Handicraft Kits. Send for details "CAL-Plasticraft" Studio City, Calif.

347 ANTIQUE Firearms; 4,000 Bargains, Coins, Indian Relics, Minerals, Cartridges, Rifles, Flintlocks, Possils, Swords, Catalog with Photographs 20c. Museum, Wenona, Ill.

350 SCREWS Machine Flat Round, Filister 9 popular sizes 70c assortment! 20 instrument gears \$1.25 others, literature 3c. Novak, 20 Patchen Ave., Bklyn 21, N. Y.

TOY circus wagon patterns. Three modern designs 50c. Ten attractive toy patterns \$1.00. Continental Products, 907 Birch, Eau Claire, Wisconsin.

THE hobby with a future. Plastic Costume Jewelry. Outfit \$1.00 postpaid gets you started. Kosto, 707 20th St. N.W., Washington 6. D. C. Dept. 2.

LOOK! Two cracker-jack tools; two unique equipment kinks. Amazing plan tells everything. Only 25c. Ideas & Plans C3, Palmyra, New Jersey.

"MAKE Saleable 'brass' electric lanterns from tin cans." Drawings, directions, 4 models \$1.00, Worthycraft, 43 Lovell Road, Melrose 76, Mass.

20 WHITTLING Patterns, X-acto knife, enough wood, instructions \$1.00, "Old Whittler", 1402 Charles St., La Crosse, Wisconsin.

LAWN ornaments, novelties, patterns: samples 25c; assortment \$1.00. L. Bazuin, Grand Rapids 3, Mich.

PLASTICS—Secret formula, instructions.
Perfect castings at home. No equipment,
experience. \$1. Torrey, 93 Federal, Boston.

WHITTLE for profit, Pattern's, Instructions, 10 saleable subjects, 25c, Whittlers Studio, 96 Park Place, St. Paul, Minnesota.

MAKE miniature music box radio, Plans and instructions 25c. Richy, 1508 Monroe St. N. E., Minneapolis, Minnesota.

80 PATTERNS, 40 Lawn Ornaments, 20 Novelty, 20 Silhouette, \$1.00. Modern Woodcraft, Saginaw, Michigan.

1000 TELUHOW Plans tell homeworkers about building 1000 projects. Lists 10c. C. King, E. Kingston, N. H.

# INFORMATION

A CONTACT service for use in the exchange of articles, or correspondents, job hunting, help seeking, business, hobbies. Inexpensive, Interesting, Profitable, Write for forms and information. Fanl, Box 1710, Greensboro, North Carolina.

RESEARCH: Congressional Library, Government Bureaus, etc. Questions, literary or scientific investigations, genealogy, business errands, attended by experts. Valuable circular, 10c. Crehore, Box 2329-Y, Washington 13, D. C.

AMATEUR—radio technical questions answered \$1.00. Box 802 B, R.R. No. 10. Ferguson 21, Mo.

# INVENTIONS WANTED

INVENTORS—The Lion Manufacturing Corporation of Chicago, a highly rated concern employing 1,400 people, is interested in inventions for their plant and affiliated companies. Our interest is in patented or patentable electrical or mechanical devices for post-war development in the following fields: Radio and Television, Sound and Recording, Household Appliances, Vending Machines, Coin Operated Amusement Devices, in fact almost anything of metal or plastic. We invite inventors to send us details concerning their patented inventions. If your invention is not patented, tell us in a general way what you have to offer. If we are interested, we shall inform you how to communicate details without endangering your rights. Lion Manufacturing Corp., 135 S. LaSalle St., Dept. H., Chicago 3, Illinois.

MANUFACTURERS actually seeking inventions call on one, and only one, organization to study complete new patents comprehensively. We, alone, are industrially sponsored for this job; relied upon by manufacturers for hundreds of reports weekly; strategically "inside" to help you—Invention, Munsey Building, Washington 4, D. C.

ALL Kinds: We have facilities and finances to make and sell your ideas, both mechanical and chemical. Send model, sample details and wishes. General Sales & Supply Company, 110 East Main Street, Madison 3, Wisconsin.

INVENTORS: Have you a sound, practical invention for sale, patented or unpatented? If so, write Chartered Institute of American Inventors, Dept. 3-C, Washington, D. C.

WANTED—Patented, unpatented inventions having profit possibilities, all kinds. If will sell, reply immediately. Descriptive booklet, references, free. Invention Reporter, 3B-11106 S. Fairfield, Chicago.

MANUFACTURER wants sensible mechanical device or idea with quick sales possibilities in low-priced field. Write Matt, 1412-C Great Northern Bldg., Chicago A.

INVENTORS: Learn how we sell your invention. Free Booklet. Inventors Patent Exchange, 336-D Palace Building, Hartford 3, Conn.

YOUR Invention presented to our clients free. Send description only. Zigrand Manufacturers Service, 506 Home, Trenton 10, N. J.

CASH for Inventions—Patented, unpatented, Mr. Ball, BC-9441 Pleasant, Chicago.

INVENTIONS Promoted, Patented or Unpatented. Write Adam Fisher Company, 183-A Enright. St. Louis, Mo.

ANYTHING in building or contracting industry. Nabert Building Corp., 145 Bellevue, Elizabeth, N. J.

INVENTORS! Have you good patentable idea? Write Mr. Metzleer, 11 West 42nd New York.

WANTED—patented items for manufacture on royalty basis. Decker Manufacturing Co., Rockford, Illinois.

## JEWELRY

MEXICAN and Cuban products, perfumes, jewelry, silver lighter bracelets and identification bracelets, eight dollars money orders include wholesale prices. Jose Cohen, San Juan de Letran 6, Mexico City.

# LANGUAGE OUTFITS

29 LANGUAGES by Linguaphone, Russian, Spanish, Portuguese—Direct conversational method for mastering any language quickly, easily, correctly at home, Send for free book, Linguaphone Institute, 54 RCA Bldg., New York, CI 7-0830.

# LEGAL DIRECTORY

PUZZLED? Digest of Divorce Laws of every state in country \$1,00. Liberty Co., 1265 Beacon St., Brookline, Mass.

MEXICAN Law Practice, A. B. Flota, Box 240, Juarez, Mexico,

# MACHINERY, TOOLS & SUPPLIES

BRINKS Bargain Bulletin, "Money Savers" & "Inbetween" carry 50 to 100 pages, each, of auction bargains in tools, machines and supplies for all shops, private, commercial & hobby. New and Used Army and Navy surplus equipment, walkietalkie, jeeps, wireless sets, household and office equipment. Wall and sign operating clocks. Free valuable premiums with all books on trades, arts and sciences. Postal brings full details. H. A. Brinkerhoff, Inc., 37 Walker Street, New York City.

CONSTRUCT Your Own machine tools from Lewis Castings, Materials and Blueprints, supplied complete at a fraction of new tool cost, Mills, Shapers, Vises, Band Saws, Jointers, etc., are ideal for a whole range of home or commercial shop work. Send 10c to cover mailing of Catalog listing 23 items, Lewis Machine Tool Co., Box 116, Station A. Dept. S-50, Los Angeles 31, California.

INDEX—Heads for sale, Very inexpensive, Sixty-two different divisions, Used on small lathes, drill press, milling machines etc. Make gears, hobbs, cutters, etc. Very accurate, and durable. Not a toy. Used by defense schools and hobbyists. Write for free folder, Long's Index Heads, 2117 East B St., Torrington, Wyo.

DRILL GRINDER—Grinds drills to factory accuracy. Calipers with direct reading scales. Circle cutters. New Tool grinder. Lowest prices. Free literature. Factory. 811-A East 31st, Kansas City 3, Mo.

STEEL beam trammels for draftsmen, engineers, mechanics. Circular Free. Clair Company, Box 92, Blythebourne Station, Brooklyn N. Y.

NU-WAY Speed Reducer-For Electric Motors, Drills. Circular Free. Dealers Wanted. Tractor-Lite Mfg. Co., Spirit Lake, Iowa.

THE Shebel Filer files all saws. Send for circular. A. P. Shebel, 730D S. Second Street, Milwaukee 4, Wisconsin.

## MAGIC TRICKS, PUZZLES, JOKER NOVELTIES

"I BETCHA"—Collection of over 100 amazing secret stunts, clever gags you can do. Win free meals, drinks, used by actors, sportsmen, magicians, gamblers. New exclusive just published \$1.00 postpaid. Interstate Company, Box 190, Ft. Worth 1, Texas.

TRICKY Match Box, it turns around! It stands up! And it opens, most weird, uncanny magic novelty trick, Complete ready to do. 25c, The Magician, 2463-K. Kensington Ave., Philadelphia, Pennsylvania.

500 TRICKS you can do! Douglas' famous Catalog of 500 Tricks, now only 10 cents. America's fastest service on magic for pocket, parlor, stage, professional, amateur, Douglas' Magicland, Dallas, Texas.

MAGIC Is Fun! Send \$2.00 for apparatus to perform 10 different, startling tricks. Guaranteed \$5.00 value! Free, with your order, book of "102 Tricks". Robbins Co., 152-S West 42nd St., New York.

PUT on a magic show after the first three lessons. Learn professional magic by mail. \$1.00 per lesson. All apparatus furnished with each lesson. Ree, Box 93, College Park Station, Detroit, Mich.

WORLD'S largest professional magic shop keeps you in touch with latest tricks. To receive mailings send 25c for 1945 catalog. Holdens, P-220 W. 42nd St., New York.

MAGICIANS', Gamblers' secrets exposed. Cards, Dice, Punchboards, Slot Machine. catalog of latest tricks, 25c. Ireland,

BE a Mathematical Wizard. Send for "Magic in Numbers"—amazing new book of tricks with figures. 25c coin. Alta Company. Box 1109. Pasadena, California.

84 CARD Tricks and our latest catalog of Magic Tricks only 25c. Ball Square Company, Dept. 11A, 697 Broadway, Somerville 44. Mass.

JOKERS' Snake matches—10c. Foolem red snapper—20c. Coin on String Escape— 30c. Enteco, 2592 Creston Ave., New York

ASTOUNDING! Blindfolded you reveal cards mentally selected by three spectators! Send quarter! Sieg. Mertke, 3477 Clark, Chicago.

NEW Magic and Fun Magazine 15c. Prize contest. Free Luck piece. Phoebus 945-C Chancellor, Irvington 11, N. J.

BE a Magician. Large professional magic catalog of latest tricks. 25c. Ireland, F-109 North Dearborn, Chicago.

TRICKS, Secrets, cards, punchboards, etc. explained. Big illustrated circular free. Mack, Box 1278-P. San Francisco.

6 SECRET Tricks and clever novelty 10c. Victor Jones, Parma, Missouri.

NEW 1945 Magic catalogue Free. Magic Shop, Minneapolis 2, Minn.

FUN Magic Mystery. Free details. Dickerson Printing Co., Gas City, Indiana.

# MANUFACTURING

MODELS, small lot manufacturing, metals, plastics, etc. Milburn, Burlington, Kentucky.

MANUFACTURING Models. Tools. Gears, Machine Parts. Baums Metal Specialties, Kansas City, Mo.

# MILK GOATS

FREE: Postcard request brings you book about dairy goats and sample monthly magazine. (Subscription \$1 yearly). Dairy Goat Journal, Dept. 568, Columbia, Mo.

# MILITARY INSIGNIA

SILK Embroidered Emblems. Sample and price lists 10c. New Insignia Guide 10c. Insignia made to order. Hobbyguild, X35 West 32nd St., New York.

FOREIGN decoration ribbons, insignia, lists, sample 20c. Insigniacraft, 236-28 Ave., N. W., Calgary, Canada.

# MINERALS & PRECIOUS STONES

347 ANTIQUE Firearms; 4,000 Bargains, Coins, Indian Relics, Minerals, Cartridges, Rifles, Flintlocks, Fossils, Swords. Catalog with Photographs 20c. Museum, Wenona, Ill.

GEMS, precious and semi-precious, all genuine, from world wide sources. Deal direct, no overhead, save money. Catalog 10c. Hill Co., Route 7-K, Salem, Oregon. "GENUINE" Arizona Rubies (Garnets).
Send Quarter for Packet. Mineral Specimens, Box 2651, Phoenix, Arizona.

# MISCELLANEOUS

ARMY GOODS (USED)

JEEP Hats and Caps 10c, cups 15c, Leggings, bayonet scabbards, 25c each; Messkits 35c, canteens, cartridge Belts, Haversacks, Holsters, Leather or canvas straps, gallon metal cans, polished instrument box 50c each, Raincoats, Ponchos Canvas Bunk bottoms 2'x7', steel Helmets, periscopes and bag, canvas bags, decorating flags, life preservers, aluminum Tool boxes, \$1 each; Fire hose 5c per ft. Canvas covers any size 5c per ft. Rubber any size or thickness 20c per lb. Pup tents \$2.50. Squad tents \$17.50. Minimum shipment \$1. Via Railway Express, N. Y. Salvage Co., 144 Chambers St., New York City.

BUY cigars direct from distributor. Box of 50 regular 15c size Tampa hand made cigars only \$6.75. Send check, money order today. Include 15c handling charge. Special No Risk Guarantee Offer—smoke 2 or 3 cigars at our risk. If not satisfied return balance and money cheerfully refunded. Tampa Quality Cigar Co., 5014 Suwanee Ave., P.O. Box 1836, Dept. B-1, Tampa 3, Florida.

GOOD "Used" self-instruction educational books on all subjects bought, sold, rented, exchanged. Satisfaction guaranteed. Complete information and 92-page illustrated bargain catalog Free. Write—Nelson Company. Dept. 2-01-2, Chicago 4.

MAKE your own glow in the dark articles.
Sell at big profit or keep for your pleasure. Use Lite-Glo—magic new discovery!
Hundreds of uses, Complete Lite-Glo kit \$1.00. Cash or C.O.D. Lite-Glo, 1412-(B), Seward, Topeka, Kansas.

MEDICAL Laboratory Technicians in great demand. We train you in your spare time, in your own home. You can practice while studying. Write for free catalogue. Imperial Technical Institute, Box 973-S, Austin 5, Texas.

FREE, fertile South-American lands! Fifty acre homesteads or 25,000 acre livestock ranches obtainable free. Valuable illustrated information, 25c. Vallesm, 395-MJ Broadway, New York 13.

FOXHOLE radio:—amazing serviceman's pastime gift batteryless, tubeless, school-boy thrill, made anywhere, anybody, Easy distance-getting instruction, \$2.00, Gadgets, Box 28 Jackson Heights, N. Y.

347 ANTIQUE Firearms; 4,000 Bargains, Coins, Indian Relics, Minerals, Cartridges, Rifles, Flintlocks, Fossils, Swords, Catalog with Photographs 20c, Museum, Wenona, Ill.

KEEP Eggs fresh 6-12 months without ice or mechanical refrigeration. Complete instructions \$1.00. Mandrake Company, 1412-E Great Northern Bldg., Chicago 4.

RECEIVE Moneymaking opportunities, mails, samples, magazines, Your name in several mailing lists, 10c, Rodgowski, 3415 Broadway, New York 31.

BUY Vitamins Direct—Save. Quality meets and exceeds U. S. standards. Free Folders, Thompson Laboratories, Dept.-A, 4524 Milford, Detroit 19, Mich.

MEXICAN-Aztec featherwork tropical bird picture cards, samples 25c, bulletin free. Mexican Products Co., 126 N. Main, Tulsa 3, Okla.

WHOLESALE List of Unusual tropical merchandise and sample 25c. Barrington Smith Co., Halfwaytree—10, Jamaica, B. W. I.

JAPANESE Contour map of eastern Attu Island. Real souvenir photostatic copies of original 14x18 inches mailed anywhere for \$5.00. Mont Reneau, Elkton, Ky.

SQUARE Dance Instructions, calls, 25 dances, \$1.00. Ozarkians, Lonsdale, Arkansas.

DAUBER and shoe shine cloth 10c postpaid. Essential Products Co., Williamsburg 3, Mo.

ALARM CLOCKS—repaired, bought, any condition. Felker, Box 21, Wilmette, Illinois.

RUBBER Moulds, stamp brings literature. Eastern Latex Laboratories, Box 153, Mattapan 26, Mass.

FREE literature how to locate buried treasure and minerals. Fisher Laboratory, Palo Alto, Calif. MONSTER mail, magazine, adsheets, circulars, opportunities, 10c, Harvey Teeple, Decatur, Indians.

RECEIVE mails, literature, opportunities. Your name in numerous mailing lists 10c. Greenwood, 277 Broadway, New York. GENUINE Italian spaghetti and ravioli sauce. Formula \$1.00, Gossander brand.

Pio Bendinelli, Box 411/2, Stevensville, Mich. PIN-UPS-All kinds. Write Novelty Stu-dios, 301D Eldred, Battle Creek 21,

INFORMATION—Locating products (wholesale) etc. Rakes, Box 5931, Chicago 80, Illinois.

FOX-HOLE-Handle removable clampon, for container, tincan, Sample 15c 2—25c. Herr Mfgs., Collinsville, Illinois.

PICTURE Painted from Photograph, Paul Fortner, Box 42, Montezuma, Indiana.

UNUSUAL Novelties, samples 10c, Modern, Box 2, Station B, New York 2.

TAILORED Homes—the modern plan book. Ad under heading BluePrints.

100 NEW YORK postcard views \$1.10. Dixie, 101 Lexington Ave., New York City. CALIFORNIA Beer Seed start package \$1.00. Calvin L. Perkins, Mathiston, Miss. FREE Drug Catalog! Druggist Z. Robins. 24 S. Hamlin, Chicago 24, Illinois

## MODELS & MODEL SUPPLIES

SHIP model kits and fittings. Complete line Fisher model yacht equipment. All Boucher, Fisher, Marine Model and Ideal Kits, fittings and blueprints at standard prices. Most complete stock in New England, James Bliss & Co., Inc., 220 State St., Boston, Mass.

BUILD The Famous P. T. Boat. A model of 80 feet of fighting fury. Most au-thentic model kit on market. 130 precision. true-to-scale parts, ready to assemble. No tools needed. Descriptive folder free, Cre-ative Crafts, Winnetka 6, Illinois.

ILLUSTRATED Catalog over 100 models, Castings and Blue Prints. Steam and Gasoline Engines, Locomotives, 10c post-paid, Active Products & Supply Co., 53 W. Jackson. Chicago 4.

PLANES, Boats, Hundreds of Hobby Items 40 page Catalog free. America's Hobby Center, Dept. S35, 40 E. 21 St., New York 10, New York.

MOST complete Illustrated Catalog—"O-HO OO" Model Railroad Parts ever published, Send 5c for mailing, Selly, 1377 Gates Ave., Dept. 815, Brooklyn, N. Y.

WORLDS largest selection model engine castings and drawings. Catalogue 10c, Wayne Miller, Suite 201, Engineering Wayne Miller, Bldg., Chicago 6,

RAILWAY Models, complete line, informative catalog HO and O Gauge 79 pages 15c. Walthers, 269 Erie, Milwaukee, Wisconsin.

MANUFACTURING dies stampings brass gears and model supplies. Send 10c for catalog. Pierce Model Works, Tinley Park, Illinois.

SHIP Model and yacht supplies, complete large 64 page Catalogue, 25c, Wm. Wild, 510 E, 11th St., New York City.

CASTINGS, blueprints for model steam engines. Circular 10c. Anton Bohaboy, 2297 Price St., Rahway, N. J.

CASH for Model Airplane Engines, Cal-row, 593 N. Snelling, St. Paul 4, Minn.

# MONEY MAKING OPPORTUNITIES

MANUFACTURER of art novelties will train ambitious men and women at small cost desiring to establish themselves in highly profitable business with splendid post war future. Easily learned. No ex-pensive equipment needed. Any community big profits. Mr. Merriman secured his first \$500.00 order eight weeks after writing us. Plastex Products, 332 Balboa, San Francisco 18, Cal.

MECHANICALLY Inclined Men—Own and operate general Appliance Repair shop, Complete, illustrated course shows you how, Welding, Refrigeration, Motor repair, How to get business, etc., all phases covered. Free literature, Christy Supply, Dept. 1449, 2835 N. Central Ave., Chicago.

PLASTICS—Learn to work with Lucite and Plexiglas. It's fascinating. It's profitable. Simplified course of instruction. Postpaid \$1.00. Materials available. Price list free. Dept. 14. California Plastic Fabricating Institute, 629 W. 9th St., Los Angeles (15), Canf.

FREE yourself from money worries. Be independent. Increase your earnings. Book, "Help Yourself To Postwar Prosperity" shows you how. Limited Supply. Get it now. Only \$1.00. National Business Bureau. Department A4, Box 5374, Chicago 7. Illinois.

ELECTRIC Clocks are every where you go. buildings, homes, parking-lots, factories, Repairs increasing. Our easy to learn course with pictures and drawings teach You how to repair these clocks. Electronic Supply Co., Box 2350-B, Houston 1, Texas.

LEARN Metascience, Remarkable drugless healing. No manipulation. No apparatus. Unbelievable simplicity and results. Inexpensive correspondence course. Write Metascience, De Land, Florida.

SCHOOL Seniors! A postal will bring you our Kwick-Sell Cardalog of graduation name cards. Hot selling everywhere! Big profits! Hurry! Craftcards, Box 235(AC). Pittsburgh 30, Pennsylvania.

\$100-A-MONTH hobby at home! soliciting, no mail order, no meeting people, Easy, enjoyable pastime. Details, 25c. (Refundable.) Laura Dickson, 359 Main Bldg, Lander College, Greenwood, S. C.

PRIZE Contest Fans Can Win A For-tune! Free announcement service! Good news for untalented contestants! Write today! National Contest Bulletin, Box 634-M, Grand Central Station, New York City,

GIANT big mail! Hundreds of money making propositions, home work offers, in-cluding big magazine, all for a dime. Gar-denville Publishers, Gardenville 12, N. Y.

MORE Money outdoors-backyard or small plot. Book of many plans that work, only \$1. Details free. Waterman, Bridgman, Michigan.

EARN money at home! Thousands do!
"Home Worker Magazine" tells how.
Sample, 25c. Sizemore, Box 6, 4917 North
Kostner, Chicago.

'MAIL Order Trade Directory" Tells you where to buy wholesale. Send 25c for latest 1945 Edition. Walters, 2639 Station C. Philadelphia, Pennsylvania.

START Now-build money making mail order business. Get yourself established. Actual examples explained. Particulars Free. Young's Industries, Kent 16, Ohio.

YOU CAN win thousands of dollars in contests. Proof. 10c brings exclusive par-ticulars. Lawrence, 4627-S Fernhill Rd., Philadelphia 44, Penna.

DETECTIVES Earn Big Money, Experience unnecessary. Particulars free, Wagoner, P-125 West 66th, N. Y., N. Y.

WANT to make \$100 weekly? No foolin'. Write Wilkin, 1348-P N. High, Hillsboro,

INFORMATION—Locating most any article, (Dime), Rakes, Box 5931-E, Chicago 80.

OPERATE your own mail order business at home. Details free, George V. Beach, 79 Essex St., Springfield, Massachusetts,

FREE samples—special offers—fine opportunities 10c. Sullivan, 61-49 56th St., Maspeth, L. I.

"VARIOUS Opportunity Catalog", Copy 10c. P. O. Box 1735, San Diego 12, Cali-

WANT financial independence? I've helped thousands. Free information. Thompson, Dept. A. 4524 Milford, Detroit 10, Mich.

MAKE fast repeat selling products at home without machinery. Large profits. Ps. Kohn, 506 W. 45th, Chicago 9.

INSECT Spray: Profitable seller; Directions, concentrate: Kaplan, 13 S. Eden, Baltimore 31.

CATALOG, opens way to profit and pleasure, 10c. Barcus, 1003 N. 13th, Terre Haute, Indiana.

EARN money evenings, copying and duplicating comic cartoons for advertisers. Comic-Ads, Argyle, Wisconsin,

FREE literature describing many money making plans. Abbot, Box 44, 210 5th making plans. Abbot Ave., New York City 10.

CASH without canvassing, 10 cents, Poul-sen & Company, Zion, Illinois,

MAKE Money—Have fun! "Tattooing". Steele, 626-B W. 17th, Los Angeles.

300 WAYS to make money, 25c. Success, Box 932-T, Birmingham, Ala,

WANT to make \$5000 yearly? No bunk: Publications, Bethany 5, Okla.

## MONUMENTS

WRITE For Direct Prices \$14.00 Up. Freight Paid, Guaranteed, Free Catalog. Granite-Marble Factory, A49, Oneco, Fla.

# MOTION PICTURE & SOUND EQUIPMENT

GUARANTEED fresh movie film! Three spools double 8mm, \$3.45! Six spools single 8 mm for Univex cameras, \$3.50! (Limit six spools each type.) Processing free! Will ship C.O.D. on \$1.00 deposit. State make of camera. Eso-S. 4038 Broadway, Kansas City 2, Missouri.

UNUSUAL glamour, travel movies, Many in color, "Allure", black-white, 8mm., \$2.00; 16mm., \$4.00. Experimenters, try projecting black-white films in natural color. Iriscope kit, \$5.00. Lists, sample, dime. Jenkins, 392-A, Elmira, N. Y.

SENSATIONAL Girl Film, 1945 release ready. Kodachrome, black and white 8mm, 16mm, Sample and catalog, 10c. Iriscope kit for showing black and white in color, \$5.00. Ray Vater, 201 A, Elmira,

BETTERPIX outdoor safety film, 100' 16mm, \$2.50, 25' double 8mm, \$1.25. Free Developing, Finished subjects sold, Exchanged. Sound Library, Better Films 742 New Lots, Brooklyn 7, N. Y.

LOOK! "The World's Greatest Passion Play", 8mm, 16mm, 35mm, Specify Sound or Silent, Rent or Purchase. Hem-enway Pilm Co., 33-Z Melrose St., Bos-ton 16, Mass.

TREMENDOUS Savings, Join original movie guild, Application blank, Big 1945 movie catalog that's different sample dime. Trans-American Sales, Morristown, New Jersey.

8-16mm SILENT-sound films. Complete rental library, All latest subjects, Free catalogue, (sample film 10c). Garden Film, 317 W. 50th, New York 19.

GORGEOUS Girls—Sparkling, Adventure. Sports, Comedy, Travel film. Equipment. Big 1945 Catalog and sample 10c. Audet, Box 6520-AG. Philadelphia 38, Pa.

8MM-16MM FILMS, Bought-Sold-Ex-changed, Complete 360' sound subjects \$5.75, Lists (Sample film 10c), Internation-al-S, 2120 Strauss, Brooklyn, New York.

100' 16mm, USED sound film, \$1.00 post-paid, We buy, sell, trade, List of com-plete subjects upon request, Blackhawk Films, Dept. PS16, Davenport, Iowa.

BRAND new 8mm Comedies 180 ft. \$3.95. 16mm 8mm Films Bought, Sold, Ex-changed, Film Exchange, 1472 Broadway, N. Y. 18.

LEARN Movie Projection, Management, Free catalog, Give age, Theatre School, Elmira, N. Y.

GLAMOUR Girls, Sample, Dime, Zientek, 1129 Monroe Circle, Baltimore 25, Mary-

FINEST Movie Screens. Inexpensive. Make them yourself. Free literature. Snow White Screen Company, Danville, Illinois.

(WE buy motion picture films and equip-ment). Paramount Film Service, Mon-mouth, Illinois.

USED 16mm sound film, Bargain price \$3.00 per 400 foot reel. Jack Curry, 919 N. 6th St., Phoenix, Arizona.

SALE-Rent 8—16mm Films, Catalogues 10c. Don Elder's, 739-B Boylston, Bos-

BUY-Swap-Rent-Sell 8mm. movie films. Harvey Iris, Box 539. Brockton, Mass.

"LOVE & ONIONS", a first class musical comedie in 16mm sound, 725 ft. \$29.50. Cope, 5869 South Figueroa, Los Angeles 3.

8MM AND 16mm Castle Films for sale. Catalogue free. Write, Peck Film Ex-change, Box 50, Yoakum, Texas.

MOVIE projectors bought and sold, List 10c. United, 2309-D, Lawrence, Toledo, O.

FREE 1945 Movie Catalog; samples 10c. Goodwill Company, Jackson, Tennessee.

SEND stamp for 16mm, 8mm catalogue. Sterling's, 679 Northampton, Easton, Pa.

SALE-rent-exchange-8-16mm movies. Send stamp for catalogue. Bailey Films, Box 2528, Hollywood 28, California.

# MOTORCYCLES, BICYCLES & SUPPLIES

PARTS accessories pistons chain Harley Davidson Motorcycles. McCann's, P.O. Box 114, El Paso, Texas.

FLOYD Clymer's Motorcycling Manual, 144 pages, 120 illustrations, Complete information, specifications, descriptions dozens motorcycles. Engines, transmissions, carburetors, square four, two piston singles, sleeve valve engines, overhead camshafts, water cooled motorcycles, spring frames, hydraulic forks, sidecars, riding instructions, Two cycle engines and power bicycles described, illustrated, Just out, \$2.00 postpaid, Clymer, 2125 W. Pico, Los Angeles 6, Calif.

CUSHMAN Motorscooters \$45; Motorized bikes as low as \$30; motors \$5 up; plenty non-rationed 10, 12, 14 inch balloon tires \$1.75 to \$6.50; (mailorder only). Send 25c for big War-Bargain catalogue No. 6 listing hundreds of bargains in midget cars, motorscooters, motorcycles, motors, parts, etc. (35c by first class mail). Midget Motors Directory, Athens, Ohio.

WHEELS, Tires, and Tubes for Motor Scooters, Midget Cars, Wheelbarrows, and other Industrial equipment. All sizes, Also Bicycle Parts and accessories. Largest stock in United States, Send dime for list. Cycle Transport Company, 1241 S. Michigan Ave., Dept. C, Chicago 5, Illinois,

FLOYD Clymer's Historical Motor Scrapbook \$1.50 Postpaid. This is the book Time Magazine said is a "must". 250 early motorcycles, automobiles illustrated, described. See our advertisements under Automobiles, Clymer, 2125 W. Pico, Los Angeles 6, Calif.

MOTORCYCLE Books—Speed and How to Obtain It \$1.50. Motorcycling Manual \$2.00. English Motorcycle Service Manual \$1.50. One Man Caravan \$3.00. Clymer's Motor Scrapbook \$1.50. All Postpaid. We mail overseas. Clymer, 2125 W. Pico, Los Angeles 6, Calif.

BUILD America's lowest priced motorscooter Speedster. Complete plans and specifications, \$1.00. Big list bargain priced used tires, motors, parts, included free! Motor Supply, Box CS-1682, Toledo, Ohio.

PROFESSIONAL Midget racers, motorscooters, midget cars, parts, Handbook catalog—50 illustrations, plans—25c. Directory bargain priced used tires, motors, parts, included free! Mid-West, 2557 Charlestown, Toledo, Ohio.

MOTORBIKE Manual containing easy to read Motorbike and scooter plans, helpful hints and catalog section \$1.00. Variety Enterprise Company, Station A, Box 5, Evansville, Ind,

PLANS, scale drawings, specifications, illustrations for building attractive Motor Scooter complete \$2.00; plans electrically driven bicycle \$1.50 postpaid. Clymer, 2125 W. Pico, Los Angeles 6, Calif.

MOTORCYCLE Muffler. Steel Packed. beautiful tone, seamless streamline design, \$6.00. Really beauties. Sandee Muffler Co., 7523 S. Western Ave., Los Angeles 44. Calif.

SEND 25c for complete motorbike plans and parts list. Motorbike Service, 2108 McLean, New Albany, Indiana.

# MUSIC. MUSICAL INSTRUMENTS

PIANISTS — Quickly improve technique, sightreading, accuracy, memorizing, playing through Mental-Muscular Coordination. Free Bocklet. Broadwell Studios. Dept. 95C. Covina, California.

SONGWRITERS: Send Poems for Free Examination, Write for free Instructive Booklet Outlining Opportunities, United Music Corporation, Salem, Indiana.

HARMONIZE your best melodies. Get that tune down quickly. Chart and shorthand \$1. Paul Stackpole, 2110 W. Venango, Philadelphia 40, Penna.

VIOLIN "Stradivarizing Plan." \$1.00. Guaranteed! Patmor (Tonepost) Fiddlery Zion, Illinois.

PLAY Swing Piano! Send 10c for instruction bulletin. Christensen Studios, 765 Kimball Hall, Chicago 4, Ill.

POPULAR Piano in 12 lessons. Beginners or advanced guaranteed. Kelly School, 1734 30th Ave., San Francisco, Calif.

MUSIC Composed, Music Printed. Reginald Belcher, Chatham, New Jersey, Established 1910.

MUSIC Printing \$5-100, Composing, arranging, Auto Litho Co., Jensen, Fla.

MAKE your violin. Everything furnished. Fraser, 2025 Stark, Saginaw, Mich.

## OLD GOLD, WATCHES

GOLD \$35.00 Ounce—Mail old gold teeth, diamonds, jeweiry, watches—receive cash by return mail. Satisfaction guaranteed. Free information. Dr. Weisberg's Gold Refining Company, 1500-B Hennepin, Minneapolis, Minn.

# OLD STAMPS WANTED

I WILL pay \$100.00 each for 1924 ic green Franklin stamps, rotary perforated eleven (up to \$1,000.00 each unused). Send 6c today for large illustrated folder showing amazing prices paid. Vernon Baker, PS-53, Elyria, Ohio.

WHAT have you to offer? A collection? A "Shoe Box" accumulation? Anything in stamps. We urgently need them, Spot cash paid, Cosmopolitan Stamp Co., 1457 Broadway (Times Square), New York.

# PATENT ATTORNEYS

INVENTORS: Learn now—without obligation—how to protect and sell your invention. Write for free "Record of Invention" form and complete instructions for making disclosure and establishing date of your invention. We also send our new free "Patent Guide for the Inventor," containing complete information about patent procedure and how to sell inventions; giving illustrations of many successful inventions; over 150 basic mechanical movements. We assure you prompt, confidential service. Delays may be dangerous, Write today for your free "Patent Guide" and "Record of Invention" form, Clarence A. O'Brien & Harvey Jacobson, Registered Patent Attorneys, 52B-C Adams Building, Washington, D. C.

WHAT Should You Invent? Our Free Book tells you what today's inventive market wants—how to put down, patent, and sell your ideas. Scores of letters in our files attest to the modern demand for inventions—our long experience as Registered Patent Attorneys will help you. Get our Free Book, "How to Protect, Finance and Sell Your Invention." Also special document free. "Invention Record" on which to sketch and describe your invention. Write today. No obligation. McMorrow & Berman, Patent Attorneys, 143-G Atlantic Building, Washington 4, D. C.

INVENTORS: Before disclosing your invention to anyone send for Form "Evidence of Conception"; "Schedule of Government and Attorney's Fees" and instructions. Sent free, Lancaster, Allwine & Rommel, Registered Patent Attorney, 413 Bowen Building, Washington 5, D. C.

PATENTS Secured. Two valuable booklets.

"Patent Protection" and "When and How to Sell an Invention", together with valuable "Evidence of Invention" form sent free. Write immediately to experienced patent counselors. Victor J. Evans & Co., 941-C Merlin Bldg., Washington, D. C.

PATENTS—Trade marks. Preliminary advice, book and disclosure form free. Personal service. Irving L. McCathran, 316 McLachlen Bldg., Washington 1, D. C. Registered Patent Attorney.

PROTECT your invention through medium of my expert personal service. Preliminary information without obligation. Horace L. Beall. 902 F Street, N.W. 4, Washington, D. C.

"INVENTOR'S GUIDE" free, containing 100 mechanical movements, information about patenting, selling inventions, Frank B. Ledermann, 154 Nassau St., New York 7.

C. A. Snow & Cc., S-427 Snow Bldg., Washington 1, D. C. Registered Patent Attorneys, Established 1875, Literature mailed on request.

PATENT Protection. Write for information. Fees. Record of Invention. Free. Randolph & Beavers, 340-A Columbian Bldg., Washington, D. C.

PATENT-Particulars and blanks, free, airmailed. Sterling Buck, P-637 North Ave., Baltimore 17, Md. Government—Registered 38 years.

PATENTS Obtained; selling service, information, recording forms free, Labiner, World Building, New York 7.

# PATENTS

INVENTORS — Foresighted manufacturers already planning post-war sale of new non-military products. If you have a useful invention, patented or unpatented, write Chartered Institute of American Inventors, Dept. 3-B. Washington, D. C.

MANUFACTURERS actually seeking . . . .
See Invention's advertisement under "Inventions Wanted."

## PERSONAL

LONELY—? Independent Club. Descriptions. Photos, particulars (10c) None Free. Big lists. Single Men-Women. State your age. Join now. Jack P. Painter, Box 966-S, Akron 9, Ohio.

IF you sincerely seek a life mate, of the opposite sex, for future married happiness we can help you. Years of honest service have shown sensational, proven results. Confidential, prompt, courteous. All ages, all religions. Personal introductions. Lifetime service. Descriptions, photos, particulars 10c. S. Benko, 246 Fifth Ave., New York 1.

BE Lonely No More! Open Destiny's Door! 50c Brings Cupid's Destiny. World's Greatest Social Publication, including nationwide names, addresses; either sex. Captivating descriptions; sparkling pictures—widows, widowers, bachelors, beautiful girls desiring early marriage, Mention your age, Destiny League, Aberdeen 75, Wash.

PHOTOSTAT Copies made of letters, legal documents, music, etc., worth preserving against loss or destruction. Our certified copies are legal evidence in court. 75c first copy 25c each additional copy. Insured. Daily mail service. Hollywood Photocopy Service, 1606 Cahuenga Boulevard, Hollywood, California.

SLEEP tight with Sleep-Rite soft waxen ear-stoppers.—that stop noise. Four months supply \$1.00. Guaranteed. Sample 10c. At leading druggists. Accepted American Medical Association. Free "Proof". Raymond Dow. 17 Park Row (1216AC). New York 7.

THIS is Hot. Look Americans. The Salvador Mendez 1945 Original National Vacation Exchange, 43-Simon Ave., Lackawanna, N. Y., will save you up to 50% on your present and postwar vacations. This plan and registration fee cost you only 50c in coin. Join now.

PSORIASIS Sufferers: Pixacol has brought relief when everything else failed. Use only as directed. Apply externally, dries quickly, convenient, Try regular \$1 bottle without investing a cent! Write: Pixacol Lab., Box 3583, Cleveland, Ohio.

BLUE? Lonely? No Dates? Cheer Up! This "Introduction by Letter" service can bring you undreamed of returns in a new pattern of life. (Strictly confidential.) The Friendship Letter Society. Lock Box 430-PS. Springfield, Missouri.

DISCOVER I.Q., special abilities, personality strengths. Take simple tests mailed you. Psychologists (Ph.D.) advise suitable jobs, schools, courses. Occupational Analysis Clinic, 52-N Lincoln, Highland Park, N. J.

SENSATIONAL offer. Beautiful Genuine Leather Wallet with 8 card windows and your name engraved in 23 karat gold all for \$1.00 plus postage. Guaranteed. Yorker Mig. Co., 24 Bond St., N. Y. C.

GET Acquainted Club—Through social correspondence thousands yearly meet their "ideal", Write for list of eligibles, Many in your State, Simpson, Box 1251, Denver, Colorado.

WIDOW and Widowers Club. (Confidential details 25c.) Write John Rankin, Springfield, Missouri.

LEARN characters at a glance! Know friends! Enemies! Sweetheart! Employers and employees need this. Scientific Proven System. Information Free. Acme. Dept. A, 6302 30th St., Detroit, Mich.

CONSTIPATED? Try "Herbalene". Works while you sleep. Produces quick safe results. Free Sample. Delfa Co., 3960 Avondale, Chicago 41.

SEE your name in newspaper headlines. Startle your friends. Fun Galore. Free Details. Write—Horne, Box 372M, Back Bay Annex, Boston 17, Mass.

FIND worthwhile dignified correspondents, set of long descriptions and confidential details 25c coin. Dept. PS-502, 6816 Navigation, Houston 11, Texas.

PIMPLES Facial Eruptions Removed Quickly, Amazing Practical Method 25c. National Research, 70 Howard Street, West Asheville, N. C.

VITAL, personal facts every man and woman after forty should know. Send only \$2.00. Modo Publishers, 752-R Northwest 66th Street, Miami 38, Florida, MAKE new friends thru old reliable club.

Free book with photos of members.

Correspondence confidential. Exchange
Company, 3827-PS Main, Kansas City, Mo.

LONELY, Have friends, romance, compan-

ionship thru correspondence. Sealed particulars Free. Lillie Smith, Box 2732, Kansas City 13, Missouri.

PSORIASIS. Dry Eczema! Rush name for amazing facts, special no risk offer. Carter-Howell Laboratory, 457 Schenectady Avenue, Dept. M-9, Brooklyn 3, N. Y.

PIMPLES, acne disappear. Clear your complexion. Write today! Immediately. Healthmaster, Dept. B-5, 1441 Prospect Pl., Brooklyn 13, New York.

PIMPLES disappear overnight. I tried everything till I found this Formula. Make it yourself \$1.00. Morean. Box 243. Lowell, Mass.

MAKE Friends, banish loneliness, through this delightfully different, unique, correspondence circle. Sealed details free. Gotham Circle, 152-F W. 42nd, New York 18, FORBIDDEN Knowledge revealed—Occult Catalogue Free Charms, Talismans, Lucky pieces, numbers, curios, Karma, P.O. Box 823, Imperial Beach, California.

LONESOME? Join World's Greatest Social Directory. Photos, Descriptions, Quicker Results; Stamp. Excel, 2149 Jackson, Chicago 12, Ill.

HYPNOTISM, Complete 20 Method Course, 25c. Western Institute Hypnotism D-1619, Palatine, Ill.

LEARN Ventriloquism, 3c stamp brings particulars. Smith, Dept. 218, 801 Bigelow, Peoria, Illinois.

YOU'LL Have penpals worldover. Illustrated Magazine with list 10c. World Card Club. King. North Carolina.

Club in West. Endorsed by ministers. Club Elite, Box 71, Los Angeles 53.

GIRL photos, spicy but beautiful, \$1.00 for group, "Little Eve," Box 211, Terre Haute, Indiana.

"BUYING Bloomers," lusty spicy hot, talkie comedy story, \$1.00 Postpaid, "Little Eve," Box 211, Terre Haute, Indiana, HEALTH, Prosperity, Happiness, Information free, Joseph Louis Schertz, 5338

Bartmer Avenue, St. Louis 12, Missouri.

MEET new friends in an interesting way.

Write the Country Club, 126 Lexington

Write the Country Club, 126 Lexington Avenue, New York 16, N. Y.

NEW scientific discovery makes new men and women. Literature \$1.00. Healthotel, South Whitley, Indiana.

LONESOME? Write to Broadway Friendship Club, 1472 Broadway, New York City for correspondence, friends, marriage.

ATHLETE'S foot remedy, Guaranteed, \$1.00 bottle postpaid, Dr. W. J. Renz, Rm. 3, Chavanne Bldg., Lake Charles, La, LONESOME? Descriptions and details. Members everywhere. Acme Club, Box

4255, Portland 8, Oregon.

LONELY? Charming persons await you.

Magazine Free. Romance-21, Portland, Me.

HAIR Falling? Dandruff? Write Tricholo-

gist, 139 Lewis Street, Phillipsburg, N. J.
BUY Vitamins direct. Save. Postcard. Matoska Products, White Bear Lake, Minn.

"SPIRITUAL Help for Your Everyday Problems"—25c. Box 2501, Los Angeles. DANIEL Williamson—Please advise address and plans. Parents and sisters.

SECURE Future. Information 10c. T. Smith, 1102 Highland, Beloit, Wis.

# PHOTO FINISHING

sensational introductory offer! Send snapshot or negative, this ad. and 3c. We'll send you a beautiful 7"x5" enlargement and free snapshot folder! Reprints—from your negatives, 16 regular-size or 8 Double-Size reprints, 25c. Candid rolls—36 exp. 35mm developed, vaporated, enlarged to 3x4, \$1.00! 18 exp. 60c. Reprints, 3x4, 3c each. We have new, perfect 35mm film. Low prices. Free Mailers, details on request. American Studios, Dept. 265, La-Crosse, Wis.

BIGGEST \$1.00 value in 35mm finishing today, 36 exposure fine grain 3\\\4x4\\\2\ell\_

BEAUTIFUL double size Pictures 3½c each, from 116 and 120 negatives, 3½4x4½ from all other sizes, All work guaranteed. Overnight service. Roll developed and 8 pictures 30c. Roll 12 pictures 45c. Roll 16 pictures 60c. Enlargements on double weight portrait paper 5x7—30c, 8x10—50c. Copies made from any picture 75c, Pacific Photo Service, Box 666, San Francisco, California.

OIL coloring photographs a fascinating hobby or profitable business. Learn at home. Easy simplified method. Previous experience unnecessary. Send for free information and requirements. National Photo Coloring School, 1315 Michigan, Dept. 1721, Chicago.

YOUR 6-8 Exposure Roll Developed and Two prints each good negative 30c: Or enlarged to about Post Card size 8 Exposures 25c, 12 Exposures 40c, 16 Exposures 50c, Rapid Poto Service, G.P.O. Box 413, New York 1, N, Y.

ROLL Developed and 8 beautiful enlargements 2 to 6 times larger. Deckled Edge—High Gloss, Any 8 exposure roll 25c coin, 12 ex. 35c—16 ex. 50c—36 ex. \$1.00. Reprint Enlargements 3c each. Alden Photos, 94-4 Astor Station, Boston 23, Mass.

SATISFACTION or your money back 2 regular size prints from each good negative on 8 exposure roll complete 25 cents or 8 jumbo size prints complete 30c. The Old Reliable. Pioneer Photo Company. Box 123-PS. Wichita, Kansas.

PHOTOGRAPHIC Statuettes. Pastest, easiest selling novelty on the market. Service Men, girls, any subject. From negatives or prints. No investment. Samples supplied. Barkuettes, Box 60, Waverly Station, Baltimore 18, Md.

EVERY picture an enlargement! 8 sparkling deckle-edge Enlargements and roll developed 25c coin; 116 size or smaller; enlarge reprints 3c. Enlarge Photo, Box 791Q, Boston, Mass.

100 MINIATURES \$1.00-134"x74"—made from photograph gummed, perforated, for stationery etc. Lang, 1334 Thorndale, Chicago.

PHOTOSTAMPS picture yourself on postage stamps, 1½c each, send for free samples. Arteraft Photo Co., 1600 Coney Island Ave., Brooklyn 30, N. Y.

INTRODUCTORY Offer—Six enlargements from your favorite negative, 25c. Skyland Studies, Box 411, Dept. "ES", Asheville, N. C.

CONFIDENTIAL developing. Two prints each negative 25c. Reprints 2c. Royal Photos. 1718 N. Sixth, Harrisburg, Penna. 25 REPRINTS 50c; Suburban Studio, PS-3, 1410 Bond, Rockford, Illinois.

# PLASTICS

PLASTIC Manufacturer wants small worthwhile toy, household, gardening, fishing inventions for Postwar molding on royalty basis. Send descriptive drawings to Samuel Nissley, 1161 N. Fifth West, Provo, Utah.

PLEXIGLAS catalin lucite assortment lb. package, dollar, instructions included. "Homecrafters," 31 Duke, Toronto, Canada.

# POULTRY & SUPPLIES

YOUR greatest poultry problem will look simple when you read American Poultry Journal regularly. 500,000 poultrymen do, why not you? Only 25c year, 5tyears \$1.00. American Poultry Journal, 532 South Clark, Chicago.

AS Modern as Temorrow—A must today— Try my system in everlasting Poultry Profits. 35 years of perpetual successes guarantees results. Money back! 50c postpaid. Lewis System (Agriculture Engineer) 273 Windsor St., Hartford 5, Conn.

RAISE turkeys the new way, write for free information explaining how to make up to \$3000.00 in your own backyard, address National Turkey Institute, Dept. 57, Columbus, Kansas,

EXPERIMENTAL Farm money-making helps on poultry raising yours for five years only \$1.00; two years, 50c. Ordenow! Poultry Tribune, Dept. 31, Mount Morris, Ill.

## PRINTING, MULTIGRAPHING, MIMEOGRAPHING, LABELS

QUALITY Printing. Lowest Prices!! Shop Orders, Shipping Tags, Automobile Forms, Noteheads, Duplicate Forms, Statements, Invoices, Time Cards, Manifold Books, Ruled Forms, etc. State requirements. Printing Service, 7922 S. Vermont Ave., Los Angeles 44, Calif, "PRINTOMATIC" Self-feeding Rotary Stencil Post Card Printer, \$9.50 Complete. All Makes Duplicator Supplies, Literature Free, Pittsburgh Typewriter Supply, 336-MA Fourth Avenue, Pittsburgh 22, Pa.

200 LETTERHEADS, 100 envelopes, Monarch size, printed with your name and address; \$1.50 postpaid in U. S. Golden State Stationers, 4171-A W. Second St., Los Angeles 4, Calif.

MIMEOGRAPHING and Multigraphing, 14
years of fine work and fair prices. Free
samples and prices, J. Allsmith, 1500 W.
Nedro Ave., Philadelphia 41, Pennsylvania.
\$2.00 POSTPAID; 150 8½x11 Good Bond
Letterheads and 150 6¾ Envelopes, 500
of each \$5.75 postpaid, Mero Products,
Box 344, Punxsutawney, Pennsylvania.

PRINTING of distinction at really reasonable prices. Samples, helpful suggestions and estimates gladly sent. State needs. Edgewood Press, Edgewood, Maryland.

LOW cost high speed precision printing. Letterheads-envelopes. Illustrated or plain. Samples free, Production Printers, Dept. B., Middleburgh, New York.

STENCILLESS! "Redigraph Duplicator" \$19.50. Circular 3c. Felker, Box 21, Wilmette, Illinois.

200-812x11 LETTERHEADS \$1.00 postpaid. Envelopes, Invoices, Cards same. Fletcher, 8708 Grand Ave., Elmhurst, N. Y. PERSONAL Post Cards—Blue or Buff 80

for \$1.00, Art Letter Service, Box 3311, Barnum Station, Bridgeport, Conn. SPECIAL—200 each; letterheads, enve-

lopes, billheads, cards \$4.00. Economic Press, Leonia 1, New Jersey. 500 ENVELOPES, \$3.00 Postpaid. Business. Personal Stationery. Mario Giglio, 441

Perry, Pontiac 16, Michigan.

EMBOSSED business cards 1,000 \$2.25
C.O.D. Spada, 10 Lexington, Wethers-

field 9, Conn.

MIMEOGRAPHING: Circulars, postcards, business size. Bonin, 21 High, Paw-

tucket, Rhode Island. 400 512x812 LETTERHEADS \$1.25, Mango, 555 S. 20th, Newark 3, N. J.

DISTINCTIVE Printing reasonably priced.
Free samples. Cramer. Box 993, Chicago.

ZINC etchings from your copy 50c postpald. Econoprint, Kokomo, Indiana.

PRINTING, instruction books, labels,
forms, stationery, Box 466, Clinton, Iowa,

PRINTING OUTFITS & SUPPLIES

PRINTING equipment, type and supplies. Send stamp for details or dime for com-

plete illustrated supply book, Kelsey Inc. X-8. Meriden, Conn. INEXPENSIVE home-made printing press.

Details free, Novelty Shop, Downsville, Louislana, MAKE your own Plastoplate printing cuts,

Simple, easy, economical.—Adayservice, Argyle, Wisconsin.

PRINTING Presses, Type, Supplies, Lists 3c, Turnbaugh Service, Loysville, Pa. PRESSES, Type, Supplies, Specimens, 3c, La Garza, 8 Walden, Cambridge, Mass.

# PROFITABLE OCCUPATIONS

ANNOUNCING home study course in commercial baking. Practical basic training. Good field for those with aptitude. Nearly depression proof. Send for free booklet. "Opportunities in the Baking Industry." National Baking School, 1315 Michigan Ave., Dept. 1729, Chicago 5, Ill.

MECHANICALLY Inclined Men—Own and operate general Appliance Repair shop. Complete, illustrated course shows you how. Welding, Refrigeration, Motor repair. How to get business, etc., all phases covered. Free literature. Christy Supply, Dept. 1049, 2835 N. Central Ave., Chicago.

LOCKSMITHING—Profitable Business or Hobby! New course teaches you how to pick locks, fit keys, de-code, masterkey, etc. Easy self-instruction lessons, Bargain price. Free details, Write—Nelson Company, Dept. 7-01, Chicago 4.

ELECTRICAL Appliance Repair. Open your own shop. Learn house wiring: electric motors, vacuum cleaners, washers, etc. Complete illustrated course shows how, Free booklet. Pacific Training School, Dept. 3-AS, 4703 West Pico, Los Angeles 6.

PAINTING flagpoles pays up to \$50.00 a day. To get into this extremely profitable profession send post card or letter for full particulars to—The Skyline Co. of America, P.O. Box 1601-A, Uniontown, Pa.

A LOCOMOTIVE Engineer or Railroad Conductor is interesting work, Information on how to obtain these positions 50c. The Student Railroader, Box 53, Elmhurst, Illinois.

\$5000 FROM Half Acre! Growing Ginseng. Seed, contract supplied, Particulars 10c. Associated Growers, Dept, 12, St. Norbert, Manitoba.

HOMEWORKERS, make, sell, shell novelties. Beginners Samples, instructions, \$1.00. Temple, 224-6th Ave. S., St. Petersburg, Fla.

\$40.00 WEEKLY, Made growing mushrooms, Fresh, Dried, Dominion Patent 331583, free spawn, North American, 169Y Yonge, Toronto, Canada.

PLASTIC Costume Jewelry made at home. Profits Good. Outfit and instructions \$2.00 postpaid. Kosto, 707 20th N.W., Washington 6, D. C., Dept. 2.

EXCEPTIONAL profits raising mink, Finest breeding stock available. Details furnished, Franklin Young, Riverhead, Long Island, New York.

MUSHROOMS grown in boxes, Instructions 50c. Spawn \$1.00, Gordon, 553 William, Winnipeg, Manitoba.

"SUCCESSFUL Red - Worm Raising!" (Copyrighted) \$1.00. Peoria Worm Ranch, Peoria, Illinois.

SIMPLIFIED chemical gardening Instructions 50c. Chemicals \$1.00. Gordon, 553 William, Winnipeg, Canada.

\$2500 YEAR in backyard. Treatise 10c. Moyer, B-252-C, Milton, Pa.

"IF It's Wealth You Desire"-Write OBA, Box 2501, Los Angeles.

# RADIOS, SUPPLIES & INSTRUCTION

HEAD Phones: Latest Type—Light Weight,
Finest Quality, with plug for tuning in
on radio, or intercommunication system.
Also adaptable for use in making a razor
blade or crystal set. Head Phones: (No
head band slightly used) \$1.25; Head
Phones: (No head band—New) \$1.75;
Head Phones: (With leather covered adjustable head bands—slightly used) \$2.50;
Head Phones: (With leather covered adjustable head bands—New) \$3.75; Plus
\$.25 for shipping charges—send Money
Order, Quantity Limited, Nico Supply
Company, 540 N. 17th St., Philadelphia
30, Pa.

YOUR New Free Catalog is Ready! Radionic's Catalog No. 26 lists hard-to-get radio parts. All available for immediate shipment. Send today to: Radionic Equipment Co., Dept. 3C; 170 Nassau St., New York 7, N. Y.

CRYSTAL Radio operates loudspeaker, instructions 25c. Sensitive crystals, Silverite, Goldite, Galena, 25c each. Scientific tuning-coils, 35c. World's Simplest single tube diagrams, 25c. Hulet, 29 E. 39th, New York.

RADIO Service men and experimenters send for our giant radio catalogue. Save dollars, United Radio Co., (1000-V), Newark, N. J.

MAKE Simple, tubeless, batteryless, distance-getting crystal radios, crystal and illustrated instructions, 25c postpaid, Allen, S-427, Clinton, Missouri.

REVISED Plans 18 Crystal Sets (SW record 5300 miles), including "Radiobuilder"—25c. Laboratories, 363-T Hampton, Hayward, California,

RADIO parts, latest, Experimenter's Kit \$3, value \$15. Many Bargains, List on request, Radioco, 1110s Marshall Bldg., Cleveland, Ohio.

LOWEST Prices, Radio Tubes, parts, Bargain lists 3c, Potter, 1314 McGee, Kansas City 6, Missouri,

BUILD improved, extra-loud crystal set. Instructions, data, 20c. Amorose, Rt. 4, Hungary Road, Richmond, Virginia.

ELECTRONIC Organ easily constructed from Radio parts. Plans \$1.00. Quacker Radio, Box 68, Salem, Ohio.

REPAIR 50L6, 3525, 12SA7, 2525, etc. Radio Tubes, Plans \$1.00-no C.O.D. Globe Radio, 2911 Elm, Dallas 1, Texas.

TUBELESS Radio made with razor blades! Complete Plans 35c, N.W.C. Radio, Lohrville 2, Iowa,

"BUILD a radio, complete kit with tubes, \$9.95, details," Radio, 9418C Ave. "A", Brooklyn, New York.

TELEPATHY'S Radio \$2. Exoteric, 2926 Nameoki, Granite City, Ill.

## RAZOR BLADES

100 DOUBLE-EDGE blue surgical steel razor blades \$1.50 prepaid, Fully guaranteed, St. Moritz Blade Co., 321 Broadway, Dept. AD, New York 7.

80 HIGH-Quality double-edge razor blades postpaid \$1.00. Special introductory offer 25 for 27c postage stamps. Neeto, 72 Gay St., Asheville, North Carolina.

## RUBBER STAMPS

SERVICEMEN'S Clothes Marking set.
Black ink set \$1.25. Black & White ink
set \$1.75 with name or number. Dept. P.,
National Rubber Stamps Works, Inc., 7 E,
48th St., New York 17, New York.

SELF-INKING Pocket Stamps—2 lines \$1.00; 3 lines \$1.25; Dater 50c, Postpaid. Circular free. Press, Warm Springs 1, Georgia.

RUBBER Stamps 25c per line. Laundry Stamps \$1.00. Pocket \$1.00. Interesting Books, circulars. Parcel Press, 53 Astor Sta., Boston, Mass.

YOUR name, address on DeLuxe cushion mount rubber stamp \$1.00—Pad 25c. Postpaid, Cash with order, Edgewood Press, Edgewood, Maryland,

1 LINE 40c, 2 lines 65c, 3 lines 85c, each additional line 20c. Blythe Rubber Stamp Co., Indianapolis 6, Indiana.

3 LINE Rubber Stamp and inked pad \$1.00, postpaid. Ideal Rubber Stamp Co., Box 83, Detroit 8, Mich.

SERVICEMEN'S Kit contains stamp, ink Pad, Indelible Ink \$1.20. Excello, Box 500, Shreveport, Louisiana.

KNOB handle cushioned, 2 lines 30c, 3—40c. Rubber Stamps, Centerport, New York.

3 LINES 35c. Signatures \$1.50, Pads 25c. Printrite, Wauwatosa, Wisconsin.

CUSHIONED, 3 lines 50c, pocket \$1.25, Federich Mfg., East Pittsburgh, Pa.

# SONGWRITERS

SONGWRITERS: Collaborate with nationally famous composer of "Boots and Saddles". Send poems for free examination. Get Free instructive booklet. Hollywood Harmony House, 126 S. La Brea, Studio L-1, Los Angeles. California.

MELODIES Written and Arranged for your Lyrics. Complete Arranging, Scoring and Copying Service. Analysis Report and Suggestions \$2.00 per song or Lyric. Workmanship Guaranteed. Tommy Kilbourne, Box 1253. Bakersfield, Calif.

PUBLISHERS-Recorders—Notice? A Real War Song For Sale. Address: Bob Carleton, Hollywood Studio, Hollywood, Calif. (28) Writer of "Jarra" title "It's The Army."

NEW songs and lyrics wanted for popular radio program and professional promotion. Free examination. Transradio Music Inc., Department P.S., 1650 Broadway, New York (affiliate of B.M.I.)

POEMS Wanted for Musical Setting, Send poem for immediate consideration. Five Star Music Masters, 646 Beacon Building, Boston.

POEMS Wanted to be set to music, Free examination, Send poems, McNeil, Master of Music, 510-PS S. Alexandria, Los Angeles, California,

SONGWRITERS—Send Poem For Immediate Examination and Free Rhyming Dictionary. Richard Brothers, 46 Woods Building, Chicago.

SONGWRITERS: Send Poems for Free Examination. Write for Free Instructive Booklet Outlining Opportunities. United Music Corporation, Salem, Indiana.

SONGWRITERS—Free booklet "Getting Ahead In Songwriting", Write today, Song Service, 331-J West 46th, New York,

SONGWRITERS—Melody, lyrics or idea made into complete professional song— \$3.00. Sholl, 2222 5th St., Harrisburg, Pa.

WANTED! Lyrics, melodies for songs, We arrange, publish, sell, Superior Song Studios, Passaic, N. J.

SONGWRITERS: Royalty Contract Free. Write for details, Puritan Publishing Co., 343 S. Dearborn St., Chicago 4, Illinois.

SONGWRITERS send for our Publishing Agreement. Mid-West Music Press, 4737 Broadway, Chicago 40.

ATTRACTIVE Publishing Offer, Newart Song Publications, 1300 Lodi, Syracuse 8, N. Y. OUTSTANDING Songwriting Service, Barnhart, 1320 48th, Des Moines 11, Iowa, SONGWRITERS! Amazing offer, Hibbeler, C-15, 2157 N, Avers, Chicago 47.

MUSIC to words. Dot Publishers, Affiliate B.M.I., 3581 Milwaukee, Chicago, 41.

# SPORTING GOODS, GUNS, FISHING TACKLE, ARCHERY

GUNS Refinished Like New by factory methods, as used by leading gun manufacturers. Send for circular. Middletown Metal Finishing Company, 55 River Road, Middletown, Conn.

BOWS-Arrows for Recreation-Hunting-Fishing, Beautiful Archery instruction book, 70 pages, 50 illustrations, only 50c, Illustrated catalogue Free, Archery Sales-Service, 617 South State, Chicago.

LEARN Gunsmithing at home, Earn money repairing neighborhood's firearms. 25 firearm and gunsmithing textbooks, catalog for 3c stamp, Samworth, Plantersville, South Carolina.

347 ANTIQUE Firearms; 4.000 Bargains, Coins, Indian Relics, Minerals, Cartridges, Rifles, Flintlocks, Fossils, Swords, Catalog with Photographs 20c. Museum, Wenona, Ill.

USED Guns, Binoculars, bought, traded, sold, Ammunition bought, Highest Cash Prices Paid, Stoeger Arms Corp., 507 Fifth Ave., New York, N. Y.

ARCHERY Equipment: Catalogue Free. Mid-West Archery, 2209-D East 75th, Chicago 49.

YOU have the gun—we have the buyer! Latest catalog 10c. Segal's Gunhouse, 752-C Northwest 66th St., Miami 38, Fla.

GUN Cabinets built to order, literature 25c. Woodcrafts, 411 Madison, Wilmington, Delaware.

THOUSAND Bargains, firearms, binoculars, war relics, catalog 30c, Smith Museum, Runnemede, N. J.

"AMMUNITION" Available to qualified purchasers. List 10c. Rudolph's, Atchison, Kansas.

SEND 10c for list 100 used guns. Frayseths. Wilmar, Minnesota.

FAMOUS Mississippi catfish bait formula, 25c. Geo. Thomas, Mankato, Minnesota.

USED guns, bought, sold, exchanged. List stamp. Howe. Coopers Mills, Maine.

# STAMP COLLECTING

1944 REVIEWED in our 599 Different Suggestive Values: Italy's Surrender, vivid Mussolini Issues; Red Army takes Kiev, Soviet Set; Teheran Conference, wonderful British, U. S. and Russian Assortment; Marshall Islands invaded, U. S. Commemoratives; Cassino falls, Fighting French; Capitulation, Romanian Airmails; Rome liberated, Religious Issues: D-Day Invasion, French Commemoratives; Robot Bombs, recent British; Patton Sweep starts, colorful European; Paris liberated, Paris Herald: MacArthur Returns, historical Phillippines; Aachen falls, Swastika Commemorative; Grecian Uprising, Charity Set and even 1944's Wallis-Putuna New Mint deGaulle Issue cataloguing \$12.39 to new approval applicants only \$1.00. Intercity Co., Dept. Y, Port Washington, N. Y.

SPECIAL Album Free—The United States Flag Series for twelve overrun Nations is the most unique, remarkable, impressive, and beautiful set of stamps ever issued. It fairly cries for a special album worthy of it, such as we have published. It's a very fine album of 34 pages. Cover designed by a famous artist. Arrangement artistic and practical, telling the history of each honored nation.—It is Free to sincere approval applicants. Just send 10c for mailing expenses, and state whether you desire approvals of the United States or foreign stamps or both. Approval Headquarters, Globus Stamp Co., 268 Fourth Ave., New York City 10, Dept. 217.

WOW! \$10.00 Worth of Fun for only 10cl 500 Foreign Stamps, unsorted and unpicked (mostly on bits of paper) just as received from the church missions and other sources, Africa, So. America, Australia, China, Philippines, Dutch Indies, and other countries are represented. Includes a few commemoratives, airmails, and stamps cataloguing up to 25c or more each! The biggest Package of Fun in Stampdom—and you might find something really valuable! Price only 10c to serious approval applicants! Money back if not delighted, Jamestown Stamp Co., Dept. No. 5, Jamestown, New York,

ZOWIE-E-E! A Barrel of Fun for only a Dime! 500 United States—Absolutely unpicked and unsorted—just as received from church missions. Many varieties, including large commemoratives airmails, high denominations up to \$5.00! Stampdom's biggest package of fun—and you might find something really valuable!! Price only 10c to serious approval service applicants. Money back if not delighted. Illustrated bargain lists with each order. Mystic Stamp Company, Department 55, Camden, New York.

SCARCE Grenada Bicolored Silver Jubilee stamp, MacArthur stamp from Australia, Abyssinian Wild Elephant issue, plus host of others from New Caledonia, Indo-China, Russia, Cuba, Wallis & Futuna, Dutch Indies, China, Philippines, etc., only 5c to approval applicants, Big Dime Packet List free! Methuen Stamp Service, Inc., Dept. 46, Lawrence, Mass.

POSITIVELY Greatest Free Offer—Latest Scott's International \$5.00 Stamp Album—covering entire World, contains 36,000 illustrated, descriptive spaces; Scott's 1945 Standard \$5.00 Catalogues "Philately's Encyclopedia"—absolutely Free to applicants for Foreign Approvals becoming customers. Bargain Stamp Service. Palm Springs, California.

FREE! The Stamp Finder! Send today for big new edition, fully illustrated, enabling you instantly to identify all difficult stamps! Also fine packet strange, fascinating stamps from Bosnia-Herzegovina, Monaco, Patiala, Cyprus, etc., including maps, ships, animals and strange scenes. All free to approval applicants inclosing 3c postage, Garcelon Stamp Co., Box 918, Calais, Maine.

EXTRAORDINARY Pictorial Collection:

Nigeria—Southern Rhodesia—Dutch Indies—Martinique—Newfoundland—Philippines—Porto Rico—St. Pierre and Miquelon—Dlibouti—Senegal—Ceylon—Jugoslavia—Ivory Coast—Madagascar—Reunion—Wallis and Futuna, Everything only 5c, Imperial Company, Box 311, Yonkers 1, N. Y.

FREE—Pick 25c worth of stamps from our first U.S. Approval Selection . . . Approximately 100 stamps to choose from . . . Excellent value . . . No obligation to buy. Lists illustrating the most popular U.S. stamps—at prices you can afford—will be included. Don't miss this opportunity! Write today. S. D. Engel Co., 38 Park Row. New York City.

FREE! Leeward Is., Cayman Is., Turks and Calcos plus 60 different mint Geo. VI Coronation poster stamps, to approval service applicants sending 3c postage, Tatham Stampco., Springfield 50, Mass.

UNITED STATES \$15.00 catalog value special 88c . . . 25 different stamps mostly defect. Guaranteed genuine. Good space fillers . . . Adult approval applicants. Merritt Brundige, 369 State St., Albany 6, New York.

VICTORY Packet Free: Includes stamps from Tanganyika—British Cayman Islands — Animal — Scarce Babyhead — Coronation — Early Victorian — Airmail —Map Stamps—with Blg Catalogue—all free—send 5c for postage. Gray Stamp Company, Dept. PR, Toronto, Canada.

KNOCKOUT Offer! Cuban Health victory set with high valued Mexican set plus 5 rare commemoratives, pictorials, airmails. Also contests held in which thousands of stamps, items given away. Send 5c, approvals included. Gem Stamp Co., 2985 W. 31 St., Brooklyn 24, N. Y.

GENEROUS Packet with Africa, Asia, British Colonies, Free French, Portuguese Colonies, Latin American and 100 different others. Everything only 10c to approval applicants. Beeken, 13814 Gallagher, Detroit 12, Mich.

WORLD'S Largest Diamond And Triangle Stamps, Free Stamp Magazine, Stamps from Fighting Free French, 20 stamps from 20 different Countries. Pictorials, Airmalis. Big Bargain 5c with approvals, Capital Stamps, Dept. 10, Little Rock, Ark.

SMOKY Mountain commemorative sheet, largest U. S. stamp issued, and 33 U. S. including commemoratives, airmail revenues, etc. Catalogs 75c—To approval applicants for Sc. Curhan Stamp Company, Dept. C. Gloucester, Mass. 114 DIFFERENT stamps from far away countries including Airmail and Free Fighting French to approval applicants for 10c. Reich Stamp Co., 4647 Kenmore, Chicago 40, Dept. S9.

SPECIAL—Airmails—21 different, including Zeppelin, Triangles, Latin America, etc. 5c with approvals. Continental Stamp Co., Box 606, Dept. C, New Rochelle, New York.

BRITISH Empire Collection! Burma, Cyprus, Gwalior, Sarawak, Tasmania; Also 50 other British, Only 5c with Pictorial and Commemorative Approvals, Lyman, 97 Nassau, New York City.

118 DIFFERENT stamps including commemoratives, charities, airmail, sets, etc. Only 3c to approval buyers. We buy collections. Badger Stamp Co., Milwaukee 3, Wisconsin.

SCARCE 1880 U. S.—Hussey Local Carrier Stamp listed at 15c, Also Costarica No. 65 listed at 40c, Both sent free to approval buyers sending 3c postage, Pladon Stamps, 1717-S Idaho, Toledo 5, Ohio.

FINE Approvals, freshly mounted. Fast, personal service. Tell me what countries you prefer and I'll send their stamps. Milton Skinner, 345 East Ocean, Long Beach 2, Calif.

EXCELLENT stamps on approval! We will send stamps of the countries you ask for! Beautiful foreign approvals as well as choice U. S.! John R. Nabholtz, 6683 Lakewood Blvd., Dallas, 14, Texas.

COLORFUL, interesting stamps make enjoyable collections and provide good conversation. Write for clean, honest approvals connected with good premium. John Stamp Co., Box 2612, Detroit 31, Mich.

TRIANGLES — Mozambique Airmail-commemoratives; British Empire commemoratives; U.S. higher values. Bonanza lot, 10c, approvals accompany. Reuter, 611-D W. 40th, Los Angeles 37.

UNITED STATES and Foreign Stamps Packet—Includes Airmails, Commemoratives, Pictorials—3c. Approvals, Smith, 237-F 8th Avenue, Roselle, N. J.

FREE—Your choice any 10 stamps from our first U. S. approval selection. Illustrated list included. Cosmopolitan Stamp Co., 1457 Broadway, Dept. F. New York.

POUND Unpicked U. S. and foreign mixture containing thousands stamps \$1.00, 5 lbs. only \$4.50, Longacre Shop, 100-C West 42nd, New York City.

FREE—Canadian Sets. Royal Visit, George VI, George V, Coronation, Jubilee, others, to approval applicants, Ensign, Box 118-P, So, Orange, N, J.

FREE! Complete "United States" stamp catalog with 1,000 illustrations! Send 10c to cover mailing, Harris & Co., 99 Transit Building, Boston, Mass,

TURKS Caicos, Grenada, Seychelles, Dominica, Caymans; everything 3c with approvals, Viking, 130 (P) Clinton St., Brooklyn, N. Y.

50 DIFFERENT including scarce airmail triangle. 3c to approval service applicants. Avalon Stamp Co., Dept. S, Springfield 8, Mass.

U. S.'s largest Stamp! S.P.A. Sheet 5c to approval applicants. Superb! Guaranteed! Popular Stampdea, 114-P North Hagerstown, Maryland.

60 DIFFERENT United States, Includes commemoratives, higher values, airmail, 10c, Charles Stone, 3547 28th St., Astoria I. N. Y.

EXCHANGE your duplicates with collectors everywhere. Stamp brings particulars. Kurtz, Box 1051, Allentown, Pennsylvania.

UNITED STATES approvals complete coverage fine quality, attractive prices, Seminole Stamps, Box 436, Coconut Grove, Florida.

FREE! 25c worth of stamps from our first foreign approval selection. Beaumont Stamp Exchange, 2667 McFaddin, Beaumont, Texas.

"THE Best"—United States and Philippine Islands Approvals, Largest varieties, America's lowest selling prices. Stamp Company, Albany, New York.

RARE Dollar value! With complete Canadian Set, Free to approval customers. Large foreign selections. Vogel, 5174 Lakeshore, Port Huron, Michigan.

BEAUTIFUL Panama "Flag Stamp" Free with purchase from our Beginners, Approvals. Suburban Stamp Sales, 1224 Grant Dr., St. Louis 14, Mo. FREE—World's only Octagonal (eightsided) stamp and 70 year old Turkey set to Approval Applicants. Charles Cleaveland, 806 North Humphrey, Oak Park, Illinois.

FREE package stamps to Approval applicants using Modern and International Jr. Albums. Johnson Stamp Co., Box 111, Hermosa Beach, California.

19TH Century U.S. Commems., Civil War Revenues. Battleships, \$5, \$10 Stamps Free to U.S. Approval Applicants. Metropolitan Stamps, 198-G Broadway, New York.

UNITED STATES Mint. No. 319, No. 481, No. 498, No. 552, No. 611, No. 545, No. 680, No. 690, Send 50c. Approvals Accompany, Whiton-Stamps, Norwalk 1, Conn. LATIN America—65 different including pictorials, commemoratives, airmails only 10c with approvals. "Crescent Stamps", London, Canada.

POSITIVELY free! Scott's latest \$5.00 International Stamp Album or 1945 Catalogue to approval customers. Claire's, 7402 Bayparkway, Brooklyn 4, New York.

FREE, 30 Different including Coassack Diamond, 12 stamp Triangle, Gobi, others. Approvals included. Send 3c postage. Pilgram, Waverly-18, Baltimore, Md.

UNITED STATES and Foreign Approvals. Fine Quality, Attractive Prices, Kenneth Archibald, 40 Railroad Avenue, Taunton, Massachusetts.

3 DIAMOND shaped Costa Rica Airs for 3 cents postage to approval applicants. Magnolia Stamp Company, Box 3097, Miami, Florida.

PINE old 19th Century U. S. Cover only 10 cents to applicants for approvals, Detroit Stamp, 10304 Dexter, Detroit 6, Michigan,

CANADIAN 150 different \$3.00, 100 different \$1.00, 50 different 20c, 25 different 05c, R. Archambault, Box 51, Station 'N', Montreal, Canada.

UNITED STATES approvals exclusively!
Attractively priced. Return postage paid.
Atwater, P.O. Box 1583S, Miami 35,
Florida.

CANADA War set 10 var. pictorials 10c with interesting approvals. Rheaume, 8949 Routhier, Montreal 12, Canada.

WORTHWHILE Premiums to serious collectors requesting approvals. Harold Bayles, Groton, Conn.

100 STAMPS 10c Approval Applicants. Morris Stamp Company, Box 74, Rock-away, N. J.
STAMP Collections, 1999 different \$2.75.

STAMP Collections, 1000 different \$2.75; 2000 different \$6.50, Ransom, 1333 Pontlac, Ann Arbor, Mich.

U. S. STAMP mixture, 100 lbs. \$18.00; 50 lbs. \$9.50; 25 lbs. \$5.00, S. Parkey, 2328 Harrison Ave., Detroit 16, Michigan.

STAMPS sent on approval outstanding quality low prices. Fred Herzberg, P-2 168 Oak, Elmhurst, Ill.

105 VARIETIES including strange Russian, Estonian Revenues, 5c. Approvals. Rex, 39 Blackstone, Bangor, Maine.

FRESHLY mounted approvals for general collectors. Phoenix Stamp Co., Dept. 3-H, 120 West 44th, New York.

25 DIFF. Finland 8c with 14-12-1c approvals. Carroll's, 745 C.W. 45th, Los Angeles 37, California.

DEALER'S Wholesale Catalog, Postage 3c. Franksco, 5031 Queensberry, Baltimore, Maryland.

55 DIFFERENT United States 5c with Approvals, Bookman, Box 145-P, Maplewood, N. J.

EXCELLENT Pictorial approvals, Reasonably priced, Crown Stamp Company, Box 331, Toronto, Canada,

STOP-Want something different and unusual in approvals? Kirklands, 7212 Farwell, Chicago 31, Illinois.

FREE! Complete Balkan aviation set with approvals. Beaman, Glenburnie 10, Maryland.

CARAMBA! Gorgeous Gilberts, Oddish Solomons—3c with approvals! Saxon, Valley Stream, N. Y.

FREE! Approval applicants select 10c worth Free—Your choice, Excel Stamp Service, Box 1315, Chicago 90.

APPROVALS that you will like, at fair prices. H. Edward Hefflon, St. Albans, Vermont.

1,000 GRABBAGS, 15c each. Special Bags 25c. Sandy, 630 Bingaman, Reading, Pennsylvania. 60 DIFFERENT United States, incl. Commemoratives, 10c. Pricelist free. Seidenberg, Baroda, Michigan.

TWENTY desirable foreign commemora-tives only 5c. Ridgeway, 316 57th St., Brooklyn 20, New York.

FREE 50 different stamps to approval applicants enclosing 3c postage, Mangels, 194-13B 111th Rd., St. Albans 12, N. Y.

SPAIN-Five large airmails. Send 10c. Approvals. Buchanan, 307 E. 23rd, New York 10.

FIFTY Stamps from fifty different coun-tries 10c. Garrow, 851 West 177th, New

EIGHT attractive airmails 3c, with ap-provals and lists, Gaydos, Kenosha, Wisconsin.

35 DIFFERENT U. S. free to approval applicants. Kinsley, 5812 63rd, Riverdale. Maryland,

FRENCH COLONIES! Given! Beautiful set for 6c postage with approvals. Jayhawk Stamp Co. Box 348, Fort Scott, Kansas.

SPECTACULAR approval service for collectors using International Junior or Modern albums, Philatelist, Aberdeen, Md.

FREE!! Sensationally interesting, money saving stamp magazine, Loewy, Aberdeen, Maryland.

LIFETIME subscription 25c! Philatelic Shopping News, 2660PS Rochester, Detroit 6, Mich.

MAGAZINE — Year subscription 20c! "Stamp Post" Station A, Pasadena 3, Calif.

100 DIFFERENT United States and Canada also Covers, Packets, and Surprise. \$1.00. Universal, 2239 Kimball, Chicago 47.

FREE! Stamp wallet, sincere approval buy-ers. Thiese, 9320 San Juan Ave., South Gate, California.

FREE Triangle Airmail with approvals. Monjar, 1750 Fairmount, Cincinnati, O.

URUGUAY packet 3c with approvals, Ephriam, 914 Sherman, Evanston, Ill.

1000 MIXED U. S. Old and New 25c. 2 lbs. \$1.00. Weatherby, Medina, Ohio.

FREE! Complete Cuba tobacco set with approvals. Seminole Glen Burnie 10, Md.

BRAZIL diamond shaped set 10c with approvals. Vargo Stamps, Racine, Wisc.

ŪNITED STATES Stamps on approvals— wide selections—Box 488A. Minneapolis.

50 Different U. S. and foreign stamps 10c. Box 799, Lenoir, N. C.

LOOK! 50 different countries-10c. Box 6618, Northeast, Kansas City, Mo.

STAMPS from 40 countries 10c. No approvals. Elzea, Bowling Green, Ohio.

POSTALLY used British Colonies on approval. Schustamp, Box 93, New York 33.

COSTA RICA diamond shape set 8c. P. Gustafson, Box 1206, New Britain, Conn.

#### TATTOOING SUPPLIES

TATTOOING pays big! Anyone can tat-too with our outfits. Instructions included. Free illustrated literature. Write Tatooco, 651 S. State, Chicago 5. BIGGEST Money in Tattooing now! No experience required, complete instructions with outfits, send for free literature. Tatooco, 651 South State, Chicago.

#### TOBACCO—PIPES

CIGARETTES: All standard brands, "by the carton", any quantity, complete in-formation 25c. National Distributors, Box 57-P.S., Muskegon Hts., Mich.

CIGARETTES, Cigars—Scarce items lo-cated—Details 25c—Mansfield Studios, Jericho, Vermont.

CIGARS-Mild. Box 50, \$4.00, plus 35c mailing; many other brands; free price list. Zibar, Roselle, New Jersey.

50 QUALITY Cigars \$3.50, \$4.00, \$5.50, Continental Cigars, Corning, N. Y.

#### TRAPPING

ELEVEN good Box Traps, Complete blue-prints 30c, Wee-Sho-You, Box 51, Detroit, Mich.

#### TREASURE FINDERS

MT-SCOPE Metal Locator fully guaranteed and unsurpassed in efficiency. Time pay-ment plan, trade-in and accessories, Free literature, Fisher Research Laboratory, literature, Fishe Palo Alto, Calif.

SEEK Buried Treasure. Methods, mysteries, devices explained. Circulars free. Century Press, Box 151D, Glen Ellyn, Ill.

#### TYPEWRITERS

SPOT Cash paid for Typewriters, Duplicators, write, DixieGraph, King, N.

#### VOCATIONAL GUIDANCE

VOCATIONAL Guidance, Testing: Experienced Casework Counselor, "Counselor" 420 W. 261st St., N. Y. C. 63.

#### WANTED—MISCELLANEOUS

WANTED Stop watches, engineering instruments, portable calculators and typewriters. Ship in confidence. If highest offer unsatisfactory, items returned pre-paid. Reliable, 2354 A 77th Ave., Phila. 38. Penna.

WE buy or sell or trade anything, large or small, specially interested in the un-usual. Farmers & Traders Exchange, Dept. B, Chittenango, N. Y.

WE'LL Swap Sell Buy anything. Free list. National Swappers Guide, 610 St. Joseph, Evansville, Indiana.

"Anything"! Highest prices buy guaranteed! Justice, Box 150, Chicago

MERCURY-Highest Prices. Free containers. Write, Mercury Terminal, Norwood, Massachusetts.

#### WATCHES

WATCHES Wanted-Broken or usable-all kinds, even Ingersolls. Highest prices paid for jewelry, rings, spectacles, alarm clocks, razors, cigarette lighters, gold teeth, etc. Cash mailed promptly. Lowe's, Holland Bldg., St. Louis 1, Mo.

WATCH and clock repairing increasing. complete home study course with drawings and pictures. Information free. Houston Chronomatic and Watch Co., P.O. Box 5367B Houston 12, Texas.

WATCH and clock repairing-complete practical course in modern horology, 66 illustrated self-instruction lessons. Just out! Low price. Information Free. Write —Nelson Company. Dept. 8-01-2. Chicago 4.

#### WELDING, SOLDERING

PERFECT welding, brazing, soldering with tested, light-work "Super-Welder," Ideal for home, farm, office appliances. Beginners become experts quickly with this simple-to-operate outfit. Full instructions. Operates AC-DC, 110 Volts. Plugs in any-where. Complete with Metallic Arc, Flame Torch, Mask, Supplies, Guaranteed, 5 Days' Free Examination, Only \$19.95, Save 2%, send check with order. Super-Welder Mfg. Co., Dept. B, 23 E. 20 St., New York 3, N. Y.

FARMERS, garagemen, repairmen, manu-facturers: Guaranteed 110/220 volt A.C. welder, 20 to 160 amperes continuous output, complete supplies, \$135,00 F.O.B. Chicago. Welds any heavy, light metals. Production, maintenance, repairs. Other sizes, \$68.00 to \$245.00. Circulars. Supplies. Williams Company, Box 4100, Portland 8, Oregon.

NEW Model electric welder 110 volt AC-DC; will weld all metais; easy to use, DC; will weld all metals; easy to use, full directions. Complete with power unit, flame and metallic arc attachments, car-bons, fluxes, rods, mask; all for \$19.95— Used by the Navy, Magic Welder Mfg. Co., 239-PS-3 Canal St., New York City.

BUILD D.C. Arcwelder without rewinding Armature, Plans \$1.00 each, 25 to 600 amperes from vehicle d.c. motors, light plant generators, automobile starter-gen-erators, Welders Club, WB-3432, Chicago 54. For Sale: Vehicle d.c. motors,

MULTIWELD Model "150" heavy duty A-C welder, 110-220 voits. Over 200 heats, 1/16" to 3/16" rods. Garages. Shopmen, Farmers—free folder. Phillip Wilson, 309-E Bridge, Streator, Illinois.

NEW electric soldering iron—solders in hard-to-reach places. \$6.75. Free litera-ture. Barnard Sales Engineering Company, 3411 Westcliff Rd. So., Ft. Worth 4,

BUILD your own 6-12 volt Arc Welder and soldering device from used material. Send \$1.00 for plans. Victory Arc Welders, Box 548, Dodge City, Kansas.

FREE Catalog of welders, welding supplies, generators, fencers, and other electrical items. Write LeJay Company, Minneapolis 8, Minn.

A.C. D.C. 1/16" welding rods. Coated mild steel (without priority). Ten pound car-tons \$5 FOB Welders Club, WB-3432, Chicago 54.

WELDING rods, all kinds, all sizes. Trial package 25; literature free. Western Welding Wire Co., 125 Santa Ave., Los Angeles 12, Cal.

SLIGHTLY used Arc Welders. Recom-mended by R. E. A. Guaranteed. Forney Mfg. Company, Ft. Collins, Colorado.

#### EVERSLIP PULLE

unaffected by weather. No pulley covering, no belt dressing required. Replace troublesome pulleys with NEVERSLIPS. All sizes. Money-back guarantee. Ask for NEVER-SLIP Pulleys on ALL power machinery you buy. Write for folder and prices. ROSENTHAL CORN HUSKER CO. Box 22-345 Milwgukee, Wisconsin



#### TEP AHEAD OF THE CROW L ROCKET YOUR AMBITIONS into reality. things you want; banish Fear, solve problems quickly! Fascinating methods and experiments. Write TODAY for startling FREE booklet and convincing FACTS. Or send \$1 for 5 amazing lessons and GREAT KEY THOUGHT. Atlanteas Guild, Box 582-B, Harrisburg, Pa. HARMONY

# Train Now

## REFRIGERATION AIR CONDITIONING

Millions of Older Units Need Expert Service. Big Afterthe-War Expansion Will Create Even More Opportunities.

Veterans Ask About "G.I." Training

Now is the time to get ready for a top job and good pay in this big, fast-growing field. A serious shortage of trained men exists in all branches, due to the war, Thousands are needed now and for big post-war expansion. Amazing opportunities for men up to 60. This 28 year old institution will give you the practical training you need. You can train at home and in our Chicago shops—largest in the country. Unique system makes everything simple, easy to grasp, Common schooling all you need, No previous experience required, Write for full facts TODAY, No obligation.

#### INDUSTRIAL TRAINING INSTITUTE

2150 Lawrence Avenue,

Dept. P2C,

Chicago 25, Ill.

SUCCESS.



• Some men are angered, embarrassed, at being thought old because they tire so quickly, get all fagged out. But, isn't there a reason for feeling like an old man at quitting time? Many men do not suspect that constant strain and drag on delicate cords in the "Vital Zone" may be to blame. Often the gentle, comforting, firm support of a Bauer & Black Suspensory brings relief.

#### FREE BOOK TELLS FACTS



Do you know why so many men say they feel years younger, livelier, with the scientific support of a Bauer & Black Suspensory? This free book gives you valuable facts every man should know about "Vital Zone" fatigue. Send for your copy today. No obligation.

#### (BAUER & BLACK)

Suspensories

Division of The Kendall Company Dept. S-410

2500 South Dearborn St., Chicago 16, Ill.

Yes, I want the real facts about Suspensories. Send me your FREE booklet without obligation.

Name	
= 5.00 ft	

Address.....

City.....State...



7 C Dept. 509 So. STATE STREET

CHICAGO 5. ILLINOIS



MAIL TODAY

Please send free Song Flute playing guide and name of nearest dealer. No obligation.

(Write address, town, state in margin)

CONTINENTAL MUSIC CO., INC. 630 So. Wabash Ave., Chicago 5, III.

# WANTED!

No, we don't want "0132057745"! But we're mighty anxious to lay our hands on that old musical instrument you're not using. We'll pay the highest prices in America for any of the following band instruments regardless of style, age or make:



TRUMPET • CORNET • TROMBONE • ACCORDION ALTO OR TENOR SAXOPHONE • FRENCH HORN BOEHM SYSTEM CLARINET MELLOPHONE

Send us your instrument for appraisal. If our offer is acceptable to you, you'll get spot cash plus ship-ping cost by return mail. If not we return it and reimburse you for shipping expense.

> WURLIIZER THE NAME THAT MEANS PRESSEC TO MILLIONS

Suite 3406, 105 W. Adams St., Chicago 3, Ill.

Qualify quickly as Draftsman or Tool Designer through sparetime home study. Many making \$100 to \$125 a week. Expanding industry calling for more machine and tool designers than available. Good pay jobs waiting. Rush name and kind of job wanted today for full free facts.

INSTITUTE OF TECHNOLOGY, Box 236, Greenville, Ohio

# Do you want

- .. to go to College?
- or to enter a Profession?

(Such as Accounting, Architecture, Nursing, Dentistry, Teaching, Social Work, Osteopathy, Beauty Culture, Optometry, Embalming, Chiropody, Law, Medicine, etc.)

#### . or get an Office Position?

To get anywhere, you practically MUST finish High School FIRST. You can complete our simplified High School Course in SPARE time at home, as FAST as your time and abilities permit. Equivalent to resident school work-prepares you for college, pre-professional examinations, business, industry. Standard texts furnished. Diploma. Credit for H.S. subjects already completed. Single subjects if desired. Low tuition, easy terms. American School, Chicago, est. 1897—endorsed by educators. Finish your high school education NOW. Write TODAY!


#### High School Course Home Many Finish in 2 Years

American School, Dept. H346, Drexel Ave. at 58th :
--

Gentlemen; Send me FREE information covering special training in subjects checked below. No obligation on my part,

- High School Course Cost Accounting for Mfg. Architecture and Building Automotive Engineering **Business Management**
- Electrical Engineering Elec. and Gas Refrigeration Air Conditioning
- Railway Training
- Diesel Engineering Drafting and Design for Men and Women **Plastics** Private Secretary Shipbuilding.

Name		•	•	•	•		•	•	•	٠	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•



#### LET JOE BONOMO

Master Builder of Men, show YOU how to build YOUR BODY into MEAT and MUSCLE; and your MUSCLES into SPRINGS of STRENGTH and STEEL, You'll be proud to say "I'm Bonomo ALL my life I've been building big muscles and powerful bodies out of scrawny little ones. I've done it for thousands with my 'Power-Plus Method, the most original System of Physical Development ever de-vised; the system that "Proves It With Results"! I'm so sure I can do it for you that I offer my MONEY - BACK GUARANTEE! Let me give you the build, strength, energy, vitality you

#### Send NOW for this Amazing, Complete 3 WEEKS "POWER-PLUS" SPEED COURSE

in muscular development for

#### ARMS, SHOULDERS, CHEST, BACK, LEGS



JACK DEMP-SEY says:

"I consider your course tops for all round physi-cal develop-ment".

Covers every part of your body inside and out. Gives you strength, build, speed and endurance. 18 daily work-out charts, 91 separate Photo-Instructor illustrations, 22 sheets of instructions showing how to do the proven 'Power-Plus' Muscle Builders. 3 illustrated Body Fact Lectures and more. Packed with facts about your body, in-

cluding diagrams of muscles, nerves, organs. \$5.00 value, but it's yours now, complete for only 97c and a 3c stamp (or send \$1.00 cash, money-order or check), or I'll send com-plete course COD. Pay postman 97c plus postal charges. ACT FAST! Clip and mail coupon to me TODAY!

For Quick Action!



BERNARR MACFADDEN says: 'Your aston-

achievement places you at the head of all

your compet-itors."

Strong men ACT, but as an inducement to urge you to act fast, if you send coupon at once, I'll send you my famous P.D.Q. Test Dozen. Find out how strong you really are! RUSH COUPON TODAY.

JOE BONOMO, Dept. 506-B 1841 Broadway, New York 23, N. Y.

Joe Bonomo, personal Bonomo Culture Institute, 1841 Broadway New York 23, N. Y.

506-B

Dear Joe: That's what I want-fast action! Rush me quick, my complete 3 weeks 'Power-Plus' SPEED COURSE, Include FREE your famous P. D. Q. Test Dozen.

1	enclose	\$1.00	Cash,	money-order

<ul> <li>Send COD, I will pay postman 97c plus postal charges</li> </ul>		Send	COD,	1	will	pay	postman	97c	plus	postal	charges
--	--	------	------	---	------	-----	---------	-----	------	--------	---------

Nar	ne.		٠	.,			+														. 1	\g	e				0				٠
Str	eet.									٠	• •		٠	٠				٠	٠					٠	٠	٠	٠	٠	•	• •	
City				٠.	0.2				50	0				 2	to	n	e i				S	ta	te								

. Zone . (Please print plainly)

# GREAT BUYS ON THESE IMPORTANT BOOKS!

#### IT'S FUN TO DRAW

A Complete Self-Instruction Course & Reference Book, with over 1000 "How-to-do-it" Drawings—9 Fun-Packed Sections complete only \$1.00

Anyone who has learned to write can learn to



#### **3000 DESIGNS & DRAWINGS**

Of Mechanical Movements, Devices, Appliances, Contrivances and Details

Every conceivable kind of mechanical motion and movement is

you need this book, 355 pages.....

#### **MACHINE WORK**

A Shop Manual and Reference Book

By Theron J. Palmateer

The ideal training guide for the beginning or semi-skilled machine shop operator. Covers instruction on ordinary jobs that involve the use of lathe, drill press, shaper, planer, milling machine and grinder. Presented in simple, easy to understand language and with many illustrations and diagrams.

Part of contents indicates scope and value of this book:—

General Information-Lubricants-tools-operating care of ma-chines-oiling-cleaning-LATHE WORK-PLANING-DRILL-ING and TAPPING-MILLING-Machine Work-GRINDING-Hand Tools, Chiseis-Files-Scrapers-Quantity Production Methods-includes 12 typical jobs and their handling

> 202 Pages-Regular \$2.25

\$1.00

#### HOW TO UNDERSTAND ELECTRICITY

By Frederick Collins

From the householder with a broken doorbell in need of repair From the householder with a broken doorbell in need of repair to the amateur experimenter who wants to do and see for himself, this book explains and simplifies "electricity." No previous technical knowledge is needed to read this book. It starts with the underlying theories and elementary rules, and proceeds in an easy, step-by-step method to magnetism, electric currents, batteries, circuits, thermoelectrics, electrochemistry, induction, dynamos, motors, transformers, measurements, etc. More than 150 illustrations throughout the book provide a visual elaboration of the text.

everyone will admire, CONTAINS COMPLETE INFORMATION STRUCTIONS ON 10 POPULAR HANDICRAFTS:-POTTERY

vide a visual elaboration of the text....

STRUCTIONS ON 10 POPULAR HANDICRAFTS:-POTTERY, METAL CRAFT, LEATHER CRAFT, WEAVING, WOOD CARVING, BLOCK PRINTING, DYEING, BASKETRY, BOOKBINDING and RUG WEAVING! All in this one 124-page interesting, stimulating book! \$1.00

# As Many As

Fill out coupon and mail today. All books FULL-SIZE, HANDSOME, CLOTH BOUND! If payment HOW TO ORDER: enclosed, we pay the postage; if C.O.D., plus postage. Examine and use the books you order for 5 days. If not satisfactory, money back at once for the books you return.

KNICKERBOCKER PUB. CO., 120 Greenwich St., Dept. A-9, New York 6, N.Y.

#### MAGIC By Barrows Mussey

Here is a practical and fascinating book which shows you how to master simple and complex conjuring tricks for your own pleasure and the entertainment of your friends. In the majority of the tricks described, little or no equipment is necessary for their successful presentation. Everyone, young or old, loves to watch white magic. And it is a rare person who has never wished he could amaze and amuse his friends with hocus-pocus. And this entertaining book tells you \$1.50

#### WATCHES By 1. J. Camm

An up-to-date book dealing with modern methods of repair, adjustment, and timing, The book represents many years of prac-tical experience with watches and is in-tended as a manual for all those interested in horology, professionally or otherwise.

P. S.: - If you have a PRICE
watch that is not run.

ning properly you should \$2.50

By Oswald

"How To Play A Winning Game" Here for the first time is a complete inrere for the first time is a complete instructive and entertaining book on America's own card game. In addition to specific advice on the strategy of play (including psychology, percentages, rules of the game, etc.) the book is enlivened by scores of poker anecdotes and amusing personal experiences.

Some of the Chapter Headings:-How to Play Poker-The Game's General Principles -Draw Poker-Stud Poker-Five-Card Stud -Seven-Card Stud-Five-Card Stud High-Low

Seven-Card Stud Five-Card Stud Figh-Low
Seven-Card Stud HighLow-Various Other Games
-Poker Probabilities and
Mathematics-Glossary and
\$1.50

#### WHY BE SHY?

By Dr. L. E. Bisch

The reader is shown how to conquer shyness at home, in business and in social life; how to banish over-consciousness of sex; the sure-fire rules of conquering shyness permanently; how to replace over-sen-sitiveness and a sense of inferiority with self-mastery; how to abolish artificiality in one's behavior and how to achieve natural-ness; how to prevent shyness in children; ness; how to prevent snyness in children; how to exercise and retain one's new found poise and self-confidence. In addition to being helpful, it is enjoyable reading. It is written with humor and sympathy. And above all, it deals with the most fascinating of all subjects—yourself!

#### CREATIVE HANDICRAFTS

By M. R. Hutchins Here are more things make and do than have before been crammed into a single volume at this low price. From a simple ash-tray to a 9x12 feet hooked rug, hundreds of projects are explained -with tools and equipment needed, simplified working drawings, picand step-by-step tures instruction that makes it easy for you to turn out finished handicrafts that AND IN-

SPECIAL

#### the machines or parts outlined on the drawing board, A practical manual deal-ing with the making of wood and metal patterns and the operations of moulding and casting, including die casting! 112 pages SPECIAL

PATTERNMAKING

and FOUNDRY WORK

By E. Molloy

For the man in the patterns shop or foundry, it is an invaluable guide to the best methods of overcoming the various practical problems likely to be encountered in everyday work. For the engineer, it presents a clear picture of the type of work involved in the production of the continuous recorded for construction.

of the castings required for constructing

with 135 photographs and diagrams regular 

#### FITTING PRACTICE

A Practical Guide To The Principal Workshop Processes For Mechanics, Fitters, Erectors, and all Concerned With Maintenance and Repair Work

By E. Molloy Includes use of tools and machines, care of equipment, time savers and short cuts, several ways of doing one job,

cuts, several ways of doing one job, tests, proving, construction problems, production planning, etc., etc. Illustrations show sequence of operations.

Part of Contents-1, Chipping and Filing, 2. Lining Out and Use of Equipment, 3, Close Fits-Use of Pulling Devices, 4, Fitting and Adjusting Bearings, 5, Bolt and Stud Fitting, 6, Punching, Riveting and Cotter Joints, 7, Connecting Rod Work, 8, Fitting Up Shafting, 9, Gland Packings.

96 pages
S1.00 \$1.00

#### The Fundamentals of CHEMISTRY

96 pages-137 illustrations-.....

By Monroe M. Offner, Ch.E.

A comprehensive and easy to under-stand presentation of the fascinating subject of Chemistry. Even if you are total-ly unfamiliar with the subject, you can acquire a firm understanding of the basic concepts and the "How To Do It" of Chemical science and its far reaching in-

fluence on our everyday life. CONTENTS-Part one deals with ele-CONTENTS-Part one deals with elements, mixtures, atoms, electrons, formulas, solutions, acids, alkalies, salts, gases, metals, alcohol, ether, etc:Part two deals with chemistry in modern life, gives absorbing information on Plastics, Nylon, Vitamins, Sulfa Drugs, Penicillin, New Metal Alloys, New Paints, Photography, Ceramics, Abrasives, and other chemical marvels of our age!
398 pages over 100 il19strations, Various

398 pages over 100 il-lustrations. Various tables and graphs.....

#### --------MAIL THIS COUPON!

Knickerbocker Pub. Co., Dept. A-9 120 Greenwich St., New York 6, N. Y.

Please send me the book or books I have checked below, It is understood that I can exam-ine them for 5 days, and if not satisfied, can re-turn them for full refund.

ı	(	)	It's	Fu	ın	T	0	D	ra	w																\$1.0	ю
ı	-	)	300	00 1	M	ech	a	ni	ca	ı	M	lo	w	en	ne	m	t	5								2.9	8
•		)	Mag	chin	e	W	O	rk												٠.						1.0	ю
ı	1	)	Ho	w T	0	U	ne	ie	rs	ta	m	đ	E	le	ec	tr	H	ci	it	,						1.0	ю
ı	i	1	Ma	gic	٠.																					1.5	50
,	i	5	Wa	tche	15			0						1												2.5	SO
ı	1	1		er																							50
ı		í		y B	7. 7			-	7		100	~			- 1		-	7								2.72	
ı	1	١.		terr																							-
	7	(		ting																							
ı	3	•		ndar																							
ı	3			ativ																							
۰		,	Cre	ativ	e	•	ar	14		••		•			•	•	•	•	*		٠.		•	•	•	*	~
ı		_	encostr		_	8	٠.			٠.			. 1	n	1	u	11		I	a	yı	m	e	nt	t.	Ser	ıd
i		s	end	C.	0.	D.	1	to	r	\$	• •			•		• •		1	pl	u	8	ŗ	00	8	ta	ge.	
	N	am	e		•	• •				•							•									· · · ·	•

Address......

City & Zone ..... State.

# What's in the Basement of the World?

We're finding out through an amazing invention that plunges miles deep to photograph the ocean's floor.


#### By VOLTA TORREY

EARLY two thirds of the earth's surface is still unexplored, because it is hidden beneath a mile or more of water. By delving deeper into the oceans, we can learn as much about the birth and evolution of the world as by peering farther into the heavens. Clues to the origin of continents, location of petroleum pools and other natural resources may be awaiting discovery beneath the seas, along with sunken ships and treasure chests. And now, ways have been found to examine this tremendous basement photographically.

Already, pictures taken far below the ocean's stormy surface have modified some of the ideas of both geologists and biologists. Further study of the 139,000,000 square miles of plains, peaks, and canyons concealed for centuries by salty water may cut in half the number of theories as to the earth's origin.

Yet, compared with a 200-inch telescope, the apparatus used to photograph an ocean's bed is absurdly simple. A POPULAR SCIENCE MONTHLY staff writer, who was permitted to examine this apparatus at the Woods Hole Oceanographic Institution on Cape Cod, found that it consists of an ordinary little camera, inexpensive photoflash bulbs, and other commonplace items, hung on a pole. But the ways devised to manipulate this equipment are amazingly ingenious.

The pressure of the water increases about a half pound per foot



as you descend into the sea; few divers can go down more than 200 feet. Sunlight penetrates only a thin upper layer; below 600 feet, the temperature is generally near zero centigrade, and only the terrific pressure and the salinity keep the water from freezing. Sending a camera to the bottom of this enormous, dark, cold, heavy, restless mass, snapping a clear picture, and recovering the camera entails a whole series of neat tricks.

Nevertheless, Dr. Maurice Ewing, Allyn Vine, and J. L. Worzel, three geophysicists now working at Woods Hole, have obtained a huge albumful of portraits of the ocean's floor. They have taken pictures at a depth of three miles, which is several times as far as William Beebe descended in his famous bathysphere. And they believe they have acquired the know-how needed to photograph the deepest pits, which extend farther down below the surface of the ocean than

SAND-RIPPLE PORTRAITS, made 51 fathoms down, are called one of the underwater camera's most significant discoveries. Similar ripples have been found as far as 83 fathoms below the surface. Until pictures like this were obtained, geologists doubted whether waves rippled the sand more than 30 fathoms down

the highest mountains soar above sea level.

They embarked on this work in 1938, on their way home from coastal survey voyages. They lost their first expensive cameras, and had to finance many of their experiments themselves. So they now use a simple little Argus. To shield it from the water's crushing weight, they mount it in a tight steel or aluminum cylinder, or seal it in a big glass test tube. To keep moisture from condensing inside it, they enclose a bit of calcium chloride or some other drying agent. And to keep bubbles off the window, they cut slots in the metal rim around it, into which any air remaining on the glass when it is submerged is forced by the pressure of the water.


But, as they explain now, "The chief problem is not optical in character, nor one of camera design. It is to find an interesting subject and to put the camera in focus with

it, to provide proper illumination, to hold the camera reasonably steady while the exposure is made, and to get the camera back afterward."

As geologists, Dr. Ewing and his associates were interested in views of the terrain under the sea. So they pointed their lenses downward, directly at it. They then solved the focusing problem by hanging the camera on a pole and focusing it on the earth at the lower end of the pole. For illumination, they hung photoflash bulbs on the same pole.

In comparatively shallow water, they can suspend this scientific

CAMERA HITS BOTTOM and stirs up "dust." The first picture looks that way, but the dust is really sediment stirred by the camera pole coming to rest



Christmas tree from the side of a ship on a wire. A tiny sail attached to the pole keeps it from twirling, and a trigger on the lower, weighted end of the pole turns the lights on and flicks the shutter when the bottom is hit. The photographers then hoist it back to their ship and see what they've got.


But the weight of the hundreds of yards of wire that may be needed to lower a 12-foot pole to the bottom of the ocean makes dangling the equipment this way too difficult and uncertain. So, in really deep water, they just throw the whole thing overboard.


When this must be done, they rig the pole differently. The weight is attached in such a way that it will fall off after it has dragged the pole to the bottom of the oceanic cellar and one or more pictures have been snapped. And a float is put on the upper end of the pole to lift it back to the surface after the weight has been dropped.

The automatic ballast release consists of a chunk of salt in a tin can nailed to the pole. The salt is placed in a cloth sack, from which a wire is run through a hole in the bottom of the can to the weight. When the water

HALF A MINUTE AFTER picture at the left was taken, the water became clear. The light, seen at top in both pictures, shows a starfish and clam shells








TRACKLESS DEEP? It's hardly that, because this picture shows a definite but mysterious track photographed 106 fathoms under the waves. Subsea photography has revealed many such unexplainable markings



SEA FERNS, formerly thought to thrive only off the English coast, were photographed growing at 50 fathoms in our Atlantic waters—first proof of this fact






A 40-FATHOM STARFISH portrayed by Dr. Ewing's underwater camera. Biologists have been surprised to find thick beds of starfish, oysters, and sand dollars in the lower levels of the ocean

dissolves the salt, the sack slips through the hole, and the weight is no longer attached to the pole.

Blocks of hard salt like those placed in pastures for cattle are cut into 1½-inch cubes for this unusual purpose. The time that it will take the sea to absorb this much additional salt can be estimated with sufficient exactness for the cameramen's purposes. They also have used clockwork and a magnetic device to trip a trigger and release the ballast, but they prefer the salt system because it is cheap and reliable.

The buoy used to bring the camera back up also is ingenious. It is made from a few feet of Neoprene hose such as is used for loading tankers. This hose is sealed at each end and filled with gasoline. Even the weight of miles of water will not compress the gasoline greatly, and the lower reaches of the ocean are so cold that there is no danger of an explosion. High-test aviation gasoline is used when it is available, but ordinary gasoline will do. It is enough lighter than salt water to boomerang the camera pole back to the surface.

Even so, the round trip to the bottom may take three hours—and the pole is not likely to bob up right (Continued on page 216)





Trails of light show what a simple matter it is for a woman to fix her hat

# Lights Trace Hand Motions


OMMON actions, such as lighting a cigarette or tying a shoelace, involve a surprising amount of complicated hand movement. Photographer David McLane proves it by attaching lights, as at right, to the wrists of a subject, who performs the action before a camera in a darkened room. After the pattern has been traced on the film, he makes another exposure with a flash bulb to light up the subject.





Here the camera has recorded the motions involved in lighting a cigarette, tying a shoelace, and ironing a towel. In picture at left, "doodling"-like lines represent fumbling for the match. A flare is seen near cigarette






# The Plane of Tomorrow Smells Like an Oil Stove


"A plumber's nightmare!" That's what any oldtime ground-crewman is likely to say the first time he sees the innards of the jet plane. But he has to admit that for simplicity of maintenance and repair the squirt job has its points.

#### By S/Sgt. EDWARD T. WALLACE

Condensed from AIR FORCE, Official Service Journal of the U.S. Army Air Forces.



Four men can pull both engines of a jet job and install new ones in a day—a task that might take five days with a conventional plane. Jet mechanics use about five wrenches where 25 would be needed on a regular fighter



Simplicity is the keynote of the jet engine. That means easier and quicker maintenance on the ground

THE P-51 mechanic, curiosity and perhaps a trace of contempt written on his features, squatted under the wing of the jet-propelled plane and ran an eye over the flame tube. Other mechanics were installing an engine in the jet job.

S/Sgt. Earl Kohler, in charge of the project, glanced up.

"How does she look, Bill?" he asked the Mustang man.

"Well," came the considered reply, "I'd call that a plumber's nightmare."

That was early in the history of jet propulsion in the Army Air Forces. Since that day, mechanics on conventional fighters and bombers have asked Kohler and his crew a million questions about servicing the jet plane.

"They want to know," says Sergeant Kohler with some impatience, "what wrenches we use. How long it takes to pull an engine. How the jet works. One guy even asked if it uses fuel. All kinds of damn fool questions."

Kohler, who operated a garage for 15 years before he went into



One of the jet engines of the P-59. Development of the Airacomet was one of the best-kept secrets of the war. "Every time I turned around," a mechanic says, "I was signing some promise to keep my mouth shut."

the Army, was one of the first AAF mechanics chosen to work on the original XP-59A jet plane while it was being put through months of tests in the California desert. After the project was revealed, he was sent to Wright Field to keep the planes in shape for training and further experiments.

"Every mechanic gets a funny feeling when he first sees the jet job," Kohler says. "I remember what I thought. I said to myself, 'Hell, this thing won't fly. There's not enough stuff.' But after the jet took off a few times, I began to get the idea."

Mechanics trained on Thunderbolts, Lightnings, Marauders, and Fortresses—any of our aircraft with conventional engines have learned to think of power in terms of solid machinery, Kohler explains. In a conventional engine everything is solid and tight. Mechanics think in terms of complicated wiring, ignition, gauges and cylinders, elaborate fuel systems. Everything is complicated.

"But in the jet plane everything is simple," Kohler says. "You put in six quarts of oil, just like an automobile."

The cooling system is just a couple of oil jets which spray lubricant and air into the two rotor shaft bearings. The oil is standard hydraulic fluid 3580. The excess runs down and forward into the accessory section, and is returned by a small scavenge pump. The system is cleaned by a Cuno filter. The generator, fuel pump, and starter are the only accessories carried over from the conventional plane, and the ignition is even more simple than the oil system. There are only two spark plugs, located in the No. 4 and No. 8 combustion chambers.

The other chambers are interconnected and ignite from these two. After the unit is started, combustion continues without further assistance from the plugs. Combustion is as steady as the flame of an oil furnace. Plugs last as long in the intense heat of the jet as they do in a conventional engine. In the jet their spark gap is considerably wider.

Kohler and his men work on the P-59A, which must be classed as a training plane in the jet field. Yet, with few exceptions, their experiences would be applicable to any jet aircraft.

"We use about a fifth as many tools,"
Kohler explains, "and maintenance of a
jejt plane is less than a fifth of what it is
on the other kind. As for the engine, it's
so damn simple I can't understand it.

"Air comes in the front end, goes through the compressors, (Continued on page 224)

## March of Science






#### FABRICS

SHRINKAGE CONTROL of wool yarn is effected by a melamine resin tradenamed Lanaset. The picture at left shows samples of processed and unprocessed yarn after severe test washing. Strands of the untreated yarn are practically fused together. Below is a pair of socks, one treated and its mate untreated, after two hours of washing with soap and soda.






DESIGN FOR HEELS has recently been originated for use by the Gotham Hosiery Co. to make stockings fit better at this strategic point. Difference lies in the new heel's being knit at right angles to the leg, thereby preventing the wrinkles that may occur with the ordinary round heels.





PLASTIC EYES, made in the U.S.A., are now taking the place of the glass artificial eyes formerly imported from Germany. They are made of acrylic resin and, besides more closely resembling human eyes than do the glass substitutes, are practically unbreakable.



72

POPULAR SCIENCE




Propeller shafts are rubberized to prevent destructive electrolytic action. Upper picture shows flame-spray method of coating; below, beader rolls a vulcanized strip against shaft




RUBBERIZING SHAFTS that


drive warships of various types now guards them against pitting by electrolysis. Synthetic rubber can be applied by flamespraying, as shown in the photograph above. Otherwise, a thin sheet of buna-S or GR-S is wound around the part normally exposed to salt water, wrapped with tape to hold the rubber against the metal, and vulcanized by a 24-hour steam bath. On wooden ships, unprotected steel shafts are attacked by electrolysis from bronze propellers.



#### FOOD

EGGS KEEP LONGER and look better when treated by a process called thermostabilization, devised at the University of Missouri. The eggs are immersed in liquids, with air circulating around them, and warmed to a relatively low temperature so that heat can penetrate the eggs before any part is coagulated. The process has not yet been adapted to commercial use. Picture shows egg held at 100 degrees F. for four days.





Piper Aircraft Corp.

This network of airways is the basis of the air tourist's map of tomorrow. Will your home town have an important place on it?

# You Can't Fly Without Airfields

Will the Air Age be kept hovering while it waits for a place to land? We haven't nearly enough airports for our postwar plane traffic.

By DEVON FRANCIS THREE times in 150 years of United States history, transportation has been revolutionized. First came the development of canals and other inland waterways; then, the construction of our great railway network; finally, the building of an incomparable highway system. Each of these in turn brought profound changes in the American way of living.

Now we are at the beginning of a new era in transportation. We are ready to broaden and deepen the foundations for what may well become the world's finest

#### WILL YOUR TOWN BE ON THE AIR MAP?

GOOD ROADS made the Auto Age come true. Only good landing fields—and plenty of them, everywhere—will make the Air Age come true.

Go back a little—to 1920, just after the last war. We had 339,000 miles of surfaced streets, roads, and highways. On these we drove 9,000,000 motor vehicles. By 1941 we had spent over forty billion dollars for road building and had 1,697,000 miles of surfaced streets, roads, and highways. They carried 34,000,000 motor vehicles. And total travel was up 534 percent.

Landing fields are even more important to flying than good roads are to motoring. You can't fly anywhere unless you can land.

The extent to which you and your town are going to share in the benefits of the Air Age depends largely upon the personal interest that you and your fellow citizens take in providing adequate landing facilities—landing strips or flightstops, airparks, air harbors.

Almost everyone is going to fly—in private planes, in air taxis and air buses, in transports. A town with good landing facilities will grow with the Air Age . . . attract residents who are progressive, successful, forward-looking . . . gain the business advantages and added employment that go with the development of a gigantic new industry . . . expand its community activities. It will be tied into the whole world-wide postwar system of air transport.

What finer tribute could any community make to the memory of the men and women who are sacrificing their lives in World War II than to build a victory landing field and dedicate it to them? It would be a living memorial, better than any monument.

To combat postwar unemployment, many states are already setting aside vast surplus funds for postwar improvements, part of which should be earmarked for landing fields. And the Federal Government, if it follows recommendations in the \$1,250,000,000 "National Airport Plan" of the Civil Aeronautics Administration, now before Congress, will share the costs with states on a 50-50 basis as in the Public Roads program.

Now is the time, therefore, to use your influence in your own community to plan a landing field and, if possible, acquire the land. Only in this way can you—and all your fellow citizens—share fully in the coming Air Age.

We should be glad to have your comments, suggestions, and questions on this subject. Address the Aviation Editor, POPULAR SCIENCE MONTHLY, 353 Fourth Avenue, New York 10, N. Y.

—THE EDITORS

MARCH, 1945



SINGLE STRIP. Simplest of air facilities is a straight landing strip. All it needs is a sod surface running into prevailing winds, with sock and markers Piper Aircraft Corp.



L-SHAPED STRIP is a natural expansion, allowing take-offs in four directions. Inexpensive hangar and fuel supply mark start of an airport

#### LANDING FACILITIES FOR PRIVATE FLYING MAY RANGE

facilities for travel in another medium—the air.

Both for the big commercial airliners, linking cities and continents, and for privately owned airplanes, giving personal wings to millions, airports, "airparks," and other types of landing areas will be built in each of the 48 states.

The bill: \$1,250,000,000.

The goal five or ten years from now: 6,000 landing areas, or one within reach of every American community with a population of 1,000 persons or more.

There is a close parallel between railroad and highway construction and the building of places where airplanes can take off and land. The major airport, with its multiple runways and instrument landing equipment,

#### A PROGRAM FOR POSTWAR EXPANSION OF LANDING FIELDS



AT PRESENT there is, on the average, only one place in every 1,294 square miles where a private flyer can sit down. Even so, existing fields are bunched in thickly populated areas, so that there are vast areas with no landing spots at all





POSTWAR PLAN calls for a landing place within reach of every American community of 1,000 or more inhabitants, plus intermediate flightstops where private flyers can land in case of trouble

> EXPANSION PROGRAM WILL PERMIT SHORTER HOPS, GREATER SAFETY, UTILITY.




T-SHAPED STRIP offers the same advantages as the "L." Lay of the ground and other conditions will determine which is the better



AIR HARBOR. If the town is on a river or a lake, it can have a seaplane base. This can be combined with a landplane field for all-around service

#### FROM SINGLE FLIGHT STRIP TO FULLY EQUIPPED AIRPARK

AIRPARK. A park or fair grounds in or near the town makes a splendid location for an "airpark"— a combined landing field and recreation center. Such sites usually have good transportation facilities. Many communities will build airparks as memorials to the men who have served their country in the war



MARCH, 1945

is to the transport plane what a track and a block-signal system is to the railroad train. The airpark and subsidiary landing facilities are to the private plane what the well-groomed highway is to the automobile.

The inland waterway was the backbone of the United States domestic transportation system in the first third of the nineteenth century. The golden age of railroad construction was the last half of that century. The extraordinary expansion of America's highway network occurred after the First World War.

Today the aviation counterpart of railroad and highway construction is a telescoped project. Landing areas to give both the airliner and the personally owned plane maximum utility will be built simultaneously.

And, interestingly enough, just as the construction of railroads and highways had a pronounced effect on the ability of the nation to defend itself against attack, so will landing facilities for airplanes contribute to national defense.


When the war is over we are going to need a lot of places where airplanes, of both the transport and personally-owned types, can take off and land.

Official Washington anticipates a twenty-


#### PLANNED AIRPORT CONSTRUCTION: HOW A CITY OF 5,000

HERE is the actual, move-by-move history of an airport planning program that is being carried out in a city of 5,000 inhabitants in western Michigan. Six sketches, redrawn by Stewart Rouse from "Michigan Airports," a

booklet prepared by the Michigan Board of Aeronautics, show the successive stages of construction to be undertaken as the growth of air traffic demands. The insets trace the acquisition of land, with the acreage of each plot.





The site is a level, sandy plain. The approaches are clear and there is room for expansion. The original purchase covers 120 acres. Work in this first stage of development includes grading, draining, and seeding the landing strips



2 Here the landing strips have been extended to the maximum allowed by the size of the property, and two of them have been paved to 2,500 feet. A taxiway and apron have been provided. Note that all paving is planned to fit in with the later stages of development

3 Two more runways are paved to the CAA standard for "Class 2" airports, as shown by shaded portion of sketch. Inexpensive unit or "T" hangars are added as needed. Proper grading and draining of original landing strips makes later paving easy 4 An additional 40 acres of ground is acquired, and the two diagonal runways are extended to 3,500foot, "Class 3," standard for limited air-line operation. First unit of administration build-





fold increase in the number of licensed airplanes by 1950. On the basis of less than 25,000 nonmilitary aircraft of record before Pearl Harbor, that would mean a half million private planes and commercial transports. Other estimates run well beyond the million mark for the end of the first decade after the war.

Today there are good landing facilities for only a fraction of either number.

We have, in fact, less than 3,000 fields, exclusive of those built for military operations. Of those, 740 are suitable for airliners.

Only 291 communities in the United States


are served now by the scheduled air-transport system. Almost 6,500 with populations of 1,000 or more have no service.

Government experts estimate that within a decade after the war 20 million passengers will ride the air lines annually as against a fifth of that number in 1941.

The number of intercontinental commercial airliner flights will be increased sharply. Planes will leave not only from the seaboards but also from cities in the interior of the country. It is a shorter distance from Chicago to Moscow than it is from New York to Moscow, for instance.

In most parts of the United States the

#### PLANS TO KEEP ABREAST OF ITS GROWING AIR NEEDS



# 

Under the CAA Air Address System, every city, town, and village in the United States eventually will be marked for identification from the air. Markings may be painted on highways or outlined in crushed stone, evergreens, or plywood

private pilot, riding cross-country, keeps a worried ear attuned to the throb of his engine and a bilious eye on the weather, because the spots where he can make emergency landings are few and far between. On the average, he has a place to sit down only once in every 1,294 square miles.

Even that figure is misleading, because landing fields are bunched around the more populous areas, leaving the great open spaces arid of facilities. Moreover, fully half the existing fields are indifferently maintained. In bad weather they are mud holes. They are badly marked. A pilot needs a telescope to spot them from the air.

We are going to have a lot more places where airplanes can take off and land. More than 60 percent of the money to be poured into standard airports and lesser landing facilities is earmarked tentatively for improving ports that can be used by airliners.

Here is a hypothetical case history of what expanded air-line service would mean: Two cities of 100,000 population lie 600 miles apart. Between them, evenly spaced, are five communities of 25,000 each. If a transport plane makes a stop at one of those five communities on its flights between the two big cities, traffic between the terminals increases by 70 percent. If two stops are made at intervals of 200 miles, the traffic increase is 160 percent. If stops are made at all the intermediate communities, the traffic between the two terminals increases sixfold.


The rest of the money earmarked for landing-field construction and improvement will go to the private flyer. Counting all the projects in the long-term plan, he will

have a minimum of 5,000 ports. Possibly, with the inclusion of intermediate landing "strips," he will have as many as 6,000 to 10,000 stopping points. If he had 8,000, he would enjoy a landing area in every 372 square miles.


The nation's smaller communities will benefit most from the airport program. Of the new airports planned, only 150 will be built in cities of more than 50,000 population; only 59 in cities of between 25,000 and 50,000; but 515 in cities of 5,000 to 25,000, and 2,326 in towns of less than 5,000.

What neither industry nor Government knows is just what America will have when the building project is complete. Airplane design, as to both size and performance, which largely dictate airport design, is in a state of flux. The commercial air lines are only guessing about what kind of equipment they will need a decade, two decades, from now. Manufacturers are only guessing about how many people will buy planes for their personal use.

#### INGENIOUS ACCESSORIES WILL




COMPARTMENT LOADING, using containers that form sections of the fuselage, has been suggested for speeding the handling of cargo. Sections would be filled at freight terminals and brought by truck to the airport, where cranes would exchange them for the incoming containers




Will the transoceanic airliners be behemoths of 200 tons gross weight, as compared with today's 40-ton standard versions? Will the domestically used transports carry 30 passengers or 100, and on hops of what length? How many coast-to-coast nonstop or one-stop schedules will be needed as against "local" schedules stopping every 50 or 100 or 200 miles? Will the take-off and landing speeds of transport planes require surfaced runways a mile in length, or a mile and a half, or two miles?

Will private-owner aircraft be standardized in the conventional fixed-wing design, or will they be largely of the whirling-wing type like the helicopter and the Autogiro? If of the fixed-wing type, will better engineering progressively reduce their take-off and landing runs, (Continued on page 211)



POSTWAR COMMERCIAL AIRPORT. Facilities must be provided for handling the huge skyliners that will shuttle across the continent and the oceans. A fine example of progressive thinking in this field is the project of the Oklahoma City Chamber of Commerce pictured

#### SPEED THE DISPATCH OF PLANE PASSENGERS AND CARGO



# Zoom Boats Sock Like Battleships

NAVY TELLS SECRETS OF ITS DEADLY ROCKETS

RANGE flames flash and smoke puffs along the decks as American landing craft approach hostile shores. But these jets of fire in the dawn's dim light cheer the men about to land, for they mark the departure of a salvo of rockets to clear the coast of Japs.

Each rocket whooshing forward will hit like a 105-millimeter shell, and hundreds of rockets now can be shot electrically from the tilted crates along the sides of a single landing craft. All told, the short-range salvos from one rocket-firing craft may be a fourth greater than the firepower of two of our modern, New Jersey class, 45,000-ton battleships.

Rockets are an ancient weapon; they stopped Kublai Khan in the thirteenth century. But they have been improved so greatly so recently that the Navy spent 10 times as many million dollars to produce them in 1944 as in 1943. And now, more huge rocket factories are being built—to supply the armed forces with more millions of dollars' worth of rockets per month this year than were ever made before per year.


The beach-barrage rocket that is clearing the way for American invaders in the Pacific weighs a little more than 15 pounds. Its body is 4.5 inches in diameter and is loaded with a high explosive. On its nose there is a tiny wheel that is whirled by the wind when the rocket swishes into the air. This arms the fuse, which touches off the explosive payload in the body of the rocket

when it strikes upon the enemy's ramparts.

Behind the explosive head of the projectile is a "motor" consisting of a long, narrow tube of propellent powder and an electrical wiring system. Current to start this motor is supplied by batteries, charged by generators fed by the ship's engines. Contact between these batteries and the wiring within the rocket is made by a little wire, known as a pigtail, which extends from the rocket's tail into the launching rack.

When current flows into the wiring system through the pigtail, the propellent powder is ignited at the end near the payload. The fire travels backwards through this tube of powder. It burns more slowly and steadily than ordinary gunpowder and emits fiery gases. These escape through a nozzle in the tail and thus drive the rocket forward.

There is a loud hiss, rather than a boom, when a rocket is fired. The tail jet is so



Portable rocket-launching racks set up on this LCVP give the tiny landing craft the firepower of a big warship. Light and easily handled, they save American lives in landing operations Rocket "gunners" wear asbestos suits and gas masks for protection against flaming gases and fumes of tail jets







pyrighted mate



Rocket racks on an LCI. Projectiles are carried in banks of ten and fired electrically. Rockets in the bottom row of each rack are fired as a salvo. As each whooshes out, another slips down in rack to replace it

Clearing the road to Tokyo: a rocket-firing LCI lets fly with a barrage to smother Japanese defenses on a Philippine beach as the first wave of amphibious troops nears the shore. Rockets hit like 105-mm. shells







GERMAN ROCKET GUN fires one of its six projectiles at Allied troops. Our Navy's work at Inyokern is designed to keep us abreast of any foreign developments in war and peace


Rockets streak from launching racks mounted on a jeep at the Naval Ordnance Test Station, Inyokern, Calif. Here, over a 1,025-square-mile tract of lava mountains fringing the Mojave Desert, the Navy tests rockets designed to be fired from ships, planes, and land installations. The driver of the jeep sits between two racks

Below, projectiles are being loaded aboard the firing platform set on the back of a quarter-ton. The jeep carries the rockets to selected firing points, from which they are launched at targets in the desert while observers take movies of their flight. Plane-carried rockets are photographed from accompanying aircraft

hot that men take cover before launching these rockets and wear asbestos suits when working with them. But this bright, yellowish, torchlike flame lasts only long enough to lift the rocket well into the air. It ceases before the projectile begins its descent toward the target.

The effect on the enemy is similar to that of heavy mortar fire. Rockets do not have the velocity or high degree of accuracy of artillery. But (Continued on page 232)






This paper house to accommodate four people costs about \$50 for materials and can be erected in about 59 minutes by two men. It is designed for an emergency shelter in case of bombing, flood, or other disaster

## Paper House Costs \$50


BUILDING a home out of paper in 59 minutes may be the answer to housing problems created by fire, flood, or other disasters. Two workmen recently did the trick with materials that had been developed for a four-season test by the Institute of Paper Chemistry, Appleton, Wis.

The basic material is chipboard consisting entirely of fibers from news, wrapping, and other waste papers. The board is treated with a fortifying agent that, according to tests, has made it resistant to "creep" even under tropical weather conditions. In addition to this, the panel material is protected against water by a resistant paint that also contains a fireproofing agent.


The house has a floor space of about eight by 16 feet. No framing or studding is used, but the panels are securely joined by a system of metal connectors. Joints in the roof members are sealed against moisture with waterproof paper tape. With two doubledeck bunks, the house could shelter a family of four. The total cost of materials for the unfurnished house is slightly more than \$50.



Sections of the paper house ready for assembly. Except for hardware and plastic windows, the structure is entirely of material developed from a base of waste paper



Here 10 of the 21 panels shown above are in place. Stringers supporting floor panels need not be used where site is leveled, but sills are laid under edges



TUNNEL connects the pressurized gunners' compartment with the control cabin. Here a crew member starts the 35-foot crawl forward. Tunnel passes over the unpressurized bomb bays


# Let's Look Inside a B-29

VER wonder what it's like inside the big belly of the Boeing B-29 Superfortress? All right, come along. We'll go through one from nose to tail.

Up in the tip of the long nose, where the bombardier sits between the feet of the pilot and copilot, you have the feeling that you are riding on the tip of a spear hurled through space. Back-to-back with the copilot rides the flight engineer with his panel of dials and indicators; behind the pilot, the navigator sits at his big table. On the other side of the fuselage, beyond the bowl of the forward top turret, is the post of the

radio man.

From this pressurized control cabin you crawl aft through a 35-foot padded and heated tunnel that passes over the bomb bays to a second pressurized compartment where the gunners rule. From a rotating pedestal "throne" in the center, the fire-control gunner looks out over the top of the fuselage from a transparent blister. Below him, on either side, sit the waist gunners in



CREWMEN REST on long missions in a compartment aft of the gunners' section. At upper left is the top rear turret. Beyond bulkhead at rear is the storage space in tail



COPILOT'S SEAT is abreast of the pilot's. Their instrument panel is fairly simple, as many dials and indicators are on the board of the flight engineer, back-to-back with the copilot

BOMBARDIER'S "OFFICE" in one of the newest Superfortresses is inspected by Lt. Edwin G. Lagasse, of Schenectady, N.Y., veteran of two raids on Japan in the B-29 "Mysterious Mistress"



the bulging side blisters. Each of these three has a sight with which to operate the remote-control turrets.

Next you come to the crew compartment, where relief crews can relax on long missions. Bunks, food, and first-aid supplies are tucked into every corner not occupied by other equipment.


Now, through a pressure-lock door, you enter the unpressurized storage space aft. This is filled with auxiliary equipment, the retracted emergency tail wheel, and other

things over which you pick your way down the narrowing fuselage to the tail.

Through another pressure-lock door you squirm into the end-of-the-world station of the tail gunner. It is surprisingly roomy. You can stand erect or climb into the tail gunner's seat behind the twin .50 caliber machine guns and the 20-mm. cannon. He looks out through heavy, bullet-resisting glass. With his own pressurizing unit and interphone, he is cozy

NAVIGATOR plots a course at a large table on the port side of the fuselage, behind the pilot. A large case holds his maps. At upper left is a part of the forward top turret and keeps in contact with his fellow crew members.

One thing that strikes you is that the B-29 is designed not only for efficiency as a fighting machine but also for the comfort of its crew. All pressurized sections are lined with a heavy heat- and sound-insulating blanket of dark-green quilted material. Heating pipes mingle with the maze of interphone and power wires. Seats are the last word in comfort. The plane is roomy and quiet—an airman's airplane.





FLAME-THROWING TANK. Darting a tongue of flame far ahead, this U.S. tank routs enemy troops from pillboxes, hay-stacks, and other hiding places. Mounting flame-throwing equipment in armored ve-


hicles makes it possible to carry this devastating weapon close up to positions that could not be approached by men in the open. Tanks so equipped were used with telling effect on the borders of Germany.

FLOATING REPAIR BASES, such as the auxiliary repair dry dock below, are one reason why our Navy has been able to strike at the very heart of Japan's stolen empire. This odd craft can submerge enough

to scoop up a destroyer through the gate seen in the stern. It then pumps itself dry, cradling the warship for repairs below the water line. Such floating dry docks follow the fleet to newly won island bases.




## How We Bomb Through Clouds



Layers of thick cloud no longer shield enemy industrial centers and other objectives from the devastating attacks of Allied bombers. While it has been known for some time that our planes could strike invisible targets, details of the amazing invention that makes it possible have just been made public in this drawing by G. H. Davis for The Illustrated London News. Known to the British as the "gen-box" or "black

box," the device resembles in principle the "echo sounder" used on ships. A radio transmitter sends signals downward to the earth. Bouncing back to the plane, these are translated into a faint outline of the terrain below on the fluorescent screen of a cathode-ray tube. Water shows up as dark patches, while buildings, ships, and other solid objects are indicated as lighter patches with the same outlines as if viewed directly.





MODELS FOR SAFETY instruction, made by Richard V. Milligan, have been used by the Carnegie-Illinois Steel Corp. to teach safe job routines to employees. One of the models is of an overhead crane (left) complete to every moving part and safety feature. The model was made from a collection of 50 tin cans, watch parts, wheels from a toy train, flashlight bulbs, locket chains, and nail polish. A small electric motor supplies power to operate the crane. Milligan's work, including experiments with alloy metals for the crane's tiny parts, covered a period of six months, during which he spent a total of 300 hours' working time.

HE SAVED 11 MILLION CASES for rifle and machine-gun cartridges. Fred Masotta (left), of the Winchester Repeating Arms Co., devised a method of shaving over-long



necks of military cartridges softened by annealing. With a special cutting tool (below) Masotta was able to salvage not only the 11 million cases, but, in addition, 26,500 man-hours of work, and to save over 440 million operations. He was twice awarded War Production certificates and has been otherwise cited for his ideas.






Watch is wound by rubbing the stem on a strip of fabric-backed Compar plastic mounted on a paddle, or fastened to the surface of the workbench



WINDING WATCHES can be a finger-cramping job, if you do it all day long. So watch testers at the U. S. Naval Observatory and in manufacturing plants grasp the watch and rub the stem on a strip of Compar, a vinyl resin derivative, fastened to a paddle or to the workbench.



Postwar airliners will be able to climb to 25,000 or 30,000 feet to fly over storms, catch favoring tail winds, and cross mountains without exposing their passengers to the discomforts of high altitudes

# Why Pressure-Cabin Transports?

Their purpose is not to permit stratosphere flying, but to let the plane seek its best operating level.

#### By ERIC SLOANE

F ANYONE should ask you why the big transport planes being planned for postwar global air routes are to have pressurized cabins, you would probably say that it is because they will fly in the stratosphere at altitudes from 40,000 to 50,000 feet. But that is not the real reason. There is no necessity for transports to fly that high.


What the sealed cabin will do is maintain


a constant comfortable pressure corresponding to, let us say, an altitude of from 5,000 to 8,000 feet. Yet the plane will be free to rise to 25,000 or 30,000 feet as necessary to obtain conditions favorable to the safest,

Whatever the altitude at which the airplane is flying, pressure inside the cabin will be kept automatically at a level that is equivalent to about 8,000 feet

speediest, and most economical operation.

Passengers no longer will have their ears pain from altitude changes. There will be no danger from lack of oxygen, no discomfort from cold, no gas pains caused by reduced air pressure, and no chance of suffering the agony of aeroembolism, or "bends." (P.S.M., Oct. '43, p. 60.) It is because of these advantages that tomorrow's huge airlines will be equipped with pressurized cabins.





Cylinders of scrap magnesium, each with a six-foot return-current wire, are buried alongside iron pipe lines to counteract currents that cause rust

Corrosion has eaten away all but 1/16 inch of the 1/4-inch wall thickness of this steel pipe. Straightedge reveals pitted surface






FIG A


In unprotected pipe, corroding sections act like anodes of a galvanic cell, sending out current to carry off iron ions that are oxidized into rust

RUST PROTECTION for buried iron pipe is a new job found for magnesium by The Dow Chemical Co., Midland, Mich. Corrosion of iron underground is caused largely by galvanic currents set up by the interaction of impurities in the iron and chemicals in the soil. Corroding sections act like the anode, or positive pole, in a galvanic cell, and iron ions are carried away by the current as shown in Fig. A. These combine with oxygen to form iron oxide, or rust. To counteract this, 14-pound cylinders cast of scrap magnesium are buried near the iron pipe and connected to it by wire. Having a higher potential than iron, the magnesium sets up a countercurrent flowing into the pipe and thus removes the cause of corrosion.







A magnesium cylinder buried near by becomes an anode itself, setting up a stronger current than the one coming from the iron and so halting corrosion



ARMADILLO is the name given by the British to this armored vehicle that they adapted from a delivery truck for use in protecting airfields in the event of enemy landings during the Dunkirk period. The tanklike defense wagon. was made by workers in the shops of the London Midland and Scottish Railway. L.M.S. shops also have turned out planes, bridges and armored trains for Britain's war effort.




BENZENE RING, represented by a hexagonal structure of six carbon atoms in the chemist's diagram of hexylmethylbenzene above, actually looks that way in the Xray photo of a molecule of the compound, reproduced at the right



# Ever See a Molecule! HERE'S ONE MAGNIFIED 200,000,000 TIMES

OR many years, chemistry students have taken the word of their instructors that the "benzene ring"—a hexagonal structure of six carbon atoms-forms the nucleus of a great class of organic compounds. Now, for the first time, they may see the real thing. By developing a method of X-ray procedure first proposed by Sir Lawrence Bragg, the famed British physicist, Eastman Kodak Company technicians succeeded in filming the keystone of these chemicals.

The remarkable picture above shows a molecule of a compound called hexylmethylbenzene, magnified about 200,000,000 diameters. Strikingly clear, the pattern of carbon atoms composing the benzene ring appears at the center. Surrounding carbon atoms may also be seen. To each of the latter are linked three hydrogen atoms, too faintly recorded to be visible, in what are known as methyl groups.



IRON. Distribution of atoms in the units of structure of iron, shown in the drawing, is revealed by the photo

below at a magnification of 150,000,000. This arrangement is called a body-centered cubic structure ALUMINUM presents a face-centered cubic structure. (Photo is magnified 100,000,000 times.) By

this technique, atomicarrangements in metuls, alloys and oxides can be analyzed



Whats are in a claubi




ANTI-"G" SUIT. Fighter pilots are not so likely to black out when they wear this suit with built-in air pockets (P.S.M., Jan. '45, p. 85). Air pressure from the plane's vacuum pump automatically inflates the pockets when centrifugal force raises the flyer's weight to 2½ times the normal pull of gravity. Pressure against the abdomen, thighs, and calves is regulated to keep blood from rushing down from the head.




SHOULDER HARNESS developed by the Air Technical Service Command holds a fighter pilot against his seat in a crash landing or upside-down flying. It is locked or released by a hand lever as shown. (Courtesy Air Surgeon's Bulletin.)






FIGHTER TACTICS against a levelflying bomber are taught to student pilots with this device developed under the supervision of the AAF Training Aids Division. A tiny model moving along a straight metal strip represents the bomber; nine other models, on curved strips, show possible fighter approaches. Each fighter path is painted to indicate machine-gun range. As the bomber model is slid along its ribbon, student pilots slide fighter models along their approaches. Bomber gunners also can use the device to learn how to guard their planes against attack. Clips hold the models on the strips.

POPULAR SCIENCE




WORLD'S BIGGEST BOMBER, the AAF's experimental XB-19A, has been given new power with the installation of four new 2,600-hp. Allison liquid-cooled engines, with turbo-superchargers and reversible-pitch

propellers. With a wing span of 212 feet, 1½ times that of the Superfortress, the big Douglas-built plane was designed to carry 18 tons of bombs or 124 fully armed men. The Army uses it in research.



JET-PROPELLED HELICOPTER. Invented by Antoine Gazda, father of the Oerlikon 20-mm. AA cannon, this craft is designed to use a jet tube on the tail to overcome torque and to push the "Helicospeeder" along.


GLIDER BOMB. Here is a specimen of another German "secret weapon"—the radio-controlled glider bomb. Nazi planes would carry these aloft and launch them against their targets, usually ships. Once on its way, the bomb would be guided by radio from the releasing plane. This sample was found by Allied troops near Paris, all packed up with no place to go.



MARCH, 1945

# Your Pin Up- DOUGLAS A-26 INVADER

Japs dread the sight of this versatile successor to the famous Havoc. Our fastest bomber, it doubles as fighter, night fighter, torpedo carrier, and attack plane. Painting by Eric Sloane



THE HOLY GHOST SHELL, otherwise known as the sand dollar or beach dollar, is being collected by soldiers along the Carolina coast. They have learned that it symbolizes the birth, crucifixion, and resurrection of Christ. In the photograph above (right), an outline of the Easter lily is shown (A) on the top side of the shell. At the center of the lily is a five-pointed star (B) that represents the star of Bethlehem. The narrow elliptical openings (C) are

reminiscent of the five wounds made in the body of Christ during the crucifixion. On the under side of the shell is an easily recognizable outline of the Christmas poinsettia (D). When the shell is broken open, cells are found, each holding five objects that look like birds in flight (E). These represent doves. Another interpretation of these birdlike objects connects them with the angels who sang to the shepherds on the first Christmas morning.

CHARTING INVASION WATERS is the big wartime job done by the Coast and Geodetic Survey in collaboration with the Navy. Shown below is the E. Lester Jones, one of the fleet of five vessels that survey the entire Alaskan and Aleutian coastline. It is


powered by twin 150-hp. Cooper-Bessemer model EN6 Diesel engines. The Jones and her sister ship Patton are 88 feet long, of wood construction, with 21-foot molded beam, and approximately eight-foot mean draft. They carry wire drag gear, echo

sounding machines, radio for communication and for giving the ship its position within a few yards. Modern equipment allows a three-mile sounding in seven seconds while the ship travels at full speed. (This job used to take four hours.) Ordinarily a peacetime aid to shipping, the Coast and Geodetic Survey is a branch of the Department of Commerce.





POPULAR SCIENCE





TORQUE GAUGE of screwdriver type measures the relatively slight holding power of small screws and nuts both with and without lock washers. It was developed by A. C. Millard, of the Bell Telephone Laboratories, New York City. A calibrated spring connects with the cone that clamps the screwdriver or wrench socket. On the upper rim of the cone a removable collar carries a scale to indicate torque.





TRANSPARENT CENTER PUNCH has a bell cap of Plexiglas to enable the operator to position the point visually while centering holes in template work for aircraft construction. Once in place, the punch is actuated by extending a spring with a knob and letting go. At the opposite end is a convenient scriber.



AFTER DISINTEGRATION

STEEL DISINTEGRATOR, made by Don Thomas, of the Clinton Machine Co., Clinton, Mich., is used for electrically removing taps, reamers, and broken-off high-speed drills that have become embedded in expensive, machined pieces. A hollow copper electrode (right) is brought into intermittent contact with metal to be disintegrated by a vibrating head. As contact is broken, an arc is made, creating a highly localized heat; while the coolant, flowing through the electrode, breaks off particles by contraction.



Broken tap, embedded in a steel bearing, is disintegrated by the electrical device above for removal. Photos at left show bearing before and after the imperfect tap has been disintegrated






# MODEL TEACHES DRY-DOCKING

FINELY proportioned miniature ships are eased in and out of a scale-model dry dock at the New York Navy Yard to train naval officers in the procedure followed with real war craft. If reproduced full size on the water front, the dry dock would extend 250 feet for every normal footstep alongside the model. From it student officers are enabled to get a concise over-all understanding of the various jobs that must be co-ordinated. The model is also used to instruct shipwrights and riggers in their respective duties in connection with docking.



The miniature ships used for instruction purposes in the model dry dock were built to scale by expert civilian employees in the mold loft of the Navy Yard. They are almost perfect reproductions of the large vessels constructed in the yard for actual naval duty with the United States fleet

Student officers assembled with their instructor around the model reviewing various steps in dry-docking. There are four phases: preparation of the dock, preparation of the ship, docking, and undocking. Each involves many operations vital to safety of ship and personnel



Model dry dock at the New York Navy Yard is used in the training of Navy men as docking officers. An idea of the scale may be had by the types of miniature vessels shown docked. Over-all view gives student officers better comprehension of operations than if they first see them on a full-size dry dock. Also, the teacher can accent operations by repetition





#### FIRST-PRIZE WINNER IN PROFESSIONAL CLASS INCLUDED


GENERAL DESIGN: Low-wing, four-place monoplane with twin tail booms, pusher propeller, and tricycle gear. COST: Around \$2,000.00. PERFORMANCE: Speed of around 115-135 m.p.h., range of 500 miles; good maneuverability and ground-handling characteristics; slow landing speed; and economy of operation.

COMFORT: Plenty of leg room, visibility, quiet operation; ash trays, sunshades, adequate baggage space; heating and ventilation equipment; split front seat, doors on either side; minimum of engine vibration. SAFETY: Tricycle landing gear gives easy landings and ground-handling characteristics; flaps permit slower

## These Are the Planes

We asked the private flyers of tomorrow to write their own ticket. The analysis of 3,345 contest entries shows what they are looking for. A DRAFTSMAN in the evergreen section of the Pacific Northwest wrote POPULAR SCIENCE MONTHLY last fall that of all the things he would like to see incorporated in his postwar private airplane, a foot throttle was on the high-priority list.

He wanted other items of comfort, too, did Tom Phelan of Seattle—a cigarette lighter on the instrument panel, and arm



#### MANY FEATURES THAT INDICATE FUTURE POPULAR TRENDS

landings, spoilers give better glide control; booms enclose propeller; fire extinguishers, two-way radio; spinproof and stallproof features; hydraulic brakes; all knobs flush with the instrument board. ACCESSORIES: Dual or throw-over controls; landing lights, self-starter, heater, glove compartment; all flight instruments; safety belts; emergency tail skids; wheel pants. This prizewinning design in the professional class was submitted by Donald J. Wheeler, an engineer in the Boeing Aircraft Company's plant at Seattle, Wash. It was selected for reproduction here because it embodies many features preferred by a majority of entrants.

## You'll Fly After the War

rests built into seats for his passengers.

Tom Phelan was one of the many entrants in this magazine's "The Plane You'd Like to Own" contest, concluded September 30, who displayed a flair for merchandising. The automobile never would have sold in the millions if it had not had, first, utility; and second, comfort.

The personal-type airplane won't sell in

the postwar years unless it has both in generous proportions. Comfort runs a close second to safety—which is first on the list of demands, by the way—in the features tabulated by the board of judges from the 3,345 entries in the contest. After safety and comfort come good looks, practicability, and performance, in that order.

In the December issue we announced



the winners in the contest, which drew designs from each of the 48 states and 10 foreign countries, and briefly sketched the outlines of the composite aircraft that the buying public will want when the war is over, as reflected in those designs.

This month we are going to make a recapitulation and draw up a bill of particulars. How many of the entrants wanted folding wings? How many wanted slots and flaps, those devices that make for greater safety in flying? How many wanted two engines instead of one? Two-control aircraft?


Some of the answers are surprising. They surprised the judges, and they surprised the judges, and they surprised the staff of POPULAR SCIENCE MONTHLY, which, in the intervening months, has had an opportunity for a more leisurely analysis of the results.

The designs submitted reflected credit on the readership of the magazine. The

entrants knew what they wanted. And what they wanted is a fair sample of the public's tastes in personal air transportation.

As Oliver L. Parks, a member of the judges' panel, put it: "This contest has advanced the thinking and engineering development at least a year in private-plane manufacture."

Composite pictures, like general averages, are intriguing for what they determine in establishing the alikeness of the thinking of large segments of the population. If the readers of POPULAR



SCIENCE MONTHLY have their way, here is a composite picture of your postwar private plane:

A monoplane, with a low wing.

An engine of about 125 horsepower.

A landing gear of tricycle design.

A capacity of four persons.

A speed of about 130 miles an hour.

A range of about 500 miles between refuelings.

In outline the plane will be a wing cradling a fuselage that will carry its power plant in the rear. On either side of the fuselage, anchored to the wing, will sweep



by Carl W. Thompson, Jr., New Castle, Del., to win fifth prize in the nonprofessional class. The model, by the way, flies very well

Ash trays

De-1cers Sunshades

Plying ving Better visibility


Ico-box unit

Television unit Anti-collision device

Built-in heater Good ventilation

Automatic trim tabs

Mant Sefety first



15% 9% 0% 15% 2% 0% 20% 18% 18% 27% 29%

BREAKDOWN of preference percentages reveals interesting differences between professional and nonprofessional entrants. For example, "NP" designers favored the low wing, while "P"class entrants went in more heavily for high wings. Preferences may show only personal taste




#### 14% WANTED FOLDING WINGS

Many entries in both classes featured wings that could be folded, usually in conjunction with roadable design. When roadability was not considered,

the popular method of folding the wings was that used in the entry of Homer O. Hacker, "NP" second-prize winner, of Dayton, Ohio, whose original sketch is reproduced at left, below. In the drawing directly below, Hacker

shows how compactly such planes, with their wings folded, can be stored in a hangar. This entry included many features that rated high preference among all the contestants








That was the vote among nonprofessionals; "P"-class entrants went 36 percent for the high wing. This interesting example with twin tail booms was submitted by Nicholas F. Pederson, of Hasbrouck Heights, N. J. Note that his design features flaps and a nose wheel that retracts through doors in the fuselage

back a boom to accommodate the tail stabilizing and control surfaces.

Safety considerations, of course, came first. That was natural. Americans have always demanded a high safety factor in their automobiles; it is even more imporon tricycle landing gear the majority was agreed. There is a story behind that. As a safety factor, tricycle gear was a feature of practically all the earliest airplanes, built just after the turn of the



COMPORT WHILE FLING WAS A PRIME CONSIDERATION century. tricycle-undercarriage plane sits on the ground with all the stability of a milkmaid's stool. It permits the wing to be at a negative MARKINGS on instruments (no lift) angle of attack at the start to show safe operating conditions were suggested by Herof the take-off run and during the man Carpenter, Raleigh, N.C. landing run. Tricycle wheels afford a pilot a lot more visibility than does the more conventional undercarriage. The

IAT RACK pro-

osed by C. Pear-

on, Los Angeles, and A. V. St. Ger-

nain, Dayton, Ohio

WINDOW in floor

of nose for land-

ings. Suggested by

Lt. James W. Sheid,

of Deming, N. M.

DOOR LATCH was

an idea of Pfc. Rich-

ard Park, of New York

SUN SHADES, accordion pleated, keep glare out of cockpit of the plane designed by William Drake, Malden, Mass.

AUXILIARY fuel

tanks for luggage

compartment. From

Lt. William Craig.

of Lemoore, Calif.

Tricycle wheels afford a pilot a lot more visibility than does the more conventional undercarriage. The nose doesn't stick up to obstruct his view of the ground while taxiing. Moreover, as an added safety factor, a tricycle-wheel job can be taxied in circles by a novice in a 40-mile wind. It takes an expert touch on the controls to do that in a plane equipped with two main wheels and a tail wheel.

One of the principal reasons why tricycle gear was abandoned as the airplane grew up was that a level wing provides no braking action in the landing run. In those days, wheel brakes were unknown, and the "drag" of the uptilted wing was counted on to bring a plane to a stop more quickly. Today, good brakes enable a pilot in a three-wheeled plane, coming in for a landing at considerable speed, to stop as "short" as a pilot using conventional gear in a full-stall landing.

Nearly 75 percent of the nonprofessional entrants and more than half of the professionals specified tricycle undercarriages.

Then there was the problem of propeller placement. A whirling propeller is potentially dangerous. People can walk into it on the ground—as not a few have. So nearly 50 percent of all entrants in both classes wanted the propeller in the rear of the cabin, enclosed in most instances between twin booms extending backward to carry the tail stabilizing and control surfaces.

The contestants had other reasons for favoring pusher propellers. Since the propeller creates much of the noise developed by an airplane in flight, putting it in the rear reduces the noise level. The pusher provides better visibility forward, reduces the chance of getting engine fumes in the cabin, and—an important safety consideration—creates less danger to the occupants in case of fire.

Incidentally, speaking of engines, that jet-propelled design of Pfc. Don L. Fotheringham, U. S. M. C., FPO, San Francisco, winner of the \$1,000 War Bond first prize among the non-

POPULAR SCIENCE

#### MANY INTERESTING NEW ACCESSORIES WERE SUGGESTED

professionals, created quite a stir. It was revolutionary thinking. But his ideas had solid support. The turbine—related in principle to jet propulsion—has been adapted to locomotives by one of America's big railroads, and automotive engineers are talking freely of the day when the gas turbine may replace the internal-combustion reciprocating engine in your automobile.

But only six percent of the nonprofessionals wanted jet-propelled craft, and only half that proportion of professionals favored them.

Safety, of course, meant the incorporation in the designs of the standard devices to insure control at low speeds. Forty percent of the entrants in each class specified slots and flaps. The slot insures a smooth flow of air over the ailerons for lateral control when the wing is at, or even below, the stall point. The flap, called a "high-lift device" by the engineers, actually adds to the wing area or so changes the shape of the wing as to achieve the same result.

Interestingly enough, only 14 percent of the nonprofessional entries and 16 percent of the professional were designed to be spinproof. Yet there was no lack of ideas for other safety devices. Charles E. Planck of Arlington, Va., for instance, favored the installation of a stall warning device on the leading edge of the wing. Partly as a safety factor, 29 percent of the nonprofessionals and 20 percent of the professionals specified two engines. Stanley D. Whitaker, of Los Angeles, winner of a \$25 War Bond in the professional class, submitted a design with wings that pivoted to maintain a correct angle of lift regardless of the attitude of the plane as a whole.

Another entry figured that small rocket units attached to the underside of the wing would give his plane that extra speed he would need in an emergency. He was on solid ground, too—U. S. military planes now use rocket-assisted take-off. Not to be overlooked was a suggestion by Murrel D. Hobt, at the AAF convalescent hospital in St. Petersburg, Fla., that spring-fitted safety belts be provided.

Comfort features abounded. If there is anything typically American, it is a demand for comfort. Many of the entries included a commercial band on their radio sets for enter-



tainment during those long hours in the air on cross-country trips. And there was something else behind that, too: a simple "homing loop" on an airplane, tuned to a commercial-band broadcasting station, can be of inestimable value in air navigation.

The enemy knows that. That's why he shuts off his broadcasting stations when our bombing fleets take off to saturate his war industries with explosives.

There were other items of comfort specified: rear-view mirrors, so a man wouldn't have to twist and turn in his seat to see what was behind him as he made a turn or a climb; better ventilation, glove compartments, ash trays, sunshades, heaters, extra leg room, and plenty of baggage room. The owner of a personal-type airplane can't get full utility out of it unless he has space to stow away his fishing tackle, golf bag, a picnic hamper, bags, and Junior's playthings.

Homer O. Hacker, of Dayton, Ohio, who collected \$500 in War Bonds as second-prize winner in the professional class, wanted built-in hangers for coats and spare jackets. And, to simplify the job of tying down his aircraft for the night, he included a steel roll-up device for the underside of the wing that could be attached to a stake or other object.

Several designers, including Harold B. Stucky, of South Hutchinson, Kan., winner of a \$25 War Bond in the nonprofessional class, specified a ladder for easy entrance to his airplane. Other entrants had their



#### 15% WANTED A HELICOPTER

ladders sliding out of the floor or door, and even out of the wing. Going the whole way on comfort, some designs were complete with built-in beds.

More than half the nonprofessionals wanted fourplace planes, while 43 percent of the professionals said that would be the amount of seating capacity they would require. Several designers suggested a front seat wide enough for three people and a small fold-up seat behind it.

But-and here was a poser for the judges-only eight percent of the nonprofessionals and six percent of the professionals wanted planes with two controls instead of three. A two-control airplane dispenses with rudder pedals by integrating the rudder control with the ailerons or by carrying a fin so designed as to overcome the normal "yawing" movement in a turn.

The chances that your postwar plane will have a wing attached to the bottom, instead of to the waist or the top, of the fuselage are pretty good, judging by the contest preferences. Almost every second one of the nonprofessional entrants preferred the low wing. Only every fourth one of the professionals wanted it. If you fly an airplane, you know what

the choice between the low wing and the high wing comes down to: largely a personal preference.

In a turn, a high wing blanks out the area into which you are turning. A low wing blanks out your view of the ground. A high wing has "pendular stability." A low wing provides a lot more all-around visibility. A high wing supplies clearance over such ground objects as bushes. A low wing is cleaner and has less "drag" because normally it has no struts.

The nonprofessional contestants favoring high-wing monoplanes ran to 18 percent, while the professionals totaled up to 36 percent; the mid-wing type enjoyed a vote of eight percent among the nonprofessionals and 17 percent among the professionals.





Another surprise was the small number of contestants pinning their hopes on rotating-wing aircraft. Fifteen percent of the nonprofessionals and 10 percent of the professionals favored helicopters. This exceptionally detailed design and construction plan was entered by Cpl. Robert W. Huzzard, of Wilmington, Ohio. It has contra-rotating rotors

Then there was the vote on amphibians. The amphibian is a sort of jack-of-alltrades. If a smooth landing surface is available on the ground, the amphibian can use its wheels. If it can't find smooth ground, or if the pilot simply chooses to use a water surface by preference, it can be put down on a lake, a river, or the protected blue water of a cove. The pilot who likes to operate off water makes an interesting discovery when he begins exploring the surface of continental United States: it is pitted with depressions full of water. One pilot using an ordinary seaplane flew all the way across the northern tier of states from the Atlantic to the Pacific and never lacked a landing place.

One out of five of the professional entries

#### 16% WANTED AN AMPHIBIAN

The versatile personal plane seen at left in drawings by A/S Perry S. Clark, of La Junta, Colo., was among the 20 percent of professional entries favoring land-and-water craft, as against 16 percent of the "NP" class. It serves not only as an amphibian plane but also as an open car, closed car, and boat


and 16 percent of the nonprofessional specified an amphibian-type airplane. Louis Aron of Hamilton, Ont., entered a design with wheels fitted into the sponsons, or water stabilizers. Mounted horizontally when the plane was waterborne, they were turned downward for land operation. The third prize winner in the professional class, AAF Capt. Adam J. Stalzenberger, Wright Field, Dayton, Ohio, submitted a sleek, two-place amphibian with a molded plastic hull. He used wing floats as housings for wheels. His design won him \$300 in War Bonds.

The straight seaplane fared badly. It drew support from only five percent in each class of entry.

There were other surprises. Notwithstanding the considerable publicity given rotating-wing aircraft in the last two years, only 10 percent of the professional and 15 percent of the nonprofessional wanted whirligigs. Of the contestants who did submit designs with whirling wings, two gave the judges pause. Henry G. Howell, of Los Angeles, submitted a two-bladed "paddle wheel" helicopter intended to carry two passengers. Another, also for two passengers and fitted with four blades operating on countra-rotating hubs, was entered by Cpl. Robert W. Huzzard, of the Clinton County Army Air Field, Wilmington, Ohio.

The judges frankly had some preconceived notions of what kind of designs would be submitted in the contest. They figured, for instance, that the readership of POPULAR SCIENCE MONTHLY would heavily favor types of planes that could be converted to highway use. And they found that they were mistaken.

The vote on "roadability," as it is called, ran even lower than that on rotating-wing aircraft. Nevertheless, some novel roadable-plane designs showed up. H. D. Boggs, of Omaha, Neb., for instance, drew up a fuselage that could shed its wings and be cradled in an automobile chassis for highway use. For flight, the fuselage was lifted from the chassis and fitted with wings. A single engine, both for the road and for flight, was mounted in



road and for flight, was mounted in the fuselage.

Incidentally, but 14 percent of the nonprofessionals and seven percent of the professionals wanted folding wings.

The professionals practically ignored airplane construction incorporating plastics or plastic-impregnated plywood. Seven percent of them liked plastics. But 20 percent of the nonprofessionals toyed with the idea of plastics.

The choice on aircraft prices in relation to speed, carrying capacity, and solidity of construction was one of the biggest surprises of the contest. It was natural to assume that the public would want a low-priced airplane. A decade ago a Government department, in fact, publicly encouraged manufacturers to produce a "\$700 airplane" for the average family purse in the thought that a modest price would lead to more widespread private flying by putting airplanes within the reach of a larger proportion of the population.


But the contestants said most emphati-

cally no, they preferred to buy planes priced in the same class as the better automobiles. They wanted nothing under \$1,000 if it didn't pay for a better type of aircraft, and they backed up their statement with designs that included luxury items. Luxury items cost money.

Popular Science Monthly is proud to have sponsored the "Plane You'd Like To Own" contest. It set a high-water mark in surveying the public's tastes in postwar personal-type aircraft. Magazines and newspapers throughout the country printed news stories about it. Undoubtedly, it will contribute to the advanced thinking going on in the rooms marked "No Admittance" in factories where tomorrow's designs are in the making.

Planes incorporating many of the features in the plane you'd like to own will be rolling off the assembly lines pretty soon.

When, at last, you are able to walk into a salesroom on "airplane row" and pick out a sky runabout, it will show the results of this sampling of private-flyer opinion.



# Big Mo

This is our mighty Missouri. With three other lowa-class battleships now commissioned she will help deliver the knockout against the Japs in the Pacific.

Official U. S. Navy Photos


BIRD'S-EYE VIEW. Looking down on the bow during AA battle practice as a 40-mm. "quad" (quadruple antiaircraft mount) goes into action. The decks of the big battle-wagon fairly bristle with these "stingers." Air-defense officers and a lookout, whose binoculars are fixed on a handlebar mount, stand on a platform in foreground

MUFFLER. For protection from the weather, Fire Controlman 3rd Class James Tucker of Richeyville, Pa., adjusts a gun "bloomer." This heavy rubber cover fits at juncture of a 16-incher and the turret. This ounce of prevention helps to keep "Big Mo's" Sunday punchers in prime shape for the all-out battle against the enemy



CRASH! Triple blast from the Missouri's No. I turret spells death and destruction to the enemy as 16-inchers roar simultaneously. Water is churned up by fire from the newest addition to Uncle Sam's mighty seapower








FIRING in a spectacular burst of flaming gases, the center guns of the two forward 16-inch turrets send out their 2,400-pound shells. The guns in action are elevated for long range. The powder charges needed to fire these monsters of destruction are contained in bags of purest silk, which burns to the last shred and leaves no smoldering spark that might pre-ignite the next load. Firing a single 16-inch gun consumes the equivalent of 300 pairs of silk stockings. The six 16-inchers pictured are two thirds of the main battery

ORDERS. Comdr. Jacob E. Cooper, USN, the executive officer, passes an order to his "talker," Seaman 2nd Class Vincent Domino, on the open bridge during gunnery practice. Domino transmits the order by battle telephone to turrets and fire-control stations

FLASH! Five-inch guns of the secondary battery fire at night and light up the ship with a brilliant glare. The crack of these guns rivals even that of their big brothers, the powerful 16-inch rifles. Twenty of them are ranged along the Missouri's sides in two levels of twin mounts, and the dual-purpose guns are effective against air and surface targets









RUBBER MAT

NEW BRAKE CLUTCHES ROAD when lowered in front of rear wheels, which roll upon it to a standstill and drag the apronlike pad on the pavement. Designed as an emergency brake, this invention by Arch Robert Jackson, Shavertown, Pa., supplements the regular brake equipment standard on motor cars. It consists of arcshaped leaf springs to which is secured a rubber mat, the bottoni surface of which is corrugated to provide friction on the pavement. For use on icy road surfaces in winter, calks are provided, extending through the rubber. A special hand lever beside the driver controls the raising and lowering of the brakes through cables extending to transverse bars that hold the mats ready in position.


FLUORESCENT HOME LIGHTING may be made available through a small spherical lamp devised by Jefferson E. Gates, Jacksonville, Fla. Unlike the system used in commercial and public establishments, it involves no unusual expense of installation, since the new lamp is provided with a specially designed adapter for attaching to conventional light sockets and for housing the necessary ballast and starter units. The lamp may be easily disengaged for replacement without the adapter's having to be removed from the socket. As with other fluorescent lights, the heating coil must be energized before the bulb can be lighted.





HERE ARE THE "MAKINGS" and a machine to fashion them into well-tailored cigarettes, all contained in one pocket-sized unit. The outfit was originated by Maurice Alland, of Los Angeles, Calif. It consists of a tobacco can containing a humidifier in the bottom, while on the inside of the lid is secured a clever device for rolling cigarettes with almost professional dexterity and neatness. There is also provision on the can for holding a supply of cigarette papers, together with fancy tips or tips that can be used as snuffers, to say nothing of a package of paper matches. All the user needs to supply in addition is a minimum of effort, plus the habit.

#### the inventors



PINCER COAT HANGER holds clothing safely, and may be made entirely of wood, plastic, or other composition. Constructed in two interlocking parts, so designed that their leverage establishes a firm grip on the supporting hook or rod, the hanger is easily disassembled for packing. It was invented by Osborne L. Horton, of Baltimore, Md.





AN INFLATABLE CHAIR to provide comfort on beaches, lawns, shipboard, airplanes, or motor vehicles is a device originated by Kenneth Graeme Hann, Cyncoed, Wales. The chair form is made of suitable fabric or other material, inside of which is arranged a series of rubber tubes equipped with one or more valves for either lung or pump inflation. Side braces help to preserve the shape of the chair when it is in use, and additional tubes will raise it from the ground when a higher seat is desired. Aboard ship, it has the extra advantage of its potential value as a life preserver.

BABY GOES SKIING when there is snow on the ground if mother has a set of these sleigh-runner attachments for the carriage. The wheels fit into curved casings mounted on the runners, and are clamped by an easy operation. Adjustment means are provided for wheels varying in size, tread, and wheelbase. For rough or uneven ground, there is a separate runner for each individual wheel to obtain greater smoothness of going. When the runners are not required, they may be attached to the underside of the carriage. The invention is by Emanuel R. Morando, New York City.





## LIFE CYCLE OF OUR

# Migrating Butterfly

The brilliant Monarch flies from the Gulf to Canada as it feeds on sprouting milkweed.


HERE is the life cycle of the familiar Monarch butterfly, told in a new and remarkable series of Kodachromes by Corydon M. Grafton, noted amateur photographer, of Norwalk, Conn. These are typical examples of the results he obtains by special techniques of his own devising.

(P.S.M., Feb. '45, p. 100.) The Monarch migrates between the north and south with the changing seasons. Some butterflies live to complete the round trip. When a traveling swarm alights to rest, bare tree branches appear covered with foliage. The prolific Monarch raises several broods a year.




Showy colors of adult Monarch are protection against its being eaten by the birds, for they advertise its unsavory flavor. Other, more tasty butterflies take advantage of this by mimicking the coloration of Monarchs

Monarch caterpillar, when it has grown long and plump, turns into a chrysalis, the pupa stage of a butterfly. It hangs itself from a twig with a silk button, and acquires a green shell spotted with gold. Later the chrysalis becomes semitransparent, and, finally splitting, releases the butterfly










# ELECTRICITY SMOOTHS PAINT

PAINT "tears" are drops that hang from pieces that have been coated by dipping. A method for "de-tearing" such objects electrostatically has been devised by the Harper J. Ransburg Company's electric-coating division, Indianapolis, Ind. The coated article, with accumulation of excess material at drain-off points, is electrically freed from this excess after the dipping operation, and then goes into the baking oven to acquire a uniform finish. The article is carried over a high-voltage conducting grid that exerts strongest force at prominences.

Tears drip off an ornamental bracket ready for treatment


"DE-TEARING"

2 Electrostatic attraction removes tears when grid is "on"




3 Same piece de-teared. Even surface requires no hand work

Without benefit of the electrostatic field, the cylinder (at left center) is sprayed on only one side




With the current switched on, the same spray, during the same period of time, completely coats cylinder





S TUDY the accompanying clock face, and you'll be able to tell time by ships' bells and by the 24-hour military system. First, it explains the six watches of Navy time. The bell, ringing from one to eight times, sounds every half hour during each four-hour watch. Odd-number strokes always mean half-past the hour. In military time, also used on teletype air reports and radio

control, the first two digits indicate the hour, and the second two digits the minutes; 0720 is 7:20. Add 12 to a.m. figures to obtain the corresponding p.m. time. Thus, 1920 is 20 minutes past 19, or 7:20 p.m. The black minute spaces just before the hour and half hour indicate two-minute periods of radio silence, designed to allow weak distress signals to be picked up.






B LAZING a trail for future commercial navigation across the top of North America, the Canadian Northwest Mounted Police schooner St. Roch last summer completed the first round trip ever made through the Northwest Passage.

Starting at Vancouver, B.C., in 1940, the specially constructed polar ship made


the pioneer west-to-east passage to Halifax, N.S., in 28 months, spending two winters locked in the ice. The return trip was made in one season—86 days from Sydney to Vancouver.

Equipped with sails and a Diesel auxiliary engine, the polar police boat has a top speed of six knots

Staff Sergeant Henry A. Larsen, skipper of the St. Roch, says that small wooden vessels can go through the Northwest Passage in summer. His own ship has timbering two thirds heavier than normal, copper sheathing, and an outside covering of Australian ironbark to resist crunching ice.



### CHRONOGRAPH MEASURES MUZZLE VELOCITY OF SHELLS FROM BIG GUNS



OW fast a shell leaves a gun's muzzle now is determined by superfast chronographs at the Aberdeen, Md., proving ground. Suitable for testing projectiles from weapons of any size, they help to perfect guns and ammunition, and to compute firing tables used by U. S. gun crews. First mag-

netized, the shell is fired through two coils suspended a known distance apart. Each passage generates an electrical signal. Between signals, an electronic device called a cycle counter totals the number of electric impulses from an oscillator, which delivers 100,000 a second.



# We Move the EARTH for COPPER

From spears to dive bombers, it has always been a prime necessity of war. How America is supplying the vast needs of today.


#### By HAL BORLAND

If IT hadn't been for a spring freshet in a Utah canyon, the Japs might still be holding a strategic Pacific island from which, instead, our bombers are now operating. That freshet leached copper sulphate from the stripping dumps of a copper mine, and from that sulphate was recovered copper vital to the dive bombers that cleared the way for our forces. By such margins are battles, and even wars, won.

A strategic metal, copper not only alloys our bronze and all the duralumin in our warplanes; it provides the nerve systems for our motors, our automatic controls, our radar, and other electrical equipment. Fortunately, we do not have to depend on leachings from mine dumps for the bulk of our copper; but war needs have so strained our production that even minor sources are important.

Copper is the only metal ever found abundantly in nature in a pure state. Long before the white men came, American Indians were mining it along the south shore of Lake Superior—copper so pure it could be hammered into tools and ornaments just as it came from the ground. In 1857 a pure copper mass of more than 400 tons was found in those mines, which have now been worked more than four centuries. What pure copper is left in them, however, today is found only as a veining of cementing material in a conglomerate rock.

To find America's copper now you must



wander all over the map and into mines which produce a considerable variety of copper ores. Principally, copper comes from Arizona, Montana, Michigan, Utah, Nevada, and New Mexico, but a dozen other states ranging from Tennessee to South Dakota are also producers. As pyrite, malachite, cuprite, chalcocite, and azurite, the ore comes from shafts a mile deep and from man-made canyons open to the sky. From these ores the copper is extracted by crushing, washing, concentrating, smelting, and electrolytic action. Silver is copper's only rival as a conductor of electricity. Iron is the only metal used more extensively than copper.

The biggest of all copper mines, both in area worked and in ore handled, is that of the Utah Copper Company, at Bingham Canyon, in the Oquirrh Mountains about 30 miles southwest of Salt Lake City. An opencut mine, it looks like the Yale Bowl grown to gigantic proportions—a bowl more than a mile and a half across, brink to brink, and nearly 2,000 feet deep.

The ore that comes from this mine is, in the geologist's words, a monzonite porphyry

One of Bingham's 41 caterpillar-mounted electric shovels scoops up a five-cubic-yard mouthful of loose ore preparatory to dumping it into one of the cars in the background. Ore is blasted loose 1,500 tons at a crack

containing finely disseminated sulphides. There are also minute quantities of gold, silver, and molybdenum in the ore, some quantities of which are recovered. Although the molybdenum content is scarcely more than a trace, so much ore is handled that this copper mine is also the second largest producer of molybdenum in the world.


Open-cut mining is essentially a job of earth moving. It consists simply of scooping away surface soil and debris, breaking up the ore beneath, and moving the ore to the concentrating plant. At Bingham Canyon the principal mining equipment includes such things as 41 caterpillar-mounted power shovels, each of which can handle five cubic yards at a scoop; 115 miles of electrified standard-gauge railroad track that coils around the 20-odd benches of the pit; hundreds of ore cars and dump cars, dozens of

big electric locomotives, over 150 miles of high-tension power and trolley lines, and a fleet of bulldozers.


Stand on the brink of the pit and you will see a scene so huge that the activity of 2,000 workmen is virtually lost. Look a little closer and you will see a shovel at work on a bench across the way. Then another, and another. You count them and tally up more than 30, most of them looking like toys. Trains creep around the benches—one, two, a dozen, even more trains than shovels; and they, too, are almost lost in the immensity of the operation. Benches that look like seat tiers in the Yale Bowl are 65 feet high and 100 feet wide, and each bench has its railroad track, its overhead power line, its working space for a power shovel.

Whistles scream, and the echoes bounce back and forth within the canyon. The

#### REFINEMENT BY FLOTATION, SMELTING, AND ELECTROLYSIS




Trainload of Montana ore rolls into the yards of the Anaconda Reduction Works at Anaconda, Mont. Like Utah ore, it has low copper content







2 The first step in refining the low-grade ore is to grind it up into small pieces in a gyratory crusher so as to break the copper ore loose from the waste rock


6 Final refinement comes with electrolysis, for which copper must be made into anode slabs (at top). From anodes, mineral is carried to pure-copper cathodes









#### PRODUCES AN ALMOST PURE COPPER FROM LOW-GRADE ORE




- 3 After a sifting process, the ore is dumped into a water-and-chemical solution from which copper-rich ore is skimmed off the top
- 7 These cathodes, representing accumulations of copper 99.97 percent pure, await hotwater bath that will rinse off the electrolyte



- 4 Dipping into the ore, a huge drum picks it up on its sides as it turns and then forces air through the ore. When it is dry, the ore peels off in sheets
- 8 Cast into ingots, copper awaits shipment to war plants where it will be fashioned into nerves and sinews for tanks, planes, ships, and other weapons





signal means that drillers have driven blast holes into the toe of a bench and are about to set off their powder charges. There is a dull rumble and a dust cloud rises. About 1,500 tons of ore are loosened with each charge set off. The shovels move up and the trains move in. Foot by foot, the levels are gnawed back. Ton by ton, the ore is scooped out and hauled to the concentrating plants 18 miles away. Pound by pound, the copper comes from the earth.

The stripping dumps are an additional source of recovery. Topsoil, waste, and ore too low-grade to concentrate are hauled by rail to gulches cutting the walls of the canyon below and beyond the mine. In these dumps, the small fractions of copper sulphides become oxidized into copper sulphate, which is water-soluble. Rains filtering through the dumps leach out the sulphates in the form of copper-sulphate solution. This run-off is trapped behind catch dams and piped to a precipitation plant where the solution runs through long vats containing shredded detinned cans. There, by a chemical replacement process, the copper and the shredded iron of the cans change places so that the copper is deposited in the bottom of the vats and the iron goes out in solution in the water. So simple and efficient is this recovery that pipe lines now sprinkle the dumps periodically to supplement the rain and melting snows and thus keep the leaching process in constant operation.

The porphyry ores of Bingham Canyon show none of the brilliant colors the layman usually expects in copper minerals. These ores are a light granite gray, with the occasional glitter of iron pyrites, or "fool's gold." For the spectacularly beautiful ores, such as azurite and malachite, one turns to Arizona, where these blue and green copper

carbonates are relatively plentiful, particularly around Bisbee. But the bulk of America's copper today comes from ores that would not especially delight the colorist, ores that even the early copper miners would have ignored.

It was native copper, of course, that man first used, copper that was found either in its pure state or in natural alloys. Objects made of such copper and alloys have been found in Egyptian remains dating as far back as 4700 B.C. And a considerable variety of both copper and bronze objects has been recovered from excavations of Mycenaean, Phoenician, Babylonian, and Assyrian civilizations of as early as 1800 B.C. The Egyptians probably obtained their copper from the Sinai Peninsula, and the early Greeks and Romans got theirs from Cyprus, which gave the metal both its name and its chemical symbol.

Here in America the early French explorers heard Indian tales of copper deposits around the Great Lakes, but no one worked those deposits extensively until about 1845. Early in the eighteenth century, however, copper ore was mined in Connecticut, New Jersey, and Pennsylvania, and attempts were made to smelt it. The venture had little success, but a few shipments of the ore were sent to Europe.


All through colonial years copper was an important metal, but not a major metal industrially. It was worked primarily by coppersmiths, of whom Paul Revere, who was also a silversmith, was one of the most outstanding. It was he who made the copper and brass fittings for the warship Constitution. At about that time he wrote to a friend that "no man but myself in the four New England States can melt the copper and draw it into spikes," and that he "could

#### COPPER.

#### **DOWN THROUGH THE AGES**



Objects made of native copper have been discovered in ancient remains that date back as far as 4700 B.C.




This conception by Da Vinci of a bronze triple-barreled fieldpiece paved the way for today's breech-loading guns



Paul Revere and other coppersmiths made copper and brass fittings for ships, and rolled sheets to cover their hulls

#### AT WAR AND IN INDUSTRY

#### **ELECTRICAL EQUIPMENT**



Switches, bus bars, contacts, and wiring demand vast amounts

#### **AUTOMOBILES**



Radiators take a lot of copper; more goes into wiring, alloys

#### BUILDING



Rust resistance makes it tops for flashings, gutters, and plumbing

#### LIGHT AND POWER LINES



Its high conductivity leaves it unrivaled as a current carrier

#### WARSHIPS



More than 225 tons go into one destroyer. Think of the lowas!

#### SHELLS



Soft rotating bands of copper give them their spinning flight

#### PLANES



A fighter requires a half ton; a Flying Fortress, 2½ tons!

#### MEDICINE



"Copperplating" is a treatment now used for "athlete's foot"

make copper so malleable as to hammer it hot." In 1809 he rolled the plates from which a boiler was made for one of Robert Fulton's steamboats.

But copper did not really come into its own until the opening of the Great Lakes mines and, not long after, the rise of the electrical industry. And it is an interesting point that while copper serves electricity so well, electricity provides the best means of refining copper.

There are three principal ways of handling copper ores. The carbonates and oxides are first treated in a blast furnace. The sulphide ores are roasted, worked in a reverberatory furnace, and finally put through a converter resembling a Bessemer. Ores with only small fractions of copper are crushed, sifted, and concentrated by flotation, in which oil and water are added to the ore, the rock sinks, and the desired ore particles are held suspended in the froth of oil and water. From the blast furnace comes a copper concentrate known as matte. From the converter comes blister copper. And from the flotation process comes a concentrate which is also smelted into blister copper. Both the matte and the blister copper, however, are refined electrolytically.

This final step calls for using the blistercopper slabs as anodes in tanks of copper sulphate solution. Pure copper sheets are used as cathodes, and direct-current electricity is passed through the solution. Pure copper is transferred electrolytically from the anodes to the cathodes, and the impurities in the original slabs collect as sludge, from which by-products are recovered. The pure copper deposited on the cathodes is then ready to be melted down, cast in bars, and formed for its final use.

Although silver is a better electrical conductor than copper, its relative rarity and its high price remove it from competition. It is being used to a limited extent now for special purposes—as heavy bus bars, for instance—but only on "loan" from the United States Treasury to release copper for more critical needs. (P.S.M., July '44, p. 122.) This emergency substitution will not continue beyond the duration of the war.

No one has ever found an adequate substitute for copper, and there are no indications that one will be found in the near future. If one were in sight, even for use only in the electrical field, the hard-pressed Germans, who have turned to nearly every substitute in the book, would be using it. But captured German material still shows copper, brass, and bronze being used in critical places, and no important substitutions for copper in electrical equipment. Germany has met its copper shortage by stripping civilian life. For copper remains king in its own broad and varied field, particularly as the nerve system for the electrical apparatus which is indispensable in modern war machines.

## Take your Pick at the WORLD'S BIGGEST



OULD you use a pair of paratroopers' snowshoes? And don't say "no" too quickly, because you may soon have a chance to buy them at a throw-away price from some store dealing in surplus war goods.

At first glance, you'd say that their only value would be for sportsmen in the far north, or boys who want to go snowshoeing for fun. When the first batch of snowshoes was offered for sale by the Government, however, a bright designer of novelty goods snapped them up. All he did was to add short wooden legs and a glass top to each. He then sold them as small cocktail tables.

It took still more imagination to find a use for a lot of officers' rowelless spurs left over from World War I, which turned up recently in a warehouse. One manufacturer converted some of them into ornaments for horsey ash trays. The remainder went to the promotion manager of a children's Wild West radio show, who distributed them as premiums. But what can be done with 100,000 hand-grenade aprons, now awaiting disposal, or flashlight cases without tops, or firing pins for heavy artillery, or wagon singletrees and axles?

Vast quantities of war goods of this nature will go on sale shortly. If you put your wits to work, you will be able to find good use for some of the items in your home, in your workshop if you have one, or

#### SOME OF THE GOODS THE GOVERNMENT PLANS TO SELL

#### FOR THE HOME

Air-conditioning units Bells, chimes, gongs Brooms Brushes Clocks Cutlery **Electrical appliances** Fire extinguishers Floor coverings **Furniture** Glassware Heating equipment House furnishings Ice refrigeration units Lamps Lamp shades Lanterns Laundry equipment Lighting fixtures

Lockers

Mechanical refrigeration units Hand tools
Mirrors Hardware
Musical instruments Insect screen

Phonographs
Pillows
Plumbing equipmen

Plumbing equipment Pottery Radios

Rodio parts
Recreation equipment
Shelving

Tableware Textiles Water coolers

Spring scales

#### FOR THE SHOP

Ammunition chests and boxes Aprons Cabinets and chests Gaskets Grinding wheels Hardware
Insect screens
Ladders
Machine tools
Nails, screws, bolts, rivets, etc


#### FOR THE FARM

Agricultural machinery
Apiarists' supplies
Dairymens' supplies
Farm implements
Fence wire
Harness
Lanterns
Live animals
Poultrymen's supplies
Storage batteries
Tractors
Trailers
Trucks

#### FOR OUTDOORS

Airplanes Ammunition Belts Bicycles Boats Buoys Carbide lamps Floats Jeeps Mosquito nets Packs Rafts Skis Sleeping bogs Small arms Snowshoes Sporting goods Tents Tires Trailers Wagons

### BARGAIN COUNTER



in connection with your sports or hobbies. To take a single item, the familiar mosquito bar may be put to many uses. The Office of Surplus Property, Treasury Department Procurement Division, which is in charge of the disposal of most of the consumers' goods in which the average man or woman is interested, has addressed a letter to the buyers of department and sporting-goods stores in which it is pointed out that these nets, which are 30 inches wide, 74 long, and 39 high, and are available in considerable numbers, may be used in civilian life for converting a cot or glider on the back porch into a sleeping room, for covering a baby bed or carriage in the yard, and for making an outdoor playhouse for small children. They will protect Boy Scouts from insects on (Continued on page 207)

#### Cash Prize Contest \$200 for the best letters on

#### "HOW I'LL USE SURPLUS WAR GOODS"

OF ALL the surplus war material which is now becoming available for civilian use, what would you most like to own? How would you use it?


For letters from readers suggesting the most ingenious and valuable ideas, POPULAR SCIENCE MONTHLY will make the following awards:

FIRST PRIZE	\$100
SECOND PRIZE	. 50
THIRD PRIZE	. 25
FIVE PRIZES, \$5 EACH	25
TOTAL	\$200


Put your wits to work and write a letter of not more than 250 words telling what it is you want and why you want it. In case of a tie, both contestants will be awarded the prize tied for. Address the Postwar Idea Contest Editor, Popular Science Monthly, 353 Fourth Avenue, New York 10, N. Y., and mail it on or before March 31, 1945.



INSECTICIDE BOMB should prove a boon to housewives and also around the farm



ASSAULT BOATS . . . CHAIN SAWS. Outdoorsmen will find a choice of equipment for both work and play



# WHY JAPAN CAN'T WIN ON LAND

The Nips are doomed when they meet us in the open. Their tanks and guns can't match ours.

#### By GOLD V. SANDERS

Photographs by WILLIAM W. MORRIS

Drawings by STEWART ROUSE

WHEN MacArthur's invading infantrymen broke away from the Lingayen
beachheads into the valleys of central Luzon,
they started a new and decisive phase of the
land war in the Pacific. Now, at last, we
had the Japs in the open where we could
get at them with the weight and power of
our superior armor and guns. We knew what
the result would be, from a cold-blooded
comparison of their weapons with ours. We
have captured Japanese war equipment of
all kinds; our ordnance experts have studied
it and found it second-rate, or worse.

The Japs are the world's most brazen copycats. Nobody knows this better than our specialists whose duty it is to examine and test their weapons of war. These experts will also tell you that the Japs are not even good at copying. However assiduously they attempt to duplicate a good weapon of another power, they never succeed in equaling it in quality and performance. In outward appearance their version may look like an exact copy of the original, but closer examination reveals crude work-

manship and a low standard of dimension tolerances. Actual testing shows up the defects to be expected from such workmanship and engineering.

So we know now that our guns outperform and outrange theirs by a wide margin in every category, from shoulder rifles to the biggest field guns. We know that our tanks outclass theirs to such an extent that there is hardly a basis for comparison. All our machinery of war is more reliable because it is well made to close tolerances. Our ammunition

is more powerful, more uniform, and more

All of this will be spelled out in piled-up Jap bodies and smashed equipment when the final battles of World War II are fought on the expansive terrain of Chinaa: they will be, according to our military experts. Up to now, our all-around superiority in weapons has not been fully demonstrated because the Japs have called all the shots. The Japs started the war, and in the first stages they determined where it would be fought—in the jungles. For such warfare they were comparatively well armed. Their shorter-ranged rifles and guns, their many mortars and howitzers were well adapted to this type of in-fighting. They have given us a lot of punishment in the clinches, but now we have learned how to beat them even at their own game. Now we are forcing the fight. We are driving them slowly but surely out of the terrain they chose. In the final rounds they will have to trade punches with us in the center of the ring.

With what can they stop our mighty tanks when that time comes? Their biggest tank gun is a feeble 57-mm. affair of relatively short range and low hitting power. It is carried by their so-called medium

tank, which looks like a relic from World War I. Its armor is less than half as thick as that of our light and medium tanks. Such armor and such guns will be faced by our high-velocity 75's, 90's, 105's and such. Our Sherman tanks, with their 75-mm. guns, smashed their tanks to pieces on Saipan and Peleliu—a small sample of what will happen if the Japs try to meet us in a major tank battle.

Up to now, the Japs have not shown up with bazookas, though this is

#### Here's the Score:

#### ORIGINALITY

What little there is of it is of poor quality. Best original Jap designs are in mortars.

#### COPIES


Even when the Nips imitate weapons of the western powers, they do a bad job, owing to low standards of manufacture.

#### DUPLICATION

Lack of standardization of weapons and ammunition creates confusion and complicates the supply problem.

POPULAR SCIENCE


#### JAPAN'S BEST TANKS ARE NO MATCH FOR OURS




#### ORIGINAL DESIGNS ARE FEW ... AND INFERIOR


90-MM. MORTAR has two hydraulic recoil cylinders that let the barrel drop back about six inches when it is fired. In later models, this idea has been abandoned


ANTITANK GUN. The Jap idea of what it takes to stop a tank (in foreground) is contrasted here with the mammoth German 88. Shells for the Nazi weapon (on stool) are almost as large as the barrel of the 47-mm. Nip gun






#### JAPS ARE CUPTCAIS...AND NOT GOOD AT THAT!





COPY OF U.S. BROWNING. Our .50 caliber aircraft machine gun, shown at left, was the pattern for this Jap weapon, which is used in naval planes. The Jap copy is one of the best of their guns we have captured. Nip naval weapons and ammunition are generally better than army counterparts






BRITISH LEWIS GUN, top right, was copied closely in the Nip machine gun shown beside it. Japs bought a few Lewises in the 30's, then made their own. At top left is Jap cartridge, with British original

a weapon which ought to be easily duplicated. It is considered likely that they will shortly be equipped with rocket launchers of this type, for they have already copied the explosive war head used by us and by the Germans. They are using it on their rifle grenades and cluster bombs dropped from planes. But the bazooka is also a short-range weapon, and they may find it hard to get close enough to use it against our tanks.

With what will the Japs counter our field artillery—the big guns that punched holes in the Siegfried line? They have fieldpieces in almost every category, but inferior ones. Their biggest is a 240-mm. howitzer, which has a maximum range of 11,000 yards. How will it stand up against our 240-mm. howitzer with a maximum range of 25,000 yards? Our 240 is an extremely mobile big gun and can be moved on only two vehicles at 30 miles an hour

ITALIAN BREDA 13.2-mm. machine gun (a little larger than our .50 caliber) also received the flattery of imitation by our Oriental friends. Top gun at right is the copy. The Nips use it as a ground gun and also for antiaircraft work, often in a dual mount. Ordnance men find it inferior to our Browning



#### THEIR COPIES FALL FAR BELOW THE ORIGINALS



FROM THE NAZIS the Japs copied a rifle grenade (bottom), including the "Munroe effect" tank-busting hollow charge (P.S.M., Feb. '45, p. 65)



GERMAN LUGER pistol reappears as the Jap Nambu. The resemblance is chiefly external. Nambu (top) is not a good gun; its ammunition is worse

and emplaced in a half hour or so. The Jap howitzer is broken up into ten vehicle loads for moving.

The longest-range gun the Japs have is their 150-mm., which throws its 89-pound projectile 22,000 yards. With this they will have to counter our 155-mm. Long Tom with a range of 25,000 or more, and our eight-inch gun with its terrific range of 35,000 yards. From here on down to the smallest-caliber fieldpieces, the story is much the same.

The best Japanese antiaircraft gun is a


dual-purpose 120-mm., which they use against both planes and tanks. It is comparable to our 120, but its maximum ceiling is 35,000 feet against our 60,000, and its horizontal range 21,000 yards as against our 27,000. Ours can shoot up to 22 rounds per minute, theirs 12. Their gun has a mechanical director to compute firing data; ours has a marvelous electronic control (P.S.M., Sept. '44, p. 115).

Close study of Japanese war weapons on the whole shows clearly that they counted upon and prepared for a war at very close

#### THEY EVEN COPIED A U.S. GUN OF CIVIL WAR VINTAGE



JAP RIFLED MORTAR at right is more accurate than other mortars because of its rifled bore. As in our old Parrott gun, a band of soft metal at the base of the projectile is expanded in firing and grips the rifling of the barrel



#### INFLEXIBILITY AND LACK OF STANDARDIZATION MAKE



RIFLES are supplied to Jap troops in two sizes: the old 6.5-mm. (about .25 caliber) at top, and the newer 7.7 (about .30 caliber). Older gun was long for bayonet use



CARTRIDGES for 6.5 (top) and 7.7-mm. rifles. Since guns of both sizes may be found in a single company, the supply problem is a headache. The 7.7's muzzle velocity is 2,300 feet per second, compared with 2,800 for U.S. service rifles

range. They went in for mortars of wide variety, and these have been murderous weapons in the kind of war they have been making all through the Pacific islands. The graves of many American Marines and soldiers bear testimony to that.

So great has been the Japanese preoccupation with mortars that they have actually shown some inventiveness in this field. They have at least nine varieties of trench mortars. The wicked little misnamed "knee mortar" was their own creation. Extremely light and simple, it throws a considerable load of death and destruction over the treetops at close range. Their largest mortar, the 90-mm. (3.5-inch) was the first produced with a recoil mechanism to steady it. In one mortar, the Japs devised a crude but effective method of controlling the range. This one has a slot near the base of the tube, which is opened and closed by varying degrees to permit escape of pressure. In still another, the Japs are making use of an American Civil War invention, the Parrott gun. This mortar is rifled. Its projectile has a copper band near the base which is expanded by the propelling charge so that it follows the rifling and thus obtains greater accuracy than is possible with a smoothbore.

Granting that the captured Japanese equipment is not the best they have now, or will have to use against us in the battles to come, what chance do they have to catch up with us in the armament race? A very slim one indeed, according to our intelligence reports. We know pretty well what they are doing, or trying to do, in this respect. Their greatly inferior productive capacity prevents their retooling

to turn out complicated machines of war, even when they have in their possession complete models from which to copy. It takes more time than they will be granted. Instead of catching up, they are falling farther behind all the time.

In their four months of fighting with Russian forces in Manchuria, back in 1939, the Japs found out that their artillery was woefully deficient and that their tanks were virtually useless. Since that time they have been hurrying desperately to make improvements. We know how well they have succeeded, and our ordnance experts say they have nothing we should fear. We are improving our weapons, too, and with a productive capacity 30 times as great as that of Japan, we are constantly widening the margin of our superiority. In a war to the death, the imitator is bound to lose, for he will never have a chance to copy the last great weapon that strikes him down.

How difficult it is for the Japs to produce a new weapon in large numbers is shown in the typical case of their service rifles. Since 1939 they have been substituting a larger-caliber gun, the 7.7-mm., for the old standard shoulder gun of 6.5mm. caliber, that is, a .30 caliber for a .25. At this late date, their soldiers are still partly equipped with one and partly with the other. Even single companies of infantry have been found using both sizes of rifles and a consequent mixture of ammunition. On top of this confusion, they have three different types of cartridges in the 7.7-mm. size, which are only partly interchangeable among the larger rifle and various machine (Continued on page 207)

#### JAP ORDNANCE CONFUSING...EVEN TO JAPS




LIGHT MACHINE GUNS, too, are made by the Japs in two calibers, 6.5 and 7.7-mm. The gun at top, above, with the flash hider, is the 7.7. Both are viewed with respect by our ordnance men. Workmanship is not up to American standards, but design is simple and they spit a lot of lead before they jam

HEAVY MACHINE GUN of 7.7-mm. (about .30 caliber) size is a modified version of the Hotchkiss developed by France. Shoots 200 to 450 rounds a minute with muzzle velocity of 2,400 feet per second. It can use only semirimmed cartridges made specially for it. This cockeyed arrangement is explained by poor thinking at the start, plus inability to change later




Private Moto has three 7.7-mm. cartridges. One can be used in an infantry rifle; another, in a light machine gun; the third, in a heavy machine gun. Americans wouldn't do that






## COMPLETE SHAVING NEEDS have been included by Worthington Fifth Avenue, of New York, in a 2½" by 3½" pocket case.



CIGARETTE ROLLING has again become a popular (sometimes not so popular) pastime with smokers. Here is an entirely new automatic roller that fits the vest pocket and makes a tight cigarette.



#### What's New in Modern Living

soybean shoe patches for resoling footwear at home are spread on worn spots on soles and pressed in with an iron. The material comes in the form of dough. It is manufactured by Elliot E. Simpson Co., of New York.

PLASTIC-COVERED HEELS for women's shoes are available in dull or glossy finish and in a variety of colors. These nonscuff heels, made by Pereles Bros., Inc., of Milwaukee, have wood cores that take leather lifts.





Open the cylinder and fill it with tobacco; then close it and turn the knob several times before inserting a paper. Revolving forks in the gadget equalize the tobacco to help in rolling.



DOLL MUFFS are one of the latest novelties. The one shown below has a doll's head and body, and the muff part forms the skirt. It was displayed at the recent New York exhibition given by the Toy Manufacturers of the U.S.A.












OIL IS REMOVED from skin or metal by an absorbent made by the Waverly Petroleum Products Com-

pany, of Philadelphia, and contained in a pad, as shown at the left.








Complete turning the knob, open the cylinder, and you have a well-packed, professionally rolled cigarette. The device is the invention of and is marketed by John A. Kappeler, of Dayton, Ohio.

MATCHES AS WELL AS CIGARETTES have space in this newly designed cigarette box of transparent



MARCH, 1945



# Things Boil Over at the Model Garage

he has ahead, Gus Wilson tries to start it slowly. He takes his time eating a he-man breakfast, and when he gets to his Model Garage shop he begins operations by doing some easy job before he tackles a hard one.

"It's common sense," he says when we kid him. "If you want an automobile engine to work right and last a long time, you don't drive it hard before it gets warmed up. It's the same way with human machinery. If you start easy in the morning, it'll do more work for you before night—that's been my experience, any-how."

But the morning that old Silas Barnstable picked to put up a squawk about the statement Joe Clark had mailed him, Gus didn't get a chance to start slowly. When he got down to the shop he found Doc Marvin waiting with a job he wanted done quickly because he had to get out in the country to attend a sick kid. It was a bothersome, dirty, hard-toget-at job, and when Doc drove away Gus's normally good temper was wearing thin at the edges.

Then Silas came in, looking even more like a bantam rooster than usual. He's our town's most notorious skinflint—a dried-up little ex-farmer who sold off his rocky acres for suburban building lots during a boom 20 years or so ago.

Silas smacked the bill down on Gus's workbench. "I won't pay By Martin Bunn

it!" he snarled. "It's robbery! Jes' because a body's been foresighted

enough to lay by a few dollars ain't any reason he should be cheated right and left. You've got to shade that bill down, Gus Wilson, or I'll never give your shop another job!"

If Gus had been in his usual good humor, he would have grinned tolerantly at the old crab, kidded him a little, and soon made him admit there wasn't anything wrong with the bill. But he wasn't in his usual good humor, and his temper slipped the leash.

"I'm sick and tired of hearing you yap about every bill Joe Clark sends you!" he snapped. "If you never come in here again it'll be soon enough to suit me!"

For a moment old Silas thought Gus was fooling. When he saw that he wasn't he started to say something, thought better of it, snatched the bill up off the workbench, and stalked out with his skinny little back as stiff as a ramrod.

Gus watched him go, and he began to feel sorry. He hesitated a moment, and then started for the door. But before he got to it, an engine took off outside, and Silas's sedan shot out of the drive and headed up the highway. Gus stared after him.

"Now," he asked himself, "what the dickens made me boil over? That's what comes of breaking my rule to start slow and easy in the morning. Well, it's nothing to worry about—he'll be back in a week or so, ornery as ever."

But weeks added up to a month and more before Gus saw Silas again. Then it wasn't in the Model Garage, but downtown as he was going into the Park House for the weekly Kiwanis luncheon. He noticed steam clouding out of the radiator of Silas's sedan,

which was parked at the curb, and then saw Silas hurrying across the sidewalk with a pail of water and an anxious look.

Gus walked over. "Hello, Silas," he said cheerfully. "Want a hand?"

Silas looked at him as if he'd never seen him before. Then he poured the water into the radiator, replaced the cap, tossed the pail into the back of his sedan, climbed stiffly into the driver's seat, slammed the door after him, and drove away.

Gus's face turned red. Policeman Jim Devine, who had been watching, grinned widely. "The old rooster's sure got his ax out for you, Gus," he said. "He's telling everyone you overcharged him and then insulted him when he kicked, and that he's off you for life. Of course, nobody pays any attention to him, but—" Gus grunted and went

into the Park House. He didn't enjoy his lunch that day.

NE afternoon a couple of weeks later, Joe Clark came into the shop looking peeved. "That fellow Brindley's on the phone," he told Gus. "Says he can't find out what's the matter with a job he has in his place, but he knows you can, and he wants to bring it over. The nerve of him! What'll I say—that you're too busy?"

Brindley is a young chap with a medical discharge from the Marines. He has opened a neighborhood garage on the other side of town from Gus and Joe's place.

"Tell him to bring it along, of course," Gus replied. "I'm busy—but not so busy I can't take time to give a hand to a kid who's trying to get started."

"Now, look here, Gus," Joe said earnestly. 
"There's a limit to good nature! I haven't kicked—much—about you telling a lot of fellows how to do jobs they ought to bring to us. But when it comes to helping an out-and-out competitor—"

Gus grinned. "We're turning down work every day because we can't handle it. And as for helping young Brindley—well, it seems to me that he was helping us when he got himself shot up on Guadalcanal."

Joe went back to the office growling, but half an hour later Brindley drove in a sedan that Gus recognized at once as Silas Barnstable's. Its radiator was steaming.

Brindley was embarrassed. "I'll bet you think I've got a nerve, Mr. Wilson," he said, "and I guess I have. But you're the top man on car troubles around here, and I thought maybe you'd help me out. I told the man

Silas hurried across with a pail of water and an anxious look



who owns this car that I could fix it, and now I can't even find out what's the matter with it!"

"We all get 'em that way once in a while," Gus said. "The radiator's boiling—no doubt about that, anyway. Suppose you tell me what you've done."

"Sure," Brindley said. There was relief in his voice, but an undertone of embarrassment, too. "There was quite a lot of work done before the owner brought the car to me. When the boiling started, he took the bus to a big shop down in the city. They checked the spark and valve timing. When they couldn't find anything wrong there, they thought that maybe the overheating was being caused by too lean a mixture, so they had their carburetor expert check the intermediate and high-speed jets. They were all right, too, so they sent the radiator to a radiator specialist to have it boiled, and then they pressure-cleaned the entire cooling system with live steam to get rid of all the inside scale. They charged a good high price for the job, and when the radiator began to boil again a couple of days later, the owner really popped off.

"Someone told him about my place, and he brought the car in. When I took the engine head off and found several of the valves burned, I figured they were causing the overheating and that regrinding would cure it. But after the valve job, the radiator was boiling as bad as ever."

"O.K.," Gus said. "I'll have a look." He got in and started the engine. "What clearance did you give the valves?"

Brindley snapped his fingers. "I am dumb," he said. "I clean forgot to tell you that two of the valves were burned so badly I had to replace them."

Gus switched off the engine. "You did?" he said. "How about the spark plugs?"

"Pretty well burned," Brindley said.

Gus got out of the car and called: "Stan! Get me the vacuum gauge!"

When the grease monkey brought the gauge, Gus attached it to the intake manifold at the windshield-wiper connection, started the engine, and let it idle. He saw the gauge read 16". "Not very high," he commented. "Take the muffler off, Stan."

Gus got back into Silas's car after Stan had finished. This time the engine took off with a roar. He throttled it down to idling speed, got out, and looked at the vacuum gauge, which now showed 20".

"I thought so," Gus said. "Switch her off, will you, Brindley? Your troubles are over—or they will be when you install a new muffler and collect your bill."

Brindley showed astonishment. "What you say is good enough for me, of course—but I don't get it. What's the muffler got to

do with the radiator boiling—and how can you tell, without even lifting the hood, what caused the trouble?"

Gus grinned. "Oh, it's just a matter of adding one thing to another and getting a sensible answer. That's where experience comes in—and experience is something a mechanic picks up as he goes along.

"To start with, every car cooling system is designed to handle just about so much heat, and not much more. When the engine generates more heat than the system can dissipate, the radiator boils.

"I knew from what you told me about the work that had been done before the car was brought to you that the radiator couldn't be clogged and that the timing hadn't gone haywire. When you told me that the valves were burned so badly you had to replace two of them and that the spark plugs were burned, I knew that the extreme heat from burning gases around the valve and valve ports wasn't being carried away quickly enough. The most likely cause of that is back pressure in the exhaust system caused by a restriction in the muffler. When the gauge registered 16" of vacuum with the muffler on and 20" with it off, it showed that the muffler caused the overheating. Let's look."

Gus got the muffler and opened it. It was almost full of scale and corrosion. "There," he said. "Put on a new muffler, and you won't have any more trouble."

"Say, that's remarkable," Brindley exclaimed. "Well, now-what do I owe?"

Gus laughed. "Forget it. Some day you'll give me a lift."

The ex-Marine hesitated; then he said: "There's something I ought to tell you. The man who brought this car to me was a customer of your's."

Gus laughed again. "I never forget a car," he said. "Do me a favor—don't tell the old grouch I had anything to do with it."

WO weeks later Gus looked up from his workbench and saw Silas Barnstable standing beside him. "Well," he asked uncordially, "what do you want?"

"Want to pay my bill," Silas told him, fishing it and a check out of his pocket.

"You're in the wrong department," Gus retorted. "Go see Joe Clark."

"No reason to snap a feller's head off!" Silas complained. "Look here, Gus—I got it out of that young Brindley that you fixed my car up when nobody else could. Let's forget and forgive."


"Oh, all right—all right," Gus said.

Silas appeared relieved. Then he got a worried look. "That don't mean that I'm goin' to put up with any overcharges. Jes' because a man's laid by—"


"Scram!" Gus grunted. "I'm busy!"


#### —IDEAS FOR THE CAR OWNER













TIRE THEFT is made extremely difficult if you make use of the simple procedure outlined in the photos and drawings above. In principle, the method consists of rounding one tire-retaining nut or bolt so that it cannot be turned by a lug wrench without a special key. The idea is adaptable either to the nuts or the bolts variously used with pressed-steel wheels.


Remove one nut or bolt from each wheel, as in the photo at the left; since only one is taken from each wheel, it isn't necessary to jack up the car. Secure each nut or bolt in a vise (protecting the threads if you have bolts), and file off the corners as in Fig. 1. The job can also be done on a grinding wheel. Test the nut or bolt to make sure that the wrench won't hold; then drill a 3/16" hole through it, as in Fig. 2. A similar hole, Fig. 3, should be drilled through the lug wrench, located about ¼" back from the edge. For the key, use a 20-d. nail with a right-angle bend about ¾" from the end (Fig. 4). The photo at the right shows how the key is held in changing a tire safeguarded this way.—C. P. FITZPATRICK.


TESTING THE BATTERY can be done in an instant with the handy dashboard meter shown in Fig. 1. It consists of a storage-battery tester, a push button, and a block of wood that serves as a mount. When in doubt about your battery, it's necessary only to press the button and note where the meter hand stops to tell whether the battery is dangerously low or sufficiently charged.


The tester should be the inexpensive voltmeter type, calibrated in zones to indicate degree of charge. With an expansive bit or chisel and gouge, hollow out the back of the 1" mounting block to receive the tester, as in Fig. 2. Determine which of its terminals should be connected to the ungrounded side of the battery, and install a push button in series with this side. Run a well-insulated wire from the button to the end of the battery cable that is connected to the starter switch. The other terminal on the tester should be grounded through the mounting bracket to the dash. Figure 3 shows this metal bracket, which also serves to hold the tester in its recess. A piece of cardboard will insulate the meter case from the bracket.

Take readings after the car has been idle for a time;

you may not get accurate results after the generator has been charging the battery or after a heavy starting drain. To verify calibration of the meter, note the reading when the battery has been fully charged, and use that as a subsequent reference point.—W. E. B.










MARCH, 1945




#### By TOM McCAHILL

ANNOYING though it may be when your engine develops a click, rattle, thump, squeak, or pounding that you haven't heard before, such noises serve two valuable purposes. They act as danger signals, and they also serve as clues by which you can determine where the trouble lies. Once you have tracked down the sound to its source, it is usually easy to decide what, if anything, you ought to do about it. Some noises—once you know what causes them—can safely be ignored.

Any knock is first of all a warning-a





# ENGINE NOISES

Does Your Engine Purr . . .

warning that some part of your engine isn't functioning as it should. It usually comes in plenty of time for you to make the necessary repair before serious damage is done. And for the wartime driver, faced among other things with a shortage of major replacement parts, this is a blessing.

All drivers are familiar, of course, with the fuel knock—seemingly always present nowadays when all our high-quality gasoline is going to the armed forces. Provided ignition timing is correct and the engine isn't loaded with carbon, this knock simply means that the engine wasn't designed for the poor gas it is forced to burn.

But those raps, slaps, thumps, metallic knocks, clicks, throbs, roars, whines, hums, and squeals—they can mean something entirely different, and they frequently do. You will find it well worth your while to learn what each means, if only to know which can be safely ignored and which can't.

An illustrated table of eight of the most

1 Shorting out each cylinder in turn will often locate the one in which the cause of a knock exists. This eliminates much unnecessary work in hunting for a faulty part. Short the spark plug with a screwdriver that has an insulated handle

2 Warped valves or broken springs like those shown in the photo cause rapid clicking. The noise can be lessened by the shorting test. New parts should be installed for the defective ones

3 Running an engine having broken piston rings can cause trouble. The ruined piston shown below was chewed up by faulty rings. Sharp clicks at all engine speeds indicate a broken ring. The noise is not decreased by shorting the spark plug



# AND WHAT THEY MEAN

or Does It Knock, Thump, Pound, and Chirp?

important of these noises is given in the chart below along with their causes and cures. You must remember, though, that noises in an engine are at best difficult to describe, and many are so nearly alike that you may find it hard to distinguish between them. With practice you should be able to tell most of them apart and learn to locate the underlying trouble by considering three

factors: the kind of noise, when it occurs, and what effect shorting out spark plugs has. This will prove a great help in determining whether to look for it on the spot or whether you can postpone the search until a convenient time.

A simple trick is used by expert mechanics to locate a knock. They hold a screwdriver or other rod of iron or steel to various parts

COMMON ENGINE NOISES				
SOUND	WHEN HEARD	CAUSE	DIAGNOSTIC CHECK	TREATMENT
SHARP RAP	IDLING SPEED	O LOOSE WRIST PIN	CAN BE SHORTED OUT	REPLACE PIN
FLAT SLAP	ACCELERATING UNDER LOAD	PISTON SLAP	CAN BE SHORTED OUT, LESSENS WITH HOT ENGINE	REBORE BLOCK AND
INTERMITTENT, HEAVY THUMP	RUNNING WITHOUT LOAD	CRANKSHAFT END PLAY	CANNOT BE SHORTED OUT, DISAPPEARS UNDER LOAD	TAKE UP
METALLIC KNOCK	IDLING AND SLOWING	WORN OR LOOSE BIG-END BEARINGS	CAN BE SHORTED OUT, DISAPPEARS UNDER LOAD	REPLACE BEARING
RAPID CLICKING	CONSTANT	INCORRECT VALVE ADJUSTMENT	CAN BE SHORTED OUT BY CYLINDERS, FEELER GAUGE SHOWS WRONG GAP	READJUST
LOUD, RAPID CLICKING	CONSTANT	BROKEN VALVE SPRING	CAN BE DULLED BUT NOT STOPPED BY SHORTING	REPLACE
THROB, ROAR, KNOCK, OR CLICK	CONSTANT; CONSPICUOUS ON ACCELERATION AND AT HIGH SPEED	LOOSE MUFFLER, BAFFLE, OR PIPE	CANNOT BE SHORTED; INSPECT FOR TIGHTNESS	TIGHTEN OR REPLACE
WHINE, HUM, OR SQUEAL	CONSTANT; CONSPICUOUS AT IDLING SPEED	WORN WATER-PUMP OR FAN-PULLEY SHAFT OR BEARING	CANNOT BE SHORTED; DISAPPEARS WITH GREASING	GREASE; REPLACE IF NEEDE



of the engine and listen at the other end to locate the point at which the noise sounds loudest. This may not be easy at first, but with a little practice the trick should prove valuable. Try holding your thumb on the rod at one end. Place your ear close to the thumb and touch the engine here and there with the other end of the rod.

If the noise originates in one cylinder, it can often be located by a process of shorting it out. In this test use a screwdriver with a wood or insulated handle and simply short out one spark plug after another until the noise disappears during the shorting. The cylinder in which the trouble is occurring can thus be determined, and the loose wrist pin, slapping piston, faulty connecting-rod bearing, or defective valve can then be ferreted out without taking down more of the engine than is necessary.

A loose or worn big-end bearing on a connecting rod can be located in this way. It also often makes itself known to the experienced mechanic by its metallic knock when the engine is idling or slowing down—a noise that disappears when the engine is under a light load. One test is to accelerate the engine and then to close the throttle suddenly, at which time the knock should be very pronounced. Examine the bearing, and if it is worn or loose, the most practical treatment is to replace it with a new one.

The identifying noise of a loose wrist pin is a sharp rap, also occurring at idling speed. Such a pin is also best replaced by a new one. If the old pin is broken, the noise will be very loud and very metallic. Such a pin is dangerous as it may break the piston and cause serious damage to the engine. Even if the noise can't be shorted out entirely, shorting will soften the sound.

A piston that has become loose in the cylinder slaps against the walls with a flat, slapping sound heard when accelerating and when under load. It is less apparent when the engine becomes hot. The noise disappears when the correct cylinder is shorted out. The remedy is to remove the faulty piston, rebore the cylinder, and install an oversize piston. Broken rings cause a sharp click at all speeds and can't be shorted out. They should be replaced before they do any damage.

Loose main bearings are indicated by a deep, heavy, dull thump, increased on acceleration and under a heavy load. However, loose bearing shells in the crankcase cause a knock so similar to a main-bearing knock that it is almost impossible to distinguish between them without tearing down the engine for inspection. If a main bearing is at fault, it is best to replace all the main bearings while the engine is torn down; but only the bearing shell that is loose needs

to be replaced. A loose shell can rarely be made to fit correctly again. Too much end play in the crankshaft causes an intermittent, heavy thump. It disappears under even a slight load. The end play should be taken up by the means provided in the design of your particular engine.

Replace loose camshaft bearings, but check first for broken or sheared dowel pins and replace them as well as the faulty bearings. Inspect the gear if end play is indicated, for it may not be tight enough on the shaft and pressing it on tighter may eliminate the difficulty. If a worn thrust plate causes end play, it should be replaced by a new one, as should a gear that has a chipped or broken tooth.


Valve noises range from light taps and slaps to squeaks and knocks, and as a rule they do not indicate trouble that might lead to a major breakdown. The most common are those caused by improperly adjusted push rods where excessive clearance results in tapping. It is simple to readjust them to the manufacturer's specifications unless the adjustment units have become worn, in which case new adjustment units should be installed. You can short out or reduce noises caused by incorrect tappet adjustment.

It may be necessary to put in a new pushrod assembly if wear in the push-rod guides
cause side slap. If the assembly is loose on
the block, indicated by a rattle, a general
tightening of all nuts is sufficient. New
valves and guides are required when valve
stems are loose in the guides. If valves stick,
the engine should be cranked over slowly
with the valve cover off so you can see
whether all the valves come to a normal
closed position. Any that do not will probably be warped or have a broken spring.
Defective units should be replaced. Broken
valve springs cannot be shorted out completely, but the sound can be dulled.

In addition to these main engine noises, there are miscellaneous knocks and thumps that it is well to know. Various loose engine supports may allow the engine to thump on its bed on rough roads or when the clutch is being engaged or disengaged. A loose muffler or loose baffle plates in the muffler can set up a disturbing racket, as can a loose tail pipe. Ungreased or worn water-pump bearings or ungreased fan pulleys will often cause an eerie whine. A loose flywheel knocks most noticeably when the engine is accelerated and also while the clutch is being engaged or disengaged. Wear in a distributor shaft or bushing often causes a grinding noise when the engine is idling. Timing gears that are meshed too tightly will hum like a worn rear end but not so loudly. Most of these parts can await repair at your convenience.

# AUTO (deas


DANDELION TIRES are now being manufactured at the B. F. Goodrich plant in Akron, Ohio. The rubber from which they are made, shown in bales at the right top, is produced from kok-saghyz, a Russian variety of dandelion. Seeds of the plant were flown here from the U.S.S.R. in 1942, and from them was grown the kok-saghyz used by Goodrich. Company experts say that the tires, all of which are going to Government use, are of top quality.



RETHREADING AXLES is made easier with the die kit shown above. Worn or damaged axle threads are corrected by placing the proper size of split die in the holding tool, locating the tool over the worn threads, turning the handle to tighten the split dies, and then backing the tool off. The makers, the New Britain Machine Company, say that the design of the tool makes it possible to tighten the die halves evenly at all times. The kits are available in a size for passenger cars and a size for trucks.




Emerging from its mold, below, is a dandelion tire




SUN TANS EN ROUTE are a possibility for the owner of an enclosed car who has the compact ultraviolet lamp pictured below. Designed for operation on the 6-volt storage battery of a car, the lamp is 4\%" by 4\%" by

9%" and weighs 3 lb. It can either be attached to the dash or hung wherever convenient within the auto. In addition to its tanning and therapeutic uses, the lamp also tends to sterilize the air inside the car when it is in use.






PLANE LOADING from trucks gets a boost in speed and efficiency with the high-lift truck body shown in the photograph at the left. Twin hydraulic cylinders operate a scissors-type mechanism to lift the loaded body up to a maximum height of 10', or to any intermediate heights, depending on the floor level of the loading door on the plane. Designed for use on Army trucks of  $2\frac{1}{2}$ -ton size, the unit has a maximum payload capacity of 8,000 lb. It was developed by the Heil Company, of Milwaukee, Wis.




DRAINAGE SCUPPERS that work satisfactorily in a wall can be improvised from ordinary building tiles of the kind shown in the photo at the right. The openings can be cut efficiently with a silicon-carbide abrasive saw.

Leaving a baffle down the center between the outer and inner openings, as indicated, makes the tile scupper lightproof. This simple solution to the problem of finding a substitute for prewar metal scuppers was



worked out by a construction foreman for the Eastman Kodak Company in Rochester, N. Y., where he employed his adaptation for both drainage and ventilation and in both inside and outside walls.



VENETIAN-BLIND DUSTERS with three and four lamb's-wool fingers are manufactured by The Lauer Company, of Chicago. The wool is mounted on steel wires and cleans both sides of a blind at once. Also made by the same company is a one-prong bedspring duster.

#### CONCENTRATED FLOOR CLEANSER


to be mixed with water before application is now being made for use either before waxing or on a waxed floor that need not be rewaxed except on worn spots. The substance, a Du Pont product, is put on with a mop or cloth and allowed to dry.



POSTWAR WASH DAY

gives increasing promise of less work for the housewife. One of the latest announcements in improved washing machinery is the automatic clothes drier of the Hamilton Manufacturing Company, of Two Rivers, Wis. It will be made in both electric and gas models. Clothes are dried in a slowly revolving chamber through which warm air, controlled by a thermostat, is blown as indicated in the drawing. Ready-to-iron damp drying takes from 15 to 25 minutes on the average.

Up to nine pounds of clothes can be dried in this postwar-planned drier that is completely automatic





POPULAR SCIENCE

Mounted on figure-rolled glass and set in a glass case, this vessel makes an attractive display model

#### TUGBOATS GO TO WAR TOO! HERE'S ONE IN MINIATURE -

By E. J. Mooney



# WATERLINE MODEL OF A NAVY TUG

Our Navy uses this 65' tugboat extensively in its home waters. With many of the details simplified, and reduced to a scale of 1/8" to 1', it makes an interesting, easily built model. The profile, plan, and sectional drawings that appear on the next two pages are full-size reproductions; you can trace the necessary templates and patterns directly from them.

Make the hull from a \%" by 25/16" by 8" block of wood, cutting it to the shape shown in the profile and the half plan. The top of the hull is identified in the plan view and in Section B-B, as well as in the profile. As indicated in Section A-A, the forward half of the hull is slightly curved between the waterline and the deck.

Use heavy cardboard or 1/16" wood for the deck. It extends beyond the hull all around to form a rub strip. Cement it in place and cut out a notch forward to take the cardboard stem. Make the rail, rail cap, and brackets from cardboard or thin wood. The bottom outboard edge of the rail is set in from the deck edge to line up with the edge of the hull. It slopes inward throughout its length except at the stem, where it is plumb. Cut three openings in each side, as indicated, to simulate freeing ports.

Make the superstructure from Bristol board. The sides and front are in one piece, as shown. Score and bend on the dotted lines; then cement the pilot-house top, trunk top, and after ends of the house and trunk in place. The molding around the top of the


Workhorses of the seas, unspectacular little tugs like this one are daily playing an important part in tending the Navy's more glamorous fighting craft pilot house is a piece of .040" wire. Cement pieces of black-painted celluloid to the inside so they cover all the cut-out openings; then glue the completed superstructure to the deck.


Oversize details are given for most of the fittings. Make the samson post from \%" dowel, paper-clip wire, and a carved wood button. Both double bitts consist of 3/32" escutcheon pins or button-head rivets, wood, and Bristol board. The anchor davit is a length of wire, bent, filed to a taper, and flattened as indicated. The hatches on deck are glued-down pieces of Bristol board. Use wire solder for the life raft—when painted, it will very nearly approach \%" in diameter. The water tank rests on Bristol-board chocks. Side-light boxes are mounted on short pieces cut from round toothpicks.

Finish the superstructure and deck with flat gray paint. Use black for the hull and trim. The starboard or right-hand light box is green; the other one is red.

For drawings, see next page







### Novel Cupboard Corner Cupboard Holds Belts


#### By WALTER E. BURTON


PATTERNED after the well-known corner cupboard of Colonial days, this project has three shelves. The bottom one is slotted for holding belts; the two others will accommodate a few small trinkets.


Use ¼" plywood for all the parts except the two sidepieces (Fig. 2) which are made of 1/8" stock. Jigsaw the front (Fig. 1) to the dimensions indicated. Bevel the vertical outer edges to a 45-deg. angle to match the surfaces of the walls against which the cupboard will be mounted. Cut the shelf as in Fig. 3 to fit against the bottom of the front, recessing the two short edges to receive the sidepieces. Fasten it to the front with brads and glue. Saw a piece of plywood 31/8" by 31/8" diagonally into two pieces to form the triangular parts that are show in Fig. 5. Mount one on the front section, as shown in one of the photos at right, to form a top. Fasten the other to one of the sidepieces to form a shelf. Secure this sidepiece to the portion already assembled, add the other sidepiece, and fasten the belt shelf (Fig. 4) between the bottom ends of these pieces.


You can determine the size, number, and position of the belt slots so they will accommodate the types of belts you own. The buckles that are shown have rings that slide into the slots. Since each ring is off center with respect to the buckle face, it was necessary to arrange the slots in an unsymmetrical manner.

After assembling the cupboard, use a rasp and sandpaper to work down any edges that are not smooth or that do not match adjoining pieces. Finish off with fine sandpaper. Bore two holes near the centers of the two sidepieces to receive mounting screws. For a natural finish, apply two coats of clear linoleum lacquer. If color is desired, use an undercoat followed by two coats of enamel.













BOATING ENTHUSIASTS Donald L. Miller and J. M. Enyedy, of Pine City, N. Y., built this 17' cabin cruiser from P.S.M. plans. Because of wartime scarcities—both of material and of time—the boat took four years to build. A Brennan four-cylinder marine engine gives a speed of 10 m.p.h. with four passengers aboard. The exceptionally watertight hull is constructed from %" mahogany and has batten seams.










COPING SAWS for cutting large patterns have been developed by Dale Watson, mayor of Lasara, Texas. One has a hollow tubular extension frame so the depth of cut may be increased. The other has gears at the corners, permitting the blade to be turned at any angle while in the cut without twisting it out of alignment. Patents are pending.

SALT-WATER FISHERMEN will appreciate the fishing-line drier that is shown below. It was constructed of dowels, wood, and brass by J. N. DuBarry, of Villa Nova, Penna. The lower photo shows how it can be knocked down for easy transportation. It measures 18¾" over all, has sufficient weight and size to be suitable for winding heavy lines, and has brass bearings.







ST. JEAN'S CHURCH, Quebec, has been reproduced in miniature by Gerald Duval, of Danielson, Conn. He spent his spare time for a year and a half building the 25" by 43" by 45" model. It has electric lights, a belfry with three bells, carpeted aisles, stained glass windows, and the same number of pews and statues as the original. A record-player inside plays organ music.



Eyelets on a shower curtain can be kept from coming unhooked from rigid plastic hangers if openings in the lower hooks are sealed with cellulose adhesive tape after insertion. This tape is waterproof and will not loosen in moist air, but it can be easily removed for taking the curtains down for laundering

> DISKS GLUED **TOGETHER**


Disks of felt cut from an old hat, glued together in pads, and glued on the feet of a typewriter will overcome much of the clatter. Use at least five thicknesses in a pad

Discarded shower-curtain hangers of the spring type will hold up vines and bushes while you mow a lawn. Clip them onto the mower frame when they are not in use

RING









Tacked lightly to the folding shelf or platform of a stepladder, a picnic paper plate will keep sticky drippings from a paint can off the ladder and will also provide a place for laying down a wet paintbrush when time is taken out on the job

Damage caused by accidentally knocking the shade off an indirect lamp can be avoided by using an anchor made of an old shade frame. Cut the wire longer than the reflector radius, tape the ends to prevent scratching, and bend them in as shown





For a simple accordion file to hold small papers, bend back and glue the flaps of a stack of envelopes so that the first sticks to the second, and so on



## THE HOME SHIPSHAPE

Light, rigid composition board, joined with small angles held by bolts and nuts, makes an excellent cabinet for storing a child's toys. You can drill and bend scrap metal 3/64" or so thick for angles or purchase them at a hardware or dime store. Use four for each shelf and four at each edge of the back. All the shelves except the top slant toward the back so balls and wheeled toys can't roll off







Providing an auto jack with an auxiliary lift bent from a piece of heavy strap iron, as shown, makes it useful for lifting large stoves, refrigerators, and the like for inserting bases under the feet or laying linoleum. The bend at the bottom should be near the floor so it will slide under low objects

Old salt shakers make convenient dispensers for talcum or shaving powder. So do small jars having plastic caps. Simply drill 1/16" holes in each cap Two or three layers of rubber insulation tape—not friction tape —wrapped on the rollers of casters act as silencers when furniture is shifted in a room

An ink bottle having a separate well for filling fountain pens is useful as a small glue pot. Put the glue in the well and water or other solvent in the main section








## Solving a Knotty Problem with a Few Deft Turns

WHAT you do with your necktie when you stand in front of your mirror in the morning often means the difference between whether it stays put or needs adjustment whenever a blonde walks by.


Raoul Graumont, of New York, author of the Encyclopedia of Knots, has made something of a study of knotting ties. He has himself devised a modern knot that not only stays put but also has the additional advantages of not crumpling a tie excessively and of not jamming when it is slipped down for taking the tie off without untying it. It is shown below with the Windsor knot. Both are similar to the old four-in-hand knot except that each of them makes use of a half hitch for the base.




GRAUMONT'S MODERN KNOT as you would see it when tying it before a mirror is shown here in four steps. The diagrams are also reversed for simplicity of presentation, the long end being in reality on the right. Above, Raoul Graumont adjusts his tie clip after completing a perfect knot



STEPS IN THE WINDSOR METHOD are illustrated below, also as they would appear in a mirror. Graumont prefers the Windsor method for broad collars because it is a wider knot but likes his more compact modern knot for narrow collars. Either can be elaborated upon by doubling both the base and the body of the knot, or by using a double base and a single turn for the body or vice versa



#### Discarded Decoys Attractive for Decorating a Country Home



TRUE examples of practical American art are the familiar wellshaped game-bird decoys, such as those made to represent the duck, gull, sandpiper, goose, or curlew. An old decoy can easily be adapted for use as a mantel decoration, cigarette box, or lamp, as shown at the left. Other possibilities will probably occur to you. If the paint has faded, don't repaint—that would hide the "antique" value —but clean the decoy with a wire brush; then varnish.-IVAN MUNDA.

#### Archery Sight Permits Snap Shooting at Different Ranges


Bow sights that can be set for a fixed range are commercially available, but a sight that may be used instantly, without adjustment, at any range, doesn't lend itself to mass production because the sight markings will be affected by the size and build of the archer, the cast of his bow, and the weight and construction of his arrows. So a sight like the one illustrated must be custom-made to suit the individual.

Seize the string at the two points shown as a guide so the arrow will always nock at the same place. Glue a small block of hardwood, for an arrow guide, to the side of the bow—at right angles to it but inclined slightly upward at the outer end. Place the nocking guide and the arrow guide so the tip of the arrow will be slightly higher than the nock when in shooting


position.

As a calibrating sight, cut a celluloid blank and tape it to the bow as shown at the left in the drawing. For sighting points, use small inverted adhesive-tape triangles. A 30-lb. bow should have one for every five yards up to 20; then for every 10 yards up to 40. Conduct preliminary shooting tests on a windless day. Stand at the preselected distances from the target and, by trial and error, set the triangles in approximately the right positions. Always draw your right hand to the same point before releasing the arrow. A convenient point is that where the joint between your thumb and hand lies directly under the right side of your chin.

The finished sight, also celluloid, is smaller, of course, than the sighting blank. It is fastened in place with two ¼" hardwood blocks. Secure a set of adhesive-tape triangles to it so they match those on the sighting blank. Glue the mounting blocks to the bow and fasten the sight to the blocks with small brass screws. Then go out on the range and carefully check the positions of the triangles. They will lie in a line not quite parallel to the axis of the bow. Score this line, then a series of crosslines, through the points, taking care to draw the latter at right angles to the axis of the bow. Fill in with India ink.—John L. Story.



MARCH, 1945



7. The direction of thrust remains the same, although the camber will be on the wrong side for best efficiency.

6. Wrap a cigarette tightly in cellophane, twisting the ends of the wrapper shut. After pulling the knot tight, you can open it and show the cigarette undamaged.

halve the area of the paper.
5. The word "prohibits," which starts on one line and ends on another.

4. It doesn't matter how big a piece you start with, but remember that each fold must.


3. The bottle must be quite dry inside, Holding it with both hands, swing it hard in an up-and-down arc. Don't let the dime circle around inside. The right motion flings it out, making a small hole in the bottle.

2. You can bet the dime on this. But use an old one and a worn brush or whisk broom.

'umous

I. First hold the pack with the face up, when both words are reversed in the mirror. Then say that you can turn one word right side up at will—and turn the pack over as

#### Handy Angle Reduces or Enlarges Drawings



This handy angle enables one to determine quickly, and with accuracy, the proportions of photographs or drawings for enlargement or reduction. To make the instrument, cut the legs of a 90-deg. angle from thin plastic, wood, sheet aluminum, or brass. Whatever the material used, it is

important that the inner edges of the legs form an accurate right angle.


Enough material should be left at the junction of the legs to permit mounting a pivoted arm, as shown. Make the arm from the same material used for the angle. When the arm is completed, it is pivoted at the exact spot where the vertical and horizon-

tal lines of the inner angle intersect. An eyelet-type rivet driven through arm and angle at this point will serve as a pivot, or a small flathead machine screw and nut may be used. The head of the screw should be countersunk flush with the underside of the angle.


In practice, when determining proportions with the completed instrument, place the angle over the drawing to be reduced or enlarged so that the inner edges of the angle are flush against two edges of the drawing. Then, using the movable arm as a diagonal, intersect the opposite corner of the drawing. Draw a line along the diagonal to the desired point, then draw two lines from this point at right angles to the lines formed by the inner edges of the legs. The resulting square or rectangle will be of the correct proportions.—C. W. B.

#### Clips and Wire Coil Make a Brush and Pen Holder


A WIRE coil, bought at an artist's supply or stationery store, and a few odds and ends create an improved holder for brushes and pens which will keep them clean and out of the way. Cut enough wood from the ends of two spring-type clothespins so that the shortened pins are approximately 1½" long. Slot one prong of each pin with a saw, insert the coil ends in the slot, and secure with wood screws. The clothespins are then clipped to a water-filled jar.—M. A. J.



#### Pipe Cleaner Tacked to Drawing Board Forms Draftsman's Pen Wiper



ANY desk contains most of the materials necessary to make a very simple pen wiper, ideal for use by draftsmen and architects. Obtain a few pipe cleaners of the wire-core variety. Cut thicknesses of cardboard to make two blocks as shown. Then stretch a pipe cleaner over both blocks, and fasten down the ends with thumbtacks. When the cleaner wears out, simply pry up the tacks to replace it.




#### Carved Turtle Box Holds Small Desk Accessories

THEOBALD the turtle would have you believe he is on his way. But he gets nowhere fast—no further than the top of your desk, where he holds paper clips, stamps, or other small articles.


This is a jackknife job. Lay out the three parts—the shell, the body with the legs, and the head and neck—on any soft wood 1" thick. Make the box section on a lathe or by hand with a mallet and chisel. An oblong cavity is

possible if the work is done by hand. Jigsaw the legs, and then use your jackknife, turning the work often to keep the proportions correct. Don't round off the knife cuts, since they add effectiveness.

Sand the pieces lightly, glue and dowel the neck, and hinge the lid; then apply walnut stain, rubbing off the excess to give the carving a weathered look. Brush a little green enamel on the top, legs, and head, and rub it off with a cloth, leaving a faint, mossy tinge. Add toenails and eyes last. The former are short lengths of round toothpicks fitted into drilled holes. They are left white. The eyes are white map tacks with the pupils painted in black.—ELMA WALTNER.







#### Gay Paper Knife Has Totem-Pole Handle

This novel paper knife will be useful on a desk either at home or at the office. Carve it from ¾" thick hardwood—birch, maple, or another that is light in color and can be whittled without too much difficulty. A paper pattern will be symmetrical if half is drawn first and the paper is then folded lengthwise and cut out.

Saw the outline roughly and then proceed with the carv-

ing. Round the edges a trifle, emphasizing the figures with carved lines. The back is simply rounded at the edges to provide a comfortable grip. Thin down and sharpen the blade with sandpaper and sand the entire piece lightly.

Finish with clear varnish, rubbed with steel wool after it has dried; then apply colored enamels to accentuate the natural wood. Draw in the features with a pen and India ink when the enamel has dried. Add two protecting coats of wax.—E. W.




POPULAR SCIENCE


#### Building a Pocket Telescope from an Exposure Meter



Quickly adjusted for focus, the finished telescope may be carried in a pocket for use both in and out-of-doors. Photos and diagram show neat appearance and simple construction







ANY people, especially sportsmen and theatergoers, have use for a small, efficient, but inexpensive pocket telescope. To make one, all you need is an old exposure meter of the extinction type, or a similar one having a tube, plus a pair of salvaged lenses and some paper and glue.

The telescope shown has a magnifying power of four diameters. It is of the Galilean or opera-glass type, the optical system consisting of a positive lens of about 4" focus and ¾" diameter for the objective, and a negative lens of approximately 1" focus and 34" diameter for the eyepiece. The objective in this case is an achromatic doublet, which, being corrected for color, produces sharper images than a simple lens. Such achromats may be obtained from old opera glasses or other optical instruments, or may be purchased for a reasonable price from dealers in salvaged lenses. The objective lens should have as large a diameter as the meter tube will permit, though usually the builder must use whatever diameter is available.

To convert a meter of the type shown into a telescope, remove all the screws and separate the sections. You will have a cupshaped eyepiece, a body tube, two nickeled tubes, and a rolled-edge collar, 34" long from the outer end. Discard the section that holds the iris diaphragm, but keep the one having the longitudinal slot. Force out the disk that is in one end of this tube. Remove the magnifying lens from the cupshaped eyepiece and replace it with the negative lens. Reassemble the eyepiece and body tube; then replace the slotted tube so it is reversed with respect to its original position. Mount the objective lens in the rolled-edge collar and insert the collar into the outer end of the slotted tube, using cardboard and quick-drying cement as a packing.


The best method of fastening the lenses in position is to machine brass adapters, if you have the facilities. An alternate method is to use wood putty, or strips of pa-


per and glue, to build up a suitable mounting.

The telescope has a 1\%" focusing movement, which is operated by sliding the slotted tube forward or back. The knurled-head screw in the body tube locks both tubes together to maintain focus.

For convenient carrying, shorten the original leather case to fit the telescope, and restitch the bottom.—ERVIN WALTERS.

Copyrighted material





#### KINGCOBRA IN MINIATURE

#### The P-63 . . . Bell's Superb New Fighter and Low-Level Strafer

THE Kingcobra is a larger, improved version of its famous older brother, the reliable P-39 Airacobra. Its greater speed, faster rate of climb, higher ceiling, and increased combat range are achieved by using a bigger engine-the P-39 has a 1,150-hp. Allison and the P-63 has one of 1,500 hp. This increase in power has necessitated using a four-blade propeller instead of the three-blade one used on the Airacobra. Both planes have the same armament-a 37-mm. cannon that fires through the propeller hub, two nose-mounted .50-cal. machine guns that are synchronized with the propeller, and a .50-cal. machine gun under each wing. Both feature a rearmounted engine and excellent forward visibility. The Kingcobra has a low-drag laminar-flow wing.

Reproduced on the facing page are halfsize plans of the model. Connect the graduations at the edges of the page to form a grid of ¼" squares. On a large sheet of stiff paper, lay out a grid of ½" squares; then transfer the lines from the small grid to the large one by matching squares. Draw a second, similar full-size layout and cut out the shapes to form patterns.


Carve the fuselage from a piece of ¾" by 1½" by 7½" balsa, pine, or other soft wood, using the fuselage-section patterns are guides. Cut out the belly to take the one-piece wing. Use a ¾" by 2" by 9½" blank for the wing, carving and sanding it to the form that is indicated by the wing-section patterns. Score and crack it at the two places where the dihedral starts. Resting the center section on the bench, raise the tips to the proper angle, support them with blocks, and cement the cracked pieces.

Fabricate the stabilizer and the rudder from \( \frac{1}{8}'' \) stock.

Thoroughly sand each part; then assemble the model, using glue or cellulose cement to hold it together. Form the fillets at the intersections of the wing and the body with plastic composition wood. Make the machine guns and the wing-tip lights from scraps of wood and glue them in place. Cut the propeller disk from celluloid. To make it seem to be whirling, pin it through the center to a piece of sandpaper; then rotate it so the sandpaper scores it. Secure it to the model with a shaped wooden hub and a brad.

Finish the model with several coats of wood filler and a coat of camouflage paint.

Distinctive ground features of the P-63 include a fourblade propeller and a retractable tricycle landing gear



Grinding off the sides of the wing nuts and providing a washer bar speed the setting up of a drill-press fence


# Machine Aids

By Edwin M. Love


HEN timesaving is an important factor, it will pay you to build adjustable machine attachments that will be useful year in and year out. They will end the necessity of hunting for suitable blocks and clamps—not always conveniently at hand—every time stops and the like are needed, and should be welcome not only in the shop operated for profit, but also in the home workshop where even a few minutes gained at the start add to an evening's enjoyment.


Several especially useful attachments are shown in the accompanying photographs and drawings. They include a pair of hinged stops, a quick-clamping drill-press fence, pivot and sliding fences, high and low auxiliary fences for the circular saw, a lathe semaphore, and a steady rest.

How are hinged stops made? One is shown at the left in the drawing below.



Two hinged stops and a sliding fence are shown in use below. At left, the nearer stop to the work acts as a gauge and the other is back out of the way while a short tenon is cut. A long tenon is being cut at right with the farther block in use and the other one thrown back. The fence holds the work upright





# That Save Workshop Time

while a pair are shown in use in the two photos. Slot the bar that is clamped flat on the table by boring end holes and ripping out the waste on the jigsaw. Make the tenon of the clamp a sliding fit for the slot. The clamp itself is made in two pieces, as shown, and can be attached readily to the edge of a drill-press, jigsaw, or bandsaw table by pulling the two blocks together with a bolt and wing nut.

In one of the photos the hinged block at the end of the stop nearer the work is down on the table and the other is raised out of the way while a short tenon is being ripped on one end of the rail. The other photo shows the farther hinged block down while a long tenon is being cut on the other end of the rail. This is a typical setup that permits both ends of one rail to be finished before going to the next. In a large shop where a run of such pieces is to be made, a single stop is usually set for one tenon and reset for the other only after the first tenon has been cut on all pieces. Most small shops, however, do not have space between machines for piling up partly finished work, and in them the hinged stops will be found particularly advantageous.


Of what value is the sliding fence? This attachment, also shown in the photos with the hinged stops as well as in a drawing, is clamped to the work to hold it accurately vertical while it is fed freehand against the saw. As used in the operations shown, such a fence enables the woodworker to rip both cheeks of a tenon simply by sliding the work lengthwise to suit.


What is the pivot fence? It is a slotted bar with an upright fin. A clamp like that for the hinged stop is used to attach it to the saw table after the fin has been set at the required distance from the side of the bandsaw or jigsaw blade and lined up with the teeth as indicated in the drawing. The fence is useful in resawing and similar work. It regulates the thickness of the piece cut and yet allows it to swing to overcome lead in the blade.

How is the drill-press fence clamped? This is done simply by grinding off the sides of the regular clamping wing nut so it will clear the slots in the drill-press table and

3/4 PLYWOOD HIGH UXILIARY TAP FOR BLOCK GROOVED TO FIT OVER RIB RIBBED SAW FENCE TO SUIT METAL FENCE 5/6×12 SLOT STOP FOR FENCE EXTENSION WING 34×2/2×18 SCREW EXTENSION 34 x 34 x 3 BLOCK AUXILIARY FENCES WITH EXTENSIONS ARRIAGE BOLT

Long pieces are sawed accurately with the help of a fence extension attached to an auxiliary fence with a loose-pin hinge. An adjustable stop in use on the extension is shown in the foreground below





Sizing cuts in turning a spindle are gauged by the lathe semaphore jig which has its flags adjusted to drop when the correct diameter is reached. At right, the spindle is supported by the steady rest as its end is bored. Note that the semaphores remain in place but are out of the way of the steady rest

by providing the fence with a washer bar, as shown in a drawing and photograph. With this arrangement it will not be necessary to take the wing nuts off completely every time the fence is put on the table or removed. The washer bar is made of wood and is reinforced with open washers bradded to the bottom of the slots to provide bearing surface for the wing nuts. It is slipped between the underside of the table and the nuts, and the nuts are turned up tight against it to lock the fence in place.

What does the circular saw require? Some manufacturers furnish saw fences that are arched for use with molding heads. Short, thin stock cannot be safely guided against such fences for ripping as the wood jams in the arch. A low auxiliary fence is therefore required to present a continuous surface for such ripping.


Two such fences are illustrated in the drawings, one for use with a flat ripping fence and the other for a fence having a ribbed back. The auxiliary fence for the former is equipped with notched blocks near the ends for fitting over the ends of the regular fence, while the blocks on the latter are attached at the top and are shaped to fit the ribs. Both fences are locked in place by wing screws turned into undersize holes bored in the blocks.

Should you have a circular saw that does not have an arched molding fence, an arched auxiliary fence can be built with attachment blocks like those on the low auxiliary fence. Make it as thick as necessary for use with a molding head.

An extension for the low fence is attached with a loose-pin hinge, as shown in the drawing. It is held rigidly straight by a block screwed over its hinge leaf and extending over the leaf on the clamped auxiliary fence. Insertion or removal of the hinge pin is all that is necessary to attach or take off the extension piece. Slot the extension as shown to take a T-bolt that clamps an adjustable slotted stop in place anywhere along the length. Such an extension fence is shown is use in one of the photos. It permits sawing long stock.

In making a high auxiliary fence, attach the clamping blocks in a vertical position, as indicated in the drawing. Plywood is best for such a fence since a solid board wide enough to fill the requirements would be subject to warping.

How is a lathe semaphore built? In this variation of a familiar lathe accessory, the flags are pivoted on swiveling arms attached to a pipe that is held in place by end supports. This type of mounting prevents interference with the tool-rest supports and permits adjustment of the flags in and out to conform to a drawing, template, or turning. The flags are made of either hardwood or metal. They rest on the roughed turning until sizing cuts reduce the diameter enough to allow them to drop. In this way, they



indicate that the correct diameter has been reached.

Since the flags tend to jump and may be thrown back by roughness of the turning, one hand can be held above while the sizing cut is being taken. No pressure should be put on the flags, however.

Several supports may be mounted permanently on the bar, and a few additional ones can be made with slotted ends, as shown. These can be attached quickly when extra flags are required for a job.


What is done in making a steady rest? Cut the body from ¾" plywood or well-seasoned hardwood to the shape indicated in the drawing, and saw the two segments apart. Hinge the upper segment with a bolt to a kidneyshaped link and latch it with a bolt that enters a slot in the upper end of a similar link. Both the hinge and latch are screwed rigidly to the lower segment.

Make three slotted guides as shown, bolt them in place, and screw block guides against them. The base clamp must be shaped to slide under the bed of the lathe, and it should have lugs to enter the slot and keep it from swiveling.

Use the rest near the center of long, slender turnings in order to stiffen them, or support the end of a spindle in the rest for

boring or turning. When the rest is used as a stiffener, it can be placed after rough turning by setting the guides into a wide sizing cut near the center, or it can be set up after the turning is almost completed. Any scorch mark made by it can be removed with light cuts and a little sanding. For end turning, the guides should bear against the tailstock side of a shoulder or bead so as to prevent the work from slipping off the spurs of the live center, as would otherwise happen.

#### PLYWOOD GRADING TERMS



#### [WOODWORKING]

Plywood is manufactured in two types: moisture resistant (M. Res.) and exterior (Ext.). Moisture-resistant plywood is bonded with such glues as soybean adhesive and is suitable for use in dry places or where it will be subjected to no more than a slight wetting from condensation or small leaks. Exterior plywood is bonded with waterproof plastic glue, which is resistant to both cold and boiling water and to This plywood is oil, alkalies, and most acids. suitable for outdoor construction, boats, and


Both types of plywood are graded according to face veneers as follows:


Good. Single, smooth sheets, practically clear all-heart veneer. Suitable for natural or stained finishes that reveal the grain.

Sound. One or more lengthwise sheets accurately joined, closely matched for grain, and free from knots, splits, checks, pitch pockets, and other open defects. Streaks, discolorations, sapwood, shims, and neat patches are allowed. Surface smooth enough for painting.

Utility. Single or pieced sheets, which may have knots, pitch pockets, and splits up to 1/16" wide that do not reduce the serviceability of the panel.

POPULAR SCIENCE MONTHLY SHOP DATA





THERE'S more to using a chisel than smacking it on the head. Seven errors are shown in the six illustrations, two of them in Fig. 4. Can you find them?

6. There should be a scrap board under the work to avoid damaging the bench.

5. First bevel the waste at both sides of the dado and on both sides of the stock; next rough the piece out parallel to the bottom. Then pare the dado to depth.

4. The bench stop endangers the edge of the chisel. Besides, this is a finishing cut, and a plane should be used.

3. If tenon cheeks are properly sawed to size, no chisel is needed. The procedure shown will leave a rough shoulder and prevent a clean, close fit.

2. Cutting should be started near the center and the ends trimmed last to avoid crushing beyond the gauge lines.

I. After scoring the back of the mortise, make full-width, full-depth chisel cuts across the grain from 1/4" to 3/8" apart to break the waste into small chips and prevent splintering into the bottom.

ANSWERS

#### Notched Jig Accurately Gauges Round Edge of Corner Shelves

A CORNER


CIRCULAR edges of corner shelves and other sectors can be cut easily on a bandsaw or jigsaw with the aid of a jig like that shown in the drawing. Simply square two adjoining edges of the stock, fit the corner in the notch, and rotate the stock and the wheel 90 deg. on the saw table.


CHISELING OUT A DADO

The jig is made from \( \frac{1}{6} \)" by 6\( \frac{1}{2} \)" cold-rolled steel, cut to shape at one end with a hacksaw and bent as indicated in the drawing. File all edges and corners smooth. Make the wheel


from ½" drill rod or flat steel, cutting the 90-deg. notch accurately. Drill both the wheel and the shank of the jig for a pivot pin and counterbore them for riveting the pin in place.

In clamping the jig, measure from the saw blade to the pivot to set it for the desired radius. To correct lead, set the jig forward or back.—W. B. WEBER.





#### Smart Tin-Plate Accessories Set Off Candy or Flower Bowl




TIN cans useless for salvage afford material for this attractive gift ensemble. Designed to hold short-stemmed flowers, it serves equally well as a candy or nut dish.

On a sheet of tin plate paste a paper pattern of the bowl holder traced on \( \frac{1}{2} \)" squares from the drawing above. Bend the piece as shown, shape four "petals," and solder them to it.

The edge of the tray is bent up and crimped with round-nose pliers. For the loop, cut a ¼" wide strip and wind it spirally around a curved piece of coat-hanger wire. Solder both ends to the underside of the tray. Burnish with fine steel wool and coat all parts with clear lacquer.—CARL BERTSCH.






#### Paper Plates Secure Ink Bottle

A SAFE holder for a bottle of India ink is quickly made of two paper plates. Cut one in half, discard one piece, and near the cut edge of the other make a hole about ¾" in diameter. Staple this piece to a second plate and force the neck of the bottle through the hole. The lower plate serves as a tray

to hold your drawing instruments.—A. D. SLATER.


#### Lapel Ornament from Fountain-Pen Cap

WHEN a fountain pen is beyond repair, the cap can be put to use as an unusual lapel vase, particularly if it is of some colorful material. Slide the clip of the cap through the buttonhole or, if there is no buttonhole, push a safety pin from the back of the lapel through the space under the clip. Insert a tiny flower or two.—B. N




MARCH, 1945

#### HOW ARE YOUR CHECKER WITS?




ERE are some puzzlers in checkers that may make the impetuous player get himself into a trap or, at best, a draw. They are favorites of Millard Hopper, the checker king, who furnishes some really tricky solutions that are given below. Before you read his answers alongside the boards, try to solve the games yourself—but look beyond what may appear at first to be obvious.


In each instance White has fewer men than Black but has the advantage of first move. If this move is made correctly, then White will win. For clarity in printing, the men are shown on white squares, although in play they move on the black. White moves toward the top of the board.



would you start with that 27-24 "two-forone"? Don't do it; you'd only lose. Play 27-23, 19-26, 28-24, 20-27, then that big 32-5 to win.


stay away from the temptation of 11-8. You can force things your way by trying 17-14, 10-17, 11-7, 3-10, 12-8, and 4-11, to win by 16-32.






AH, AH! DON'T! You'd only get a gold brick with 18-14. There's a better buy at 18-15, 10-26, 27-24, 20-27, and a 32-5 sweep.


AVOID SAVING the man on 9. It sets the trap. Move 2-6, Black jumps 5-14, and then move 30-26, 21-30, 6-9, 30-23, 9-11, and Black resigns.






25-21 LOOKS GOOD, but it's only a draw. If you play 28-24, 26-17, 27-23, 20-27, 25-22, 17-19, and 32-5, Black's game will be hopeless.

DON'T FALL FOR 27-24, 20-27, 32-7 or Black may win. Instead, play 28-24, 19-28, 3-7, 12-19, 7-16, 8-12, and 16-19.







KEEP 'EM ROLLING FOR A HIGH SCORE

#### **Action Checker Game Is Real Skill Tester**

By MYRON FLEISHMAN


IGH scoring and some exciting manipulation of the board are possible with this new game played with seven checkers borrowed from your regular set.

The board itself is easily made. It consists simply of a frame of ½" by ¾" stock around a sheet of stiff cardboard. Two ends of the frame extend for handles, as shown in the drawing. Three dowels serve as feet. One of these, as indicated, is a 2¼" length of ¾" diameter dowel and is centered on a batten across the bottom of the board 8½" from the end that does not have handles. The other two are 1½" lengths of ½" dowel. They are placed in the corners at the handle end, as shown. This arrangement allows the board to slant toward the handles when it rests on a table.

To play, seven checkers are inserted in the slots at the handle end, and the board is raised so that they will roll down the incline to the other end. The player scores from 10 to 30 according to the markings on the slots into which the checkers roll. If any fall over


during the process they are removed from the board. Those that enter the unnumbered outside slots do not score, but they are not removed.

The board is next permitted to tilt back again, and the checkers are allowed to roll back to the starting end. Scores are again counted and added to those made in the first play. Checkers that fall over are again removed. The board is then raised by the handles and tilted to roll the checkers a third time, and the operations are repeated until there are no checkers remaining to be rolled. Each player has three turns, and high score wins.



# TOY WALKIE-TALKIE THRILLS YOUNG COMMANDOS





THAT young "commando" in your home will be the envy of the neighborhood when he goes out to play war with a toy walkie-talkie like that shown above. For all its G.I. look, the toy is built of scrap stock and a length of webbing or a belt.

The rectangular case is a  $2\frac{1}{2}$ " by 3" by 10" closed box, with rounded top and bottom pieces overhanging the sides  $\frac{1}{8}$ " all around. Make the body of two  $\frac{1}{2}$ " by 2" by 9" pieces and two that are  $\frac{1}{2}$ " by  $2\frac{1}{2}$ " by 9", gluing and nailing the simple butt joints for

strength. The mouth and ear pieces shown are turned in a lathe and then sawed off on a diagonal, as shown in the drawing, but if you are good at whittling there is no reason why you can't shape them by hand. Two dowels form dummy controls on one side.

How the telescoping antenna is put together is shown in the drawing. Drilling the ½" diameter dowel takes great care, and it is best to drill from both ends.

Finish with khaki paint and trim with white as in the photo.—FRANK MCCARTY.

Ball-Bearing Swivel Caster Makes
Excellent Mount for Punching Bag

IF YOU have trouble finding a standard swivel for suspending a punching bag, use a plate-type ball-bearing swivel caster for the overhead mount. It can be readily held on by screws. The caster works on very nearly the same principle as the regulation swivel.—K. M. MARTIN.




#### Tricky Keyless Latch Opens Only to Secret Combination




AN INTRIGUING addition to a cabinet or desk is a door that can be opened only by those in on the secret. A certain combination of twists is required to throw the latch shown, tricky enough to puzzle the uninitiated.

Turn the shaft and bushings from steel or brass, make the latch to suit the door, and drive the latch bushing into an undersize hole in the latch. Press the shaft bushing into the door frame from inside; then slip a washer over the protruding portion. A wooden cover keeps the latch in place; the latch bushing should extend 3/32" past it. Insert the shaft from the front of the door, slip on a suitable spring, and fasten the retainer with a 3/32" pin, which protrudes 5/16".

File the blocking plate from a big washer, checking it against a drawn pattern. Screw it to the cover plate as in the drawings (Figs. 1, 2, and 3). In Fig. 1 the latch is closed; the knob can be pulled out and given a partial turn clockwise (as seen from inside the door). It is then pushed in and given half a turn to the position in Fig. 2. When it is again pulled out and turned further as in Fig. 3, the latch is open. The positions shown are for a door hinged on the left.—John M. Avery.








## TABLE TRICKS



WATCH THE SURPRISE on your friends' faces as you get the laugh on them with this napkin-tumbler trick. Ask one to extend his arms, grasp a covered tumbler in each hand, and lift them quickly over his head. One tumbler will fly up; the other will prove unexpectedly heavy—for that one you will have filled beforehand with lead shot, iron nuts, screws, or nails to add weight and catch your victim unawares! The napkin hides them.

CAPILLARY ATTRACTION between water and ordinary string will help you to empty one glass mysteriously into another. Twist several feet of string into a skeinlike length, put one end in the glass of water, and let the other end hang over the edge to a point below the bottom. Now hold the empty glass beneath it, and soon the string will begin to act as a wick, drawing water from the filled glass up over the edge and allowing it to drip down to the other one below.





NOW YOU SEE IT, and now you don't! Place a coin or medal under a clear glass of water while no one is looking and challenge your friends to tell, without moving the glass, what is under it. Because of refraction of light rays, bent by the water so they cannot reach the eye of an onlooker through the sides of the glass, nothing can be seen under the tumbler. But if you now drink the water out through a straw, the coin will be plainly visible to all! Of course, the coin can also be seen all the time by anyone who looks down through the top of the tumbler, so arrange the glass on a table at a high enough level to keep from giving the trick away to an observant onlooker.

SEPTEMBER 1

HERE'S ONE THAT SCIENCE can't explain nearly so simply as the practical observer with a quick eye. Rub your finger briskly on your woolen coat sleeve and make a little paper cylinder follow it obediently around the table. Your scientific friends will say that it is impossible to create electricity that way. And if they try, they will fail. So would you if you didn't know the trick. Rubbing your finger is just a gag. What you do is to blow gently on the table just behind the little cylinder in order to make it roll!



SLEIGHT OF HAND is always interesting in an after-dinner gathering. This trick is simple, but it requires some dexterity that can be attained with a little practice. You will need a loose ring on your fourth finger and an ordinary kitchen match. Hold the match between the thumb and forefinger and show it to the assembly. Then wave the hand rapidly for an instant, and, lo! the match will have disappeared. What happens, of course, is that you secrete the match in the ring behind the finger. This can be done easily by bending the middle finger out of the way into your palm as you wave.








BOTTLE-CAP VACUUMS are more of an illusion than a reality. Tell your friends that you can create a vacuum in a metal bottle cap by sucking the air out, and make a great pretense of doing so. Then to "prove" that you have a vacuum, place the cap on a handkerchief draped over the palm of one hand and lift it. The handkerchief will come up with it! This isn't because of a vacuum, though. Have the removed cork from the cap in your hand under the handkerchief, and press it into the cap to hold the cloth, as in the photo above.

FIRE FROM AN UNLIT MATCH, or from a plain scrap of paper, will startle your guests. Attract their attention so they will see that the match or paper isn't afire when you drop it into a tumbler; then place a saucer over the tumbler and soon clouds of white smoke will arise. Have a few drops of household ammonia in the bottom of the tumbler and surreptitiously rub a drop or two of muriatic acid on the bottom of the saucer! Vapors from the two liquids combine to form a dense white smoke. The match or scrap of paper is used merely as a bluff.



## Controlled Light... The Photographer's Paintbrush

By KONRAD CRAMER

EVER since the introduction of the modern tungsten-filament bulb, the amateur photographer has had at his command easily controlled illumination in quantities limited only by his pocketbook. Later, when the short-lived but brilliant photoflood lamp was marketed, he really got more light than he could properly handle. The average amateur, as a consequence, tends to use too much light with too little control. So these two factors—the control and the intensity of light—are worthy of particular attention on the part of the studious amateur.


To be able to control light, you should understand the simple fundamentals of light and shade. Otherwise you will do a lot of needless running back and forth, moving

of your lamps vertically and horizontally, and checking by peeking frequently at your subject through your view finder before you finally arrive at the lighting effect that you are seeking. The top drawing on this page shows an apple on a plate. If you look closely, you will see a fly crawling on the surface of the apple. Imagine, if you will, that you are that little fly and that someone is squirting water at you. Where on the apple, the plate, or the table would you be safe from the steady stream of water? Obviously, the only secure places lie within the shaded areas. Now imagine that, instead of water, light rays are hitting the apple, the plate, and the table. The areas that are directly hit by these rays are bathed in light. The areas that are not directly hitthose that remain dry when water is played on the objects —are shadowed.

The human head is roughly the same shape as an apple. The only differences are that the head has a few hollows, such as the eyes and the mouth, and a few protuber-

ances, such as the ears and the nose. Below the picture of the apple are two sketches of a human face. The first one is filled in to show light and shade when the light source is at A. The second one is unshaded. Trace it three times on a piece of transparent paper; then, imagining the light source to be first at A, next at B, and finally at C, try shading the three sketches. If you can't conceive where a shadow should go, recall to mind the little fly. Wherever he would remain completely dry, draw in dark shadows. Wherever he would get a little moist, put in light shadows or, as they are called by artists, half shadows.

Now that you have learned the principles that, properly applied, will give you a cer-






Using natural daylight and but one spot—to high-light the model's hair—the photographer has caught here that elusive but highly desirable feeling of naturalness that distinguishes the true craftsman

tain amount of control over the directional quality of light, you should concern yourself with the amount or intensity of the light. Extremely strong light is essential only if your subject is in motion, and it is best supplied by flash bulbs. Although these may be used without shutter synchronization, a synchronized-flash shot is better because it insures a picture every time the shutter is released. Too many flash pictures are monotonous because the reflectors are

mounted too close to the camera, thus eliminating all possibility of varying the direction of the light. To overcome this, don't mount the flash on your camera, but make it independently movable. Excellent results can be achieved with batteries of flash bulbs if they are used judiciously.

For a little less intensity, a photoflood lamp is indicated, although it has two rather serious inherent disadvantages that should be carefully weighed against the obvious



idea to add a diffusing screen to the reflector because it will give a soft and flattering light. One made from spun glass is best, but one made from a square of crepe de Chine will do if you mount it far enough away from the bulb so there is no danger of fire.

3. One of the readily obtainable mushroom-type bulbs. Although rated at only 150 watts, they have built-in reflectors that make them highly efficient. The

Both of these pictures were taken at too slow a shutter speed and underdeveloped if judged by usually accepted rules for good photography. This is especially true of the scene at the left

advantages. In the first place, the light given off, being rather harsh and raw, is hard on a model's eyes. So portraits that are made in such a light may be unsatisfactory because of the subjects' strained facial expressions. Second, the photoflood bulb has a comparatively short life expectancy. Since you can't be sure that it won't go out at a crucial moment, this tendency to an untimely end doesn't contribute to your peace of mind. Then too, it makes photofloods expensive to use.

If you are an average amateur and have only regular house-wiring facilities available, you should be able to make good pictures with the following lighting equipment:

1. One or two 500-watt PS-40 Mogul-base bulbs in 16" bowl-type reflectors. These are excellent for general lighting purposes. The efficiency of the reflector is of great importance. The collapsible paper type is one of the most popular and is highly recommended.

2. A 500-watt T-20 bulb in a sunray reflector. This should be used for secondary lighting in doing portrait work. It is a good



most convenient way to mount one is on a flexible cable that is fastened to a heavy base. This allows instant adjustment.

4. A small spotlight with an adjustable beam. Such a light is handy, but be sure not to buy one of the smallest sizes. The bulbs are short-lived because they are inadequately ventilated.

Studio lighting is composed of two elements—general illumination and effect lights. General illumination is that which fills the room where you are working. It should be nondirectional. The degree of intensity needed depends on the reflecting power of the walls of the room—you will need more light in a dark-walled room than in one with light walls. This factor must also be considered when using flashbulbs. Effect lights are those that are played on a subject to produce a certain result. Naturally, they should be of higher intensity than the general illumination. You will probably be more successful in the beginning if you use but one effect light. Add additional lights only as you gain experience.

After setting up your lighting, determine whether or not balance has been achieved by looking at the scene through a blue viewing filter or a few layers of blue cellophane sandwiched between two pieces of window glass. Such a device will show up any uneven lighting much more clearly than the naked eye can perceive it.

To make sure of a high percentage of correct exposures with a certain lighting setup, conduct the following experiment. Calculate




Two 500-watt bulbs—one placed near the camera for an effect light and the other used for background lighting—provided all the necessary illumination for this fine portrait study

Small mirrors were used as reflectors to light up the centers of the morning-glories in the photograph below



what you think is the correct exposure and take a picture at that exposure; then take one at an exposure that is five times as long and another at an exposure a fifth as long. Develop the films and select the negative that will give the best results on No. 1 or No. 2 paper. The exposure that produced this negative will then be your standard exposure for that particular lighting setup. However, it may not be sufficient to bracket an exposure in this manner if the parts of a scene vary greatly in brightness. Then it becomes necessary to relate the exposure correctly to the development that the film receives. This balancing of exposure and development is the only means by which such contrasting material as that shown in the barnlantern picture on page 178 can be brought under control.

Whenever you find that you must use too slow a shutter speed, increase the intensity of your illumination. A good standard exposure for portrait work is ¼ sec. at f/6.3. If you use film



THE only light used in this photo was that from the lantern. A reflector was placed to the right of the subject. The flame gave a light-meter reading of 100 while the rest of the subject didn't budge the meter at all. This indicated that the brightness range was too great; so the flame was reduced to give a reading that indicated an exposure of 6 sec. at f/32. Such an exposure would have been correct for white light, but the flame was orange; so a 6-min. exposure (a tremendous overexposure) was used. The film was developed for  $4\frac{1}{2}$  min. at 70 deg. to 0.5 gamma. The print, on No. 2 paper, was developed for 6 min. at 70 deg. in an amidol developer with 45 c.c. of a 10-percent solution of potassium bromide.

that is larger in size than 2¼" by 3¼", it's not a bad idea to economize by making a mask to permit shooting two exposures on one sheet.

The barn-lantern picture that was just mentioned was taken as an experiment to find out how little light will suffice for good photographic work. The result seems to prove that it isn't necessary to bring a powerhouse into your home to photograph still life.

Each of the other pictures that are reproduced on these pages presented a distinct lighting problem for the photographer to solve. The winsome little "mother" on page 175 was posed in natural daylight. This alone, however, left her hair looking dull and lifeless; so a spot was used to high-light her tresses.

On page 176, the photo of the woman reading is an excellent example of balanced lighting. Thegenerallighting was in the form of daylight from a window at the left. For an effect light, a 60watt bulb was used in the tabletop lamp. The window shades were drawn until the lamplight effect was clearly visible in a blue viewing filter. This was necessary since the object was to get a picture of a scene that was flooded by the light of the lamp. If the general lighting had been stronger, the lamp would not have looked like a source of light. The film was overexposed— 1 sec. at f/6.3—and underdeveloped—0.5 gamma. A straight print was made on No. 1 black paper, developed in amidol with a 10percent bromide solution.


The coy sophisticate, also on page 176, was shot with natural daylight as general lighting, to which was added a spot for high light. The next picture, on page 177, was lighted by two 500-watt bulbs. One was placed near the camera and the other was used for general background lighting. The photo below it—that showing the morning-glories in a vase on a burlap background—was illuminated entirely by arti-

ficial lighting. Small mirrors were used to reflect the light into the centers of the flowers.


Remember that the difference between a good picture and a poor one is largely a matter of how they are lighted. Keep your lighting simple—one general light and one effect light are all you really need at first—and keep it under control. Don't manipulate your lights purely by trial and error, for that will waste time; instead, visualize the little bug on the apple and anticipate the effect your lighting will produce.

# CAN YOU BEAT THESE PICTURES?


We will pay \$5 for any photo used on this page. Write your name and address on each print. Enclose a stamped, self-addressed envelope and the negative, addressed envelope and send your contribution to the Curious Photos Editor.



THIS CHANDELIER OF BULLETS was made at the Ford Willow Run testing field where Liberator bombers, manufactured at the rate of one an hour, try out their .50-cal. machine guns. The giant magnet retrieves the spent bullets from the backstop so that they can be melted down for salvage.



MOTORBOATING can be more pleasant than it seems in the photo below. Some unwary driver had left his car parked on the beach, and the tide beat him to it. J. C. Soderblom, of Jacksonville, Fla., also happened by with his camera before the driver showed up.





GAS WITHOUT COUPONS was a lucky break for this boy who had a can handy when a gasoline tank truck went over a bank and 3,500 gal. of gasoline were spilled. Which all goes to show that even an ill wind can blow someone some good. H. T. Warren, of East Braintree, Mass., had a camera instead of a can.



Light is directed past the revolving wire drum to simulate dancing waves

specialty with Lee Zavitz, who achieves remarkable movie illusions with the ingenious use of commonplace materials. To obtain the effect of a sky filled with cumulus clouds, Zavitz directs a strong light through a pane of glass that has been daubed with shoe whiting. The result, projected on a background screen, is a convincing il-

lusion of reality. For a long shot showing the rugged Maine coast as a distant horizon, he used chicken feathers glued to a model of terrain to simulate weatherbeaten trees along the bleak shore. In a "process shot" that called for rippling waves on water, he



A glass plate daubed with shoe whiting is the heart of this ingenious illusion. The gaunt tree is a prop in the studio




To get weatherbeaten trees, Zavitz glues on chicken feathers

used the equipment shown at left above, in which light is projected past a slowly revolving wire drum to a background screen. These effects were staged for a Hunt Stromberg production called "Guests in the House."



PHOTOFLASH EXTENSIONS may be given greater flexibility with the use of a three-way socket as at the left. By using such a socket with two 15' extension cords—which would otherwise let the bulbs be placed only 15' away from the camera—you can place one 15' away and the other as much as 30' away.—L. H.

A CRACKED PLATE at the top of a tilting tripod head, often caused by strain, age, or careless handling, can be replaced with a piece of the molded plastic paneling commonly used for switchboards. Remove the damaged plate, use it as a template to mark the paneling, and drill it to receive the mounting bolts and camera screw.—W. E. B.



180

POPULAR SCIENCE

ADJUSTABLE RACKS designed by employees of the Glenn L. Martin Company have almost halved the time required to load formed parts for insertion in an anodizing tank. One type of rack consists of a center post with a toothed frame at the bottom; work is stacked log-cabin-style about the post and held at the top by an adjustable pressure plate. A hook at the top of the center post facilitates handling on an overhead conveyor. Another rack, used for longer work, consists of two posts separated by means of two channel sections.










LACQUERING THE GLASS in welders' shields and goggles has been found to increase greatly the resistance of the glass to scratch burns. In continuous spot welding it has been sometimes found necessary to change glass three times a day because of lowered visibility caused by scratch burns; yet lacquered glass has been used for as long as five weeks, after which it was necessary only to remove the coating and relacquer to continue using the same piece of glass. The idea was developed by Lafean Stine and S. Cyril Ertter of the York Safe & Lock Company, of York, Pa., after they noticed while welding a safe that sparks did not stick on a lacquered surface. They report that dipping the glass in lacquer gives the most durable coating.

SHEET-METAL SECTIONS pressed in forming dies at the Northrop Aircraft plant in Hawthorne, Calif., were difficult to remove by hand, and the use of pinch bars often damaged finished ones. An extractor devised by sheet-metal operators Mel T. Patch and Lee Howerton now removes sections from the die in a quarter of the time previously required, and without injury. It consists of two L-shaped bars connected by a crosspiece and hinged on pins that project from the male die. Both bars are shaped into hooks at the lower ends. A rubber band holds the device free of the work during forming. When the section is finished, the operator swings down the extractor so that its hooks engage the work. As the die is lifted, the section is pulled out.





WIRING BOARDS, on which intricate groups of wires and cables can be assembled, are the suggestion of W. L. Jackson (at left above) and John Downes, Westinghouse employees. The boards are used as an adjunct to the construction of complex switchboards, replacing the difficult and tedious job of wiring each board strand by strand. Under a suggestion-award system, Jackson received \$1,832.25 for the idea, and Downes was given \$610 for assistance in working out the details.



#### By ERVIN WALTERS

GAS-FIRED furnace is almost a "must" when you want to heat-treat or carburize steel; melt aluminum, brass, and similar metals; or perform any other operation that requires temperatures up to 2,000 deg. F. Such a furnace, built primarily for salt-bath treatment of tool-steel parts at temperatures in the neighborhood of 1,500 deg., is shown in the accompanying photographs. Scrap materials were used for the most part in building it.

Make the outer shell from a metal tank, a large paint can, or one of the kind used for auto grease. The shell shown was a compressed-air tank 12" in diameter. Cut off enough of the top to trim the shell to a length of about 12". Drill two holes to receive ¾" pipe—one about 4½" from the bottom and the other on the opposite side, 3" or so from the top. The lower hole is the intake through which the gas-and-air mixture enters the furnace chamber. The other is an exhaust, which functions when the top of the furnace is covered.


Spread a ¾" layer of dry sand over the bottom of the shell. On this, lay 21/4" firebrick, trimming it to fit. Use half-width firebricks, known as "soaps," to line the cylinder. Ten soaps, each 21/4" by 21/2" by 9", were used in the furnace shown. Two of them should have holes for the ¾" pipe. The lower hole should be cut on a bias so the intake pipe, when put into position, will be roughly tangent to the fire chamber. Set the soaps in high-pressure furnace cement. Use the same cement to fasten them together along their vertical edges. Fill the triangular spaces between the soaps by ramming into position a mortar made by mixing equal parts of fire clay and pulverized firebrick-or fire clay and sand-with enough water to form a stiff, rather dry paste.

Dry the furnace thoroughly before you use it. To hasten the drying-out process, suspend a 100-watt lamp inside the fire chamber while you make the other parts.

One way of making holes in the shell for the 34" pipe is to drill a 14" hole and then to ream it to size with a I" taper reamer. Finish the reamed holes with a file to smooth the edges

Use firebrick "soaps" to line the fire chamber, placing them on edge and securing them to the firebrick bed with a good high-pressure furnace cement

Mix fire-clay mortar and ram it into the spaces between the soaps. The fire chamber has here been plastered up with black furnace cement







POPULAR SCIENCE

### Gas Furnace for the Shop

Make a cover from two firebricks with a narrow space left between them; or, for easier handling, mold a doughnut-like cover out of the fire-clay mortar; or use an old grindstone of the proper diameter.

The fuel system consists of a blower, an air-and-gas mixing chamber, and connecting piping. The blower shown is an old vacuum-cleaner motor, complete with fan and housing. An ordinary hair drier without the heating coil could have been used, but the bearings in such a drier are not rugged; so they may not last under extensive service. Lacking either a vacuum-cleaner motor or a hair drier, you can adapt any induction or universal motor by adding a fan and a housing. These may be made from tin-can material. Provide a sliding or swinging cover over the intake opening of the fan housing to regulate air volume.

Although a constant blower speed is practicable, the illustrated motor was equipped with a rheostat to reduce the speed to a usable level and to provide control. This was taken from an old motion-picture projector and connected in series with one motor terminal. In series with the other terminal was wired a porcelain lamp socket. The wiring diagram is shown at the bottom of page 184. Experiment showed that a 100-watt lamp in the socket was just right for reducing the speed of this particular motor to the proper range. Another resistance unit that might have been used is

a water rheostat (see P.S.M., Nov. '44, p. 171). If you don't have a rheostat or the inclination to assemble one, you can create a resistance by wiring one or more lamps in series to reduce the speed of the motor to about 1,500 r.p.m.—you can determine the best speed when the furnace is in operation.

The method of mounting the blower depends on its design. That illustrated rests on a horizontal plywood board that is supported by two blocks. The rheostat and lamp are mounted on the same board, and the air intake is underneath, between the two supporting blocks. A guard made of \( \frac{1}{4}'' \) mesh screen protects the lamp.


Put a fitting on the discharge side of the fan so it can be coupled with the 34" pipe system. For the blower shown, a picklebottle lid, with a hole in it over which was soldered a length of 11/4" brass tubing, was used. A short 34" nipple, threaded at one end and with the other end built up with sheet metal to fit snugly inside the brass tubing, was then inserted. To this nipple was screwed a 90-deg, street ell, which was, in turn, coupled to a 45-deg. street ell. This was screwed into a tee, care being taken to place it at one end of the run rather than at the take-off. To the other end of the run, a longer nipple was added. The free end of this nipple was cut to a bevel to conform roughly to the inside curve of the furnace.


The gas jet goes into the take-off of the tee. It is a 4" length of 1/8" pipe or 3/8"


This shows the way the pipe fittings are arranged to connect the blower and the fire chamber. Note the beveled end of the pipe, which roughly matches the inside curvature of the fire chamber

As described in the text, the mixing chamber holds a tube, which acts as a gas-injection nozzle. When it is in place, the jets must face the furnace


Mount the blower, rheostat, and ballast lamp on a base that is made from a piece of plywood. Here the air intake is below the support







MARCH, 1945



tubing and runs through a hole drilled in a standard pipe plug, which is screwed into the take-off. The inner end of the tube is flattened for a distance of ¾" so the inside walls are about 1/16" apart, and then soldered shut. Four or five holes are drilled with a No. 50 bit along one of the resulting edges. The jet must be positioned in the tee so these holes open toward the furnace end of the pipe system, as shown in the drawing at the bottom of this page. Use a length of approved gas hose to connect the jet to the nearest domestic-gas outlet.

A convenient stand, shown above, was welded up from scrap material. It is bolted to a base that is made from 2" by 8" pine and equipped with four sturdy casters.

This furnace will produce a flame that is roughly spiral in shape and somewhat uneven in intensity. This unevenness is not objectionable when the work is held in a crucible. If a more even flame pattern is desired, install two inlet pipes virtually tangent to the fire chamber and on opposite sides, as shown below. When using a crucible, set it on a circular piece of firebrick higher degree. Repeat this produce a flame that is higher degree. Repeat this produce a flame that is higher degree. Repeat this produce a flame that is higher degree. Repeat this produce a flame that is higher degree. Repeat this produce a flame that is higher degree. Repeat this produce a flame that is you are reasonably sure that all has been driven out. Otherwise is will damage the furnace lining worst, will injure persons in the force of the furnace is as safe as parable piece of shop equipment.




You can make your own crucibles from sections of 4" steel pipe by welding disks in position to form bottoms. Each container should be about 7" high

At left, the completed furnace mounted on a stand that was designed for mobility. Finish the outside of the fire chamber with a coat of baking enamel


that is placed in the middle of the chamber.


Some experimenting may be required to get the right gas-and-air mixture. If the flame billows out of the furnace without much roar, you need more air or less gas. If it jumps around or goes out, you need more gas or less air. The flame will roar steadily when properly adjusted. Use a taper at least 18" long when lighting the furnace and always have the room well ventilated. Most of the heat thrown out will be projected upward; so some overhead shielding may be required.

Probably the mortar work will not be bone dry when you light the gas the first time, even though the furnace has been drying for a week or so. For this reason, operate the furnace just long enough to warm up the fire-chamber walls. After an hour or two, warm the walls to a little higher degree. Repeat this process until you are reasonably sure that all moisture has been driven out. Otherwise imprisoned water may cause an explosion that, at best, will damage the furnace lining and, at worst, will injure persons in the vicinity. Once dried out, and with adequate ventilation, the furnace is as safe as any comparable piece of shop equipment.



#### NEW SHOP IDEAS








SWISS NEEDLE FILES are easily broken if kept with heavier tools. This case, small enough to fit into a machinist's tool box, accommodates 28 files and unfolds as a bench stand.

Make the case of \%" mahogany to the dimensions shown, assembling it with glue only and rounding all edges and corners. The base consists of four sections hinged together. When folded, it should fit snugly into the case. To prevent it from entering too far, glue small strips to the bottom edges of the outside sections as shown.


Holes %" deep and ¼" apart are drilled in each section to receive the files. A stain and oil finish completes the case.— F. McC.





CENTER HOLES must be free from chips or dirt if accurate lathe work is to be done. They can be cleaned quickly with the device shown at the left, which can be turned in a few minutes from any bit of scrap rod. Dimensions are not important, but the angle of both cones should be exactly 60 deg.

In use, a piece of thin cloth—¾" by ¾" is a good size—is slipped into either slot and twisted about in the hole.—C. J. JESNIG.


CYLINDRICAL WORK is easily marked, soldered, or welded on this support, as it can be turned to any position without rolling it all over the workbench. The heel flanges were cut off two old roller skates and the skates were screwed fast upside down to a heavy baseboard. This arrangement saves much working space on a crowded bench.







A BROKEN DRILL embedded several inches deep in a big casting was removed by a welder as shown above. He first wrapped a welding rod with asbestos to prevent it from arcing against the sides of the hole, but left the tip bare. The ground clamp was laid on the casting and the rod inserted to strike an arc against the drill. When he felt the rod had fused with it, the welder broke the circuit by lifting the ground clamp. The drill could then be lifted out by the rod, saving the casting.—JOHN KRILL.




# TRICK LATHE TOOL DOES SLENDER TURNING


By W. A. Conway

TURNING long, slender work is an irksome job at best and sometimes almost
impossible with the ordinary lathe steady
rest; but here is a combination steady rest
and tool that permits reducing the diameter
of drill rod for nearly its entire length.
With the stock inserted in a hardened guide
bushing made to fit, it can be turned down
from the end to within reasonable distance
of the chuck. Interchangeable bushings
permit handling work of diameters up to
about ¼".

The shaft shown was designed for a cross-slide turret block, but it can be clamped on the conventional compound rest, as shown in the photos, or the design may be changed if desired. Such a tool also works successfully in a drill press, the holder being clamped to the table and the stock to be reduced being held in the chuck.


Cut the body from ½" steel bar or plate, using a metal saw for roughing out and a grinder or abrasive wheel for finishing, and drill and ream the hole for the bushing. Turn the bushing from tool steel, drill and ream its hole to the size of the stock to be handled, and countersink the end the stock






enters. Cut notches to form the tongue with a saw and file. Install the bushing temporarily, with the tongue in the vertical position, and scribe a deep, permanent straight line across it and the body for use in aligning and making fine adjustments.

The two pins projecting 3/16" from the body hold the bit in position, and it is secured by the L-shaped clamp. Note the overhang in the drawing that keeps the clamp from turning on the body when the cap screw is tightened. The extent to which the bit projects over the bushing hole determines the turned diameter of the work. Set the bit roughly with the help of a scale and make a test cut; then make fine adjustments by loosening one setscrew and tightening the other to shift the bushing.



### Question Bee

### Can you name these automobile parts?




Photos courtesy General Motors


- 8. Brake linings.
- 7. Sealed-beam headlight unit.
  - 6. Generator brushes.
    - oil-control ring.
- 5. Piston, two compression rings, and one
  - ANSWERS

- 4. Valve
- 3. Shock absorber.
  - 2. Camshaft.
  - I. Crankshaft.

## String Controls Switch in Two-Tool Setup

THE string-and-spool switch arrangement shown in the drawing and photographs was originally devised as a temporary measure to give convenient control of a motor that operated two power tools. It has, however, given good









service for more than five years. Three common spools, fastened to the bench with wood screws, serve as pulleys for a continuous loop of stout linen cord that is held taut by a coil spring. Attach the cord to an extension on the handle of a single-pole knife switch. A slotted cover for the switch (not shown) was also added. The spring acts as a handle at one end of the loop, and a split and glued dowel gives a finger grip at the other. For minimum friction, wax the cord or use two small silk-thread spools on a single axle for the middle pulley.—W. B.

#### Circuit for D.C. Shunt Motor Needs No Starting Rheostat

ORDINARILY a rheostat or other starting resistance is used in the armature circuit of D.C. shunt motors to limit the current that would otherwise flow at first through the armature windings because of their low resistance. The second control that this involves is sometimes inconvenient, especially with automatic equipment. To dispense with the rheostat, use the circuit shown below, bringing out separate leads from the field and the armature if these are not already supplied. The field is connected to the line through a safety switch that is normally kept closed. The motor can then be started by the armature switch without flashing over at the brushes .- HAROLD P. STRAND.






#### Holes in Pulley Reduce Slip

sometimes a problem on V-belt drives if one of the pulleys is small, as on a circular saw. I found that I could eliminate slippage on my saw by drilling a series of \(\frac{1}{2}\)" pul-

ley, spacing them ¼" in from the outer edge. Two additional holes were drilled at right angles to each other through the center of the pulley, and all burrs were carefully smoothed off. Care must be exercised in drilling to avoid drill breakage on the slanting inner surface.—W. H. KISSEL.

#### Plaque Conceals Light Switch

To HIDE the light switch in his study and to add an unusual decorative touch, one home owner covered it with an ornamental plaque, pinned as shown to the toggle of the switch. Pressing up or down controls the light.—K. M.







#### Decorative Hurricane Lamp Turned of Hardwood

ONE or a pair of these hurricane lamps will make good-looking ornaments for a living room or dining room and will be found useful in warm weather for lighting a porch or terrace. A 1½" by 3½" by 3½" hardwood block is required.

The circular recess for the chimney is easily cut with the piece mounted on the faceplate of the lathe. Although the dimensions given in the drawing are fairly standard, it is safer to take them from the chimney to be used, for chimneys may be found to vary slightly. Round the corners while the piece is still in the lathe. Finish to blend with the room furniture.—Norbert Engels.



#### **Button Bunny Put on Place Card**



THREE buttons of different sizes sewed to the front of a folded sheet of mat stock form the head, body, and tail of an attractive place-card bunny. Draw in the ears and paws with crayon and add a bow of yarn, tying it on the underside of the card, which is folded so as to stand upright.—B. N.



#### Map Markers Made from Common Pins


WITH map pins in demand, you may wish to make your own. Hold the point of a common steel pin with pliers, heat the head cherry red, and plunge it into a dish of household borax, a small amount of which will adhere. Heat this until it fuses into a ball of borax glass. Dip the head into powder again and reheat to increase the size. When cool, dip it in colored enamel.—KARL J. BURG.


#### Wrapping Cord Woven into Baskets Around Ice-Cream Sticks

SIMPLE yet interesting baskets can be woven with materials no more elaborate than ordinary wrapping cord and the sticks from popular types of ice cream.


Use a soft pine board ¾" to 1" thick for the base, cutting it to shape with a coping saw. Drill two tack holes in one end of each stick and attach the sticks no more than 1" apart around the circumference of the base. Glue an end of the cord to the base behind a stick, and then weave it in any pattern. That shown at the right below is a simple loop around each stick; that at the left is a loop around every other stick. Where a stick is skipped as in this case, the number used must be even.

Bevel the side of the base for a widetopped basket.—J. LEORA BROWN.






#### Wiring Puzzlers to Test Your Electrical I.Q.



TO MAKE a photographic dryer, Smith used a 600-watt replacement coil sold for use in toasters and stretched it over a series of hooks inside an asbestos-lined box. But he found the wire heated to redness, scorched the prints, and threatened to burn the box itself. To halve the amount of heat, should he cut the resistance wire in half, add a second element in series, or connect another in parallel?



A RADIO engineer, needing a 16½-ohm resistance across an amplifier transformer for testing purposes, found he had nothing but four 10-ohm resistors in his parts drawer, which therefore had to serve. How did he connect them?


Added to the unshunted resistance, this gives a total of 16.6 ohms.

Substituting known values:  


$$\frac{20 \times 10}{20 + 10} = \frac{200}{30} = 6.6 \text{ ohms.}$$

two of them with the fourth. The formula for parallel resistances is:

 $\mathbf{R}' \times \mathbf{R}'$ 



wishing to save wire, Jones hooked up two bells this way. Button a was to ring bell A, and button b bell B. Although pushing both buttons at once would cause a short circuit, Jones thought this would be of too short duration to harm the transformer, and he expected no trouble. He had trouble anyway. Why?




NOT having a double-pole, double-throw switch on hand, a photographer connected a S.P.S.T. switch a and a S.P.D.T. switch b as above to throw two flood lamps from series to parallel or vice versa. As all worked well in the positions shown, he considered himself lucky. Why was he even luckier than he thought?

I. Add a second element in series with the first, thus halving the current.

2. The bells will ring continuously even when neither button is pressed.

3. If switch a is closed while switch b is thrown to the right, a short circuit results and fuses will be blown. But it is sults and fuses will be blown. But it is satisfactory way. Can you do it?






WARPED PHONOGRAPH RECORDS that slip against other records on an automatic changer can often be straightened simply by placing them between glass and leaving them in a warm place for a few hours. Use two scrap pieces of plate glass at least 12" square and lay a sheet of paper between each surface of the record and a glass to avoid damaging the grooves. Put a weight, such as an electric iron, on top. A shelf over the kitchen range, or some similar spot, should provide sufficient warmth to take out the bend.


Occasionally a record so straightened will retain a slight curve that permits the convex surface to slip. This can be corrected by repeating the straightening operation with a 4" circle of heavy paper or thin cardboard on the center of the convex side.

Slipping usually occurs when a record is so warped that the drag of the needle is greater than the drag of the record on the one below it on the automatic changer. Two adjacent records in a set may be warped and still fit together in such a way that they do not slip. In such a case straightening is unnecessary.—WILLARD ALLPHIN.




SAFETY CAN BE ASSURED in working with experimental high-voltage electronic equipment by incorporating a double-pole double-throw switch in the circuit, as shown in the diagram above, instead of the customary line switch. This acts on the same principle as the more expensive and hard-to-obtain interlock switches, permitting the condensers to discharge automatically when the switch is thrown over. The resistor is added to prevent excessive sparking at the contacts. Since the discharge takes place in a matter of milliseconds, a 1-watt resistor is adequate.—George O. Smith.

shorts in a condenser, such as are apparent when a radio goes dead over part of the dial, can be traced quickly by rigging up a homemade tester consisting of two dry cells and a door buzzer. Disconnect the stator leads and connect the cells and buzzer in series with one section of the condenser at a time, as shown below. Then slowly rotate the condenser back and forth, watching the segments closely. A short will show up as sparks between the plates, which can then be straightened.—Otto H. MILLER.



#### MEASURING IMPEDANCES

#### [ELECTRICAL]



With the aid of an ordinary A.C. voltmeter, it is fairly easy to measure the actual impedance value of chokes, output transformers, and large paper condensers. If you have an inductance-capacitance-impedance-frequency chart, the impedance measurements so determined can be converted to henries or microfarads.

In Fig. 1, R is a known resistor approximately equal to the impedance of the inductance but to prevent extracting not less than

In Fig. 1, R is a known resistor approximately equal to the impedance of the inductance but, to prevent overheating, not less than 2.500 ohms, while L is the choke to be measured. Read  $V_1$  and  $V_2$  with the A.C. voltmeter; then use the following formula:

Impedance of L in ohms= R x V<sub>0</sub>

If R is 4.000 ohms,  $V_1$  is 88 volts, and  $V_2$  is 22 volts, then  $L = \frac{4.000 \times 22}{88} = 1.000$  ohms.

When impedance readings are made on transformers, the secondary must be loaded with a resistor of the value of the speaker voice coil normally used. The correct pair of secondary taps to match an 8-ohm speaker to a required output can be determined by measuring the impedance of the transformer with an 8-ohm resistor across dif-

ferent secondary taps.

In Fig. 2,  $R_1$  is a known resistor approximately equal to the impedance of the transformer but, to prevent overheating, not less than 2,500 ohms, and  $R_2$  is a resistor equal to the impedance of the normally used speaker voice coil. For push-pull transformers, use the two plate taps and ignore the center tap. Then, as with chokes, read  $V_1$  and  $V_2$  and use the following formula:

Impedance in ohms=  $\frac{R_1 \times V_2}{V_1}$ 

If  $R_1$  is 8.000 ohms,  $R_2$  is 8 ohms,  $V_1$  is 60 volts, and  $V_2$  is 50 volts, then impedance  $=\frac{8.000 \times 50}{-6.666} = 6.666$  ohms.

POPULAR SCIENCE MONTHLY SHOP DATA





# COMPLETING YOUR CARRIER-CURRENT RECEIVER

#### PART II

WITH strict wartime prohibitions against the use of radio transmitters by amateurs, and with sharp-eared Government monitors waiting to pounce on the source of any unauthorized transmission, many a radio experimenter has found carrier-current communication the best legal outlet for his energies. Though similar in many respects to radio, this method of transmission differs in that the signal is not radiated generally, but is instead merely fed into a wire. At some other point a receiver connected to the wire picks up the signal.

These photos of the receiver show its simplicity. Note the absence of the ordinary tuning condenser






Thus it's quite practicable to build for yourself a transmitter and a receiver that, plugged into light sockets, will give entirely private communication between two separate

points. One of the most useful applications is a sort of "electronic baby-tender"; you plug the transmitter in the nursery, connect the receiver in a friend's home where you are spending the evening, and scoot for home if and when you hear your child call.

The theory of operation, and the construction of a carrier-current transmitter, were described in an earlier installment (see P.S.M. for February 1945, pp. 192-194). Worth emphasizing again, however, are certain cautions that hedge the wartime use of even this limited form of communication:

1. Since in certain strategic areas Gov-



POPULAR SCIENCE

ernment rules prohibit all unlicensed communication, check up first to make sure that you do not live in such a locality. Your local War Emergency Radio Service will be able to tell you.

 Don't connect your transmitter to an aerial. This form of activity, like photographing new battleships and burglarizing arsenals, is apt to bring a vigorous response from the authorities.

Limit the transmitter output to 10 watts or less, and keep the frequency between 150 and 200 kc. Higher frequencies may radiate, while lower ones are needed by power engineers for their own messages.

4. If you plan to use your carrier-current equipment between your house and a specific friend's, check to make certain that both houses are fed by the same power-distribution transformer. The reason is that limited output power may not suffice to push the signal past the choking effect of such a transformer.

The receiver circuit, shown on page 194, is basically that of a T.R.F. receiver. It is similar to conventional broadcast receivers of this type, save that it has fixed tuning. Since you are interested in receiving only one station—your own transmitter—you can dispense with the complexity of tuning condensers. A second advantage of fixed tuning is that you can, with a simple modification, use standard 175-kc. intermediate-frequency transformers to serve as readymade, neatly packaged, and highly efficient tuned circuits.

The one modification is made in the primary of the input transformer (the one connected to the grid of the 6SK7). The

conventional way of connecting these transformers is to use parallel tuned circuits, as in diagram A; but because you will hitch one primary onto a power line, not another vacuum tube, you will need a series tuned circuit. The standard color code of the Radio Manufacturer's Association calls for red and blue leads to the primary of I.F. transformers, and green and black leads to the secondary. As you get the transformer from a radio-supply store, the circuit


Plugged into an outlet in a neighboring house, this neatly boxed receiver faithfully reproduces any sounds that are picked up in the nursery at home will be that of diagram A; take the coil out of its can and change its connections to those in diagram B. Keep the red lead attached to the same coil lead, because the orientation of the coils makes a difference. It's a good plan to install some sort of lug to which to solder the fine coil wire so that it won't get broken by handling of the red lead after the coil is back in its can.

Other tubes than those called for in the circuit diagram may naturally be used. For the power tube, any tetrode, pentode, or beam power tube may be made to do, though with varying rates of gain. A 6K7 or other remote-cutoff pentode can replace the 6SK7. A 6SQ7, 6Q7, or other diode-triode tube can replace the 6SF7, provided that another triode or pentode amplifier stage is added to make up for the lower gain.

Aligning the receiver and tuning the transmitter to it is fairly simple. Essentially, the procedure consists of using the transmitter as a test-signal generator while aligning the tuned circuits in the receiver. To do this, you will need to impress an audio-frequency signal on the transmitter output; one simple way is to run a temporary jumper from the grid of the audio power tube in the transmitter—the 6L6—to the ungrounded side of the 6.3-volt heater line, thereby putting a 60-cycle hum signal on the transmitter.

Disconnect the coupling condensers





A standard 175 kc. l. F. transformer will be found to be connected in two parallel circuits, as above

The first (input) transformer must be taken apart and rewired with its primary in series, like this

from the transmitter output secondary to the 110-volt line, and leave them off until aligning is complete. Temporarily ground one end of the output secondary, and run a test lead from its ungrounded end out to the plate of the 6SK7 in the receiver through a condenser of about 500 mmfd.

The signal should be amply strong enough to drive through substantial mistuning of the transmitter and receiver. It may be that the transmitter is tuned to a frequency beyond the range of the receiver transformer; in that case, try exploring with the trimmer in the transmitter oscillator circuit so as to bring the frequency into the range covered by I.F. coil adjustments. Adjust the trimmer of the second I.F. transformer to give maximum volume.

Next, move the test lead from the 6SK7 plate back to the coil side of C<sub>B</sub>, and retune the trimmers on both I.F. transformers for maximum output. Finally, remove the test lead entirely and sharpen the tuning.

With the receiver now tuned, place it as far from the transmitter as you can and still hear the hum from the receiver speaker, and adjust the trimmers on the 6V6 plate tank circuit in the transmitter. If you wish to accentuate the reception for tuning, try hanging about 4' of wire from the ungrounded end of the secondary in the transmitter, wrapping it loosely around the lead that carries power to the transmitter. Then trim the tank circuit to give maximum volume in the receiver, remove all temporary connections, replace the permanent ones, and you're done.—JOHN W. CAMPBELL, JR.

#### KEY TO RECEIVER PARTS

CA, CB: .002 mfd., 600 volt, mica

C<sub>2</sub>, C<sub>3</sub>, C<sub>4</sub>, C<sub>9</sub>, C<sub>10</sub>: .1 mfd., 400 volt C<sub>5</sub>, C<sub>6</sub>: 250 mmfd., mica

C7, C12: 20 mfd., 25 volt, electrolytic

C<sub>13</sub>: .25 mfd., 400 volt C<sub>14</sub>, C<sub>15</sub>: 10 mfd., 450 volt R<sub>1</sub>: 2 megohms, ½ watt

R2: 250,000 ohms, 1/2 watt

Rs, Rs, Rs: 500,000 ohms, 1/2 watt

R4: 500,000-ohm potentiometer, ½ watt

R<sub>5</sub>, R<sub>11</sub>: 300 ohms, ½ watt R<sub>7</sub>: 1 megohm, ½ watt R<sub>8</sub>: 100,000 ohms, ½ watt R<sub>10</sub>: 500,000 ohms, ½ watt


R<sub>12</sub>: 40,000 ohms, 1 watt R<sub>13</sub>: 25,000 ohms, 10 watt

T<sub>1</sub>: 70 milliamp, power transformer

T2: 8,000-ohm output transformer

## radio ideas






TELEVISION PROJECTION of images of a size to suit the room or auditorium in which they are viewed is possible with a reflective optical system developed by RCA. The principle has long been used in astronomical telescopes, but RCA experts in optics, electronics, and mechanical engineering were required to adapt it to short-throw projection and also to cheapen the cost to make it practical for television sets.

Special mirrors and a special lens are employed. A mirror with a concave spherical

YACHTSMEN'STELEPHONES—8-wattradio transmitter-receivers that formerly kept small boats in touch with land telephones and with other vessels—are now being used on Merchant Marine wartime cargo ships. A midget Western Electric ship-to-shore phone is shown in the photo at right in use on a Merchant Marine training vessel.

complete Radio-Tool Kits in portable size are issued by the U.S. Air Service Command's Supply Division to communications men at bomber and fighter stations in England for repair work on aircraft radios. Among the tools are a full set of socket wrenches, a drill motor and drills, soldering irons, assorted pliers, hammers, screw-drivers, open-end and adjustable wrenches, files, and a hacksaw.



This television-projection optical system gathers sufficient light to show a bright image on the lens even in daylight. Left, molding a lens; center, compact cabinet unit


surface takes the image from the television receiving tube and transmits it through a correcting lens to a flat mirror which projects it onto the screen.

One surface of the lens is flat while the other rises slightly at the center and edge from a depressed intermediate area. This makes it optically positive in the center and negative in the outer portions. To reduce the cost, a transparent material was found for molding the lenses on optically finished metal surfaces.


One compact television unit has the projection system mounted vertically in the cabinet, as shown in the drawing. The image is projected on a built-in screen.



#### HOME EXPERIMENTS WITH



EACH MOLECULE in magnetic material is itself a tiny magnet, according to the generally accepted theory. Ordinarily these molecules are arranged haphazardly, and the material has no definite polarity. When iron or steel is magnetized, however, the molecules are lined up in the same direction, and the ends exhibit both attraction and re-



pulsion for another magnet. Heat destroys magnetism because it loosens the bonds that hold the molecules together.

Magnetize a needle by stroking it on a permanent magnet, and it attracts one end of a compass needle and repels the other. Heat it red hot, and it attracts the compass feebly, if at all, and both ends behave alike.



WITH A "MAGNETIC SWING" made from copper wire bent into a U and hung loosely on copper-wire hooks, you can show how electricity and magnetism interact. Mount one pole of a bar or horseshoe magnet to project 1" or so through the "swing," as shown at the right. Touch the two leads from a dry cell to the two supporting wires, and the swing moves, the direction depending upon the connection. Reverse the connection, and it moves the other way.

When the swing moves out, the magnetic field created by the current flowing through it is of the same polarity as that of the magnet pole; when it swings in, the field is the opposite. This principle is applied to many automatic electrical switching devices and to electric motors.

MAGNETIZED IRON FILINGS illustrate the molecular theory of magnetism in another way. Fill a glass or paper tube nearly full of filings and, taking care not to shake the filings, magnetize them by stroking them over a permanent magnet. Tested with the compass, they have the same effect as the magnetized steel needle, attracting one end and repelling the other.

Now shake the tube to allow the filings to assume a haphazard arrangement. Either end of the compass needle can then be attracted feebly to either end of the tube. This is because disturbing the arrangement destroys the magnetism of the filings as heating did that of the needle.





#### MAGNETISM.

THOUGH NOT MAGNETIC, copper can be made to react to magnetism. Mount a horseshoe magnet on a 12" length of string so it can be spun by twisting the cord, and under it mount a copper disk to spin freely on a pivot. Adjust the length of the string so the magnet

won't quite touch the disk. Then twist the string a dozen times and release it. As the spinning magnet gains speed and gets closer to the copper disk, the disk begins to rotate.

Although the copper itself does not became magnetic, a magnetic field is set up around it by eddy currents induced by the revolving magnet. This reacts with the magnetism of the horseshoe to produce motion. The same principle is employed in household electric meters, with eddy currents produced by the A.C. itself.







THIS DANCING COPPER COIL demonstrates an odd trick of electromagnetism. Many who are aware that magnetic materials are drawn into a coil through which an electric current flows don't know that the turns of the coil tend to draw closer together at the same time because of magnetic attraction. Wind a loose coil 2" or so in diameter of a dozen turns of fine copper wire. Suspend one end from a stiff wire leading from one terminal of a dry cell and have the tip of the other end barely touching a little mercury in a dish.


Touch a wire leading from the other terminal of the dry cell to the mercury, and the coil immediately contracts because of the magnetic attraction between the turns, and in doing so it breaks the electrical circuit. When this happens, the coil spreads out again, the tip makes contact with the mercury, and the circuit is remade. This again causes the coil to contract, again breaking the circuit, and the process is repeated. The effect is best if the turns are rather close together.

MAGNETIC SEPARATION, known in many manufacturing plants where iron bolts and other parts must be separated from non-magnetic metals, can be shown with a model that makes a fascinating toy. Wind 100 turns of bell wire around half the length of a bolt about 6" long. Then make a continuous-belt carrier of paper, slipping one end over the other half of the bolt, which is left bare or covered with a glass tube to help the belt to turn. The other end of the belt may turn on a dowel or another glass tube. Motive power can be simply by hand or by any arrangement desired. Install a tent-shaped separator made of paper as shown.

Connect the ends of the bell wire to the terminals of a dry cell—one cell provides sufficient current—and drop sand and iron filings on the belt as it slowly turns. As they

reach the end at the magnet, the sand falls off immediately on the far side of the separator, while the filings stick until they reach the other.





## Silver

. . . most useful precious metal,
 it is prized for coins, jewelry,
 plate, photography, and medicine.

Mirrors are silvered with a solution of silver nitrate to which first ammonium hydroxide and then potassium hydroxide are added in drops

#### By KENNETH M. SWEZEY


F THE precious metals, gold, silver, and platinum, silver is both the most common and the most useful. Beauty, malleability, sonorousness, and resistance to atmospheric oxygen have put it in demand for coins, jewelry, tableware, ornaments, and bells since the beginning of history. Because it has the highest electric conductivity of any substance, it is prized in electric equipment. Silver nitrate, its most common salt, is used in making indelible ink and hair dyes, in photography and silver plating, and in medicine as an antiseptic and germicide taken both internally and externally.

The metal is found both in its native state and as a salt. Its chemical symbol Ag is derived from its Latin name argentum. The familiar sterling silver is solid silver alloyed with 7.5 percent copper to give it hardness. United States coins are a similar alloy of 10 percent copper. Plate is silver coated on a cheaper and harder metal such as steel or brass.

Because silver is the most highly reflecting of all the metals, most mirrors are coated with it. Minute particles of metallic silver, separated from a solution of silver nitrate by the addition of a reducing agent, are deposited on the glass. You can demonstrate the technique by silvering the inside of a small flask. After you have acquired

To silver a flask like that shown below, pour the ammoniacal silver solution into it and add a reducing solution. This changes the compound into finely divided metallic silver that is deposited on the glass





experience, you can silver telescope mirrors and ornamental glass objects. Use a porcelain, enameled, or paraffin-coated tray as a container.

The reducing solution must "age," so it should be made several days or even weeks in advance. Make it by dissolving 22 grams cane sugar in 250 ml. water in which has been mixed 45 ml. ethyl alcohol and 1 ml. concentrated nitric acid.

Do not make up the silvering solution until just before using for, although it is safe while fresh, it becomes concentrated when it stands and forms silver fulminates—sensitive chemicals that may explode at the slightest touch. Immediately after use discard the remaining solution by washing it down the drain with plenty of water.

This silvering solution is mixed in a large beaker or in an Erlenmeyer flask. For a first-rate silvering job, use only distilled water. Dissolve 5 grams silver nitrate in 75 ml. water, and add slowly with constant stirring some concentrated ammonium hydroxide. A dark-brown precipitate of silver oxide will form first, but it will dissolve as more ammonium hydroxide is added. When the solution begins to clear, put the ammonium hydroxide in drop by drop until it is completely clear.

Now add very slowly and with constant stirring a solution made up of 2 grams potassium hydroxide in 80 ml. water. Silver oxide will again be precipitated, and it again will begin to clear with the addition of more hydroxde. Stop adding the potassium hydroxide, however, while the solution is still a light brown, disregarding any suspended matter that may be present.

Clean the flask to be silvered with alcohol or ether and follow with a swabbing of nitric acid applied with cotton on the end of a glass rod. Rinse the nitric acid off with distilled water. Then immediately half fill the flask with the silvering solution and add the reducing solution until it is full, swirling the flask to mix the two. The temperature of both solutions should be about 18 deg. C. (64 deg. F.). Keep swirling the flask gently, and in a few seconds bright silver will appear on the inside surface. This coating should be sufficiently thick in about five minutes, after which the flask should be emptied down the drain and rinsed out to prevent forming of a fulminate. A coat of varnish or shellac will keep the silvered surface from tarnishing.


Although silver does not react directly with oxygen, it tarnishes by reacting with sulphur such as is contained in rubber bands (vulcanized with sulphur), eggs, and mayonnaise. Traces of hydrogen sulphide in the air also cause the black coating that requires frequent polishing.


To show the nature of tarnish, you can produce it quickly by exposing a silver object to hydrogen sulphide gas. Cover a few grains of iron sulphide in a small vial with dilute hydrochloric acid, place the vial in a tumbler, and put beside it a silver spoon that has been moistened with water. Cap the tumbler loosely and stand it outdoors or in a well-ventilated room, for the gas has a foul odor and is poisonous.

Most people remove the tarnish from silver by rubbing with a soft abrasive such as infusorial earth or precipitated chalk. An electrolytic method requiring no manual effort is also known to housewives. The silverware is placed in a clean aluminum pan, with each piece touching the aluminum, and is covered with water containing several teaspoonfuls of washing soda (sodium carbonate). To hasten the reaction, the water is heated almost to boiling. The silver, touching the aluminum and surrounded by sodium

Tarnish is removed from silver electrolytically with an aluminum pan and washing soda. To show tarnish is a sulphide, generate some hydrogen sulphide in a lightly covered tumbler containing a piece of silver







Black silver nitrate stains can be removed from cloth by copper chloride, hypo, and a water rinse

carbonate solution, forms one plate of an electric cell which first turns the silver sulphide tarnish into metallic silver and then deposits this on the pan. Steel wool easily removes discoloration from the pan.

This electrolytic method does not wear

the silver away any quicker than abrasive rubbing. It should not be used on silverware having a "French finish," that, is, a finish in which the depressions are toned with gray, since it may clean out the depressions as well as the surface.


Silver nitrate (AgNO<sub>3</sub>) is formed by dissolving silver in dilute nitric acid. In its pure form it is a white crystalline substance that readily dissolves in water. It is a strong oxidizing agent and will burn the skin, leaving a black stain of finely divided metallic silver. Silver nitrate stains on cloth may be removed by treatment with a 20-percent solution of copper chloride, then with a 10-percent solution of sodium thiosulphate (photographers' hypo), and a final rinse in plain water.


Add a solution of a soluble bromide, chloride, or iodide to a solution of silver nitrate, and you will get a light-sensitive salt of the kind that makes possible the whole magic of modern photography. Mix the salt with gelatin, spread the suspension thus made on a photographic plate or film, place this in a camera, expose it to the light through the lens, and the salt mysteriously changes. Examined under a safe light, the plate shows nothing unusual: but put it in a reducing or "developing" solution, and it is darkened by black metallic silver in density exactly proportional to the light that struck it.

The action of light-sensitive silver salts in photography can be demonstrated. Working under a red safe light, dissolve 1 gram silver nitrate in 30 ml. water and 1 gram potassium iodide in another 30 ml. water. Put 10 drops of each solution in each of two test tubes half filled with plain water and add a little standard photographic developer. You will have a whitish precipitate in the tubes. Take one tube into the light, and this precipitate will quickly turn black, the silver iodide changing into metallic silver under the influence of the light and the developer.

Again working under the safe light, complete the photographic process by adding a concentrated solution of hypo to both tubes, shake them for a minute or two so the "fixer" will dissolve the iodide that has not been acted upon by light and prevent its later conversion into black silver. The solution that was not exposed clears up completely, while the other becomes clear except for the settling metallic silver.

Here's how film works. Make two solutions of silver iodide and developer. Expose one to light to turn its precipitate black, as at left. Hypo clears both except for silver in the exposed tube






king tut's tomb, so you tell your friends as you present the puzzle above, was protected against vandals by a trick device like this. The chances are that most of your friends who try to open the little puzzle will have many a moment of frustration before they learn the secret.

Building details are given in the drawing above for the four parts—base, slide, cover, and brass stop. They are easy to make, but must be accurate. The stop fits into the depression in the slide and locks the box once the slide

and cover are in place. To open the box, merely turn the puzzle over, swing the cover out the proper amount, and let the stop fall into its depression. The slide can then be pulled back since its pivot hole is in reality a slot.

Use hardwood so the pieces won't wear, and finish with a stain and varnish. The dovetail can be glued into the base to avoid carving both from one piece.—George Barr.




CAN YOU REMOVE the eight wooden washers from the ladder shown at left without taking them off the string? This is an ancient Chinese puzzle, and it is still a teaser.

Thread the needle back through the washers and the holes in the rungs, beginning at the one on the top right in the drawing and keeping a loop above this washer so it is never really off the string. Now, thread the string through again, this time beginning at the upper left and taking the string through the washers but not through the rungs. All that then remains to be done is to draw the loop at the upper right through, and they will be off the ladder and on the string.—G. B.

DIAMETER OF HOLE

THREE TAGS held together with a cord, as shown at right, can be separated

easily by folding the slit portion through the hole in the large tag in the way indicated. It's a puzzle, though, that will fool a lot of people. Make the tags of cardboard that bends without cracking, and use reinforcement rings.—ROBERT M. COWAN.



#### Roadside Stand Made as Two-Wheeled Cart


THE farmer or other country dweller whose land sometimes produces a profusion of fruit or vegetables frequently finds that a roadside stand is a simple and profitable venture. Most stands, however, must be permanently placed, remaining out in full view in seasons when they are of no use. The stand shown can not only be trundled out of sight

when not needed, but also has the asset of an unusual and attractive appearance. It may consist of the wheels and axles of an old buggy or surrey, fitted with a simple 4' by 7' box body. Prop legs, a frame for



the awning, and a pole handle complete the essential parts. Paint the wagon stand a gleaming white and set it off with an awning of pleasing maple green for an attractive contrast.—BRUCE MACINTOSH.

#### Wire and Planks Serve as Unloader of Gravel or Coal in Truck



Army Motors, was devised overseas by Captain D. M. Googins, a member of the 184th AAA Gun Bn.

The unloader is constructed as shown in the drawing above, allowing about 1" side clearance between the plank ends and the truck body. The forward plank is fitted with a short vertical two-by-four that can be chained to hold the plank upright while the truck is being loaded.


If a power shovel is used for loading, the

ward of the center of the truck body; a little slack in the cables be-


tween the two planks allows the rear load to be dumped separately. Hook the cables to another truck with the brakes set; a convenient tree, or some other suitably solid object. During the unloading process, which consists merely of driving the truck slowly ahead, the truck floor will be scraped clean if one or two men "ride" the rear plank.

ARRANGEMENT

#### Rotating Lights Scare Ducks Away from Newly Planted Fields



Rotating the lights themselves isn't necessary with the flasher circuit shown above, for the lamps are energized in sequence. The original model, pictured below, uses a junked washing machine to turn them



WIDGEONS were a tough problem for farmer Joe Mc-Millan of La Conner, Wash., and none of the classic methods of widgeon assault—beating dishpans, waving red flares, shooting off firecrackers, and even potting a few with shotguns—seemed effective to him. For the widgeons, a breed of duck with a fondness for seeded fields, would merely retreat in the darkness until the rumpus ceased and then swoop back to feast on his newly planted acres.

McMillan on the road to a solution of his widgeon problem was the discovery that one part of his land was left severely alone by the foraging ducks. This part was near a curved highway, and auto headlights swept over it as they made the turn. His solution, evolved with the aid of Eugene Schuh and Charles Wildebour of the local utility company, was to build a widgeon-frightener: a revolving light improvised from eight headlights mounted on an old washing machine.


So thoroughly did this gadget alarm widgeons that Mr. McMillan's fame spread; lately the Government's Fish and Wildlife Service has come out with plans for a simplified duck-scarer, shown schematically at left above. In this design the lights themselves do not revolve, but are lighted in sequence by a flasher that gives the illusion (to widgeons) of rotation.—E. M. BERNARD


A BEAM 2,500' LONG is produced by this portable and rechargeable searchlight, according to its makers, the U-C Lite Manufacturing Co. of Chicago. It's powered by




a 6-volt storage battery that can be recharged without removal from its container by an A.C. rectifier, a homelighting plant, or other D.C. source. The lamp head may be turned in any direction and the unit is well balanced for . carrying on a shoulder strap or by hand. A snap-on lens gives a floodlight effect.

TESTING ELECTRIC FENCES has commonly been done with devices that simply showed the presence or absence of a potential on the section being checked. The tester in the photo below will indicate if current is being drawn off by weeds, branches, or cracked insulators to an extent that might render the fence ineffective in the control of livestock, according to the Prime Manufacturing Company, of Milwaukee, Wis.





#### Shades Tailored to Fit Each Window



COLORFUL figured or plain satiny oilcloth can be made up in your own home into durable, washable window shades. Patterns are available to carry out the decorative scheme of a kitchen or bathroom, while for other rooms there are handsome felt-backed oilcloths in white or cream with stainfinished brocade designs. Old rollers may be used if the springs are still good, or you may purchase new rollers of the desired width at a hardware or department store.

Cut the oilcloth ¼" narrower than the roller and 12" longer than the window. At the bottom turn up a plain hem with the longest stitch on your sewing machine or attach a scalloped border, as shown in the

drawing. In either case leave a pocket for a stick to hold the end flat. Then lay the oilcloth on the floor or a table and tack the upper end to the roller, using ¼" tacks so as not to damage the spring and checking to see that the finished side will be toward the room. Oilcloth usually comes very wide, and for kitchen and bathroom windows it may be possible to save material by using the width for the length of the shade if the pattern is such as can be turned sideways.

Handsome, serviceable shades for porches and playrooms can be made in the same way with fine matting. If you can obtain the proper widths, all you need do is tack it to rollers; otherwise you must cut it and bind the edges.—ELIZABETH KETCHAM.


#### Miter-Gauge Rod Serves as Auxiliary Fence on Circular Saw

For cutting duplicate pieces to identical length with the miter gauge, the rip fence is often used as a stop gauge, but pieces so cut off tend to wedge between the blade and the fence. Separate attachments are available, or a makeshift arrangement can be

set up by holding a piece of wood against the fence with a C-clamp. However, the purpose can be served admirably by using the miter-gauge rod as shown.

In the rip fence, well in front of the saw blade, drill a hole for a sliding fit for the miter-gauge rod. Then, directly above this hole, drill and tap a second hole for a thumbscrew to tighten on the rod. Work is set up to the rod while held against the miter gauge, but is clear of the stop when cut off.—BURL KNUTSON.







### Base Added to Station-Wagon Seat for Use in a Recreation Room

F YOU are planning to hold a large party in your basement recreation room, you probably will need extra seating facilities. You can use the leather seats from a station wagon for the purpose simply by adding temporary wooden bases to them. Make each base, as shown in the accompanying drawing, from four boards and four 2" by 4" corner posts. For a modern effect, make the base shorter and narrower than the seat. The over-all height of the seat

and base should be 15" to 18". Finish the base by countersinking and puttying all fastenings, sanding smooth, and painting with a bright-colored enamel. Attach the seat with hooks and eyes to anchor it for use of your guests. Then, after the party, put the seat back in the car and store the base for future use.—ROBERT M. FLETCHER.





**GROWTH-REGULATING SUBSTANCES** 

for use as selective herbicides—that is, for killing one plant while leaving another in perfect health—have been examined by two scientists, C. L. Hamner


and J. W. Mitchell. Experimenting on bindweed, they discovered that one of the most potent of these compounds is 2, 4 dichlorophenoxyacetic acid. In the photo at the right, the area shown at the left of the dividing line was treated with the acid. That to the right was untreated. Mr. Hamner asserts

TAKING THE JOLT out of tractor riding is the special feat of this new suspension seat, developed and manufactured by the Monroe Auto Equipment Company, of Monroe, Mich. Ever since that spine-jolter, the tractor, was first introduced, farmers have been far from comfortable while operating it. In this seat, a special triple-action hydraulic shock absorber offers resistance to violent action on the part of the coil spring under the seat, providing a level ride for the operator when the chassis bounces up and down over the usual rough terrain traversed by tractors.

AND PUTTIED

that such a treatment constitutes a new principle in weed control. The acid produces a cancer-like growth in the weed that leads to death by physiological response, not by the usual caustic action.






MODEL OIL DERRICK, 10½ feet tall, including base, duplicates all the important operations of the full-size rigs. Built by engineers for the Baash-Ross Tool Co., Los Angeles, Calif., it displays the operation of various tools far underground by showing them turning inside transparent plastic tubing. Insets show (at top) the ½-hp. operating motor, and (lower left) tool in its transparent plastic tube.



PLASTIC BINOCULAR CASE is made by Bakelite Corp. of low-pressure laminate. Advantages are lightness, dimensional stability at all temperatures, and resistance to moisture and fungus.

MODEL PREVIEWS of complete factory layouts have become standard with planning engineers of the Westinghouse Co. and others. Since every piece of model equipment is accurately scaled, engineers can tell the space each machine will occupy. Below is a Plexiglasenclosed model of a synthetic-rubber factory designed by the Blaw-Knox Co. The model was made by Display Studios, of Pittsburgh.



POPULAR SCIENCE

guns. The Japs are smart enough to realize this situation gives them a terrific supply problem, but their lack of productive capacity in their factories evidently has made it impossible for them to correct it in time.

Before this war is over, the Japs may have their entire army supplied with the larger, improved rifle. Even so, they will still be outclassed in that category, for their newest rifle is not as good as our old Springfield—to say nothing of the Garand. They have finally achieved a muzzle velocity of 2,300 feet per second, as against 2,800 for the Springfield and Garand. Their effective range is now only 600 yards, as against our 1,000. In other words, the service rifle with which the Japs will end this war is not as good as the one with which we ended the last one.

It is much the same story throughout the whole comparative picture of war weapons. If the Japs could not copy as simple a thing as a shoulder rifle and produce one equal to the original, given all these years to do it, what chance have they to equal the extremely complicated machines with which we are fighting the war?

There are various explanations of Japanese backwardness among our experts who are well informed about the Japs and their production methods. Some think it is due primarily to a lack of engineering brains, some to a dearth of skilled mechanics, some to their limited factory capacity. It may be a combination of all these factors, and others besides. Whatever it is, the end result is the same—a hopeless tardiness in producing the weapons for fighting such a war as this, a fatal lack of adequate armor with which to meet us in the final showdown.

No doubt the Japanese war lords are aware that their finish will come quickly if and when we get into China with such force and equipment as we now have in Europe. Estimates in Washington differ widely as to how long it will take us to achieve such a landing. The Japs may be expected to stake everything upon preventing us from making a landing in force, and that includes their whole navy and all their air forces, to the last ship and plane.

# World's Biggest Bargain Counter

(Continued from page 129)

overnight hikes, and are generally useful to hunters and campers, especially as they roll up into 6 by 30-inch rolls and the T bars come apart for easy packing.

The Procurement Division maintains sample rooms at its eleven regional offices in the United States and one in Puerto Rico. In its Washington showroom, for example, it is currently displaying dummy rifles suitable for cadet drill; bolo scabbards which can be converted into belt tool carriers; skis, shoes, discarded packs, a Signal Corps signaling device, various surgical instruments and appliances (some of which make excellent model-making tools), and cots and mattresses.

Already on the retail market are the first items of electrical equipment, such as compact field telephone sets of the Army Signal Corps. Each of these consists of two self-contained telephone units five by nine by 10 inches with connecting wire. The bells work on a magneto and, as the instruments are built for the most rugged service, there is hardly anything to get out of order. One department store advertises these at \$29.95.

Lanterns are available in wide variety boat signal lanterns, circular masthead lanterns, and signal lanterns with swinging handles.

Of great appeal to those who need a small boat is the so-called M-1 flatbottom assault boat, constructed of quarter-inch waterproof plywood on oak frames. The over-all length is 13 feet, 6% inches, the beam or width amidship five feet, four inches. These boats are sold to dealers with a retail ceiling price of \$75. Since the transoms are too high for outboard motors and have to be cut down for that use, dealers may add a reasonable charge for the work, as well as for supplying thwarts, oarlocks, and other accessories. The Maritime Commission has some used and reconditioned boats for sale to individuals at a top price of \$56.

Life rafts will also be distributed by the Maritime Commission. They might be used for diving floats at lake resorts.

Very few of the items will be sold directly to the public by the Government, but department stores, mail-order houses and other retail outlets are supplied with a publication, "Surplus Reporter," which lists the items that are being released as surplus property.

Besides the Treasury Department's Office

of Surplus Property, which handles most consumers' goods, and the Maritime Commission, which sells ships, small craft, and marine fittings and supplies, there are several other disposal agencies. The Reconstruction Finance Corporation will sell capital and producers' goods, such as raw materials, manufacturing plants, real estate, machinery, airplanes and parts; and its subsidiary, the Defense Supplies Corporation, also will dispose of some surplus goods. The War Food Administration will sell surplus food. The Army and Navy, although selling large quantities through the disposal agencies, will sell certain small lots, mostly through their own salvage depots.


To co-ordinate the activities of all agencies in an attempt to avoid the many mistakes made in disposing of surplus goods after World War I, Congress has set up an overall policy-making body, known as the Surplus Property Administration. It will set the pattern for the sale of all Government surplus property, but will not actually conduct sales itself.

# Phosphor Crystals Have Role in Postwar Electronics

PHOSPHOR crystals that absorb light and continue to shine in the dark will exert a strong influence on the postwar development of electronics, says Dr. H. W. Leverenz, of the Radio Corporation of America. In fluorescent lamps they will function as illuminants for homes, business buildings, and streets. Other phosphor crystals, it is predicted, will display news and entertainment on the screens of our television sets, while kindred phosphors in the screens of electron microscopes will aid in fathoming the mysteries of bacteria and molecules toward the end of promoting a healthier and happier life. Phosphor crystals have been known for centuries, but it remained for electronic research to put them to practical use. Through work with television, highly efficient luminescent materials have been devised to glow in almost any conceivable color.


Salvage every scrap of waste paper — old magazines, newspapers, wrappings, corrugated boxes, and outdated correspondence. It can be reworked into cases for blood plasma and other supplies for our fighting men.

### Simple Paper-Perforating Knife



PERFORATING single sheets of paper, mimeographed forms, and thin cards for tearing "on the dotted line" is easy with this quickly constructed device. The base and paper guide are made of wood. The perforating knife is a length of old hacksaw blade and has a knob handle. Assemble as shown in the drawing above. In use, place the paper to be pierced on the base and bring the blade down sharply.—KEN MURRAY.

#### **Novel Sandpaper Pencil Pointer**



To PRODUCE a fine point on a pencil, remove the metal knife from a plastic sharpener, insert the pencil, and lay a scrap of sandpaper over the groove, holding it in place with the left thumb. Light pressure of the thumb gives a long point—heavier pressure gives one with less taper.—K. M.



"Is that Dutch enough for you?"



#### WHEN YOU BUY NEW TIRES:

### Choose the Name You Can Trust in Rubber!

The factors that dictate wise tirebuying have changed.

Because today ALL tire manufacturers use the same raw synthetic (GRS) in building their tires, extra value depends entirely on the skill of the maker.

This GRS (Government Rubber Styrene) is a wholly new material. It requires new compounding and fabrication techniques. Hence the size of a manufacturer's plant or his prewar popularity are no longer reliable guides to the quality of today's synthetic tires.

That's why it will pay to give more attention to the name that is

"signed" to the new tires you buy.


The name "Seiberling" molded into a synthetic tire means:

- it was designed and engineered by men who have repeatedly distinguished themselves in the creation of basic tire-building improvements,
- it was built by the organization recognized as "Experts in Rubber",
- it is marketed by people who have a priceless reputation for honesty.

You can select a Seiberling Synthetic Tire with complete confidence. It bears —

THE NAME YOU CAN TRUST IN RUBBER

BUSINESS MEN DISPLAYING THIS



# LIGHTER MOMENTS with fresh Eveready Batteries



"Lucky this is on practice maneuvers and lucky we had a tailor with us!"

"Keep Your Eye on the Infantry the Doughboy does it."

THE CHANCES are that you are having difficulty obtaining "Eveready" flashlight batteries. We want you to understand the reason for this wartime shortage. Practically our entire production is earmarked for the Armed Forces and vital war industries.

After the war "Eveready" batteries will be plentiful again. And for your advanced information they will be even better . . . designed to give longer life, improved service.

1000



The registered trade-mark "Eveready" distinguishes products of National Carbon Company, Inc.

encouraging a shrinkage rather than an expansion of landing areas? If whirling-wing craft—which can take off straight up and land straight down—are first in popularity, will communities be dotted with relatively small fields, rather than a few larger ones?

To all these questions only the public can answer. Any air line or manufacturer would



"Okay, Tower! Just one more thing, please. How the devil am I going to find out which is Runway 257J?"

give a year's earnings to get those answers in advance. The trouble is that the public itself doesn't know them yet.

Using the only lamp by which man's feet are guided—the lamp of experience—manufacturers, air-line executives, and private flyers are counting on compromises in arriving at airport sizes and runway lengths.

While at least two manufacturers are planning the construction of airliners to accommodate 100 passengers or more, which would require 10,000-foot runways, Charles I. Stanton, Deputy Administrator of Civil Aeronautics, says:

"Twenty- to 60-passenger airplanes are going to be the backbone of our domestic air-transport system for some years to come, because they can furnish long-distance travel with intercity bus-schedule frequencies. Edward Warner, of the (Federal) Civil Aeronautics Board, concludes that 50-passenger airplanes are likely to be the best for transatlantic services also."

Cities, anxious to be on the main line of air traffic, are in a quandary. It is axiomatic among airport engineers that if you double runway lengths, you require four times as much over-all area in an airport. They state, too, that if the terminal is placed in the center of the airport, with runways sticking out like the spokes of a wheel—a favorite current design of some of the planners—you again quadruple the size. That automatically pushes the airport farther from town. Great expanses of land rarely are available at the city limits except at prohibitive prices.

So compromises will be made. A few of the big cities will have super-airports with a few paved runways nearly two miles in length. Very likely these will be for airliners engaged in intercontinental flying. There will be hundreds of terminals with runways no more than a mile in length for intercity schedules.

Typical of the outsize airports to come is Idlewild, under construction for New York City. It will cover 4,057 acres, contain a dozen paved runways and, when complete, will be able to handle a theoretical total of 5,760 take-offs and landings each 24 hours. Chicago has under consideration a vast airport covering 3,600 acres fronting on Lake Michigan.


Of the first half dozen runways to be built at Idlewild, by the way, two will be 10,000 feet long, and the other four will scale down to 8,200 feet, 7,500, 6,500, and 6,000 (2,000 yards).

For airliner operation, airport saturation depends not on the size of the landing area but, instead, on the number of schedules that can be handled hourly. That, in turn, depends on the number of planes that can be dispatched and landed under instrument-flying conditions—when fog, snow, or heavy rain lowers the "ceiling" and reduces visibility. That, finally, depends on the installation of parallel runways and the refinement of radio aids.

Parallel runways now permit only six departures and as many arrivals an hour in instrument weather. Engineers are hopeful of boosting that to 30 in and 30 out—or one movement per runway each two minutes—in the next few years. In clear weather a movement of 70 planes an hour on one runway is considered feasible.

Just what the private pilot will have in landing facilities in the postwar years will depend in part on demand, in part on the vision of the men planning for the future of private flying. The utility of the private plane hinges on that hoary conundrum: Which came first, the chicken or the egg? Should private flying create the demand for

(Continued on page 212)



## No Flying Without Airfields

(Continued from page 211)

landing areas, or should landing areas create the demand for planes?

The national aviation planners are banking on an increased demand for planes if the landing areas are created first.

Very likely several hundred of the larger airports ultimately will be closed to private flying. Even now the big terminals discourage the patronage of the private pilot by charging him landing fees. (At New York City's La Guardia Field, for example, the minimum charge for a private-plane landing is \$2.50.) They don't welcome private planes for the same reason that a rail-road terminal does not plan for, or welcome, the business of the private motorist.

In the postwar years the landing areas for the private pilot will have all the landscaped beauty of the express highway. They will cluster around the perimeters of the big cities, or, indeed, be built right within the city limits, within easy reach of the business district. They will be as much a part of the smaller community as the playground or the town square.

Nor will they be limited to that. Intermediate landing areas, probably to be known as "flightstops," will be sprinkled liberally throughout the country. In the form of T's or L's to provide take-offs and landings for all wind directions, they will be built at the intersections of major highways, and more than likely be adjoined by the counterparts of the automobile tourist camp. There the itinerant pilot can land in the face of a storm front or tarry overnight.

Col. Earle Johnson, national commander of the Civil Air Patrol, Army Air Forces auxiliary, suggests that both for the future of civilian flying and for the military security of the nation landing facilities can well be made postwar victory projects—taking the place of "useless" war memorials.

The national airport program is identified inseparably with national defense. Airports mean facilities for moving armies from one border of the country to the other by air overnight. They mean the opportunity to concentrate fighting and bombing planes at any point that may be threatened. They mean mass flying, and mass flying means a backlog of men who will know at least the rudiments of aviation if they must be thrown into military training in another emergency.

Tomorrow's airport-airpark-airstop-air harbor network gives promise of crystallizing what airmen have been talking about almost since the turn of the century—mass three-dimensional travel.

# Engineer of the Flying Blanket

The Story of Bob Sambleson

In Bridgeport today, in England tomorrow, Bob Sambleson works as if the outcome of the war depended upon him alone. And that's the spirit of his associates who stopped the peacetime manufacture of electric blankets and sent them sailing through the sky in the form of electric flying suits for the AAF. They give our fliers warmth and unhampered movement . . . when they are flying in the crippling cold of 60 below, four and five miles above the earth. General Electric Co., Schenectady, N.Y.



Bob Sambleson grew up on Long Island. He liked sports, radio, and Scouting. Canoeing up the Hudson River, with another Scout, was an early adventure.



Since graduation, Bob has been with G.E. at Bridgeport. His wartime job is designing electric flying suits; he often takes part in cold-room and flight tests.



He studied hard at Stevens Tech, won a varsity "S" in lacrosse, wrote a musical comedy for the college players, and was president of his fraternity.



Electric suits, plugged in like a toaster, keep our fliers toast-warm. Sambleson and his fellow-engineers have designed 285 electric garments.






GENERAL ELECTRIC



Hear the General Electric radio programs: "The G-E All-girl Orchestra" Sunday 10 p.m. EWT, NBC-"The World Today" news every week day 6:45 p.m. EWT, CBS.




# New Electroaire Power Unit Converts Standard Drill Press to Automatic

This exact control over feed and retraction speeds permits ready conversion of a standard drill press with tapping head into an automatic tapping machine, capable of producing Class III threads, even with comparatively unskilled operators. By adjusting speed to conform to the lead pitch of the threads being tapped, the tap will cut without forcing threads, and on the reverse the tap will actually "float" out of the part with no strain against the thread angle.


Air-powered jigs and fixtures can be opened, closed, and indexed by the Electroaire Power Feed. The unit can be set for a predetermined number of cycles so that multiple holes can be drilled in the same piece without ejection, by means of an indexing fixture controlled and synchronized by the Electroaire Unit. One operator can run as many as two or three drill presses, turning out topquality work with few rejects and with a minimum of tool breakage, thus effecting a great savings in time.

Present stockpiles of finest quality materials used in the manufacture of Wrigley's Spearmint chewing gum are now exhausted—necessitating discontinuance of production. When a supply of proven materials—known to be up to the finest standards of quality—is again available, Wrigley's will resume production—And Wrigley's Spearmint will be back to again help you on your job. In the meantime they are manufacturing a war brand. Wholesome but not excellent enough for the Wrigley brand name.

You can get complete information from Electroline Manufacturing Company, 1975 East 61st Street, Cleveland 3, Ohio



Set up to punch 3 holes simultaneously



Shows holes being drilled automatically

Z-58

POPULAR SCIENCE





# a Nicholson file for every purpose

3000 kinds, cuts and sizes for every industrial, farm, home and "hobbyist" use. FREE BOOK, "File Filosophy" (48 pages), on kinds, use and care of files.

Nicholson File Co., 19 Acorn St., Providence 1, R.I.

(In Canada, Port Hope, Ont.)

### What's in the Basement?

(Continued from page 68)

where it was dropped. The scientists have considered, but not tried, putting a tiny radio transmitter on the pole so that it can send out an SOS when it breaks water.

Another, more sporting, method is generally used now to regain the 200-pound, free-floating, camera rig. Buoys, salt cubes, and weights are put on dummy poles, which are dropped at the same time that the important one is tossed to Davy Jones. By varying the amount of salt, these extra poles can be made to rise at 15-minute intervals. And by following these guideposts as they pop up, the photographers can be reasonably certain of finding the pole bearing their camera.

Even though the apparatus is not attached to the ship, several exposures can be made on each descent. A clockwork, started by the pole's collision with the bottom, advances the film and clicks the shutter. Two pictures usually are taken because the first one is likely to be clouded by sediment stirred up by the pole. The first shot, in fact, often looks as though there were a cloud of dust on the floor of the ocean, but a second view, 30 seconds later, is frequently as clear as though the scene were on a sunny shore.

An ordinary large flash bulb can be sent down 60 fathoms (360 feet), and little bulbs can be lowered 650 fathoms without protection. For deeper dives, the little flash bulbs are placed in glass cups, exactly like the sediment cup on an automobile fuel line. Dr. Ewing also has obtained some 12-volt bulbs in Pyrex envelopes, three sixteenths of an inch thick and about two inches in diameter. These have proved satisfactory at a depth of nearly four miles.

Motorcycle batteries hung on the camera pole light the bulbs. The batteries are enabled to withstand the pressure by overfilling them with liquid and substituting little rubber balloons for the caps. The balloons permit equalization of the interior and exterior pressure. Very little insulation has been found necessary for the wiring. Lucite sleeves are placed around the electrical connections, however, in such a way that the increasing pressure of the water tightens the connections as the apparatus descends.

Best results have been obtained by hanging the flash bulbs below the camera on the pole, between the lens and the bottom being photographed. Cone-shaped reflectors are substituted for the platters generally used. And the photographers hope eventually to obtain special under water flash bulbs with built-in, conical reflectors.

(Continued on page 220)

# From a string on a strut...

# To this...

In the EARLIEST days of aviation, airplanes had no instruments—and a pilot flew "by the seat of his pants."


Sometimes aviators tied a piece



of string to a strut. In normal flight it whipped straight back. If the string deflected to one side it indicated that the plane was slipping sidewise. But mostly they flew by the feel of the wind in their faces, and by direct observation of the ground and the horizon.

In 1914, at the beginning of World War I, flight instruments began to appear. One of the first was the Sperry Magnetic Compass for instrument panel mounting—a big improvement over former compasses of the marine type which were placed on the floor of the cockpit.

The Sperry Turn Indicator was introduced in 1918. It was so basic in design that practically every airplane that flies today carries an instrument of that type. A few years later another basic flight instrument appeared on instrument panels—the Sperry Directional Gyro. Being non-magnetic, it eliminated the swaying needles and magnetic error of the usual compass, and is still



Instrument panel of a Sperry "flying laboratory" showing the last word in modern flight instrumentation.

found among the dozens of amazingly accurate flight instruments on which pilots depend today.

Sperry flight research has grown many times over, and it



Sperry engineers testing intricate flight instruments in a B-24 lent by the A.A.F. and fitted by Sperry as a flying laboratory.

embraces the new science of electronics in many of its projects. Under the stimulus of wartime demand, new devices have been developed in record-breaking time—and in record-breaking numbers.

Many of these developments

are secret. But it is one of the few compensations of war that many of them will someday be adapted to peacetime use. Radar ... automatic flying devices ... new types of compasses such as the Gyrosyn . . . the Attitude Indicator . . . instrument landing systems . . . airport traffic control instruments . . . and many others.

When that time arrives, Sperry's research laboratories will tackle the task of making peacetime flying safer, swifter, more economical, and more comfortable.

WAR BONDS-TO HAVE AND TO HOLD!


# SPERRY


C O R P O R A T I O N 30 Rockefeller Plaza, New York 20

FORD INSTRUMENT CO., INC. SPERRY GYROSCOPE CO., INC. VICKERS INC.

Waterbury Tool Division, VICKERS INC.

Buy War Savings Bonds and Stamps regularly.





### When It's Clear Sailing Again

In these crucial days every shipbuilder is producing only for Victory. So Defoe's job for the duration is to build fighting ships for the Navy. But some day there'll be clear sailing again for pleasure vessels. Then, it will be anchors aweigh for safer, swifter, more beautiful new yachts, embodying new materials, new power plants, new comforts and economies. One of the most interesting developments for ocean-going yachts will be seen in the advance of instrumentation. This will include the magic of radar, improved radio, electro sounding and gyro-compass control—combining the most perfect ship protection in the history of the sea. Postwar private craft built by Defoe naturally will reflect this organization's forty years of yacht-building experience as well as the new techniques and high standards of precision craftsmanship developed here in record-breaking construction for the Navy. Defoe's Yacht Division invites correspondence and will give individual attention to all inquiries.

CUSTOM YACHT DIVISION

DEFOE SHIPBUILDING COMPANY, BAY



CITY, MICHIGAN

Four White Star Renewal Citations now decorate the Navy "E" Award won by Defoe workers.

BACK THE ATTACK -BUY WAR BONDS SHIPS FOR VICTORY SERVANTS FOR PEACE

MARCH, 1945

Buy War Savings Bonds and Stamps regularly.

219



# VALSPAR STANDS UP FINE!

An "ocean of Valspar" would hardly exaggerate the amounts used these war years! Millions of gallons of Valspar paints, varnishes and enamels are meeting the toughest of all tests—protecting our armaments and military installations against

> Arctic blizzards and blazing tropical sun.



People at home who want the best in paints, enamels and varnishes have been using huge amounts of Valspar too. Valspar is the best you can buy. Valspar Varnish never turns white—Valspar paints and enamels give protection . . . lesting beauty . . . make home repairs easy! Ask your dealer for Valspar—today!

### What's in the Basement?

(Continued from page 216)

Peacetime probing of the depths with the photographic apparatus now available is almost certain to yield new clues to many mysteries. Dr. Beebe reported after his record-smashing bathysphere descent that "there are so many interesting things down below that you cannot hope to remember them all when you come to the surface." But the camera does not forget. Nor is it affected, as the mental processes of divers may be, by the pressure at great depths.


Life is more abundant in the ocean's lower stories than in its upper stories. The denizens of the deep perish if brought up in nets—possibly, too, only the weaklings are caught. "Photography," says Dr. Ewing, "appears to be the only certain method of taking a census of the population."

Conceivably, luminescent organisms will be found in the bottom of the big oceanic basins. Although the fish that dwell about midway down can hardly see at all, the creatures that live farther down sometimes have well-developed eyes, like those of the fish that frequent the surface. Hence, some scientists suspect that there may be some source of light in the areas far beyond the sun's rays.

Mysterious tracks have been found in many of Dr. Ewing's pictures of the sea floor, and the use of bait to lure the makers of those tracks within range of the camera is being studied. Dogfish sharks already have cavorted before the lens at greater depths than the biologists suspected them of descending; surprisingly thick beds of starfish, oysters, and sand dollars have been discovered; and the botanists have been shown photographs of sea ferns, like those formerly found only off the coast of England, growing beneath the Atlantic near the American shore.

Until recently, geologists doubted whether waves rippled the sand more than 30 fathoms (180 feet) below the surface. Now they have photographs of ripple marks 100 fathoms down. This is a fact of considerable significance, because these marks are a means of determining the conditions under which sediments are deposited.

Previous explorers have obtained samples of the oozes and rocks beneath the oceans by shooting special underwater guns into the bottom. In these materials, evidence has been found that the world is at least 1,300,000,000 years old. By photographing as well as lifting out and analyzing parts of the foundation under the seas, much more may be learned about things that happened long before Adam and Eve.



# BETWEEN MODUFLOW AND CONVENTIONAL HEATING Control SYSTEMS


THE CHARTS above are actual temperature recordings taken from two identical houses. One was equipped with ordinary "on and off" heating controls. The other was equipped with MODUFLOW, Honeywell's remarkable new heating control system. Compare the ups and downs of the old system with the smooth, even comfort of MODUFLOW. Moduflow eliminates wasteful overheating and drafty, cold floors . . . Every home can afford the greater comfort and efficiency of Moduflow.

### HOW Moduflow WORKS



Moduflow operates on an entirely new principle. It can be used with most automatic heating plants, either hot water, warm air or steam. Shown here is a warm air system. The heavy black lines show the simple additions required. Room temperature is controlled by the Moduflow Thermostat while temperatures of the warm air supply are governed by the bulb in the duct. The Reset Panel, operating at the command of these instruments, controls the burner and fan. Air at the right temperature is continuously circulated. Send coupon for the complete story of Moduflow.





Postwar Home"





shock absorber: On the power strokes, each piston in a Wright Cyclone has to absorb a blow of 15,000 pounds, or a force equal to the weight of three elephants. The full weight of this force hits a piston face only 61/8 inches in diameter.



WEIGHT-KILLER: This is the Wrightdesigned forged cylinder head which cuts weight from aircraft engines. Stronger than cast aluminum heads, its extra power cuts weight per HP. This cylinder alone will turn out 150 HP, enough to power three training planes. Equal in power, a locomotive and a Wright Cyclone aircraft engine make an amazing contrast in size and weight. Both develop 2,200 HP. Yet the Cyclone, with its 55-inch diameter and weight of only fractionally over a pound per horsepower, would fit easily into the cab of the 200-ton locomotive.

A vast difference in bulk is one reason why locomotives ride on rails while Cyclones fly. All aircraft power is a specialized field—tremendous power packed into small space at low weight, but Wright engines lead this field, for they are highest in power, lowest in weight. That's why Wright engines have powered leading planes for 25 years.


### Write for "ENGINOLOGY" a 100-page booklet on the "Why" of engines

A complete, non-technical booklet on engines and their relation to planes and propellers. Describes operating principles of engines. Explains combustion, supercharging, ignition, carburetion. Just send twenty-five cents in stamps or coins to: Wright Aeronautical Corporation, Dept. P.S., Paterson 3, New Jersey.



AIRCRAFT ENGINES

A DIVISION OF CURTISS-WRIGHT CORPORATION



222

Buy War Savings Bonds and Stamps regularly.

POPULAR SCIENCE

# Here's how your car FEELS...

# ... after MARFAK chassis lubrication!

"She sails along beautifully," you'll say to yourself, after your car has received a MARFAK chassis lubrication job. And it'll stay that way, too. Because Texaco MARFAK sticks to the job, resisting washout, squeeze-out, wearout! MARFAK is always applied by chart, never by chance. Eliminates the possibility of missing a king pin or control arm lubrication fitting. Ask your Texaco Dealer to give your car that "MARFAK feeling" today!

THE TEXAS COMPANY

Let us



For Your Enjoyment . . . 2 Great Radio Programs

Tune in JAMES MELTON: The TEXACO STAR THEATRE every Sunday night.

METROPOLITAN OPERA: Complete broadcasts of great operas every Saturday afternoon.

Consult newspapers for time and stations



• Marlin is ready to produce its outstanding line of accurate, dependable .22's as soon as war contracts permit. They will be the best Marlins in history—built to standards of performance and long life that made the name famous. Now is a good time to look over the Marlin line. Send for catalog today!

Illustrated: Model 80-DL

#### CLIP MAGAZINE REPEATER CAL. .22

8 shots "at a clip" for small fur-bearing game and pests. Recommended for target practice by N.R.A. A man-sized gun at a low price.

Model 81-DL 25-shot Repeater. Bolt action tubular magazine .22 for general purpose hunting of small game, without need of frequent loading.

Model A1-DL Automatic .22. Six quick shots at fast-moving small game, crows, hawks, etc. Shoots regular and high speed .22 long rifle.

Model 39-A. Lever Action Repeater. By many considered world's best all-around light rifle. Only lever action .22 made. All working parts exposed by turning of single hand screw.

Marlin FIREARMS CO.

NEW HAVEN, CONM

#### SEND FOR CATALOG

Handsomely illustrated prewar catalog, with full specifications of Marlin Guns.

THE MARLIN FIREARMS CO.

Enclosed 3c for mailing catalog of Marlin Guns.

Name

Address

PS-3

WATCH THE INFANTRY ----- THEY CARRY THE GUNS!

## "Plumber's Nightmare"

(Continued from page 71)

mixes with kerosene in the combustion chambers, and is ignited. It blasts out through the flame pipe, and that's all there is to it. How the hell that makes an airplane fly, I don't know."

Engineers, explaining the jet force which drives a plane, have compared it to the strong, sudden whip at the nozzle of a garden hose when water is turned on full force.

"Most mechanics are surprised to learn that there are only eleven bolts holding the engine in place," the sergeant comments. "And not very big bolts at that. In the engine there are but two main bearings and one shaft.

"I can pull an engine with an inexperienced crew in 35 minutes, and four men can pull both engines and install new ones in a day. Where we used to spend five days doing a certain job on a conventional plane, we can do the same thing for a jet in a day. Where other mechanics would use 25 wrenches for a certain type of job, we generally use about five."

All the equipment necessary for changing a jet engine can be carried in the plane, and this consists of a small wing hoist and frame, and a cradle to support the engine when removed. Since the unit is so close to the ground, no work stands are necessary to reach any part of it.

Mechanics invariably ask about the jet exhaust and want to know how close a person can stand in front or behind the engines, Kohler says. Most of them have heard fanciful stories about women having their dresses whisked off by the suction of air going into the engines. And there is one story, widely told, of an officer who tried to look into the rear end and got his cap visor scorched off back to the eagle. Kohler does not believe these tales, but he does know a guy who stepped into the exhaust and was kicked back 70 feet in fast somersaults.

"I'd say a person should keep at least 200 feet behind a jet engine when it is blasting," the sergeant recommends. "You can stand closer without getting hurt."

Once a flight is over, mechanics don't need to let the plane cool off before beginning work on the engine. By the time they get the cowling off, the engine is cool enough to be taken out.

Development of the AAF jet plane, one of the best-kept secrets of the war, took place at Muroc, Calif., where Kohler said he signed away his life every day. "Every

(Continued on page 228)

# Meet the Men

# WHO USE YOUR BATTERIES!



The Navy and Merchant Marine send rapid ship-to-ship messages by battery-powered flasher signal lights when radio might give a ship's position to the enemy.



It's difficult to locate men drifting in the sea! Water-tight battery lights on buoyant lifesaver suits have saved the lives of many torpedoed Merchant seamen.



For emergency communication by voice, the Merchant Marine uses a portable megaphone to broadcast orders and instructions. Dry batteries power the megaphone.



Two men and a bazooka make a winning team! But it takes large quantities of ammunition and dry battery power to keep these portable, hard-hitting weapons firing.



Deadly flamethrowers are blazing the road to Victory! Dry batteries create the spark that sends these efficient weapons into instant, flaming action against the enemy.



The Signal Corps man with a Walkie-Talkie has freedom of speech as long as he has plenty of dry batteries! Handie-Talkies are also powered by war batteries.




When they come Home — Burgess Batteries will be back again, too ... powering flashlights, radios, telephones, instruments and controls for millions of homes, farms and industries throughout America.

# BURGESS BATTERIES

IN THE NATION'S SERVICE

BURGESS BATTERY COMPANY, FREEPORT, ILLINOIS




The tough Liberator bomber is systematically wrecking Axis war industries and vital military installations, from Bangkok to Berlin, to hasten the day of Victory.



In rebuilding the peacetime world, huge Consolidated Vultee planes will play an important role in the swift transportation of goods and people over global skyways.


#### Other planes designed and built by Consolidated Vultee are:



CATALINA . . . patrol bomber



CORONADO ...4-engine flying boat




VALIANT ... basic trainer



PRIVATEER . . . search plane



RELIANT . . . navigational trainer



SENTINEL . . . "Flying Jeep"

# CONSOLIDATED VULTEE AIRCRAFT CORPORATION

San Diego, Calif. Vultee Field, Calif. Fairfield, Calif.

Tucson, Ariz. Fort Worth, Texas New Orleans, La. Nashville, Tenn. Louisville, Ky. Wayne, Mich.

Dearborn, Mich. Allentown, Pa.

Elizabeth City, N. C. Miami, Fla. Member, Aircraft War Production Council



MARCH, 1945


# TRANSCONTINENTAL "Plumber's Nightmare" RECORD Smasked!

# by Army-Boeing-Wright

SEATTLE TO WASHINGTON – 6 HOURS, 3 MIN., 50 SEC. MORE THAN 383 MILES AN HOUR

AC Ceramic Aircraft Spark Plugs fired all four of the great Wright "Cyclone" engines which carried the mammoth Boeing-built Army transport 2,323 non-stop miles—and broke the speed record for planes of any size.

Achievements like this demand utmost reliability the quality for which AC Spark Plugs have been known to motorists, operators of buses and trucks, yachtsmen, and farmers since 1908. This same reliability is also now serving our armed forces, in the air, on the ground, and on the water-and is keeping essential transporta-



SPEED FINAL VICTORY - BUY WAR BONDS

(Continued from page 224)

time I turned around I was signing something, promising that I would keep my mouth shut."

Even the commanding officers at an AAF base near by did not know what was going on inside the restricted area of the desert. Pilots were forbidden to fly over it and no amount of rank could get a curious officer into the field. On several occasions, the jet plane was seen smoking through the sky and frantic telephone calls came from the neighboring air base notifying jet crews that a burning plane had fallen on their field. The callers were politely thanked for their concern.

One afternoon, when the experimental plane was smoking heavily, the neighboring air base called out its fire and crash equipment and sent it clanging down the highway to the secret station. The crash wagons pulled up at the main gate and demanded to be let inside, drivers shouting that they had the location of a burning plane.


Again, the guards were compelled to thank them quietly and politely-and keep the gates locked. On another occasion a bird colonel became so curious that he drew himself up to full height before the guards and demanded to know what was going on behind all the secrecy and mystery. A security officer had to be called out to pacify him.

"Colonel," he said, "behind those hangar walls is the hope of tomorrow. We are coming out with a gadget that will revolutionize the sewing machine."

Perhaps the simplest function of jet maintenance is servicing the plane with fuel. This is no more involved than calling the kerosene truck and filling up. The fuel is thoroughly filtered to safeguard the barometric fuel controls. These units do what the regulator on a turbo-supercharger does—they maintain a constant power with changing altitude. The engine can operate on nearly any hydrocarbon fuel such as gasoline, kerosene, alcohol, and even hair tonic or brandy.

The jet engine has about 10 percent as many moving parts as a reciprocating engine and, since there is only a rudimentary ignition system and no carburetor, there is no elaborate mixture control, nor prop control, nor icing worries.

"You get all that in something they call a plumber's nightmare," Kohler says. "I take them apart and put them back, and I still can't find what makes them fly. It's the airplane of tomorrow—and it smells like an old oil stove."



Three years ago a tool salesman — today owner of a modern new plant, busy on highly precise aircraft tools, with plenty of plans for postwar business — that's the "success story" of Andy Langdon. His interest and skill in machine work came from an Atlas lathe and Atlas drill press in his basement workshop.

He foresaw the need for special precision tools, enlarged his garage, added an Atlas lathe, and started business. Soon he was forced to move to the white building shown above. But his work and staff kept expanding until he needed to build for himself.

His specialty has been work for Douglas Aircraft on tiny parts only 1/16" in diameter to full Atlas lathe capacity with tolerances of .0005".

#### SEND FOR LATEST CATALOGS

Are you planning on a home shop after the war with the idea, perhaps, of writing a "success story" of your own in the busy times ahead? We'll gladly send catalogs.

New Atlas pattern service for wood craftsmen. See ad on page 238.



# ATLAS PRESS CO.

355 North Pitcher Street, Kalamazoo 13D, Michigan



Van Roy BARD \$5

Signet of Quality in Pipes



VANROY COMPANY, INC. .

Moments of relaxation are enriched by the rare contentment of smoking a VanRoy—the pipe with a noble heritage of distinguished quality. Be discriminating in your choice of pipe companionship—select a VanRoy.

EMPIRE STATE BUILDING, NEW YORK I.





# CASITE

GUARANTEES SUMMER STARTING
IN WINTER WEATHER OR
DOUBLE-YOUR-MONEY-BACK

#### **CLEANS OUT MOTORS • KEEPS MOTORS CLEAN**

A pint in the crankcase every oil change and a pint through the air intake every three months.

Your car dealer, service station or garage will supply guarantee certificates.

THE CASITE CORPORATION . HASTINGS, MICHIGAN



While planning to enjoy making things in your postwar home workshop, remember that a fine assortment of Stanley Tools will add good craftsmanship to recreation. Stanley Bit Braces, for example, have long been the choice of professional experts in woodworking. Featuring shorter chucks, stronger jaws, improved head construction, fine finish, Stanley Bit Braces will turn out work you'll be proud of.

#### Let Experts Help in Your Selection

Stanley has a free booklet for you, "The Joy of Accomplishment." Crammed full of helpful suggestions for the hobbyist, it contains: a primary list of tools and a list of tools to be added as needed. You'll also find the big Stanley textbook: "How to Work with Tools and Wood," mighty useful. It's yours for only \$1.00. Mail the coupon today.

MAIL STANLEY THE TOOL BOX OF THE WORLD



Stanley Tools, 145 Elm St., New Britain, Connecticut.

Please send by return mail

- ☐ The FREE booklet: "The Joy of Accomplishment."
- □ 188-page book: "How to Work with Tools and Wood." \$1.00 enclosed. (In Canada: Send order to Stanley Tool Co. of Canada, Ltd., Roxton Pond, Quebec)

Name	 	
Address	 	
City		

### How Zoom Boats Sock

(Continued from page 84)

they can be fired so that each salvo overlaps a previous one. Targets may be determined by using ranging rockets. And the blast effect and fragmentation from a barrage of bursting rockets can be employed to make the area where men are about to land too hot and lively for the foe to linger there.

Secondary fortifications, including mines, wire, machine-gun nests, and shallow pill-boxes can be virtually eliminated. Even men protected by large, strong fortifications can be temporarily stunned by a rocket bombardment.

The 4.5-inch rocket, moreover, is only one of several calibers now in use. The smallest is called a SCAR, sub-caliber aircraft rocket, and is only 2.5 inches in diameter. The largest is five inches in diameter. Recent developments, however, have made it possible to produce bigger rockets, aim them more certainly, and use them at longer ranges. For example, it has been suggested that an automatic computing device similar to the electronic bombsights now in use might enable a fighter-plane pilot to launch rockets at a target with greater accuracy.

Since there is no recoil, the apparatus from which rockets are launched can be lighter and much simpler than a gun. The U.S. Navy put rocket launchers on its LCS (S), landing craft, support (small), while the British were putting them on their LCT (R), landing craft, tank (rocket). Some of the latter craft were turned over to this country more than a year ago. After careful tests, Navy authorities ordered more of them converted to American designs and specifications with the utmost speed. Until recently, these vessels were definitely hush-hush.

Meanwhile, rockets were used with sensational success on the Navy's LCI (G), landing craft, infantry (gunboat), in the Pacific. A single LCI skipper estimated that his craft fired 1,000 rockets into the beaches of Guam.

Washington authorities report that the Japs have made comparatively little use of rockets. But American officers have found that invasion casualties can be reduced by using more rockets.

The Army is directing the production of propellent powder, and the Navy is in charge of assembling, loading, and testing rockets. Home-front workers are being asked to turn them out faster, in greater quantities, to save American lives.—Volta Torrey.

# Your Coming New Zenith will be the World's Finest Radio because

All Zenith's Engineering Power is Concentrated on

# "RADIONICS EXCLUSIVELY"

THE vast new science of RADIONICS is a jealous wife. She demands undivided devotion from him who would share her secrets and master their application. Many of these secrets are still so sensational that they cannot even be made public!

It is only natural that you can expect the world's foremost radio values in the coming new Zenith Radionic models. For Zenith does not divide its engineering and manufacturing power among unrelated fields like refrigerators, washing machines, electric irons, cooking ranges and vacuum cleaners. Zenith has no intention of competing with lifelong specialists in those fields.

RADIONICS demands a degree of imagination in engineering and precision manufacture unknown in other mass production fields. That's why every Zenith worker has always been, always will be, a highly trained specialist in "RADIONICS EXCLUSIVELY."

Before the war, this policy made Zenith one of the largest radio manufacturers in the world ... with an unrivaled record of top performance in millions of sets, at lower service expense to owners than any other make!

In the war, "RADIONICS EXCLUSIVELY" has made Zenith Radionic military equipment famous in every branch of our armed forces! This has meant a wider, more intensive development by Zenith in High Frequency, the basis for all FM, Television and Short Wave advancements. It is a matter of record that years ago short wave communication was introduced into the U. S. Navy by Zenith.

No wonder Zenith—and only Zenith—is able to launch a RADIONIC REVOLUTION!

Yes, your coming new Zenith Radionic Radios, Global Portables and Radio-Phonographs will bring miraculous tone of such clarity, brilliance and beauty as you've never heard before! They will combine advanced engineering, precision quality and low cost as never combined before!

The ZENITH RADIONIC REVOLUTION is on the way! Watch for it! Don't risk your radio dollars—put them on a name you know will be a proven winner. Keep your eye on Zenith for the best in radio, and see Zenith first!

ZENITH RADIO CORPORATION, Chicago 39, III.

All Production Now for War or Rehabilitation

COPYRIGHT 1948, ZENITH RADIO CORP.



# motors, too, need a spring tonic!



AFTER a tough winter's work, motors get sluggish, unresponsive — downright lazy. The faithful old engine has spring fever — caused by accumulated sludge, gum and acid in the lubrication system. What it needs is an internal bath—LOOSITE — to clean out the engine—thoroughly, safely, economically . . . then a tonic—SILOO—to prevent further accumulations of dangerous petroleum residues and corrosion.


Have your service station or dealer give your car both treatments — LOOSITE to clean every vital part of the lubrication system . . . and SILOO, added to fresh crankcase oil, to keep it clean. It's simplicity itself . . . and you'll avoid costly layups and repairs resulting from gum and sludge.

Cars must last longer! Give yours the break it deserves — LOOSITE and SILOO for better performance and prolonged usefulness. See your service station or dealer now!

### Petroleum Solvents Corp.

Solvents For All Types of Petroleum Residues
General Offices: 331 Madison Ave., New York 17, N. Y.

P. S. If you heat with oil - write for information on our Fuel Oil Tank Solvent.



# AVAILABLE NOW for service inside war plants. LATER, for general use

Want to scoot around FAST, at Amazing Low Cost? Then, pick the New Improved CUSHMAN! Beats anything you ever saw. Ten times faster than walking! 500 miles on \$1 worth of gas! Built for long, hard use!

So practical, economical and durable that thousands now serve in the nation's great war plants.

POWERFUL 4 H. P. ENGINE. No clutch pedal or gear shift, Floating Drive applies power smooth as Fluid Drive. Hand accelerator controls starting and speed-adjustment. Special springing, long wheel base and balloon tires provide Smooth Riding. Low center of gravity and heavy brakes provide Safety.

2-wheel and 3-wheel models with 200-lb, and 250-lb,-capacity package boxes.

WRITE! See your dealer who handles the CUSHMAN, or send for full details. Be among the first to own a genuine CUSHMAN when available outside war plants. Send Now!


CUSHMAN MOTOR WORKS, Dept. S-35, Lincoln, Nebr.





#### New R-F Resonance and Coil Winding CALCULATOR

Easy to use! For fast accurate determination of resonance factors and coil winding data. No. 37-955. Postpaid, only 25c.



# WHEN IT'S AN EXIDE ...YOU START




A man is known by

the company he keeps. You can generally depend upon the services of the dealer who sells only products that are KNOWN to be of high quality.

The increasing requirements for batteries by our armed forces need not dislocate home front transportation if everyone cooperates. Regular inspection by your Exide dealer will help you prolong the life of your present battery and put off the day when you must buy a new one.

THE ELECTRIC STORAGE BATTERY COMPANY, Philadelphia 32
Exide Batteries of Canada, Limited, Toronto





and keen edge-holding teeth cut smoothly without slivering the ends or edges of cuts. What's more, these saws keep right on making glue-smooth cuts for long periods without filing. The saw shown is one of many types in Atkins Circular line. If your dealer doesn't have the one you want, remember that Atkins energies are still all-out on war work. Send a dime today for the useful Atkins "How to do it" book.

E. C. ATKINS AND COMPANY
428 South Illinois Street
Indianapolis 9, Indiana

Always Ask for "Silver Steel"

# Announcing NOMA'S \$50,000 FOUNDATION for Toy Designs and Ideas

Amateurs or Professionals

—Designers or Inventors—

Anyone who has ever

dreamed up a toy!



Cash in on Noma Toys' nation-wide search for new . . . appealing . . . different toys. We will consider anything from a rough idea to a complete working model.

There's big money in toy designing Write Noma Electric Corporation for full information.

NOMA Electric Corporation
55 West 13th Street • New York 11, New York






Steel back of Speed Sweep brushes is the basis of unique construction for faster, easier, better sweeping. Block is narrower — easier to handle. Tufts of longer, better fibres are more compact — provide "spring and snap" action. Handle instantly adjustable to height of sweeper — reduces fatigue and strain. Speed Sweep brushes are built to outlast ordinary brushes 3 to 1.

FULLY GUARANTEED. Since Pearl Harbor Speed Sweep brushes have proved their superiority in many thousands of factories under varied conditions. They are unconditionally guaranteed to meet your requirements. Prompt shipment on AA-5 or higher priority rating. Write for styles, sizes, and prices today.

MILWAUKEE DUSTLESS COMPANY
528 N. 22nd St., Milwaukee 3, Wis.

# "HARLEY-DAVIDSONS Really TAKE THE

# ROUGH TRAILS!"



That's right, Dick — we WILL KEEP ON BUILDING — so all you fellows can end the war quicker — and come home to enjoy motorcycling days on your own Harley-Davidsons.

# HARLEY-DAVIDSON MOTORCYCLES

HARLEY-DAVIDSON MOTOR CO. Department PS, Milwaukee 1, Wisconsin

Address......

Please send at once free copy of 24-page "Enthusiast" Magazine, filled with motorcycle action pictures and thrilling stories.


Name.....

City\_\_\_\_\_State\_\_\_\_

MARCH, 1945

Buy War Savings Bonds and Stamps regularly.

237



williams' "Supersockets" actually are
more than wrenches;
they are an extremely
flexible system for multiplying the skill and productivity of human hands. "Supersockets", with their almost
endless combinations of handles,
parts and different socket types,
enable the operator to assemble
a special tool to exactly fit the particular job at hand.

Five different patterns, with drives ranging for 1/4" to 1" square, cover every application. They provide the utmost in speed, safety and power. Write Dept. S-3, for free Data Sheets Nos. 4, 9, and 24 describing these time-saving tools.

### J. H. WILLIAMS & CO. BUFFALO 7, N. Y.



DROP FORGINGS AND DROP-FORGED TOOLS

# Mortila

#### MANY USES IN THE HOME

Ever ready, pliable plastic plugger-upper keeps out dust and dirt, mosquitoes, flies, ants, etc.

Fills holes and cracks around windows, screens, casements, drainboards, sinks, bathtubs. Use inside or outside. During cold weather, weather strips.



#### EASY TO APPLY

Unrolls like ribbon. Just press into place and it stays put. Does not crack, chip or shrink. Can be painted. A roll covers about 80 feet.

At Hardware, Paint, Dept. Stores and Lumber Yards . . . \$1.25

Higher west of Rockies and Canada

Free Booklet

J. W. MORTELL CO.

534 Burch St.

Kankakee, III.



# NEW atlas PATTERN SERVICE

FULL SIZE PATTERNS for making furniture, household equipment, cabinets, toys are now available through Atlas. They work like templates in airplane construction to save time and insure accurate workmanship.

### No. 11 SLATTED ROOF WREN HOUSE

You'll be fascinated with the housekeeping activities of our little feathered friends when they return from the Southland if you have this cozy home ready for them. The step-by-step directions of the Atlas full size pattern will enable you to build this Wren house easily and quickly. Price .20



#### No. 12 EARLY STARTER GARDEN HOTBED

You can get the jump on other war gardeners by starting your seeds in this ingenious hotbed. It is a most interesting and practical project that will pay extra dividends in usefulness. Price .25

Order patterns by number, inclosing exact cash, check or money order. Price includes mailing costs. Pattern envelopes show many other useful pe available at low cost.

ATLAS PRESS CO. PATTERN DEPT.
Dept. B-3 P. O. Box 74, Pleasantville, N. Y.



### ANGLE BRACKET AND SPEED NUT COMBINED

If your product requires brackets for assembly, why not use brackets with self-locking nuts built right in them? Why fumble around with separate lock washers and threaded nuts and use a wrench besides to keep them from turning? Why handle 9 parts (bracket, 2 screws, 2 lock washers, 2 nuts, screw driver, and wrench), when 4 parts will do a better job? (SPEED NUT, 2 screws, and screw driver.) Think of the savings in manhours and material this could mean in your plant!

These SPEED NUTS lock with a firm spring tension

that permanently prevents vibration loosening. They reduce weight, speed up assembly, and strengthen the structure. And since they are produced on high speed automatic machines, these self-locking brackets are not expensive.

Hundreds of manufacturers have improved both their

products and assembly methods by changing over to Tinnerman angle brackets. Write for samples.

#### TINNERMAN PRODUCTS, INC.

2022 Fulton Road, Cleveland 13, Ohio

In Canada: Wallace Barnes Co., Ltd., Hamilton, Ontario In England: Simmonds Aerocessories, Ltd., London






THE BASIC PRINCIPLE
of Spring-Tension Lock is
Embodied in all Speed Nut Designs

MARCH, 1945

Buy War Savings Bonds and Stamps regularly.

PIPE-SMOKERS: Taste the flavor and admire the beauty of these new MONTEREY PIPES



# MISSION BRIAR

#### GIANT ABOVE - GROUND GROWTHS **MELLOW WITH AGE**

MONTEREY Pipes from California, made of Mission Briar, smoke with a special leisurely sweetness, because these big burl-growths have peculiar advantages (1) mellow with age (2) tempered by weather (3) of unusual soundness (4) with a beautiful grain which adds to the fine smoking-quality. Ask for MONTEREY PIPES, only ones made of MISSION BRIAR, at your dealer's, Select Grain \$3.50, Specimen Grain \$5.



The Mission Country of California where Mission Briar grows on the sunny slopes of the Pacific Coast. Next advertisement will show the "Topping" operation.

Kaufmann Bros. & Bondy, 630 Fifth Ave., N. Y. 20, N. Y.



#### A WHOLE TOOLSHOP IN ONE HAND

The sky's the limit with the Handee. Its usefulness is as extensive as the number of quick-andeasy-to-change accessories you own-there are more than 300 in the Chicago line to grind, drill, polish, cut, rout, carve, engrave, sand, saw, etc.

Because it's perfectly balanced and weighs only 12 ounces the Handee is the "non-fatiguing" tool. Operates on AC or DC current at 25,000 r.p.m.



With 7 Accessories, Postpaid to all who have Priorities.

Free new 64 page Catalog of complete Chicago line.

#### CHICAGO WHEEL & MFG. CO.

1101 W. Monroe St., Dept. P.O., Chicago 7, III.

- SEAL OUT DRAFTS
- SAVE FUEL
- BE COMFORTABLE

with

## KALK-KORD

THE NON-HARDENING CAULKING AND SEALING COMPOUND

You can quickly and easily seal loose windows against drafts with Kalk-Kord-use it around window frames, too, inside and outside.

Neat and clean to use, Kalk-Kord seals cracks without tools -just press in place with fingers. Comes packed in convenient • Caulking window beads or rolls. Will not stain paint or any surface. Does not harden, crack, chip, or shrink. Waterproof and unaffected by . Sealing cracks temperature changes.

For Sale by Sears, Roebuck retail stores Paint Dept. 30, or by mail from Sears



Other Household Uses

- and door frames
- Sealing around bathtubs and sinks
- in plaster, woodwork, masonry
- Sealing around baseboards

Product of

PRESSTITE ENGINEERING COMPANY 3976 CHOUTEAU AVE. • ST. LOUIS 10, MO.





"Have never seen a Calculator with so much valuable information," writes a user. All you do is just set dial and...

- Convert linear to board feet
- ▶ Determine slope per foot in degrees
- Compare hardness, weights, shrinkage, warping, ease of working of various woods
- Find bit sizes for head, body and thread of standard screws
- ► Determine nail specifications
- ► Get helpful tool sharpening tips

Heavy varnished cardboard, soil-proof, 6 inches in diameter, fits tool kit. Greenlee Tool Company, Rockford, Illinois.




Send for yours now!

GREENLEE TOOL COMPANY, 2124 COLUMBIA AVENUE ROCKFORD . ILLINOIS

Enclosed is	10c.	Send	your	"Handy	Calculator"
by return i	mail.				

Name		 	 -	 -		-	 	-	-	-	 	-	-	-	 	
Addre	ss	 	 -	 _		-	 	-	-	-	 	-	_	-	 	
_					,											

### MIGHTY but Gentle!



IT'S A HARD HITTING "SOFTIE"-Nupla Hammer uses a new semi-soft, flexile plastic that HEALS ITSELF when dented or deformed. Hits hard blows without damage to delicate parts or finishes. Non-inflammable! Not affected by oil or gasoline! A new tool every craftsman wants and needs. 3 sizes and 7 wts.

SOLD AT HARDWARE STORES EVERYWHERE.
Write for name of local dealer.

NEW PLASTIC CORP.

1017 N. Sycamore Ave. Los Angeles 38, Calif.

MIGHTY DE PLASTIC HAMMERS

### Sand Casting—Forging—Heat Treating—Case Hardening BRONZE FOUNDRY



is again available in limited quantity without priority. Orders filled in sequence as received. INVENTORS-SCHOOLS-CRAFTSMEN use FOUNDRYETTE for making castings quickly for new inventions, for instruction, and general purpose. Order now for early delivery. Three sizes are available capable of making bronze castings of 1½, 3, and 6 pounds weight, aluminum, copper, brass, etc. \$17.50, \$24.00, \$34.50, f.o.b. Kansas City. Domestic gas supply and 110 volt AC or DC energy required for operation. Write for circular.

KANSAS CITY SPECIALTIES CO. Box 6022, Dept. S-52 Kansas City, Mo.

## RATIONED MOTORISTS



# GASOLINE MILEAGE

Now you can get up to 30% extra gasoline mileage with a Vacu-matic on your car. Quicker pick-up, smoother running, added power and precious gasoline savings guaranteed.

Automatic Supercharge Principle
Vacu-matic is entirely different! Operates on
the Supercharge principle. Saves gas. Automatically provides a better gas mixture. Guaranteed to give up to 30% extra gas mileage, more
power and better performance.

FITS ALL CARS
Constructed of six parts,
fused into a single unit.
Adjusted and scaled at
the factory, Very quickly
installed by anyone.

### AGENTS TRIAL OFFER

Every car, truck, tractor a prospect. Send name address on postcard for big money making offer and how you get yours for introducing.

Vacu-matic Co., 7617-1166 W. State St., Wauwatosa 13, Wis.

## THE POSTWAR PAINT for a Glorious Postwar World

PLASTIC FINISH

AMAZING The paint of modern science. Resin-based; creates a plastic finish that is tough, fadeproof, waterproof and resistant to gas and fumes. Fun to use on Interior and Exterior.

Self-flowing, self-leveling. Amateurs get professional results.

#### WASHES LIKE TILE

One coat covers any kind of surface brick, stucco, plaster, wallboard, wood -yes, even old wallpaper, Will not crack, chip, chalk or peel. Cannot be thinned by water. Try it-comparel Per quart. SPECIAL

### MONEY-BACK GUARANTEE

If, after using 25% of this plastic finish paint, you are not 100% satisfied, return remainder and receive full refund. Order for cash, postpaid or C.O.D. plus small express charge. COLORS: White, Ivory, Cream, Buff, Dusty Rose, Grey, Peach, Blue, Brown, Black and 3 shades of Green. Specify interior or exterior and color - gloss, semi-gloss or flat. Gallon covers 350 square feet.

### PLASTIQUE NU-FLO FLOOR FINISH

Eliminates waxing and polishing. Non-skid. \$= 95 Amazing plastic finish. Qt. does average kitchen. 12 colors and clear. Per Quart . .

DEALERS - PLASTIQUE PAINTS OFFER YOU A

#### NU-FLOPRODUCTS 333 N. MICHIGAN AVE., CHICAGO, I ILL.




6" diameter, Easily read, clearly marked single index scales. Gives logarithms, reciprocals, squares, square roots, sines, and tangents. Continuous circular calibrations cannot go scale." Invaluable in multiplication, division, proportion, conversion, all mathematical problems. Made of durable heavy pure white Vinylite, Complete with instructions, \$2.95, Leather-

PRECISION INSTRUMENT CO.

Box 654, Dept. N Church St. Annex New York 7, N. Y.





### NOW! a model for every type of correctable hearing loss!

Zenith Radionic **Hearing Aids with** 

> New Neutral-Color Earphone and Cord



• Think of it! No matter what your type of correctable hearing loss, you can now get a Zenith model designed to restore you to the world of sound. And it will be as little noticeable as eyeglasses-thanks to the Neutral-Color Earphone and Cord which blends with any complexion...enables you to wear a hearing aid with poise and confidence.

Ask the Zenith dispenser near you for a free demonstration. Find out about the exclusive external tone control which enables you to adjust your Zenith for different voices and surroundings as easily as you focus binoculars. No obligation! Send coupon for free literature and name of nearest dispenser.



#### Each Complete, Ready-to-Wear

- I Standard Model A-2-A. New, improved model of the famous Zenith standard hearing aid for the person of average hearing loss. Only . . . .
- 2 Air Conduction Model A-3-A. A super-power instrument with exceptionally wide range of volume control and amazingly fine tone quality. Only .
- 3 Bone-Conduction Model B-3-A. A totally new instrument created specially for the very few who cannot be helped by any air conduction aid. Only

#### --- PASTE ON PENNY POSTCARD AND MAIL-

Zenith Radio Corporation, Dept. PS-14 6001 Dickens Avenue, Chicago 39, Illinois Please send me free literature about Zenith Radionic Hearing Aids-together with name and address of nearest Zenith dispenser.

Name	
Address	
City	£4.4-

Buy War Savings Bonds and Stamps regularly.

- COPYRIGHT 1945, ZENITH RADIO CORP



THOMPSON BROS. BOAT MFG. CO. Two Large Factories—Write to Either Place (143)

219 Ann St. PESHTIGO, WIS.

> **Catalog Free** Save Money



Boeing B-29 "Super-fortress" Greatest of All Bombers

119 Elm St. CORTLAND, N. Y.

Please state the kind of boat you are interested in



**Model Values** 261/2" Boeing B-29 SUPERFORTRESS. Semf-solid. Line-Controlled. \$1.00 C-D Kit AU-200.

Soars for hours Huge 84" Super CONDOR Soarer. Glider. C-D Kit E-5019, \$1.00

If your dealer can't supply you, order di-rect, including 20c extra for packing-post-

BLACK WIDOW C-D Kit T-155 \$1.50


CATALOG 5C CLEVELAND MODEL & SUPPLY CO.

4508E26 Lorain Ave., Cleveland 2, Ohio, U. S. A. Balance 4"x 9" Base. With either \$6.00



Metric or Avoirdupois Weights . . Catalog with 3000 illustrations of labora-tory Apparatus sent for 75 cents, Catalog listing 10,000 chemicals, drugs, minerals, etc., and 1700 scientific books sent for 25 cents. LABORATORY MATERIALS CO., 7317 Vincennes Ave. Chicago 21, III.





Today Missouri Pacific uses a fleet of high powered General Motors Diesel locomotives to haul long heavy loads of oil and war freight, and to provide swift dependable passenger transportation.


### PUTTING RAILROADING ON A NEW PLANE

These days the railroads are doing things that would have been impossible a few years ago. And one of their most powerful and modern tools is the General Motors line of Diesel locomotives.

Since the day that the first of these locomotives took the rails, they have rolled up the impressive total of more than 200 millions of miles of operation on America's major railroads. In the things they have done—moving tremendous loads, maintaining fast, regular schedules, always on the job—lies the forecast of a new day for railroading when the war is over. Then the full possibilities in Diesel motive power may be applied to the carrying of passengers and freight throughout the country.

That is why it's a great new day for railroading, with greater days ahead.


ON TO FINAL VICTORY
BUY MORE WAR BONDS



LOCOMOTIVES . . . . . . ELECTRO-MOTIVE DIVISION, La Grange, III.

ENGINES . . 150 to 2000 H.P. . . CLEVELAND DIESEL ENGINE DIVISION, Cleveland II, Ohio

ENGINES . . 15 to 250 H.P. . . . DETROIT DIESEL ENGINE DIVISION, Detroit 23, Mich.



# MILLERS FALLS COMPANY Greenfield • Massachusetts

### STOKER EMPTIES OWN ASH!

A remarkable stoker already used by thousands of home owners—fits into any furnace or boiler. Manufactured since 1934. So automatic it takes the coal from your present coal bin through a pipe to the furnace, going around corners if necessary. Keeps house at even temperature, empties its own ash in sealed containers, no coal to shovel, no clinkers to dig, only bituminous stoker of its kind on the market. Send for full information NOW!

POCAHONTAS FUEL COMPANY INCORPORATED
341 EAST 131st STREET • CLEVELAND 8, OHIO



### STAN and PEppy - Pal" GARDEN TRACTORS

• 1 to 9 H.P. Circulars on request. War limits production—We supply repairs for all SHAW Tractors sold in our 41 years in business.

### BUILD YOUR OWN RIDING TRACTOR—"WAR HORSE"

using old auto parts, powered by 2 H.P. or larger air-cooled engine; or walking type Garden Tractor ½ to 3 H.P. or convert truck or auto into Farm Tractor. Each with steel or rubber tires; will plow, cultivate. Plans for building, in few hours, any one of above, postpaid for \$1.00 (state which wanted) or all 3 for \$2.00. Money Back Guarantee!

SHAW MFG. CO., 5703 FRONT ST. Galesburg, Kansas

668PS North 4th St., Columbus, Ohio


### NEW OTTAWA SAW

FREE 6 H. P.
EASY to MOVE

Saws big logs, small logs, limbs. Pulley for belt work.
Easy to handle, weighs less than lower powered units. FULLY
GUARANTEED. Cash in on fuel shortage. Turn wood lots into cash.
OTTAWA MFG. CO. 301 PINE ST. OTTAWA, KANS.



# TERRIFIC BARGAINS WAR SURPLUS LENSES AND PRISMS



### TANK PERISCOPE

Complete set mounted components.

#### MFG. FOR NAVY'S 7 POWER BINOCULARS

COMPLETE SET OF LENSES AS ABOVE AND THE PRISMS TO MAKE A MONOCULAR (TELESCOPE) with objective Lens of

two inch diameter. Stock No. 5100-N-Monocular Set......\$5.00 Postpaid

2 Cemented Achromatic Lenses (color corrected) which may be combined to make a microscope objective lens with a focal length of  $\frac{1}{2}$  inch. Use these to make a microscope for microphotography.

REDUCING LENS SET—Stock No. 1004-N....\$1.20 Postpaid Two big Lenses, 13'4" and 2" in diameter. Will make objects look smaller than they actually are.

All Items Finely Ground and Polished but Edges Slightly Chipped or Other Slight Imperfections which We Guarantee Will Not Interfere with Their Use. Come Neatly Packed and Marked.

### YOU CAN EASILY MAKE

Telescopes Magnifiers Photographic Gadgets
and Hundreds of Experiments with these Low Cost Lenses
To translate millimeter measurements; 25.4 mm. equals one inch.

#### SPECIALS IN LENS SETS

Big 10 Page Project and Idea Booklet with all sets—describes successful developments—points the way to new experiments.

Set No. 301-N "Our Advertising Special" 15 Lenses for \$1.60 Postpaid. For making your own powerful telescopes, low power microscope, strong magnifiers, drawing projector, photo cells, telephoto lens, dummy focusing camera, Kodachrome viewer, stereoscopic viewer, ground glass and enlarging focusing aids. For experimental optics, portraits of babies and small pets, copying, ultra close-up shots, and many, many other uses.

Set No. 305-N "The Gadgeteer's Delight" 35 Lenses for \$5.00 Postpaid. Contains all the lenses in the above set plus twenty more expensive lenses increasing your field of experiment and gadget making. All our lenses are neatly packed and marked.

Set No. 310-N "The Experimenter's Dream" 60 Lenses and New Complete 50 Page Booklet—\$10.00 Postpaid. Contains all the lenses in the above sets plus 25 others that make this a sensational buy. The variety of lenses in this set will enable you to conduct countless experiments and build a wide variety of optical equipment.

New 50-Page Illustrated Idea Book . . . \$1.00 Postpaid. "Fun with Chipped Edge Lenses" describes a wide variety of uses for our lenses and contains much information especially designed for the homemade construction of optical items.

PORRO ABBE PRISMS—Stock No. 3006-N.. 25c ea. Postpaid Size 9 mm. x 17 mm.... Worth 20 to 40 times above quotation.

### TANK PRISMS

90-45-45 degree prisms of huge size—534" long, 21'a" wide, finely ground and polished. Used to build a Periscope . . . . excellent also for experiments, classroom demonstrations at high schools, colleges, camera clubs, astronomy clubs. Some of our ingenious customers have used these Prisms to make camera stereo attachments, photometer cube, range finder, etc. Normally, these Prisms would retail from about \$24 to \$30 each.

Stock No. 3004-N....SILVERED TANK PRISM-Price \$2.00 each Postpaid. Illustrated Booklet on Prisms included FREE.

Stock No. 3005-N......PLAIN TANK PRISM-Price \$2.00 each Postpaid. This one is excellent for projecting all the colors of the spectrum, Illustrated Booklet on Prisms included FREE.

FOUR TANK PRISMS—Special—\$7.00 Postpaid. . . . This is the most sensational bargain we have ever been able to offer.

Order by Set or Stock No.—Satisfaction Guaranteed

### EDMUND SALVAGE COMPANY

27 W. Clinton Ave., Dept. 10, P. O. Audubon, New Jersey

MARCH. 1945

Buy War Savings Bonds and Stamps regularly.



# FUE PUMPS

Pulsing steadily, hundreds of times a mile, your AC Fuel Pump is the strong, reliable heart of your fuel system. It has given you long, faithful service because of its inbuilt quality and scientific design.

You can prolong that faithful service indefinitely, if you insist upon an AC when you replace your present pump with a new or rebuilt one.

BUY WAR BONDS . BRING VICTORY QUICKER



A genuine steel pack muffler WITH A BEAUTIFUL MOTORBOAT TONE. Sandee Mufflers feature improvements far in the lead, years ahead of competition. Increases mileage and power, reduces back pressure and gives better performance. Savings in gasoline will pay for a Sandee Muffler.

MERCURY DUALS \$17.50

SINGLES-FIT IN PLACE OF REGULAR MUFFLER

Chev., V-8 Ford, Plym., \$5.00 Chrys., Olds., Buick, etc., \$7.00 These mufflers will outlast two regular stock replacements. Dealers Wanted

### WESTERN AVE., LOS ANGELES 44, CALIF.



### ENGINES IN STOCK



The G. H. Q. miniature gasoline engine that really operates is still available. Over 100,000 sold to date. 1/5 H. P. Complete with flywheel and propeller, fuel, 15 accessories and full instructions. Fully bench tested and ready to run. Power for all models, \$20 complete. Send only \$1.00—Shipped Collect C.O.D. same day. Send 25c for illustrated Catalog of hundreds of hobby items.

GHQ MOTORS, Dept. SV35, 40 East 21 St., New York 10, N.Y.

DRI-AIR Chemical absorbs dampness in basements, game rooms, storerooms. Guards against mildew, rust. Kills musty odors. Complete unit \$5.50, f.o.b. Chicago. Get free folder.

TAMMS SILICA COMPANY Dept. D-127, 228 North LaSalle St., Chicago 1, Ill.

DRI-AIR is featured by

leading department stores, furniture and hardware dealers everywhere

A business of your own, Big money making Hollywood style pottery and birdbatas without moulds. Wishing-wells, stucco-rock, benches. Marbling and cement water-paints. 10c brings sample, literature, pictures. Hollywood CementCraft, 8523 Wonderland Ave., Hollywood 46, California

### Easy To Turn Trees Into Money

Makes Lumber, ties, shingles, crates lath,


Belsaw Models in 10. 14 and 20 feet sawing lengths. Patented Mechanical Feed, accurate set works and positive Use tractor or old auto engine for dogs. low cost power. Thousands used for com-mercial sawing. Pays for itself quickly. Send post card today for FREE booklet, 'How To Make Lumber' and Catalog of Woodworking Equipment,

BELSAW MACHINERY CO. Dept. 1846-F 3542 Main Street, Kansas City 2, Mo.

### 10-VOLTS from DIRECT CURRENT

with KATO KONVERTERS, Furnish standard 110-v. AC from 32, 110, or 220-v. DC. Good deliveries on sizes 350 through 2500 watts on priority orders, Good deliveries on 5, 714, 15 & 25 KW AC generators, Mfgr's of motor generators, frequency changers and high frequency generators and high frequency generators.

KATO ENGINEERING CO., 121 Elm St., MANKATO, MINN., USA





### —greater hobby satisfaction...when you work with quality Delta Homecraft\* Power Tools

Trouble-free performance assures you of lots of homecraft fun and healthful recreation . . .

If you could ask the thousands of Delta homecraft hobbyists the reasons why they prefer Delta Homecraft Power Tools, you would probably get many different, enthusiastic replies. But, taken together, they would all "boil down" into one word — quality.

Delta Homecraft Power Tools have always had a reputation for quality — "hidden values" in construction that mean you get more for your money.

You can't always see Delta quality with your eyes — and yet you can tell it's there!

For one thing, the accuracy of Delta Homecraft Power Tools proves they are quality tools. You enjoy greater assurance of seeing a project turn out according to the plans.

The dependability of Delta Homecraft Power Tools means quality, too. A flick of a switch and they're ready to give you the economical, unfailing performance you expect.

And, because of quality, Delta Homecraft Power Tools are sale — meeting the highest safety standards of schools and industry.

To be sure that you enjoy a full measure of the pride and pleasure that comes from using your hands to make good-looking things, include quality power tools in your homecraft hobby plans—Delta Homecraft Power Tools!

Right now, save to make your dreams come true — and at the same time, do right by our fighting men — by buying War Bonds.

- Double-sealed ball bearings you don't have to worry about oiling, because they are lubricated for life.
- Precision-bored bearing seats that assure accurate alignment of parts.
- Bearings that are preloaded—an extra manufacturing operation that insures longer bearing life.
- A Precision-ground shafts, to assure true, accurate performance.
- Dynamically-balanced pulleys, to eliminate annoying, damaging vibration.

HM-23

### Free Colorful Delta Book!

Shows you how to get started in homecraft. Illustrates modern shop layouts — in color. Tells how manual hobbies aid mental health. Mail the coupon for your free copy of "Happiness Is In Your Hands."

\*Trade Mark Reg. U. S. Pat. Off.



### Tear out coupon and mail today!

THE DELTA MANUFACTURING CO.
682C E. Vienna Ave., Milwaukee 1, Wisconsin

Please send me my free copy of "Happiness Is In Your Hands" picturing the ideal creative hobby and telling how to get started in it.


Name		 
Address	 	 


City...... (.....) State.....

MARCH, 1945

Buy War Savings Bonds and Stamps regularly.

249





\*Residual Shrinkage less than 1%

REEVES BROTHERS, INC.



### Shinola Wax Shoe Polishes in HARD-TO-GET COLORS



• If you've got a nick or mar to cover in a table top...or want to bring back the rich, mellow finish on an old piece of cherry, maple, or pine furniture... or finish a repaired section to match older wood...here's an assortment of colored waxes all ready to use.



Shinola Wax Shoe Polish in Neutral, Brown, Ox-blood, and Black, applied and finished like any other wax, is also grand for models, leather and linoleum. And remember—Shinola helps keep shoes new-looking longer.

SHINOLA





NEUTRAL - TAN - BROWN - OX-BLOOD - BLACK

# In Harmony with Good Taste



Blatz blends into your symphony of pleasure with perfect harmony, adds a welcome note, with smooth, rich overlones of enjoyment. For Good Taste that strikes a responsive chord, try Blatz.

Fast Becoming America's New Favorite



BEER

MARCH, 1945

Buy War Savings Bonds and Stamps regularly.

251



dry pipe in a class by itself for complete smoking contentment.

HENRY LEONARD & THOMAS, INC.

OZONE PARK, NEW YORK

Here's one thing you can do while

you're waiting for restrictions to be lifted on outboard motors: Ask the owners of Sea-Horses if they aren't glad they paid a little moreto get the best.

It will be the same after the war. Get a Sea-Horse, even if you have to wait for delivery. You'll never be sorry. Years of extra service and top performance all the time, will more than repay you for your wait.

DO YOUR DUTY -**BUY WAR BONDS** 



# SEA-HORSES

for DEPENDability

If you are interested in selling AND SERVICING Johnson Outboard Motors after the war, write us now-no matter what your location may be.

JOHNSON MOTORS WAUKEGAN, ILLINOIS







Why drive a sluggish car when you can have new car performance for an investment of a few dollars? Scientific new steps in the production of Burd "Graf-Flox" Piston Rings give them phenomenal self-lubricating qualities. All of the harmful abrasive particles left by grinding are removed by an exclusive method. Then, deeply penetrating col-

loidal graphite is applied by a secret process. These steps in making Burd "Graf-Flox" Piston Rings eliminate run-in, assure faster seating, prevent scoring, seizing, scuffing or sticking in grooves. Give your motor a new lease on life . . . save gas and oil. Mail the coupon for full facts and two free helpful books.



MARCH, 1945

Buy War Savings Bonds and Stamps regularly.

253

HANDBOOK




Quick, Mabel! Reach in my pocket for the Weldwood Glue.

MATERPROOF GLUE-

THEN you want to fix things fast...remember Weldwood Glue. It's quick to mix...easy to use...tremendously strong...stain-free... rot-proof...and permanent. At hardware stores, lumber yards, chain stores.

### WELDWOOD WATERPROOF



#### BUILD AUTHENTIC MODELS SHIP



Our kits and instructions are complete to the last detail. Clear plans simplify construction. Send \$2. today for SHIP MODELS ILLUSTRATED, WITH A GUIDE TO MODELING—the first book of its kind ever published — of ship models, of real ships, of masts, of rigging, of deck gear, covering all types from whale-boats to PT's from "Slavers" to Corvettes. Many color plates, close-up photos, decolor plates, close-up photos, de-tailed drawings and actual plans in addition to a salty text and glossary of nautical terms.

Catalogue included with your order.

MARINE MODEL CO. Dept. B-6, 29 West 15th St. New York 11, N. Y.



## **VRENCH**

Does more things, easier and quicker, than any other tool! Remains locked to the work with hands removed. Holds anything, any shape with a grip that never slips Is actually Hand-Vise, Clamp, Super-Plier, Adjustable End-Wrench, Pipe-Wrench, Locking Wrench, and Toggle-Press-ALL IN ONE! Light, trim, handsome. Fine alloy steel, zinc plated.

Sold through Tool Jobbers and Dealers.

Double-Lever Action

Gives Hand

PETERSEN MFG. CO., Dept. P-3, DeWitt, Nebr.



### BY ROMEC

 You have a surprise coming in our April announcement. True to ROMEC tradition, we will announce another ROMEC First. That will be a fully submerged Water Injection Pump. A year ago, this was merely an aim. Now it becomes a reality.

ROMEC precision aircraft pumps pioneered in the first "round the world" flights, pioneered the non-pulsating rotor principle, high altitude booster pumps, hydraulic pumps, and the solution to corrosion in water injection systems. Write today if you want us to mail you a copy of the April announcement on the fully submerged ROMEC Water Injection Pump.

OWNEC PUMP COMPANY • 129 Abbe Road • ELYRIA, OHIO

# werful . . . efficien

This New DURO 10" Tilting Arbor Saw has many new features and basic improvements

A versatile low-cost machine for cutting metals, woods and plastics, with many exclusive advantages. Entire arbor and tilting mechanism suspended on rugged, extra-heavy precision machined trunnions.

Has capacity up to 31/4" depth of cut and a working surface 1080 square inches with regular extensions, or 1395 square inches with special extensions. Distance in front of blade is 1434", and from blade to rip fence with regular extension 17", or 25" with special extension providing greatest possible utility. Cast iron table top is made of close grained and polished surface. Motor mounting is designed for most Standard Motors. Has improved guards and safety


features as integral part of unit — also patented accurate improved Rip Fence and Miter Gauge.

Send for Catalog—for full details and prices on the DURO 10-inch Circular Saw. Also lists specifications and prices of complete line of DURO single and multi-spindle Drill Presses, Circular Saws, Jointers, Routers, Shapers, Grinders, Lathes, Scroll Saws, Flexible Shaft Units and Portable Electric Drills.


MACHINE DIVISION TOOL

DURO METAL PRODUCTS CO., 2686 N. KILDARE AVE. CHICAGO 39, ILL

ALSO MAKERS OF DUBO HAND TOOLS



Available on Priorities Only



I SIDE-TRACK MOISTURE

> YOU enjoy better smoking!

In the Smokemaster pipe, an ordinary pipe cleaner, inserted in the stem, works while you smoke. As smoke is drawn through the stem, the pipe cleaner under the smoke passage, absorbs moiscure as fast as it forms.

The smoke always has a clean, dry passage. You enjoy your favorite tobacco at its very best-uncontaminated by rank, biting juices.

Smokemaster, made to Briarcraft standards, is a fine-looking pipe too-one you'll be proud to own.

In many popular shapes, of Native Briar. At leading dealers.



Pat. No. 2,166,537


Moisture is absorbed by pipe cleaner inserted in

the stem. Smokemaster Custom-made \$7.50

Smokemaster Standard \$1

Briarcraft, Inc., 347 Fifth Ave., New York 16, N.Y.

# mokemaster



# THIS BOOK FREE

A U.S.-approved program, sponsored by the National Rifle Association, to train

citizens in the use of rifles. Send TODAY for above 48-page FREE booklet, and details on how to get expert rifle training.



5974 St. John Street, New Haven 5, Conn.



OO Price complete tool dealers, or send remittance direct to

(Less Motor)

### NORK WIGGLER

for FAST and Accurate Set-Ups

Wiggler body hardened alloy steel. Ball shaft enables you to indicate accurately from tool makers buttons, holes, ground surfaces, gauge blocks, etc. Needle-Point shaft is for finding centers and truing to layout lines. Bent shaft holds any type indicator and allows it to be positioned on any circle to 6-inch dia. The only Universal Wiggler of its kind.

NORK PRODUCTS COMPANY Dept. 236, 5897 S. Main St. Los Angeles 1, Calif.



Cuts new teeth in 50 seconds! Any size tooth 4 to 16 points. Old teeth fall off as chips. Simple to operate. A perfect

8931 Venice Blvd. Los Angeles 34, Calif.





**DECORATE Your MODELS and PROJECTS** with GOLD, SILVER, NICKEL, COPPER If you have a hobby—a home workshop—you need

this new battery model Warner Electroplater. Easily and quickly, you can electroplate models and projects; you can

your work! Electroplate your models. Decorate metal projects. Replate worn objects. It's Easy!

4 Anodes. All necessary supplies: Electro-plating Compounds for Gold, Silver, Nickel, Copper-also Degreaser, Cleanser, Instruction Book and Wiring Diagram. Get more fun

from your hobby, make your workshop complete, order your battery model Warner Electro-plater today. ONLY

\$19.75, shipping charge collect. WARNER ELECTRIC CO. Dept. A-75, 360 N. Michigan, Chicago 1, III.





### Use Your Drill Press as a Wood Planer!

Planes. Parallels, Finishes-anes all wood-leaves Swiftly planes all wood—leaves knots smooth and finished. AMAZING SPEED—30 seconds

AMAZING SPEED—30 seconds for planing, paralleling and finishing 8"x24" board surface with 1/32" cut or less, 3 high speed steel blades—Double-Screw ADJUSTMENT, Safe, accurate, a lifetime tool. A perfect paint and varnish remover—blades cut underneath surface, \$7.50, postage paid, 5-day trial offer, Free literature, ACT TODAY!

H.J. BERRY MFG. CO., 2299 Scott St., Detroit 7, Mich.



With Our six in. tool steel cutters. Make mouldings, casings, drop-leaf tables, grooves beading & jointing 1" wide \$1.50, 11/2" \$1.75 ea. Postpaid. State size hole. List & folder free. John A. Sandstrom, Box 517, Stow, N. Y.






#### *DEPENDABLE*

Genuine Gerstner Tool Chests render com-plete service to fine tools day after day. Free Catalog for Machinists and Toolmakers. GERSTNER TOOL CHESTS 545 Columbia St., Dayton 7, Ohio.



DROP FORGE & TOOL CORP. UTICA, N.Y.



VOU can do it yourself-get rid of leaks, dripping, dampness, mustiness-by applying Smooth-On No. 7 Iron Cement to IN-SIDE cellar wall and floor surfaces. You brush it on like paint. Fills in cracks, crevices, pores in concrete, brick, stone. Hardens in 24 hours, expanding slightly, sealing tightly. Inexpensive, for you don't need professional help-and you get a lasting result.

Use it, too, to waterproof troughs, cisterns, tanks, fountains, swimming pool, garage, outbuildings.

Ask for Smooth-On No. 7 at your nearest hardware store-or write us direct if store hasn't it. Comes in 5-, 25-, 50- and 100-lb. sizes. 25 lbs. cover 100 sq. ft.

#### REPAIR FREE HANDBOOK

Full directions for waterproofing cellars, with instructions for repairing leaky heating and plumbing systems, household equip-

> ment, auto parts, etc. pages. 170 diagrams. Pocket size. Just send coupon.



#### ---Sign and Mail NOW-----Smooth-On Mfg. Co., Dept. 58 570 Communipaw Ave., Jersey City 4, N. J.

Name..... Address.....

Please send me Smooth-On Handbook

3-45..... Doit with SMOOTH-ON

257



With the Foley Automatic Saw Filer you can put yourself into a fine cash business with steady customers and make a good living. The Foley automatically joints the saw. making all teeth even in size, shape, spacing. The Foley is the only machine that files all hand

saws, also band and cross-cut circular saws. how to start a saw repair shop. No canvassing. Send coupon today.

### FOLEY Automatic 5A

FOLEY MANUFACTURING CO.

319-5 Foley Bldg., Minneapolis 13, Minnesota Send Free Plan on Saw Filing business, no obligation

Name

Address

### FREE BOOK Tells How To

444444444444444444444



- -get better gas economy
- -prolong tire life
- —preserve exterior finish
- —keep your car in the best operating condition.

#### Get a FREE COPY from any General Motors dealer, or use coupon below.

Customer Research Dept., Room 1764 GENERAL MOTORS, DETROIT 2, MICH.

Please send FREE COPY of new edition 64-page "Automobile User's Guide" containing 196 practical suggestions on wartime operation.

Name	please	print	***********
Address	please		
City		***************************************	
Make of car now owned		Zone	State.
		yec	r model

### DRILL PRESS OWNERS!

HERE'S 1 TOOL WITH 5 DISTINCT USES

THE BARRON MULTI-PURPOSE ROTARY WOOD PLANER

PLANES & SURFACES - PANELS & BEADS \$ 750 ROUTS & GROOVES . RABBETS . TENONS

Converts ANY drill press into a time saving, low cost planer, paneler, tenoner, etc. Surface finishes paneler, tenoner, etc. Surface finishes all types of tough grained and knotty surfaces to agate smoothness. Safel Guaranteed harmless to drill press. Thousands now in use. SOLD ON MONEY BACK GUARANTEE. Full refund on 5 day trial. Shipped prepaid on receipt of \$7.50—or C.O.D. YOU RISK NOTHING. Free literature.

BARRON TOOL CO., INC. 370 Architects Bldg., Detroit 1, Mich.

#### ALL METAL AUXILIARY DRILL PRESS TABLE

Has 234 sq. in, true working surface. Equipped for shaper and many other important workshop \$785



### TRUSTABLE TO PROTECT ANYTHING RUSTABLE! USE

For Guns, Tools, Locks, Hinges, Tackle

If your dealer hasn't it, write McCambridge & McCambridge Co. Baltimore 23, Md.




# Lumber—Plywood Available Harold Hunt wants to send you big revised No. 14 Catalog. 124 pages of woodworking ideas. 12 pages of rare woods in colors. UNEQUALED BARGAINS in imported and American woods, supplies. Send only 10c to cover postage and handling. Those already holding this catalog—send for revised sheets. CRAFTSMAN WOOD SERVICE CO. 2723 S. Mary St., Dept. 8-55, Chicago 8, M.



### DURAPOINT DRILLS

For: Concrete. Stone, Glass, Hardened Steel. Write for price

Durapoint Tool Company, 4342 Umatilla Street, Denver 11, Colorado





STUDY AT HOME for PERSONAL SUCCESS and LARGER EARNINGS. 35 years expert instruction -over 108,000 students enrolled, LL,B. Degree awarded. All texts furnished. Easy payments. Send for FREE BOOK-"Law and Executive Guidance" AMERICAN EXTENSION SCHOOL OF LAW

Dept. 51-S, 646 N. Michigan Ave., Chicago 11, III.





### Bean's Fine Cut Pipe Tobacco



A special fine cut tobacco the same as our sliced tobacco, except that it is a little milder. Suitable for both cigarettes and pipe. We are sure you will like this mild blend. Price \$1.35 lb.: 70c half pound postpaid. Write for New Spring Catalog.

L. L. Bean, Inc., Freeport 189, Maine

Mfrs. Fishing and Camping Specialties



Turn wood lots into cash; help save other fuels to win the war. Use Ottawa—fastest cutting; easiest way. Cuts large and small logs, fells trees. Thousands in use. Built to last with special heavy stiff saw blade. Positive safety clutch control, driven from any power take-off. OTTAWA MFG. CO., p-301 Forest Ave., Ottawa, Kansas

FREE BOOK

Buy War Savings Bonds and Stamps regularly.

Persons

write

for details.

Itsa Two men in a glider soared in the air for 50 hours and 26 minutes

> For sheer ecstasy, glidingsailplaning—is a sport literally "out of this world!"

> Do you want relaxation? Step into your Yankee Doodle Two and drift with sleek silent wings on a sea of lazy clouds.

> Do you want thrills? Depend on the same sturdy Yankee Doodle Two. If you choose, there's a breath-taking thrill in every minute.

Maybe you don't want to break any world's records but, whether you have plans or dreams, you interested in want wings for the future ... sales agencies

If you fly for pleasure—and flying at any speed under 125 miles an hour is for pleasure, not for transportation-then you want

THE FAMOUS



### DYNAMITE DAVE GETS A STAY-MOIST SHAVE

LIFEBUOY SHAVING CREAM'S HEAVY LATHER SURE STAYS MOIST -KEEPS WHISKERS SOFT FOR AN EASIER SHAVE



THANKS FOR THE TIP, AL. LIFEBUOY'S "STAY-MOIST" LATHER REALLY SOFTENS MY TOUGH WHISKERS



YES, SIR! EVEN WITH COLD WATER OR A USED BLADE IT GIVES ME A BETTER SHAVE THAN QUICK-DRYING LATHERS




LIFEBUOY SHAVING CREAM'S HEAVY "STAY-MOIST" LATHER!

120 TO 150 SHAVES IN THE BIG RED TUBE

and dealers:-Cal. .22 at \$2.00 M.; Cal. .177 at \$1.80 M. Place your order now for a NEW Benjamin Air Rifle or Benjamin Air Pistol. Write today for Illustrated folder of POSTWAR MODELS and POSTWAR PRIORITY PLAN. BENJAMIN AIR RIFLE CO., 811 MARION ST., ST. LOUIS 4, MO.

### PLASTIC ENAMEL Gives Lasting Beauty TO WALLS, **WOODWORK & FURNITURE** SUPERIOR Liquid Plastic

DRIES TO TOUGH, HIGH-GLOSS FINISH



**Applies Easily With Brush** 

 A new enamel miracle perfected by Science! It's a true plastic you apply easily with a brush. Beautifies all surfaces. Dries to long-wearing, brilliant white plastic finish. Leaves no brush marks. Nonyellowing, non-scratchable. Can be washed like porcelain.


Guaranteed to be top quality - the finest available.

#### ORDER NOW ON MONEY-BACK GUARANTEE

 No. 1 for walls, woodwork. No. 2 for furniture. Pure white. Can be tinted with oil colors. \$5.95 per gallon with Special Thinner. Express prepaid or COD if desired.

SEND YOUR ORDER OR WRITE FOR FREE ILLUSTRATED FOLDER SUPERIOR PAINT AND VARNISH WORKS

2254 Elston Avenue . Chicago 14, Illinois



HERE'S the cleverest little tool kit you ever saw. Made to fit your pocket. Think of it—8 wrench sizes—1 screwdriver—and one pair of grip-tight pliers in neat pocket case. Made of the most durable steel. Will give years of service. Just the thing for Radio Repair Men—Auto Mechanics—Vending Machine repair menand countless others. A Lucky Buy makes it possible for us to set a limited number for \$1.10 prepsid. You will never get a bargain like this again. Send for your set NOW with your money-order.

LANDAU LABORATORIES Dept. P.S. 549 W. Randolph St. C., C., C.,

### SHORT CUT

Be an expert, Learn to be a Telegraph ed. Intensely interor Radio Operator. Thousands of men needed. esting work good pay. Learn at home or wherever you are, quickly, easily with the famous Candler Speed System, Book of particulars Free.

CANDLER SYSTEM CO.

Box 928, Denver 1, Colo., U.S.A.

TRAINING — SECRET INVESTIGATIONS — FINGERPRINTS — Easy Method—Short Time. By Former Gov't Detective—Rewards. Home—Travel—Secret Code-Booklet FREE—WRITE
INTERNATIONAL DETECTIVE SYSTEM,
1701-P Monroe St., N. E., Washington, D. C. 18

# SHARPEN YOUR DRILLS WITH THE

Complete with

This precision fixture was developed for factory use by aircraft tool engineers. Real shop size and not a toy. Sturdily built, attaches to bench or grinder frame. Has new PROTRACTOR FEATURE which enables you to adjust quickly for different drill angles. Thousands now in use—home and repair shops, garages, factories, farm shops—wherever accurate holes are drilled. E-Z is simple to operate. Gives faster drilling, perfect hole centers and clearance. Guaranteed to do the work or money back.

SHARPENS ALL ROUND SHANK DRILLS FROM THE SHORTEST

TO 11" LONG—3/32" TO 1 1/16" DIAMETER

SAVE MONEY WITH E-Z. Comes complete with instructions, ready to sharpen your dull drills as good as new. Low price of \$2.80 because of our volume business on this wanted precision tool. The E-Z protractor gives you proper angles for cutting extra hard material, ordinary use, for soft material, wood. Plexiglas, Lucite, Plastics, Send check or money order for \$2.80.

WE PAY POSTAGE AND SHIP IMMEDIATELY. Write for FREE folder giving scientific data on drilling techniques.


drilling techniques.

F. TEN EYCK, Dept. S4, 758 S. Irolo St. FRED

MODEL No. 1 is already set for 59° drill angle, no adjustment needed for 99 7 of drills. Sturdy shop model. Postage paid \$1.98.







U. S. Carrier Launches Navy's Grumman Hellcats





It's as simple as that. And it explains, more than anything else, America's proud record of production for war. "Yankee" Tools have been in the thick of this national production . . . turning screws, boring holes, gripping metals at the bench . . . doing what good tools are supposed to do, and what the ingenuity of "Yankee" Tools does faster, easier, and better. When the war is over, every workman who wants "Yankee" Tools can have them. We're working toward that day with everything we've got. In the meantime, take care of your present "Yankee" Tools and keep asking your dealer for "Yankee" by name. They've got what it takes to save time, labor, and money on countless jobs.

### "YANKEE" TOOLS

make good mechanics better North Bros. Mfg. Co., Phila. 33, U.S.A. Established 1880

Makers, also, of "Yankee-Handyman" Tools



Steadier on roughest roads, easier to compensate, still more accurate, You'll want the improved HULL STREAMLINE AUTO COMPASS with the new shockproof mounting bracket. Limited supply at your dealer's. Circular free. Price \$3.50.

HULL MFG. CO., P. O. Box 246-E3, WARREN, OHIO



#### WORLD'S LOWEST PRICED Vest Pocket Size FREE TRIAL ADDING MACHINE

GUARANTEED ACCURATE. Not a toy. ONLY \$250 Operates with only a finger flick, Adds. TOTAL COST
SEND NO subtracts, multiplies, divides, Counts subtracts, multiplies, divides, Counts up to ten million. Pays for itself over and over, ideal Gift—for Business, Income Tax and School use, MONEY BACK GUARANTEE, Send name and address, Pay Postman only \$2.50 plus postage. (Send full cash if outside U. S.) Money Back in 10 days if not delighted, AGENTS WRITE.

CALCULATOR MACHINE COMPANY (Mfrs.)

DEPT. 452 P. O. BOX 1118

CHICAGO, ILLINOIS



radiators, machinery parts, etc.

Take Victory Model Handiweld anywhere to job, operate right from light socket. You'll find a thousand uses for this welder around your home, garage, workshop. Also in garages, factories, repair shops, the shops; mechanics, inventors, plumbers, farmers, etc. Order a "Victory Model" Handiweld now. SEND NO MONEY. We'll rush one to you with rods, helmet, operating instructions, and all necessary parts with the exception of a large jar and a small piece of extension cord; these most everyone has. Pay postman only \$1.95 plus a few cents postage. If not delighted return Victory Model Handiweld in 5 days from receipt and money paid for it will be refunded promptly. Rush your order now.

KUMFY PRODUCTS Dept. R-205, Cincinnati 26, Ohio

#### TRAILER BUILDERS' SUPPLIES!

To Build, Remodel or Modernize! Save money on Supplies. We are the largest and most complete trailer supply House in the States. Our new large 1944 catalog 10c; Blue prints and building instructions 25c.

National Trailer Equipment Company 719 N. Seventh St. Milwaukee 3, WIs.



With this Electronic Button With this Electronic Button you can make your own Telephone—Amplifier—Detectiphone. Attach this button to piece of cardboard—transmit conversation to another room. Music also transmitted to distant places. Most interesting, electrical apparatus ever discovered. Enables you to perform hundreds of experiments. So tiny it can be concealed in dozens of places. A Pre-War Product. Electronic Button including 5000 word instruction booklet with 50 illustrated experiments postpaid only \$1.00. Electronic Products Company, Saint Charles, III.

### Blueprints \$1.00 - Catalog FREE

Detail construction Blueprints on 6 Lewis metal and wood-working tools postpoid for \$1.00. Includes prints for Lewis 10" Shaper or Milling Machine, Drill Press, Vise, 16" Band Saw, 6" Jointer, 8" Circular Saw. Plain or semi-finished costings available for these tools save up to 80% al comparable new tool cost.

Effectivated 22-page Cotalog—cent free with Element Order—describes 20 Lewis tools. WEITE TOORY!

LEWIS MACHINE TOOL CO. P.O. Box 118, Sta. A. DEPT. D-16, LOS ANGELES 31, CALIFORNIA

## Qualify for Certified Grapho-Analyst Degree,

Earn up to \$100 weekly, up to \$1 hourly spare time, in new uncrowded profession. Graduates in employment and credit fields, and in private police departments, courts, practice as Personal Problem and Voca-tional Counselors, 3,000 word test lesson and illustrated GRAPHO-ANALYST Free

ADDRESS A.I.G.A., INC., 126 JOPLIN, MO.



Buy War Savings Bonds and Stamps regularly.



LHS Pipes \$1.50 to \$10-AT ALL GOOD DEALERS L&H Stern, Inc., 56 Pearl Street, Brooklyn 1, N.Y.



For tool room, machine shop, school shop, home shop or repair shop. Accurately machined. Best semisteel castings. Adjusting screw of hardened steel with fine pitch thread and long bearing. Jaws hardened steel, grooved or plain, Sizes 1½"·2½"·4" Jaws. No. 250 MILLING ATTACHMENT VISE



A most necessary fixture for small shops and even emergency work in large ones. Fits any 8"-9"-10" South Bend. Atlas. Craftsman, Sheldon or other lathes of similar sizes. Has graduated vertical feed screw and 360 degree graduation for vertical angle adjustments. Easily mounted on cross slide and held by one T-slot bolt. Equipped with PALMGREN VISE, 2½" Jaws opening full 2½". Vise has one plain and one grooved jaw for holding round pieces.

MAKES MILLING OPERATIONS POSSIBLE ON ANY LATHE

Width Depth Opening Jaw Jaw Height Price 2½" 1-7/16" 2½" 10½" \$24.75

ORDER DIRECT-Write for Circular No. 347 CHICAGO TOOL AND ENGINEERING CO. 8396 South Chicago Avenue Chicago 17, III. Avoid another winter of ...

# rosted riends



STEP UP HOME COMFORT WITH

BALSAM-WOOL ATTIC INSULATION!



Icy entertainment-freezing guests! Even though fuel must be saved, you can avoid those bone-chilling evenings. It's easy and inexpensive to make your home far more comfortable-now -by installing Balsam-Wool Attic Insulation.

Laid like a rug in your attic, Balsam-Wool will save up to 20% in fuel . . . by keeping precious heat from escaping through the roof. And Balsam-Wool has everything an insulation needs to give you permanent results. It's windproof, moistureproof and fire resistant . . . proved in thousands of American homes.

GUARANTEED SATISFACTION—Balsam-Wool -"the Aristocrat of Insulation"-is sold under a money-back guarantee of complete satisfaction. See your lumber dealer about buying Balsam-Wool on easy monthly payments-or, mail the coupon for complete information.

# Balsam-Wi

WOOD CONVERSION COMPAN	VY .
Dept. 211-3. First National Bank Blo St. Paul 1, Minnesota	ig.
Please send me more information a modernizing homes with Balsam-Wo Nu-Wood. I am a home owner \( \sigma, \) retains architect \( \sigma, \) contractor \( \sigma, \) student \( \sigma, \) postwar planner \( \sigma \)	ol and
Name	
Address	
CitySta	de



a safe, convenient plan for forward-looking shop men and home craftsmen.

With manufacturers now engaged 100% in war production, the pent-up demand for shop tools is tremendous. You can avoid prolonged waiting for your tools, or the necessity of buying something less satisfactory, by reserving a preferred delivery position now. Use this convenient coupon to get details.

#### BOICE-CRANE CO. 944 Central Ave., Toledo, Ohio

Please send, without obligation or cost, details of the Boice-Crane Purchase Priority Plan, together with a copy of your catalog on shop tools.

NAME STREET CITY

TODAY'S HEAVY-DUTY TAPERED ROLLER BEARING With More Load - Carrying Rollers TYSON BEARING CORPORATION . MASSILLON, OHIO



TELESCOPING MEASURING

. . . Measure All Holes, Slots, Etc.—5/16 Inch to 6 Inches . . . Gives You Outside Micrometer Accuracy on Inside Measurements FINISH YOUR OWN SET OF FOUR TOOLS

PART OF THE MACHINE WORK ALREADY DONE—ONLY
SIMPLE LATHE WORK NECESSARY TO COMPLETE. No special tools
required—Threading, Knuriling, etc., already done. Kit includes all
material (part machined); simple drawings, and detailed instructions.
Just mail your name and address to:
ALCO SHOPS, 2628 Armstrong Avenue, Los Angeles 26, California

Measure All Holes, Slots, Etc.-3/32 to 5/16 inch. Gives You Outside Micrometer Accuracy on Inside Measurements. Finished Set of Three Hardened and

Only \$795 C.O.D. Ground Tools

Plus Usual Postal Charge

ALCO SHOPS, 2628 Armstrong Avenue, Los Angeles 26, California

## ANYWHERE

Reliable, economical electric service any

Reliable, economical electric service anywhere, anytime, with an Onan Electric Generating Plant. Driven by Onan built, 4-cycle, gasoline engines, these power plants are of single-unit, compact design and sturdy construction. Suitable for all types of service.

Models range from 350 to 35,-000 watts, A.C. types from 115 to 660 volts; 50, 60, 180 cycles, single or three-phase; 400, 500 and 800 cycle, single phase; also special frequencies. D.C. types range from 6 to

types range from 6 to 4000 volts. Dual voltage types available. Write for engineering assist-

ance or literature.
D. W. ONAN & SONS.
1825 Royalston Avenue, Minn. Minneapolis 5,

Grinds Std., 59°

from 3/32" to 1" dia., up to 6" long. Will grind

to 6" long. Will grind rounded curve on drill

ONLY \$1.85

### GET THE IMPROVED SUPER DRILL GRINDING ATTACHMENT



**USED BY THE ARMY AND NAVY** Pays for itself the first week

You're an expert from the start with the Super Grinder. Does work like the highest priced grinders. Gives a true center, and desired clearance.

Saves drills, time and money. Grinds drills in 25 seconds. No shop should be without the SUPERB DRILL GRINDER. Mail your check or money order for \$2.95 with printed address. The Super will come by return mail complete with instructions. Postpaid.

> CRANDALL MFG CO. Dept. FB-3, 1512 W. Slauson Ave. Los Angeles 44, Calif.

MONEY BACK GUARANTEE



EAKS WALLS, FLOORS

Stop those leaks! End that seepage! Use STOP-IT-amazing quick setting. waterproof material. Simply mix with water and apply. Sets hard and permanent. At your dealer or write direct.

TAMMS SILICA CO. Dept. S-211, 228 N. LaSalle St., Chicago I, III.



the MODERN TROUBLE SHOOTER

> .. LOCATES TROUBLE INSTANTLY in electric circuits, fuses, cut-outs, motors, radios, appliances. Tests

everything electrical from

100 to 550 volts. Indicates


hot or grounded wires. Tells AC from DC. Far superior to ordinary clumsy test bulb.

PUTS "FINGER" ON THE TROUBLE SPOT - - QUICKLY

Saves precious time. Indispensable in shop or home. Has patented safety features. Vest pocket size with clip. Lifetime guarantee. List \$1.50 (Priority A7 required) Purchase through regular electrical dealers.

L.S. BRACH MFG. CORP. 55 Dickerson St.

Newark, N .J.





### Clean Rust and Scale out of the Radiator

### DU PONT **Cooling System Cleanser**

Dissolves rust, scale and grease without harming hose, packing or metal parts. Cleans thoroughly, without reverse flushing, even if radiator is badly clogged and car is overheating. Do the job now, because neglect today may mean expensive repairs later.



# NHIBITOR

### **KEEP RUST OUT ALL SUMMER**

After cleaning rust out of the cooling system, put in a can of DU PONT ACID & RUST INHIBITOR. It will prevent more rust forming—and guard against acid, too.

#### You can also PREVENT LEAKS

You can also make the cooling system LEAK-PROOF by pouring in a bottle of DU PONT COOLING SYSTEM SEALER. Won't clog radiator or harm hose or metal parts.





BETTER THINGS FOR BETTER LIVING ... THROUGH CHEMISTRY



Here's what you might expect from improper fitting



But here's what the New Super-TELEX and Scientific Fitting will bring you

Since no two hearing losses are identical, Telex has created a nine-point Scientific Fitting Service for each individual. To recreate near-natural hearing, parts are carefully assembled for your Super-TELEX after each step of the personal analysis has been completed. Through this scientific method of "Personalized" Fitting, normal tones are shaped for individual reception.

,	-TELEX-
	Hearing Centers from Coast to Coast CONSULT YOUR TELEPHONE BOOK
	TELEX LABORATORIES, 55 Telex Park, Minneapolis 1, Minn. Please send me a free copy of your new book "New Hearing Through the Miracle of Electronics."
,	Name
	Address
	CityState



# FALSE TEETH

with SOFT rubber-like PADS—at home—and CHEW ANYTHING. Make ANY plates BETTER THAN NEW, in a few minutes. Wear uppers and lowers at all times with SOFT, COMFORT-ABLE, LASTING PADS, which cling, ending bother of powders. COM-FIT PADS are READY-MADE—easily applied—just stick in and trim—

MADE—easily applied—just stick in and trim—no heat or cement required. These MODERN REAL PLASTIC pads last MANY months. Tasteless, odorless, sanitary. Clean as usual. Can be easily removed. Money back if not FINE. Save TIME and MONEY by mailing \$1.00 TODAY (for 4 pads) to COM-FIT CO., Dept. PB, 546 S. Meridan St., Indianapolis 4, Ind.




R uinous SLUDGE causes bucking, sluggish motors, wastes gas, retards pep and power.

Use LUBAID-T for dissolving gum, sludge and carbon binder; for freeing piston rings and sticky valves, for pepping up motors.

See your garage or service station NOW. If LUBAID-T is not stocked by your dealer or his jobber, write us. 12 oz. size 60c—Quart, \$1.00.

LUBAID Company Milwaukee 1, Wisconsin



\$2.50 Postpaid A glass cutter that really cuts DURAPOINT TOOL COMPANY, 4342 Umatilla Street, Denver 11, Colorado

After War
THE WORLD'S SAFEST ELECTRIC JIG
SAWS will again carry the name:





# WURKSHOP WISDOM

How to cover a table

You can renew that wooden table or desk top with leather, linoleum, canvas or oilcloth. Here's how:

1. Sand surface. If worn or soft, seal pores with coat of thin Casco Glue. Let dry.



2. Apply standard mix Casco to top, and stretch your covering material in place, slightly oversize. Iron out wrinkles. Turn table upside down on smooth floor, or cover with weights.

3. Trim edges after glue has set.

Hard compressed fibreboards, formica and other alcohol-proof resinoids also can be used. Rough with heavy sandpaper before gluing. Homecrafters prefer Casco for these reasons:

Unusual strength: Casco forms a bond of remarkable strength—strong as the wood itself.

Greater durability: Casco is highly resistant to dampness, heat and age because it sets chemically, like concrete.

Easy to mix: You mix Casco with cold water. You have no heating problems, no "chilled" joints.

Economical: You mix Casco Glue as you need it. Casco powder keeps indefinitely. Just keep lid tightly covered.

For rugged outdoor jobs and water projects, use Cascamite. It's highly water-resistant, moldproof. You can get Casco




CASCAMUTE


—and Cascamite—in 10¢, 25¢ and larger sizes at hardware stores.

FREE Casco Project Booklets and Gluing Guide with useful household gluing hints are yours for the asking. Address Casein Company of America, Dept. PS35, 350 Madison Ave., New York 17, N. Y.

## CASCO Powdered GLUE

Sets chemically—hardens permanently!











Postwar PORTA-LITE today . . . the handiest portable electric lantern, now improved in seven ways! Amazingly light, unusually useful . . . in home, office, factory, for sportsmen, night workers. Large rubber-grip bail may be hung on arm or belt, over motor in car, or on bumper as emergency light. Bail is adjustable—bright beam may be directed at any angle desired, while changing tire, etc. Uses 2 or 4 flashlight cells, only type replaceable anywhere. New patented circuit prevents corrosion and faulty contacts—adds years to life. Weatherproof switch, tarnish-proof reflector, bulb guard base. Streamlined all-metal case, double-plated, highly polished. ORDER TODAY!

WARNER ELECTRIC CO. Dept. A-81 360 N. Michigan, Chicago 1

# SKIN \*\*\* SCALP

So Many Druggists Say!



Copyrighted #

Here's a Doctor's formula - Zemo - a stainless liquid which appears invisible on the skin - yet so highly medicated and soothing that the first applications promptly relieve itching, burning of Eczema. Psoriasis and similar skin and scalp irritations - due to external cause. Zemo ALSO aids healing.

Apply clean, stainless invisible Zemo any time. It won't show on skin. Buy Extra Strength Zemo

for stubborn cases.

When Writing Advertisers Please Mention Popular Science Monthly





# WANTED ...

# Ideas and Inventions For Postwar Products

Automatic Electric Company, originator of the dial telephone and leading manufacturer in the field of communication and electrical remote control, seeks to make contact with inventors and others who may have patentable ideas or inventions for sale or license. Objective is the acquisition of newly invented or improved products which have peacetime application, which will make use of the company's expanded productive capacity, and which will help to maintain employment for its engineering, production and sales personnel during the postwar period.

Inventions should relate to wire communication, point-to-point radio, electrical remote control, or to mechanical, electrical or electronic devices used in such systems, and replies should be addressed to Mr. C. S. Cadwell, vice-president. All ideas submitted will be given careful consideration and treated with the utmost confidence.

# AUTOMATIC ELECTRIC COMPANY

1033 West Van Buren Street Chicago 7, Illinois

### Electrically Welded Endless

### Paramount

### BAND SAW BLADES



Made in widths from 1/16" to 134"

Make your band saw do more work for you. The proper width of blade will extend the scope of this important machine. Burrill's Paramount Blades are made from tough Nickel Alloy Steel properly tempered. Teeth accurately set and filed, and all saws carefully straightened. Send order and check today. Delivery will be made as promptly as war conditions permit, from a few days to a week or two. You can obtain these saws at the following prices:

Other sizes at proportional prices

Your satisfaction is guaranteed
BURRILL SAW & TOOL WORKS

405 E. Main St., Ilion, N.Y.

### Make extra money as shop agent for SCHERR TOOLS



### MEASURE TO

1/10,000" with the Reed Micrometer, with accurate vernier. A modern precision tool, Help your shapmates to buy Scherr Precision Tools-micrometers, combination squares, surface gages, sine bars, etc. Prices interestingly law. Scherr precision quality. Deliveries immediate. No priority. Ask us about the Scherr Shap Agent extra income plan, and full description of Scherr Precision Tools.

beautifully finished, sturdy, enduring. I" Micrometer as shown, postage prepaid. \$5.73



#### SPEED MACHINE SET UP

with the Scherr Dial Test Gage, famed for long service. Reads to 1/1000"

at a glance. Universal ball joint for use at any angle. \$12.00

All Scherr products carry 10-day money-back offer, giving absolute protection. In ordering, send check, M. O. or we'll ship C.O.D.





### Handbalancing Is FUN!

Enjoy the thrills of handbalancing. Walk on your hands. Learn this fascinating, muscle-building sport at home with my simple, inexpensive, Step-by-Step method. Mail penny card today for full information. POWER, 923 W. Vine, Kalamazoo 44, Michigan



### PIN-UP GIRLS

The kind men like! (Pocket size).

10 different PIN-UPS sent for 50c or 25 assorted for \$1. Shipped prepaid in plain wrapper. No C. O. D.'s. Send cash or money order. No stamps.

NUDKI, Dept. P-236 Box 126, G. P. O., New York 1



Buy War Savings Bonds and Stamps regularly.

POPULAR SCIENCE

This One

7ZWJ-JGX-E9X5



BUILT FROM OLD **AUTO GENERATORS** AND PARTS



### THERE'S LOTS OF ENJOYMENT IN THESE PROJECTS

Making practical things that work and save money is always fascinating, especially when you can do it in spare time and with spare equipment you may have in your garage or workshop. If you need a welder, you can make that, too. In fact, the fifty basic plans in the LeJay Manual contain instructions that will enable you to make 100 or more individual items. Think of the extra money you can earn making and repairing things for other people.


#### LEARN HOW TO BUILD

200 Amp. Generator Welders Workshop Spot Welder Large Transformer Welders **Gunsmith's Carbon Welder Electric Fencers** Armature Rewinding **Bench Grinders** 6, 12, 32 and 110-Volt Motors Wind Driven Light Plant Insect Electrocutors Electric Bicycle Pusher and Many Other Things.

#### PLANS EASY TO FOLLOW

These plans were made for YOU and others like you, who are not in any sense electrical experts or mechanics. They are simple, yet efficient, and do not need a lot of expensive tools to carry them out. Thousands of amateurs are having fun and making profits with the many things these plans helped them to build. The illustrations shown are only a few of the many things you can make.





#### IT'S FUN AND IT'S EASY

to build this Fast Freezer. Our plans cover every detail and you need no expert knowledge of refrigeration or carpentry. Can be built of new or used parts. Operates on any voltage.

#### MAIL THE COUPON NOW

for our Special Combination Offer of the Fast Freezer plans and the 1945 LeJay Manual for only \$2.25, or specify which of the two items you require at quoted price.

### LEJAY MFG. CO.

LEJAY MANUFACTURING CO.  423 LeJay Building, Minneapolis 8, Minn.  Gentlemen: Please send me both the LeJay Manual for 1945 (\$1.50) and the plans for your New Fast Freeze (\$1.00), for which I enclose \$2.25 in Cash () Mone Order () Check—add 5c exchange ().  I need only the LeJay Manual and enclose \$1.50 (I need only the Fast Freezer Plans and enclose \$1.00 (I need only	SAVE	ON	THIS	COME	BINATION	OFFER
Gentlemen: Please send me both the LeJay Manual for 1945 (\$1.50) and the plans for your New Fast Freeze (\$1.00), for which I enclose \$2.25 in Cash ( ) Mone Order ( ) Check—add 5c exchange ( ).  I need only the LeJay Manual and enclose \$1.50 ( I need only the Fast Freezer Plans and enclose \$1.00 ( NAME				A 30 C TO	8, Minn.	
I need only the Fast Freezer Plans and enclose \$1.00 ( NAME	Gentlem 1945 (3 (\$1.00)	en: Pl \$1.50)	ease send and the which I e	d me bot plans fo enclose \$:	h the LeJay r your New F 2.25 in Cash	ast Freezer
ADDRESS	I need o	only t	he LeJay Fast Fre	Manual ezer Plan	and enclose and enclose	\$1.50 ( ) \$1.00 ( )
A EDICTION ANY LOCAL DATE OF THE PARTY OF TH	NAME.					
CITYSTATE	ADDRES	ss				
	CITY				STATE	

### Greater Pleasure from Your Hobbies with Knives that Respond to Your Touch...X-ACTO

New! No. 83 X-ACTO deluxe all metal knife chest. The finest in knife sets complete with 3 solid aluminum handles and 12 interchangeable blades, in handy wooden chest. Price \$5.00 complete. Other knives and sets from 50c to \$3.50.

RE-BLADE TO

RE-SHARPEN

Men at work with X-ACTO knives know the joy of using finest surgical steel blades that are always sharp-that always make precision cuts with ease.

No matter what the carying or cutting job, be it  $\alpha$ frisket, a model airplane, or a piece of 16 ply cardboard, get to know the satisfaction of using X-ACTO for with a twist

of the wrist you insert a new blade. Result? A knife that is factory-fresh!

For greater pleasure in your work or arts and crafts, get an X-ACTO Knife Chest.

Write for 32 "How to Build Solid Scale Model Warplanes' -10 cents

On sale at Habby and Medel Dealers, Hardware and Dept. X-ACTO CRESCENT PRODUCTS CO.



POPULAR SCIENCE



Great American Sales Co., 55 E. Washington St., Dept. 752, Chicago 2, III.



TOMATO rapidly grows to a height of 10 to 12 feet-often as high as 16 to 20 feet. Grow on trellis, on side of home, barn or anywhere. Can be grown as a bush in garden. Beautiful, large, crimson, solid, meaty fruits of best quality. The most productive of all tomatoes. Trial packet 10c-3 for 25c, postpaid.

CASH PRIZE CONTEST Send for FREE Garden Book giving full details about CASH PRIZES to growers of this new tomato.

BURGESS SEED & PLANT CO. 207 C. T., GALESBURG, MICH.

Externally Caused

Discouraged by soaps and salves? SEBOLINE applied nightly often shows improvement in a week. Money Back if not completely satisfied after 2 weeks. Skin Specialist Prescription. SENT ON TRIAL. You risk nothing. FREE Send for Free Booklet at Once. Don't suffer embarrassment any longer. WRITE TODAY. Seboline Lab., Dept. LL, P.O. Box 350, Independence, Mo.

### Tired Kidneys Often Bring Sleepless Nights

Doctors say your kidneys contain 15 miles of tiny tubes

Doctors say your kidneys contain 15 miles of tiny tubes or filters which help to purify the blood and keep you healthy. When they get tired and don't work right in the daytime, many people have to get up nights. Don't neglect this condition and lose valuable, restful sleep. When disorder of kidney function permits poisonous matter to remain in your blood, it may also cause nagging backache, rheumatic pains, leg pains, loss of pep and energy, swelling, puffiness under the eyes, headaches and dizziness.

Don't wait! Ask your druggist for Doan's Pills, used

Don't wait! Ask your druggist for Doan's Pills, used successfully by millions for over 40 years. They give happy relief and will help the 15 miles of kidney tubes flush out poisonous waste from your blood. Get Doan's Pills.

# TOUT A PARAME INDUSTRIAL WELDER FOR ONLY

### TO SAVE YOU VALUABLE TIME and MONEY!

Designed to Do High-Grade Welding Inexpensively

Maintenance men, farmers, mechanics, machine shops, foundries, auto, general repair and job welding shops using the DYNAMIC WELDER find it so indispensable and useful that they cannot afford to be without it. If inexperienced you can easily learn to do a variety of highgrade welding jobs by following the practical, simplified operating and welding instructions furnished.

WORKS ON IRON, STEEL, BRASS, BRONZE and OTHER METALS

Has eight metallic and carbon arc welding heat stages. Does work you would think only possible with a larger, more expensive machine.

READ WHAT USERS SAY...

Repair Shop Owner says, "It will do more than you say"

"I want to say I operate a repair garage and am more than satisfied with the welder. It will do more than you say." C. P., Butler, Ohio

It's the Greatest Portable Outfit

"Now I am equipped for all kinds of welding and I must say it's the greatest portable outfit for welding any man could ever wish to own. I wouldn't sell mine for the cost of plenty welders I have seen which were very high in cost but not in convenience. You may put me on file as a booster of your wonderful welding product." W. J. B., St. John, N. B., Canada

Better Than I Expected

"I have done quite a little welding with my welder and will say it is better than I expected. The price, convenience, and variety of work that can be done with the Dynamic are the attractive points." W. R. P., Portland, Ore.

EASY TO OPERATE!

DYNAMIC SUPERCHARGED WELDER

### GET DETAILS ON OUR 10-DAY TRIAL OFFER!

Once you see a DYNAMIC in operation you won't want to be without it. Its simplicity will amaze you. In a year the DYNAMIC only costs you about 6c a day. Comes complete, ready to operate, with helmet, rods, cables, electrode holder and operating instructions, etc. Nothing else to buy. Write today for free priority assistance and particulars on how to qualify for one of these amaz ingly low-priced welders. Act now while they are still available.

DYNAMIC WEL

13 East 23rd. Street—CS

CHICAGO 16, ILLINOIS

Buy War Savings Bonds and Stamps regularly.

273

COMPLETE

AMAZINGLY SIMPLE

TO OPERATE!

This portable DYNAMIC WELDER easily carried

right to the job - plugs

into any convenient,

volt light circuit.

properly wired 110


**WORKS OFF** 

ELECTRIC

LIGHT

CIRCUIT

110 VOLT



# POST-WAR PRODUCTION will demand Precision Machining



"HOW TO RUN A LATHE"

A useful handbook for machinists, apprentices, and shop students. Contains complete information on the operation and care of engine lathes, grinding cutter bits, turning, facing, boring, tapering, drilling, reaming, tapping, thread-cutting, etc. Consists of 128 pages, 51/8" x 8", and 365 illustrations. Send 25c for your copy.

Manufacturing costs must be kept within reason in order to meet the keen competition that is sure to come with the postwar period. Then, if ever, shop machinery will be needed that can operate with unquestionable precision. There will be no margin for loss of time, labor, and material resulting from the use of inaccurate, obsolete machines.

South Bend Lathes are designed and built to provide the extreme accuracy required for efficient production. Throughout the war they have been performing hundreds of essential war production operations with toolroom precision. Their war-time record stands as a recommendation worthy of careful consideration when peace-time plans are made. Substantial savings in capital investment, power consumption, floor space, and labor costs often result from their selection.

Today, South Bend Lathes are better in every way. All of our facilities are still devoted to their manufacture. Improvements have been accelerated to meet war production needs. Their smooth, vibrationfree operation at high speeds permits finish turning and boring with such precision that subsequent grinding, honing, or lapping operations can often be eliminated.

South Bend Engine Lathes and Tool-room Lathes are made in five sizes: 9", 10", 13", 14½", and 16" swing. The Precision Turret Lathes are available in two sizes: ½" and 1" collet capacity. Write to-day for your copy of our Catalog.

### SOUTH BEND LATHE WORKS

LATHE BUILDERS FOR 38 YEARS

